



DC35GN-15-Q4

15 Watts • 50 Volts • Pulsed & CW
GaN on SiC Wideband Transistor
QFN 4x4 mm

GENERAL DESCRIPTION

The DC35GN-15-Q4 is a COMMON SOURCE, class -AB, GaN on SiC HEMT transistor capable of broadband pulsed and CW RF power applications. This transistor utilizes gold metallization, air-cavity Cu-base QFN package with high-thermal conductivity to provide superior electrical and thermal performance with excellent reliability & ruggedness.

FEATURES:

- Wide-band DC-3.5 GHz general purpose driver applications
- Ideal for Pulsed Radar, Avionics, ISM, and CW Communication
- 15 W Pulsed and CW Psat and 18 dB Power Gain @ 1.4 GHz
- Low-cost QFN package with excellent RF & Thermal performance
- 50V Bias Operation with high breakdown voltage

ABSOLUTE MAXIMUM RATINGS

Maximum CW Power Dissipation

Device Dissipation @ 25°C 15 W

Maximum Voltage and Current

Drain-Source Voltage (V_{DSS}) 125 V

Gate-Source Voltage (V_{GS}) -8 to +0 V


Supply Current (I_{DD}) 700 mA

Maximum Temperatures

Storage Temperature (T_{STG}) -55 to +125° C

Operating Junction Temperature +200 °C

PACKAGE OUTLINE QFN 4X4 mm



TYPICAL PERFORMANCE SUMMARY ¹ @ 25°C

Parameter	Units	0.960 GHz	1.2 GHz	1.4 GHz	2.7 GHz	2.9 GHz	3.1 GHz	3.5 GHz
Output Power Psat	W	20	21	19	20	20	20	16
Power Gain	dB	18.5	18.3	18	13	13	13	12
η_D Drain Efficiency	%	65	72	66	60	63	60	60

¹ Bias Condition: Vdd=+50V, Idq= 40 mA (Vgs= -2.0 ~ -4.5V typical), PW= 1 mS, DC = 10%
RF performance measured on the recommended evaluation board.

For the most current data, consult MICROSEMI's website: www.MICROSEMI.com
Specifications are subject to change, consult the RFIS factory at (408) 986-8031 for the latest information



DC35GN-15-Q4

15 Watts • 50 Volts • Pulsed & CW
GaN on SiC Wideband Transistor
QFN 4x4 mm

DC FUNCTIONAL CHARACTERISTICS @ 25°C

$I_{D(Off)}$	Drain leakage current	$V_{GS} = -8V, V_{DD} = 50V$			1	mA
$I_{G(Off)}$	Gate leakage current	$V_{GS} = -8V, V_{DD} = 0V$			0.2	mA
BV_{DSS}	Drain-Source breakdown voltage	$V_{GS} = -8V, I_{DD} = 2mA$	125			V
$V_{GS(TH)}$	Gate Threshold Voltage	$V_{DS} = 50V, I_{DD} = 2mA$	-4.8	-3.4	-2.5	V

ELECTRICAL CHARACTERISTICS¹ @ 25°C

Symbol	Characteristics	Test Conditions ¹	Min	Typ	Max	Units
P _{out}	Output Power	P _{in} =0.32W Freq=1400 MHz	15	19		W
G _p	Power Gain	P _{in} =0.32W Freq=1400 MHz		18		dB
η_D	Drain Efficiency	P _{in} =0.32W Freq=1400 MHz	55	66		%
D _r	Droop	P _{in} =0.32W Freq=1400 MHz		0.1		dB
VSWR-T	Load Mismatch Tolerance	P _{in} =0.32W Freq=1400 MHz			5:1	
Θ_{jc}	Thermal Resistance including PCB, T _{base} = 85 °C	Pulse Width=1 mS Duty=10% CW		3.5 8.4		°C/W

¹ Bias Condition: V_{dd}=+50V, I_{dq}= 40 mA (V_{gs}= -2.0 ~ -4.5V typical), PW=1 mS, DC = 10%
RF performance measured on the recommended evaluation board.





DC35GN-15-Q4

15 Watts • 50 Volts • Pulsed & CW
GaN on SiC Wideband Transistor
QFN 4x4 mm

TYPICAL CW PERFORMANCE DATA 300 – 500 MHz Band

Frequency	Pin (W)	Pout (W)	Id (A)	RL (dB)	η_D (%)	Gain (dB)	Droop (dB)
300 MHz	0.32	20.4	.633	-11	64.5	18.1	N/A
400 MHz	0.32	21.4	.649	-12.5	66	18.3	N/A
500 MHz	0.32	21.4	.635	-12.3	67	18.3	N/A

PERFORMANCE PLOTS









DC35GN-15-Q4

15 Watts • 50 Volts • Pulsed & CW
GaN on SiC Wideband Transistor
QFN 4x4 mm

TYPICAL BROAD BAND PULSED PERFORMANCE DATA¹ 0.96 – 1.215 GHz Band

Frequency	Pin (W)	Pout (W)	Id (A)	RL (dB)	η_D (%)	Gain (dB)	Droop (dB)
960 MHz	0.32	22	.680	-12	67	18.6	0.25
1100 MHz	0.32	22	.630	-10.5	72	18.6	0.12
1215 MHz	0.32	21	.600	-14.7	71	18.3	0.10

PERFORMANCE PLOTS



For the most current data, consult MICROSEMI's website: www.MICROSEMI.com
Specifications are subject to change, consult the RFIS factory at (408) 986-8031 for the latest information







DC35GN-15-Q4

15 Watts • 50 Volts • Pulsed & CW
GaN on SiC Wideband Transistor
QFN 4x4 mm

TYPICAL BROAD BAND PULSED PERFORMANCE DATA¹ 1.2 – 1.4 GHz Band

Frequency	Pin (W)	Pout (W)	Id (A)	RL (dB)	η_D (%)	Gain (dB)	Droop (dB)
1200 MHz	0.32	21.4	.590	-10	72.5	18.3	0.1
1300 MHz	0.32	20.4	.580	-17	70.3	18.1	0.1
1400 MHz	0.32	19.3	.580	-12	66.5	17.9	0.12

PERFORMANCE PLOTS



For the most current data, consult MICROSEMI's website: www.MICROSEMI.com
Specifications are subject to change, consult the RFIS factory at (408) 986-8031 for the latest information







DC35GN-15-Q4

15 Watts • 50 Volts • Pulsed & CW
GaN on SiC Wideband Transistor
QFN 4x4 mm

TYPICAL BROAD BAND PULSED PERFORMANCE DATA¹ 2.7 – 3.1 GHz Band

Frequency	Pin (W)	Pout (W)	Id (A)	RL (dB)	η_D (%)	Gain (dB)	Droop (dB)
2700 MHz	1.0	20.4	.680	-6.0	60.0	13.1	0.12
2900 MHz	1.0	20.2	.640	-10.2	63	13.1	0.10
3100 MHz	1.0	17	.550	-9.5	62	12.3	0.09

PERFORMANCE PLOTS



For the most current data, consult MICROSEMI's website: www.MICROSEMI.com
Specifications are subject to change, consult the RFIS factory at (408) 986-8031 for the latest information







DC35GN-15-Q4

15 Watts • 50 Volts • Pulsed & CW
GaN on SiC Wideband Transistor
QFN 4x4 mm

TYPICAL BROAD BAND PULSED PERFORMANCE DATA¹ 3.1 – 3.5 GHz Band

Frequency	Pin (W)	Pout (W)	Id (A)	RL (dB)	η_D (%)	Gain (dB)	Droop (dB)
3100 MHz	1.0	20.0	.670	-6	60	13	0.2
3300 MHz	1.0	18.0	.580	-7.6	62	12.6	0.12
3500 MHz	1.0	16.0	.540	-8.4	60	12	0.11

PERFORMANCE PLOTS



For the most current data, consult MICROSEMI's website: www.MICROSEMI.com
Specifications are subject to change, consult the RFIS factory at (408) 986-8031 for the latest information




DC35GN-15-Q4


15 Watts • 50 Volts • Pulsed & CW
GaN on SiC Wideband Transistor
QFN 4x4 mm

THERMAL IR SCAN DATA (Freq = 1.2 GHz)

DC P_{diss}=10.5 W, T_{base} =87°C, T_{max}=181°C , R_{th}= 9°C/W



CW P_{diss}=8.4 W, T_{base} =86°C, T_{max}=150°C , R_{th}= 7.6°C/W






DC35GN-15-Q4


15 Watts • 50 Volts • Pulsed & CW
GaN on SiC Wideband Transistor
QFN 4x4 mm

THERMAL IR SCAN DATA (Freq = 1.2 GHz)

1mS,10% Pdiss=9.7W,Tbase =85°C, Tmax=117°C,
Rth= 3.3°C/W



6mS,30% Pdiss=9W,Tbase =85°C, Tmax=131°C,
Rth= 5.1°C/W






DC35GN-15-Q4

15 Watts • 50 Volts • Pulsed & CW
GaN on SiC Wideband Transistor
QFN 4x4 mm

EVALUATION BOARD LAYOUT Q4 EB2 ASSEMBLY DIAGRAM AND BOM FOR 300-500 MHz



Board Material: Rogers RO4003C, 12 Mil Thickness, Er = 3.38, 1 OZ Cu
8 Mil Dia Vias below package, Qty: 39, Solid Cu Filled. Board Size: 1.5 x 1.3 inches

Item	Description 300 - 500 MHz
C11,C12	0603, 39 pF, $\pm 5\%$, 250V, ATC 600S
C1	0603, 10 pF, $\pm 5\%$, 250V, ATC 600S
C9	0603, 1.8 pF, ± 0.25 pF, 250V, ATC 600S
C4,C5,C13	0603, 470 pF, $\pm 5\%$, 100V, AVX, X7R
C6,C14	0603, 10000 pF, $\pm 10\%$, 100V, AVX, X7R
C8,C15	1206, 4.7 μ F, $\pm 10\%$, 100V, AVX, X7S
R1	0603 300 Ω
R8	0603 360 Ω
R5	0603 5.1 Ω
R2	0402 5.1 Ω
R3	0402 68 Ω
R6	0603 20 Ω
R7	0402 0 Ω JUMPER
L1	0603HP, 15 nH, 5% Coilcraft
L2	0603HP, 56 nH, 5% Coilcraft
L3	1008AF, 0.9 μ H, 5% Coilcraft
L4	0603HP, 7.5 nH, 5% Coilcraft
L5	0603HP, 4.7 nH, 5% Coilcraft
J3	TSM-105-01-S-SV-A, SAMTEC
Q1	DC35GN-15-Q4 QFN 4X4, 24L

Note: RF Input is DC short but Gate Input is DC Blocked

For the most current data, consult MICROSEMI's website: www.MICROSEMI.com
Specifications are subject to change, consult the RFIS factory at (408) 986-8031 for the latest information




DC35GN-15-Q4

15 Watts • 50 Volts • Pulsed & CW
GaN on SiC Wideband Transistor
QFN 4x4 mm

EVALUATION BOARD LAYOUT Q4 EB2

ASSEMBLY DIAGRAM AND BOM FOR 960-1215 MHz and 1200-1400 MHz



Board Material: Rogers RO4003C, 12 Mil Thickness, Er = 3.38, 1 OZ Cu
8 Mil Dia Vias below package, Qty: 39, Solid Cu Filled. Board Size: 1.5 x 1.3 inches

Item	Description 0.96 - 1.215 GHz	Description 1.2 - 1.4 GHz
C1,C11,C12	0603, 39 pF, $\pm 5\%$, 250V, ATC 600S	0603, 39 pF, $\pm 5\%$, 250V, ATC 600S
C2	0603, 2.4 pF, 250V, ATC 600S	N/A
C3	N/A	0603, 3.9 pF, 250V, ATC 600S
C9	0603, 1.8 pF, ± 0.25 pF, 250V, ATC 600S	0603, 1.8 pF, ± 0.25 pF, 250V, ATC 600S
C4,C5,C13	0603, 470 pF, $\pm 5\%$, 100V, AVX, X7R	0603, 470 pF, $\pm 5\%$, 100V, AVX, X7R
C6,C14	0603, 10000 pF, $\pm 10\%$, 100V, AVX, X7R	0603, 10000 pF, $\pm 10\%$, 100V, AVX, X7R
C8,C15	1206, 4.7 uF, $\pm 10\%$, 100V, AVX, X7S	1206, 4.7 uF, $\pm 10\%$, 100V, AVX, X7S
R1	0603 0 Ω JUMPER	0603 6.2 Ω
R5	0603 5.1 Ω	0603 5.1 Ω
R3	0402 12 Ω	0402 12 Ω
R6	0603 20 Ω	0603 20 Ω
L1	0402HP, 2.2 nH, 5% Coilcraft	0402HP, 2.2 nH, 5% Coilcraft
L2	0402PA, 1.9 nH, 5% Coilcraft	0402PA, 1.9 nH, 5% Coilcraft
L3	0603HP, 39 nH, 5% Coilcraft	0603HP, 27 nH, 5% Coilcraft
L4	0603HP, 7.5 nH, 5% Coilcraft	0603HP, 7.5 nH, 5% Coilcraft
L5	0603HP, 4.7 nH, 5% Coilcraft	0603HP, 4.7 nH, 5% Coilcraft
L6	0402HP 1nH, 5% Coilcraft	0402 0 Ω JUMPER
J3	TSM-105-01-S-SV-A, SAMTEC	TSM-105-01-S-SV-A, SAMTEC
Q1	DC35GN-15-Q4 QFN 4X4, 24L	DC35GN-15-Q4 QFN 4X4, 24L

For the most current data, consult MICROSEMI's website: www.MICROSEMI.com
Specifications are subject to change, consult the RFIS factory at (408) 986-8031 for the latest information




DC35GN-15-Q4

15 Watts • 50 Volts • Pulsed & CW
GaN on SiC Wideband Transistor
QFN 4x4 mm

EVALUATION BOARD LAYOUT Q4 EB2

ASSEMBLY DIAGRAM AND BOM FOR 2700-3100 MHz & 3100-3500 MHz



Board Material: Rogers RO4003C, 12 Mil Thickness, Er = 3.38, 1 OZ Cu
8 Mil Dia Vias below package, Qty: 39, Solid Cu Filled. Board Size: 1.5 x 1.3 inches

Item	Description 2.7 - 3.1 GHz	Description 3.1 - 3.5 GHz
C1,C11,C12	0603, 18 pF, $\pm 5\%$, 250V, ATC 600S	0603, 18 pF, $\pm 5\%$, 250V, ATC 600S
C2	N/A	N/A
C3	0603, 2.4 pF, 250V, ATC 600S	0603, 1.5 pF, 250V, ATC 600S
		ATTACH AT 1st HOLE
C7	0603, 1 pF, 250V, ATC 600S	0603, 1 pF, 250V, ATC 600S
C9	0603, 1.2 pF, ± 0.1 pF, 250V, ATC 600S	0603, 1.1 pF, ± 0.1 pF, 250V, ATC 600S
		AS CLOSE TO L5 AS POSSIBLE
C4,C5,C13	0603, 470 pF, $\pm 5\%$, 100V, AVX, X7R	0603, 470 pF, $\pm 5\%$, 100V, AVX, X7R
C6,C14	0603, 10000 pF, $\pm 10\%$, 100V, AVX, X7R	0603, 10000 pF, $\pm 10\%$, 100V, AVX, X7R
C8,C15	1206, 4.7 uF, $\pm 10\%$, 100V, AVX, X7S	1206, 4.7 uF, $\pm 10\%$, 100V, AVX, X7S
R1	0603 0 Ω JUMPER	0603 0 Ω JUMPER
R5	0603 5.1 Ω	0603 5.1 Ω
R2,R7	0402 0 Ω JUMPER	0402 0 Ω JUMPER
R3	0402 22 Ω	0402 22 Ω
R6	0603 20 Ω	0603 20 Ω
L3	0402HP, 1 nH, 5% Coilcraft	0402HP, 1 nH, 5% Coilcraft
L4	0402HP, 1 nH, 5% Coilcraft	Jumper Copper Foil
L5	0603HP, 1.8 nH, 5% Coilcraft	0402HP, 1 nH, 5% Coilcraft
L6	0402HP, 3.9 nH, 5% Coilcraft	0402HP, 3.9 nH, 5% Coilcraft
J3	TSM-105-01-S-SV-A, SAMTEC	TSM-105-01-S-SV-A, SAMTEC
Q1	DC35GN-15-Q4 QFN 4X4, 24L	DC35GN-15-Q4 QFN 4X4, 24L

For the most current data, consult MICROSEMI's website: www.MICROSEMI.com
Specifications are subject to change, consult the RFIS factory at (408) 986-8031 for the latest information




DC35GN-15-Q4

15 Watts • 50 Volts • Pulsed & CW
GaN on SiC Wideband Transistor
QFN 4x4 mm

QFN 4X4 mm PACKAGE OUTLINE & DIMENSIONS

All Dimensions are in mm (typ).



PIN	FUNCTION
1,6,13,18	RF GND (Source)
2,3,4,5	RF IN (Gate)
7,8,9,10,11,12	N/C
14,15,16,17	RF OUT (Drain)
19,20,21,22,23,24	N/C
Backside Exposed Pad	RF GND (Source) & Thermal Pad

Notes:

1. Backside exposed pad must be connected to Solid Cu filled vias for optimum RF & Thermal performance. See recommended evaluation board layout



DC35GN-15-Q4

15 Watts • 50 Volts • Pulsed & CW
GaN on SiC Wideband Transistor
QFN 4x4 mm

The information contained in the document is PROPRIETARY AND CONFIDENTIAL information of Microsemi and cannot be copied, published, uploaded, posted, transmitted, distributed or disclosed or used without the express duly signed written consent of Microsemi. If the recipient of this document has entered into a disclosure agreement with Microsemi, then the terms of such Agreement will also apply. This document and the information contained herein may not be modified, by any person other than authorized personnel of Microsemi. No license under any patent, copyright, trade secret or other intellectual property right is granted to or conferred upon you by disclosure or delivery of the information, either expressly, by implication, inducement, estoppel or otherwise. Any license under such intellectual property rights must be approved by Microsemi in writing signed by an officer of Microsemi.

Microsemi reserves the right to change the configuration, functionality and performance of its products at anytime without any notice. This product has been subject to limited testing and should not be used in conjunction with life-support or other mission-critical equipment or applications. Microsemi assumes no liability whatsoever, and Microsemi disclaims any express or implied warranty, relating to sale and/or use of Microsemi products including liability or warranties relating to fitness for a particular purpose, merchantability, or infringement of any patent, copyright or other intellectual property right. The product is subject to other terms and conditions which can be located on the Web at <http://www.microsemi.com/legal/tnc.asp>.

Revision History

Revision	Date	Affected Section(s)	Description
2.0	09-16-14	-	Initial Preliminary Release
3.0	12-04-14	-	Added more Preliminary Data
4.0	2-17-15	-	Added more Data, Updated PCB layout and BOM
5.0	5-1-15	-	Added 3.1-3.5 GHz Data, PCB Layout and BOM

For the most current data, consult MICROSEMI's website: www.MICROSEMI.com
Specifications are subject to change, consult the RFIS factory at (408) 986-8031 for the latest information