

COAXIAL ADAPTER, BMA - SMA, 50 Ohm, Panel, jack / jack (female / female), flange mount

37_BMA-SMA-50-1/1--_U

Properties

- Wide range of different configurations
- Most common interfaces available
- Accurate transitions
- Effective and reliable interconnection solutions
- Appropriate materials



Product configuration		
Interface type	Gender	Standard
BMA	jack (female)	IEC 60169-33_MIL-STD-348A/321
SMA	jack (female)	IEC 60169-15_MIL-STD-348A/310_CEECC 22110

Interface and material data		
BMA		
Piece parts	Material	Plating
Centre contact	Copper Beryllium Alloy	Gold Plating (without Nickel underplating)
Outer conductor	Copper Beryllium Alloy	Gold Plating (without Nickel underplating)
Body	Stainless Steel	
Insulator	PFA / PTFE	
SMA		
Piece parts	Material	Plating
Centre contact	Copper Beryllium Alloy	Gold Plating (without Nickel underplating)
Insulator	PFA / PTFE	

Electrical data	
Impedance	50 Ω
Interface frequency	18 GHz
VSWR	DC - 9 GHz ($\leq 1.07 + 0.017 f \text{ GHz}$)

Electrical Data (frequency related)		
Frequency range	Return loss	VSWR
9 GHz ... 18 GHz	20.1 dB	1.22

COAXIAL ADAPTER, BMA - SMA, 50 Ohm, Panel, jack / jack (female / female), flange mount
37_BMA-SMA-50-1/1--_U

Mechanical data	
Weight	0.0061 kg
Mating cycles	500

Environmental data	
Operation temperature	-65 °C ... 125 °C

Ordering Information Table		
Item number	Item description	Packaging type
22645649	37_BMA-SMA-50-1/1--_UE	Single

Additional Information	
Remarks	Impedance matching DC to 9 GHz: VSWR <= 1.07 + 0.017 * f [GHz] 9 to 18 GHz: VSWR <= 1.22 / return loss >= 20.1 dB

HUBER+SUHNER is certified by ISO 9001, ISO 14001, ISO 45001, IATF 16949, AS/ EN 9100 and ISO/TS 22163-IRIS. Waiver: Facts and figures herein are for information only and do not represent any warranty of any kind.
DOCUMENT PIM-P1934 / Date of publication: 12.04.2024 / uncontrolled copy