


SCREW ON FEMALE RECEPTACLE


R128.609.001

HERMETIC

Series : BMA



All dimensions are in mm.



COMPONENTS	MATERIALS	PLATINGS (µm)
BODY	STAINLESS STEEL	GOLD 0.5 OVER NICKEL 2
CENTER CONTACT	BERYLLIUM COPPER	GOLD 1.3 OVER NICKEL 2
OUTER CONTACT	BERYLLIUM COPPER	GOLD 1.3 OVER NICKEL 2
INSULATOR	PTFE	
GASKET	ALUMINIUM ALLOY	
OTHERS PARTS	STAINLESS STEEL	
-	-	-
-	-	-

Issue : 0449 F

In the effort to improve our products, we reserve the right to make changes judged to be necessary.



SCREW ON FEMALE RECEPTACLE

R128.609.001

HERMETIC

Series : **BMA**

PACKAGING

SPECIFICATION

Standard	Unit	Other
1	-	Contact us

ELECTRICAL CHARACTERISTICS

ENVIRONMENTAL

Impedance		50 Ω
Frequency		0-22 GHz
VSWR	1.25* +	0.000 x F(GHz) Maxi
Insertion loss		0.07 √F(GHz) dB Maxi
RF leakage	- (NA - F(GHz)) dB Maxi
Voltage rating		500 Veff Maxi
Dielectric withstanding voltage		1500 Veff mini
Insulation resistance		5000 MΩ mini

Operating temperature	-65/+125 ° C
Hermetic seal	10-5 Atm.cm3/s
Panel leakage	NA

OTHERS CHARACTERISTICS

Assembly instruction **NA**

Others :
* de 0 -10 Ghz

MECHANICAL CHARACTERISTICS

Center contact retention		
Axial force – Mating end	27	N mini
Axial force – Opposite end	27	N mini
Torque	NA	N.cm mini
Recommended torque		
Mating	NA	N.cm
Panel nut	280	N.cm
Mating life	1000	Cycles mini
Weight	2.234	g

Issue : 0449 F

In the effort to improve our products, we reserve the right to make changes judged to be necessary.




SCREW ON FEMALE RECEPTACLE


R128.609.001

HERMETIC

Series : BMA



RECOMMENDED MOUNTING HOLE DETAIL



Assemble metal gasket onto connector. Screw both parts into the housing.
 Tighten the connector up to 280 N.cm + or - 10 N.cm torque (use special tooling set RADIALL R282 322 000).
 Thus the connection hermeticity is guaranteed at $1 \cdot 10^{-5}$ cc/sec.
 Then solder the pin on the track.
 Be careful not to put too much solder.

Issue : 0449 F

In the effort to improve our products, we reserve the right to make changes judged to be necessary.

