

7.7 ~ 8.5 GHz Low Noise Power Amplifier

Key Features:

Broad Frequency Range:	7.7 ~ 8.5 GHz
High Gain:	48 dB
High P1dB:	31 dBm (typ.)
High OIP3:	40 dBm (typ.)
Single DC Supply:	+10V @ 700mA
I/O port:	Pins
Package:	Drop-in module

Electrical Specifications¹: (at +25°C)


Parameter	Symbol	Test Condition	Min	Nom	Max	Unit
Frequency Range	BW		7.7		8.5	GHz
Gain	S ₂₁	7.7 ~ 8.5 GHz	46	48		dB
Gain Flatness	ΔG	7.7 ~ 8.5 GHz		+/-1.0		dB
VSWR (Input/Output)		7.7 ~ 8.5 GHz		1.5:1	1.6:1	
Reverse Isolation	S ₁₂	7.7 ~ 8.5 GHz		50		
Noise Figure	NF	7.7 ~ 8.5 GHz		2.5	3.0	dB
Power at 1dB Gain Compression		7.7 ~ 8.5 GHz	30	31		dBm
Output Third Order Intercept Point	OIP3	7.7 ~ 8.5 GHz	35	40		dBm
DC Voltage	Vd		+9.7	+10	+10.5	V
DC Current	Id	@Vd+10V		700		mA
Operating Temperature			-40		+85	°C
Impedance				50		Ohm

Absolute Maximum Ratings

Parameters	Ratings	Units
DC Power Supply Voltage	+12	V
Drain Current	1.0	A
Total Power Dissipation	13	W
RF Input Power	10	dBm
Channel Temperature	150	°C
Storage Temperature	-55 ~ 125	°C
Operating Temperature	-40 ~ 85	°C
Thermal Resistance	13	°C/W

¹ Specifications are subject to change without notice.

Outline Drawing (not scaled)



Richardson RFPD

1950 S. Batavia Avenue
Suite 100
Geneva, IL 60134
United States of America

Telephone: (800) 737- 6937

(630) 262- 6800

Fax: (630) 262- 6850

Website: www.richardsonrfpd.com

E-Mail: rfpdsales@richardsonrfpd.com

IMPORTANT NOTICE

RICHARDSON RFPD, INC. AND ITS AFFILIATES RESERVE THE RIGHT TO MAKE CHANGES TO THE PRODUCT(S) OR INFORMATION CONTAINED HEREIN WITHOUT NOTICE. RICHARDSON RFPD, INC. ASSUMES NO RESPONSIBILITY FOR ANY ERRORS WHICH MAY APPEAR IN THIS DOCUMENT.

WARRANTY INFORMATION APPLICABLE TO THE PRODUCT IDENTIFIED HEREIN IS AVAILABLE UPON REQUEST. NOTHING CONTAINED HEREIN SHALL CONSTITUTE A WARRANTY, REPRESENTATION OR GUARANTEE OF ANY KIND. RICHARDSON RFPD, INC. EXPRESSLY DISCLAIMS ALL OTHER WARRANTIES, EXPRESS AND/OR IMPLIED INCLUDING BUT NOT LIMITED TO WARRANTIES OF MERCHANTABILITY, AND OF FITNESS FOR A PARTICULAR PURPOSE, USE OR APPLICATION.

NO PART OF THIS DOCUMENT MAY BE COPIED OR REPRODUCED IN ANY FORM OR BY ANY MEANS WITHOUT THE PRIOR WRITTEN CONSENT OF RICHARDSON RFPD, INC.

WARNING

RICHARDSON RFPD, INC. PRODUCTS ARE NOT INTENDED FOR USE IN LIFE SUPPORT APPLIANCES, DEVICES OR SYSTEMS. USE OF A RICHARDSON RFPD, INC. PRODUCT IN ANY SUCH APPLICATION WITHOUT WRITTEN CONSENT IS PROHIBITED.

Richardson RFPD - 800-737-6937 (U.S. & Canada) - 630-208-3637 (International)
Or visit www.richardsonrfpd.com See important product notice on last page of this document.

Internal Richardson Document #	Origination Date: August 2008	Rev: 1B Date: October 2017	Page 2/2
--------------------------------	----------------------------------	-------------------------------	----------