



RF COAXIAL CONNECTORS GENERAL CATALOGUE

Edition 2007/2008



HOW TO USE THIS CATALOGUE

How to select a suitable connector for a particular cable

A straight BNC plug, crimp style, is required for cable RG 142

- consult the section on cables, see pages 28 to 34
- select the desired flexible cable RG 142
- in the column „cable group, crimp“ you will find U9
- then refer to BNC series on page 199
- from the contents section, find „Cable Connectors“ on page 202
- from there, look for “straight plugs, for flexible cables, cable entry H+S full crimp”
- select cable group U9 and find suitable connector:

on page 203 □ 11_BNC-50-3-16/133_NE (single packaging)

on page 203 □ 11_BNC-50-3-16/133_NH (100 pcs packaging)

Please note that cable RG 223 and EF 142 will also be suitable for the selected connectors, as these cables also fit into cable group U9.

How to find matching cables for a particular connectors type

For example, to find which cables fit the 11_BNC-50-3-5

- consult the connector type index starting on page 425
- select 11_BNC-50-3-5 from the BNC series section, and find page 202
- the cable group column will indicate U7 and U10 for this connector
- refer to the cable section on page 28
- find suitable cables for group U7 □ G03232, GX03272, RG 58, RG 303
and for group U10 □ RG 142, EF 142, RG 223, RG 400, EF 400

How to use the „Type Index“

The type number index should be used when you have a connector part number, but no actual information about it. The type index on page 425 contains an alphabetical listing of all connectors found within this catalogue. Each part number is referenced against the appropriate page number, where all relevant information is located.

- More information about connector selection see page 11
- Suitable tools see page 385
- For any accessories (insulating washers, taper sleeves, solder tags, fastening screws, etc.) see page 403

IMPORTANT NOTE:

This catalogue does not show all the articles we have in our product range.
For more information, please contact our affiliate or agent in your country.

CONTENTS

CONTENTS				General information	
				Suitable cables	
Micro miniature “board to board”, snap-on Micro miniature, snap-on Micro miniature precision, snap-on	50 Ω	12.4 GHz 6 GHz 65 GHz	MMBX MMCX MMPX		
Micro miniature, snap-on	50 Ω 75 Ω	6 GHz	MCX		
Subminiature: snap-on (SMB), screw-on (SMC), slide-on (SMS)	50 Ω	4 GHz 10 GHz 4 GHz	SMB SMC SMS		
Subminiature, screw-on Subminiature precision, screw-on Subminiature precision, screw-on	50 Ω	18 GHz 26.5 GHz 40 GHz	SMA PC3.5 SK		
Subminiature acc. DIN 41626/2, slide-on Subminiature, quick-latch	50 Ω	4 GHz 1.4 GHz	1.0/2.3 QLA		
Subminiature “blind mate”, slide on	50 Ω	18 GHz	BMA		
Subminiature, quick-lock Miniature, quick-lock	50 Ω	18 GHz 11 GHz	QMA QN		
Miniature, bayonet	50 Ω 75 Ω	4 GHz 1 GHz	BNC		
Miniature, screw-on	50 Ω 75 Ω	11 GHz 1 GHz	TNC		
Miniature twinaxial, bayonet Miniature triaxial, bayonet	not defined 50 Ω	200 MHz 3 GHz	BNO BNT		
Miniature high voltage, bayonet	50 Ω	300 MHz	SHV MHV		
Mid size, screw-on Big size, screw-on	50/75 Ω 50 Ω	11 / 1 GHz 7.5 GHz	N 7/16		
N and 7/16 for corrugated copper tube cables	50 Ω	11 GHz (N) 7.5 GHz (7/16)	QUICK-FIT		
Adaptors: within and between series, precision, quick-mate and PIM				Adaptors	
Assembly Tools Accessories Mounting Holes Type Index				Appendix	



GENERAL INFORMATION

SERIES NOT MENTIONED IN THIS CATALOGUE

For several reasons, only the most popular HUBER+SUHNER connector series and the appropriate connectors are mentioned in this catalogue. Connectors series such as C, UHF, SMPX etc. belong to the extended product range. The selection within these series however is rather limited. For more information, please contact our subsidiary or agent in your country.



Series	Coupling mechanism	Frequency range	Interface standard
C – mid size coaxial connector	bayonet	DC – 11 GHz	– IEC 169-7 – MIL-C-39012 – DIN 47222
4195 – mid size coaxial connector	screw-on	DC – 14 GHz	– IEC 169-11 – VG 95277
UHF – mid size coaxial connector	screw-on	DC – 200 MHz	– IEC 169-12
PC7 (sexless) – mid size precision coaxial connector	screw-on	DC – 18 GHz	– IEC 457-2 – IEEE Std. 287
SMPX – micro miniature coaxial precision connector	snap-on	DC – 40 GHz	– MIL-STD 348A/326 – DSCC 94007/94008
PC2.4 – subminiature precision coaxial connector	screw-on	DC – 50 GHz	Mateable with: APC-2.4, OS-50, HP-2.40 and RPC-2.40

FAKRA - THE HUBER+SUHNER CONNECTORS FOR THE AUTOMOTIVE INDUSTRY

The FAKRA connectors meet the requirements of automotive electronics in the fields of Multimedia, Telematics, Safety&Security.

They are compatible with the international ISO 20860, the North American SAE/USCAR and the German DIN 72594 standard. The design of the connector interface is based on the proven SMB connectors to IEC 169-10, but includes an additional plastic housing. This housing contains a mechanical locking device which prevents disconnect in high vibration environments. Our connectors are space- and weight-saving, and they offer over 13 mechanical and colour codings which virtually rule out confusions during connection. Detailed information

on our FAKRA connectors are listed in a special product catalogue (Item no. 23040275).



SERVICES AND SUPPORT

Non standard connectors

Although our standard assortment is broad and miscellaneous, there are customer requirements which need a special solution. Thanks to capabilities and years of experience, HUBER+SUHNER is the ideal partner when customized solutions are demanded.

3D Files

For the exchange of CAD models between various CAD systems, HUBER+SUHNER is providing the customers with 3D files in IGS or STEP data format.

Simulations

HUBER+SUHNER has the ability and the tools for computer simulation of customer specific printed circuit board layouts.

ENGINEERING NOTES, GLOSSARY, ETC.

Since there is a RF Connector Guide available from HUBER+SUHNER, we deal with connector specific data only in this catalogue. We do not go into details regarding engineering notes or glossary etc. If you want to know more about RF connectors, please order the HUBER+SUHNER RF Connector-Guide under article number 648116 (english version) or 84009865 (german version)






DEFINITIONS AND TYPE CODES

HUBER+SUHNER PART NUMBER

11_BNC-()50-3-4/XYZ ([1] [2])



Examples: 82 MMCX-S50-0-51

...../111 NH

...../111 NY

S = SMT (Surface mount)

N = Nickel underplating

H = Packing (bulk, 100 pcs)

Y = variable industrial packing
(quantity depending on size of connector type)

LEGEND

Plating code (XYZ)

- 0 = silver
- 1 = gold or SUCOPRO
- 2 = nickel
- 3 = SUCOPLATE
- 4 = chromium
- 5 = tin plated
- 9 = stainless steel

Additional code for plating [1]

- N = gold plating, nickel underplated
- U = gold plating, not nickel underplated

Additional code for packaging [2]

- E = single packaging
- F = bulk with 50 pieces


- G = tape and reel with 750 pieces
- H = bulk with 100 pieces
- L = tape and reel with 1500 pieces
- Y = variable industrial packing

Extension for special attribute: ()

- L = left run thread
- P = press-fit
- Q = quick-mate
- R = reverse sex
- S = surface mount (SMT)
- T = reverse sex surface mount (SMT)
- U = unusual types (deviation from standard interface)
- V = reverse sex press-fit
- Z = zinc die casting

CONNECTOR PATTERNS

DEFINITION OF PLUG AND JACK



plug

A plug is a connector featuring the active part of the coupling mechanism (for example coupling nut).




jack


A jack is a connector featuring the coupling mechanism complementary to the plug.

PATTERNS


10... Right angle panel cable plug(male)/flange mount




11... Straight cable plug (male)




12... Straight bulkhead receptacle, plug (male)




13... Straight panel receptacle, plug (male), flange mount




14... Straight bulkhead cable plug (male)




15... Straight panel cable plug (male)




16... Right angle cable plug
(male)




17... Right angle bulkhead
receptacle, plug (male)




18... Right angle panel receptacle,
plug (male), flange mount



19... Right angle bulkhead
cable plug (male)




20... Right angle panel cable jack
(female), flange mount




21... Straight cable jack
(female)




22... Straight bulkhead receptacle,
jack (female)




23... Straight panel receptacle,
jack (female), flange mount




24... Straight panel bulkhead ca-
ble jack (female)




25... Straight panel cable jack (fe-
male), flange mount




26... Right angle cable jack
(female)




27... Right angle bulkhead
receptacle, jack (female)



28... Right angle panel receptacle,
jack (female), flange mount




29... Right angle bulkhead cable jack (female)




31... Adaptor jack/jack (female/female)




32... Adaptor plug/plug (male/male)




33... Adaptor plug/jack (male/female)




34... Bulkhead adaptor jack/jack (female/female)




35... Bulkhead adaptor plug/plug (male/male)




36... Bulkhead adaptor plug/jack (male/female)




37... Panel adaptor jack/jack (female/female), flange mount




38... Panel adaptor plug/plug (male/male), flange mount




39... Panel adaptor plug/jack (male/female), flange mount




41... T-adaptor, 3 plugs (male)




42... T-adaptor, 2 plugs (male), 1 jack (female), asymmetric




43... T-adaptor, 2 jacks (female), 1 plug (male)




44... T-adaptor, 2 plugs (male), 1 jack (female)




45... T-adaptor, 1 plug (male), 2 jacks (female), asymmetric




46... T-adaptor, 3 jacks (female)




47... T-cable junction




51... L-adaptor jack/jack (female/female)




52... L-adaptor plug/plug (male/male)




53... L-adaptor plug/jack (male/female)




54... Bulkhead-L-adaptor jack/jack (female/female)




55... Bulkhead-L-adaptor plug/plug (male/male)




56... Bulkhead-L-adaptor jack/plug (female/male)




57... Panel L-adaptor jack/jack (female/female), flange mount




58... Panel L-adaptor plug/plug (male/male), flange mount




59... Panel L-adaptor plug/jack (male/female), flange mount




61... Protective cap for plug (male)




62... Protective cap for jack (female)



63... Shorting jack (female)




64... Shorting plug (male)




65... Termination




71... Straight bulkhead cable feed through



80... PCB T-cable junction



81... Straight PCB plug (male)




82... Straight PCB jack (female)




83... Straight PCB cable terminator




84... Right angle PCB plug (male)




85... Right angle PCB jack (female)




86... Right angle PCB cable terminator










87... PCB T-adaptor jack/jack (female/female)



88... PCB T-adaptor plug/plug (male/male)



89... PCB T-adaptor plug/jack (male/female) 		
90... Combi-print-connector 	91... Edge mount PCB plug (male) 	92... Edge mount PCB jack (female) 
93... Right angle PCB plug with ground pin in-hole and SMT signal pin (male) 	94... Right angle PCB jack with ground pin in-hole and SMT signal pin (female) 	95... Straight PCB plug with ground pin in-hole and SMT signal pin (male) 
96... Straight PCB jack with ground pin in-hole and SMT signal pin (female) 		

SELECTING CONNECTOR, PLATING AND PACKAGING

HOW TO SELECT THE SUITABLE COAXIAL CONNECTOR SERIES

Technical Elements


Frequency, cable type, impedance and coupling mechanism are key factors to consider in selecting a coaxial connector series. Depending on the application, other factors such as sealing, temperature, working voltage, IM performance, vibration etc. also have to be taken into account.

Connectors must, at a minimum, provide the same level of performance as the cable or the application to which they are attached. This means, before selecting a connector series the cable type or the application has to be known. Its structure, dimensions and frequency range restrain the connector series that can be used.

The table below shows the different cable structures and the suitable connector series.

CABLE STRUCTURE	SUITABLE CONNECTOR SERIES
Coaxial cables	BNC, BMA, DIN 7/16, DIN 1.0/2.3, MCX, MMCX, MMBX, MMPX, N, QN, PC 3.5, SK, QLA, SMA, QMA, SMB, SMC, SMS, TNC
Balanced twin cables	BNO
Triaxial cables	BNT
High voltage (coaxial cables)	MHV (H4), SHV
Board to board	MMBX

Cut-off frequency as well as coupling mechanism of a connector series limit the frequency range that a connector can operate. The following table shows the frequency range of different connector series within this catalogue.




Frequency range of connector series

COUPLING MECHANISMS

Coupling mechanisms make it possible to mate connector pairs and also determine whether or not the mated pair can meet the specified mechanical and electrical characteristics, such as operating frequency.

The following four types of mechanisms are commonly used for the series described in this catalogue.


Screwed Coupling Mechanism



The coupling mechanism consists of a thread and a coupling nut. Special attention must be paid to the maximum torque permitted and the coupling nut captivation.

The screwed connection is used in series like SMC, SMA, TNC, N and 7/16 because the mechanism guarantees the most solid, stationary coupling suited for e.g. test and measurement, military and telecoms applications.


Bayonet Coupling Mechanism



The bayonet coupling is a twist -snap connection. The coupling mechanism is best known through the BNC.

The bayonet connection often is chosen as coupling when it is important to have a sturdy mechanism and at the same time fast mating. Therefore, the mechanism is reliable for test and measurement applications as well as military systems. Used in the series BNC, BNO, BNT, SHV and MHV.


Snap-on Coupling Mechanism



The snap mechanism is commonly used for connectors with small mechanical dimensions and high packing density. Because this type of connection is easy to use, it is often designed into PCB applications.

The main feature of the snap-on mechanism is that the engagement and disengagement action can be completed extremely quickly. This mechanism is very reliable when used for small connectors such as MMCX, MMPX, MCX and SMB series.


QUICK-LOCK Coupling Mechanism



A QUICK-LOCK coupling mechanism is basically a snap-on interface with additional self-locking. Demating is performed by retracting the unlock-sleeve of the male connector.

Quick-Lock connectors prevent unintentional loosening of mated pairs and they provide a fast and reliable interconnection. The QMA and QN connector interface feature this time saving locking mechanism.

Slide-on Coupling Mechanism



The slide mechanism is used extensively where a high packing density and easy handling is needed. A typical application is the interconnection of daughter boards to mother boards.

This mechanism is often used for various DIN-multiport connectors and also with connectors such as BMA, MMBX, SMS or DIN 1.0/2.3 which are commonly attached to PCBs.

COUPLING MECHANISMS	CONNECTOR SERIES
Bayonet	BNC, BNO, BNT, MHV (H4), SHV
Quick-Lock	QMA, QN
Threaded	DIN 7/16, DIN 4.1/9.5, SK, N, PC 3.5, SMA, SMC, TNC
Snap-on	MMCX, SMPX, MCX, QLA, SMB, MMPX
Slide-on	BMA, MMBX, DIN 1.0/2.3, SMS

Overview coupling mechanisms

For further technical information, such as contact captivation, attachments etc., please refer to the HUBER+SUHNER RF CONNECTOR GUIDE (Item no. 648116), Chapter RF CONNECTOR DESIGN.

PLATING INFORMATION

We are your plating technology specialist and your competent partner for developing and applying proper coatings for specific uses and conditions. This section explains the metallic plating used for the different HUBER+SUHNER connectors.

The demands towards connector platings are multiple, such as:

- > add conductive material to supply sufficient current carrying capacity (good electrical and thermal conductivity)
- > diminish or eliminate surface oxidation/corrosion and provide protective coating over conductors
- > provide good contact between conductors
- > achieve a good solder or weld attachment surface
- > obtain a better wear resistance (abrasion resistance and hardness)



Our main platings are

- > gold
- > silver
- > SUCOPLATE® (H+S plating)
- > SUCOPRO (H+S plating)

Gold

Gold (acc. to MIL-G-45204C Type II) is a precious metal available either as soft fine gold or as hard version. It is a good heat and electricity conductor and unaffected by air and most reagents, which makes it a superb material for electrical signal transmission. Gold can be deposited on nickel or copper. It is quite expensive compared to other plating materials

Application

The major use of gold in RF applications is for plating. Inner conductors are frequently gold-plated when e.g. good conductivity, excellent oxidation resistance and continuous mating (repeatability) are required (e.g. in defence applications). Even in highly polluted atmospheres, a gold surface will be free of oxide.

Gold offers the following main advantages:

- > excellent wettability / solderability
- > excellent protection against corrosion
- > low contact resistance
- > good wear resistance

Color: ► gold colored



Silver

Silver is often used for the plating of coins. It is a little harder but also cheaper than gold. Its excellent electrical and thermal conductivity makes it very suitable for surface plating. Silver is used in RF applications for making solder, brazing and sliding contacts. Having the best conductivity of all metals also means that this metal can carry a high current load with the least loss. This characteristic is particularly advantageous when a low passive intermodulation product is desired.

Other features of silver are that it is easily shaped, provides very good heat conductivity, good corrosion resistance in air and water and - in addition - the lowest contact resistance. A disadvantage is that silver tarnishes (creates an oxide film on the surface) when exposed to ozone, hydrogen sulphide and sulphur. Tarnishing does not have any influence on the electrical performance.

Application

Silver is the standard plating for connector bodies and inner pins of 7/16 connectors. Traditionally, silver plating is well-known as a very good plating for low passive intermodulation components.

Thanks to its good solderability, silver is used for soldering ferrules and cable entries.

Silver offers the following main advantages:

- > excellent electrical conductivity
- > good corrosion resistance
- > low contact resistance
- > good solderability
- > good passive intermodulation properties

Color: ♦ silver colored



SUCOPLATE®

As one of the leading RF connector manufacturers, HUBER+SUHNER has delivered several hundred million coaxial connectors with SUCOPLATE plating to demanding customers worldwide. These components, featuring unique mechanical and electrical properties, are used in a wide range of applications such as off-shore, airframes, space, test+measurement, telecommunications and wireless.

SUCOPLATE is a copper alloy composed of three components: copper, tin and zinc. Being non-magnetic and non-allergic (nickel-free), SUCOPLATE is an attractive alternative to nickel plating.

It has a good electrical performance and corrosion resistance. The non-magnetic property in the contact area is also important for obtaining negligible passive intermodulation products (PIM) in communication systems such as base transceiver stations. SUCOPLATE performs just as well as silver, as it has a PIM level of less than -155 dBc.

SUCOPLATE offers the following important performance highlights:

- > superior electrical conductivity and low contact resistance
- > non-magnetic
- > excellent passive intermodulation performance equal to silver
- > uniform plating thickness
- > high abrasion resistance
- > low surface friction
- > excellent adhesion and ductility (no cracking when bending parts)
- > tarnish resistant
- > high corrosion resistance
- > nonallergic

Color: ➤ similar to stainless steel



SUCOPRO - THE GOLD PLATING FOR THE FUTURE

SUCOPRO is a thin gold plating developed by HUBER+SUHNER, featuring a nickel-phosphorus alloy (13 % phosphorus) underlayer.

Below 300 °C the NiP is amorphous and non-magnetic. The gold layer - which is not subject to oxidation itself - protects the nickel-phosphorus underlayer against oxidation, thus allowing good wetting while soldering. It provides stable, low contact resistance and improved protection against oxidation and corrosion. As it contains only a thin layer of gold, the solder joints will not become brittle.

The nickel-phosphorus layer provides very good corrosion resistance, high wear resistance and hardness, and a diffusion barrier against gold, copper, tin and zinc. Between 300 °C and 500 °C, it changes its structure to microcrystalline and its hardness increases, but no brittleness or weak adhesion occurs.

Application


Initially, SUCOPRO was developed for piece parts which demand an excellent solderability and/or wear resistance, means PCB-connectors and adaptors. But more and more customers select this plating also for cable connectors and adaptors.

Meanwhile, SUCOPRO is an excellent plating for almost all subminiature connectors.

SUCOPRO plating offers the following main advantages:

- > excellent wear resistance for more than 1000 mating cycles
- > non-magnetic
- > excellent corrosion resistance
- > excellent wettability / solderability
- > very high strength of soldered joints without embrittlement
- > low contact resistance
- > good passive intermodulation properties

Color: ➤ gold colored



PACKAGING INFORMATION

HUBER+SUHNER attaches great importance to high quality, economic packaging. This section will give you an overview of the types and packaging materials used. All our packagings have to fulfill the following functions:

- Protection of the connectors against mechanical stress, humidity and dust during storage, transport and usage
- Identification and information about the product
- Easy handling for production
- Economic and useful recycling after use

All packagings fulfill the specification according to ISO 14000. For further information please contact your local HUBER+SUHNER representative.

Single and Bulk Packaging

Plastic bags from HUBER+SUHNER are sealed by welding or provided with a Mini-Grip closure (bulk only) for reclosing after use. They are easy to handle and are marked for recycling with the material recycling symbol according to the recommended international DIN standard. For product identification and retraceability, they are labelled with the type version and the order, batch and assembly instruction numbers.

Material: LDPE or PP, transparent

Attributes: Electrostatically conductive,
External resistance $10^8 \dots 10^{10} \Omega$
Air-tight
Chemically resistant
Chlorine-free
Halogen-free



Single (sealed by welding)





Bulk (mini-grip)

Tape+Reel Packaging

The main benefit of T+R packaging is the customer preference for automating connector assembly in the production process using existing assembly machines. This in turn enables them to reduce the cost of the whole manufacturing process. In addition to that, the connectors are protected during transportation and processing. Our Tape+Reel packaging meets the international standards EIA 481 and DIN IEC 286-3. The fully automated packaging machine provides perfect packaging quality.

Material:	Reel	Polystyrene (PS)	(anti-static)
	Carrier Tape	Polystyrene (PS) or Polycarbonate (PC)	(anti-static)
	Carrier Tape	Polystyrene (PS) or Polyethylene Terephthalate (PET)	(anti-static)
	Box	Cardboard	—



Summary

Type of Packaging	BULK	SINGLE	TAPE&REEL	Notes
Cable Connectors	×	×		- standard for high volumes - standard depending on connector size
Flange Connectors	×	×		- standard for high volumes - standard depending on connector size
PCB Connectors	×		×	- small quantities - standard for high volumes with automatic processing
Adaptors		×		- standard - other packaging on request

CABLE ENTRY VARIANTS, SOLDERING, IP RATINGS, VSWR CONVERSION TABLE

CABLE ENTRIES FOR FLEXIBLE CABLES

HUBER+SUHNER® Full Crimp

Full crimp connectors with crimped centre and outer contacts allow quick and simple assembly with high reliability.

1



Full crimp connectors are normally supplied in three parts: centre contact, body and crimp ferrule.

2




During crimping, the centre contact is accurately positioned in the crimp insert.

3




The pre-assembled cable is pushed into the body. Due to a snap mechanism between center contact and insulator, center contact is captivated and protected against axial displacement.

4




The final operation is crimping of the outer contact ferrule

Cable Entry Crimp



The centre contact is soldered and the cable braid is crimped to the connector body. The crimp technique enables an economic assembling of high reliability. Suitable taper sleeves are available; see page 406.


Cable Entry Clamp



The clamp type cable entry is recommended for weather-exposed applications. The cable jacket is secured by a rubber gasket and the cable screen by an axially tightened press ring.


CABLE ENTRIES FOR SEMI-RIGID CABLES

Soldered, with Pin and Insulator




Centre contact and body of the connector are soldered onto the centre or outer conductor of the cable.

Soldered, without Pin and Insulator (SMA for Semi-Rigid cable .141")



Pin and insulator are formed directly by the cable. The body is soldered to the copper jacket. This design features a very low reflection coefficient, short length, low cost and ease of assembly. Recommended for connections which must not be undone frequently, moisture-sealed.


Solderless Cable Entry, Clamp Cone



Specially for assembly of large size semi-rigid cables. The copper jacket of the cable is held by a clamp cone.

CABLE ENTRY FOR CORRUGATED COPPER TUBE CABLES

HUBER+SUHNER QUICK-FIT® (e.g. for 7/8" cable)







Humidity-proof cable entry for RF cables with corrugated copper tube. The cable entries support standard foam dielectric cables 1/2", 7/8", 1_1/4" and 1_5/8" and 1/4", 3/8" and 1/2" highflex SUCOFEEED as well as the equivalent products of Andrew, RFS (Kabelmetal), NK Cables and Eupen. Special assembly tools (see page 399) are available.

- FEATURES:**
- low, stable and reproducible PIM (Passive Intermodulation Product)
 - quick and easy assembly
 - competitive pricing
 - IPrating (IP68 for QUICK-FIT connector types)
 - cable multi-brand compatibility

SOLDERING

Soldering is an important technique in the assembly of electronic products. It is the process of joining two metals by the use of a solder alloy, and it is one of the oldest known joining techniques.

Good soldering quality as a prerequisite for reliable joints can be achieved only through a soldering process in which a great many variables both with respect to materials and to techniques have been optimised in a integrated system. The various mass-soldering processes all have their own particular characteristics. They differ in the way in which the solder flux and the solder alloy are applied to the parts to be joined and in the manner by which the heat is supplied. The following information describes the soldering methods, temperature and dwell time. This information should be considered as a recommendation. Depending on the specific application, it is up to the user to select the most suitable method.


ITEM TO BE SOLDERED		USUAL METHODS
Centre conductor of coaxial cable		• Soldering iron • Resistance heating
Outer conductor of Semi-Rigid cable		• Inductive (RF) • Soldering iron • Resistance heating
Connector for printed circuit board through-hole version		• Wave soldering • Reflow soldering • Soldering iron
Connector for printed circuit board surface-mount version		• Reflow soldering • Soldering iron
Connector with solder tab		• Soldering iron • Reflow soldering

In addition to the soldering method, temperature and dwell time, parameters such as the flux, surface, material and geometry of the parts to be soldered must be taken into account.

Soldering temperature and dwell time

	TEMPERATURE	DWELL TIME
Wave soldering - Single wave - Double wave	max. 260° / 500 °F max. 260° / 500 °F	approx. 3 sec. approx. 5 sec.
Reflow soldering - Infrared - Heating plate	temperature profile depending on component (typical profile see below)	
Condensation	215 °C / 419 °F lead solder 230 °C / 446 °F leadfree solder	10 – 30 sec. 10 – 30 sec.
Other methods - Iron soldering	variable	approx. 2 sec.

Typical profile for reflow soldering



Commonly used solder

Depending on components, soldering temperature etc., the following solders are used:

SnPb	63/37	183 °C lead solder
SnPb	60/40	188 °C lead solder
SnPbAg	62/36/2	179 °C lead solder
SnAgCu	50/48.5/1.5	215 °C leadfree solder
SnAg	96.5/3.5	221 °C leadfree solder

The higher melting temperature during leadfree soldering is critical for the cable stripping dimensions during assembly. The expansion of the cable dielectric will be larger.

How do you judge the quality of a solder joint?

A good (reliable) solder joint will, during the lifetime of the equipment in which the joint is situated, perform its mechanical and electrical functions without failures. Visual aspects of good soldered joints are:

1. Good wetting
2. Correct amount of solder
3. Sound and smooth surface












All soldered joints on a printed board should give a uniform impression regardless of their location on the printed board. Solder should flow evenly over the surfaces to be soldered and run out thinly towards the edges of the joint. The contact angle should be well under 30° if the surfaces are sufficiently large. Good wetting of both the component and the solder land with the correct amount of solder is so important that this is the major criterion in the assessment of soldered joints. The solder should wet the entire periphery of the termination to be soldered, and from the edge of the solder land the thickness of the solder coat should increase uniformly up to the termination.

Leadfree solder joints have a different appearance from their tinlead counter parts.

- grainy and less bright
- larger wetting angle

IP RATINGS

The IP rating system provides a means of classifying the degree of protection from dust and water afforded by electrical equipment and enclosures. The system is recognised in most countries and is set out in a number of standards, including IEC 60529.

1st. DIGIT: PROTECTION AGAINST SOLID OBJECTS		2nd DIGIT: PROTECTION AGAINST LIQUIDS	
IP x...	Description / Test	IP ...y	Description / Test
0	 No protection	0	 No protection
1	 Protected against solid objects over 50 mm, e.g. accidental touch by hands	1	 Protected against vertically falling drops of water
2	 Protected against solid objects over 12 mm, e.g. fingers	2	 Protected against direct sprays of water up to 15° from the vertical
3	 Protected against solid objects over 2.5 mm (tools/wires)	3	 Protected against sprays to 60° from the vertical
4	 Protected against solid objects over 1 mm (tools /wires / small wires)	4	  Protected against water sprayed from all directions - limited ingress permitted
5	 Protected against dust - limited ingress (no harmful deposit)	5	   Protected against low pressure jets of water from all directions - limited ingress permitted
6	 Totally protected against dust	6	 Protected against strong jets of water, e.g. for use on shipdecks - limited ingress permitted
Example: IP 67: Totally protected against dust and protected against the effects of immersion between 15 cm and 1 m.		7	   Protected against the effects of immersion between 15 cm and 1 m
		8	   ... m Protected against long periods of immersion under pressure

REFLECTION → CONVERSION TABLE

VSWR	Rf	RL (dB)
1.010	0.005	46.06
1.020	0.0099	40.09
1.030	0.0148	36.61
1.040	0.0196	34.15
1.050	0.0244	32.26
1.060	0.0291	30.71
1.070	0.0338	29.42
1.080	0.0385	28.30
1.090	0.0431	27.32
1.100	0.0476	26.44
1.110	0.0521	25.66
1.120	0.0566	24.94
1.130	0.061	24.29
1.140	0.0654	23.69
1.150	0.0698	23.13
1.160	0.0741	22.61
1.170	0.0783	22.12
1.180	0.0826	21.66
1.190	0.0868	21.23
1.200	0.0909	20.83
1.210	0.095	20.44
1.220	0.0991	20.08
1.230	0.1031	19.73
1.240	0.1071	19.40
1.250	0.1111	19.08
1.260	0.115	18.78
1.270	0.1189	18.49
1.280	0.1228	18.22
1.290	0.1266	17.95
1.300	0.1304	17.69
1.310	0.1342	17.45
1.320	0.1379	17.21
1.330	0.1416	16.98
1.340	0.1453	16.75
1.350	0.1489	16.54
1.360	0.1525	16.33
1.370	0.1561	16.13
1.380	0.1597	15.94
1.390	0.1632	15.75

RL (db)	Rf	VSWR
50.00	0.0032	1.006
49.00	0.0035	1.007
48.00	0.004	1.008
47.00	0.0045	1.009
46.00	0.005	1.010
45.00	0.0056	1.011
44.00	0.0063	1.013
43.00	0.0071	1.014
42.00	0.0079	1.016
41.00	0.0089	1.018
40.00	0.01	1.020
39.00	0.0112	1.023
38.00	0.0126	1.025
37.00	0.0141	1.029
36.00	0.0158	1.032
35.00	0.0178	1.036
34.00	0.02	1.041
33.00	0.0224	1.046
32.00	0.0251	1.052
31.00	0.0282	1.058
30.00	0.0316	1.065
29.00	0.0355	1.074
28.00	0.0398	1.083
27.00	0.0447	1.094
26.00	0.0501	1.106
25.00	0.0562	1.119
24.00	0.0631	1.135
23.00	0.0708	1.152
22.00	0.0794	1.173
21.00	0.0891	1.196
20.00	0.1	1.222
19.00	0.1122	1.253
18.00	0.1259	1.288
17.00	0.1413	1.329
16.00	0.1585	1.377
15.00	0.1778	1.433
14.00	0.1995	1.499
13.00	0.2239	1.577
12.00	0.2512	1.671

Rf	RL (dB)	VSWR
0.005	46.02	1.010
0.010	40.00	1.020
0.015	36.48	1.030
0.020	33.98	1.041
0.025	32.04	1.051
0.030	30.46	1.062
0.035	29.12	1.073
0.040	27.96	1.083
0.045	26.94	1.094
0.050	26.02	1.105
0.055	25.19	1.116
0.060	24.44	1.128
0.065	23.74	1.139
0.070	23.10	1.151
0.075	22.50	1.162
0.080	21.94	1.174
0.085	21.41	1.186
0.090	20.92	1.198
0.095	20.45	1.210
0.100	20.00	1.222
0.105	19.58	1.235
0.110	19.17	1.247
0.115	18.79	1.260
0.120	18.42	1.273
0.125	18.06	1.286
0.130	17.72	1.299
0.135	17.39	1.312
0.140	17.08	1.326
0.145	16.77	1.339
0.150	16.48	1.353
0.155	16.19	1.367
0.160	15.92	1.381
0.165	15.65	1.395
0.170	15.39	1.410
0.175	15.14	1.424
0.180	14.89	1.439
0.185	14.66	1.454
0.190	14.42	1.469
0.195	14.20	1.484

VSWR = Voltage Standing Wave Ratio
 Rf = Reflection Coefficient
 RL = Return Loss

SUITABLE CABLES

The HUBER+SUHNER Coaxial Connectors are suitable to a wide range of different cable types, such as flexible cables, Semi-Rigid cables, corrugated copper tube cables, etc.

Please find hereafter the specifications of all cables (cable groups) mentioned within this catalogue.



The wide range of Flexible and Semi-Rigid Cables ...



... as well as Corrugated Copper Tube Cables

FLEXIBLE CABLES

Screen Type	Cable group		Cable type	Ω	Centre conductor			Insulation	
	Crimp	Clamp			mm/inches	Material	Ø mm/inches	Material	Ø mm/inches
single screen	● U0		K 01152-07	50	7 x 0.06/.002	CuAg	0.19/.007	PFA	0.52/.020
	● U1	● U1	K 01232-05	50	7 x 0.10/.004	CuStAg	0.30/.012	PTFE	0.83/.033
	● U1	● U1	RG 178 B/U	50	7 x 0.10/.004	CuStAg	0.30/.012	PTFE	0.83/.033
	● U1	● U1	EF 178	50	7 x 0.10/.004	CuStAg	0.30/.012	SPEX	0.82/.032
	● U1	● U1	RG 196 A/U	50	7 x 0.10/.004	CuStAg	0.30/.012	PTFE	0.83/.033
single screen	● U2	● U2	RG 174/U	50	7 x 0.16/.002	CuSt	0.48/.019	PE	1.50/.059
	● U2	● U2	RG 188A/U	50	7 x 0.18/.007	CuStAg	0.54/.021	PTFE	1.55/.061
	● U2	● U2	RG 316/U	50	7 x 0.18/.007	CuStAg	0.54/.021	PTFE	1.54/.061
	● U2	● U2	EF 316	50	7 x 0.18/.007	CuStAg	0.54/.021	SPEX	1.54/.060
	● U3		G 01130 HT	50	0.40/.016	Cu	0.40/.016	PE/HL	1.4--1.9/.055-.075
double screen	● U4	● U4	G 02232 D	50	7 x 0.16/.006	Cu	0.49/.019	PE	1.50/.059
	● U4	● U4	K 02232 D	50	7 x 0.18/.007	CuStAg	0.54/.021	PTFE	1.54/.061
	● U4	● U4	K 02252 D*	50	7 x 0.18/.007	CuStAg	0.54/.021	PTFE	1.54/.061
	● U4	● U4	EF 316 D	50	7 x 0.18/.007	CuStAg	0.54/.021	SPEX	1.54/.061
single screen	● U5	● U5	RG 179 B/U	75	7 x 0.10/.004	CuStAg	0.30/.012	PTFE	1.53/.060
	● U5	● U5	EF 179	75	7 x 0.10/.004	CuStAg	0.30/.012	SPEX	1.55/.061
	● U5	● U5	RG 187 A/U	75	7 x 0.10/.004	CuStAg	0.30/.012	PTFE	1.53/.060
	● S5		S 02223-02	75	0.35 / .014	Cu	0.35 / .014	SPE	1.55 / .061
single screen		● U6	G 03133-06	75	7 x 0.14/.005	CuSt	0.42/.016	PE	2.50/0.98
double screen	● R6		G 02133 D-05	75	0.31/.012	Cu	0.31/.012	PE	1.95/0.78
single screen	● R7		G 02233	75	0.24/.009	CuSt	0.24/.009	PE	1.50/.059
single screen	● U7	● U7	G 03232	50	7 x 0.31/.012	Cu	0.93/.037	PE	2.95/.116
	● U7	● U7	GX 03272	50	19 x 0.18/.007	CuSn	0.90/.035	PEX	2.95/.116
	● U7	● U7	RG 58 C/U	50	19 x 0.18/.007	CuSn	0.90/.035	PE	2.95/.116
	● U7	● U7	RG 303/U	50	0.95/.037	CuStAg	0.95/.037	PTFE	2.95/.116
	● U8		S 03232-1	50	7 x 0.39/.015	Cu	1.17/.046	SPE	2.96/.116
double screen	● R8		K 02253 D-02	75	7 x 0.10/.004	CuStAg	0.30/.012	PTFE	1.55/.061
double screen	● U9	● U10	RG 142 B/U	50	0.95/.037	CuStAg	0.95/.037	PTFE	2.95/.116
	● U9	● U10	EF 142	50	0.95/.037	CuAg	0.95/.037	SPEX	2.95/.116
	● U9	● U10	RG 223/U	50	0.89/.035	CuAg	0.89/.035	PE	2.95/.116
	● U11	● U10	RG 400/U	50	19 x 0.19/.008	CuAg	1.00/.039	PTFE	2.95/.116
	● U11	● U10	EF 400	50	19 x 0.20/.008	CuAg	1.00/.039	SPEX	3.03/.119
single screen	● U12	● U12	G 03233	75	7 x 0.16/.006	Cu	0.48/.019	PE	2.95/.116
	● U13		G 03130 HT	75	0.50/.020	Cu	0.50/.020	PE/HL	3.0-3.4/.12-.13
double screen	● U14	● U14	G 03233 D	75	0.47/.019	CuAg	0.47/.019	PE	2.95/.116
double screen	● S16		S 04262 D	50	1.40/.055	CuAg	1.40/.055	SPE	3.78/.148

List of abbreviations

Cu plain copper wire
 CuAg silvered copper wire
 CuAg/CuAg double screened silvered copper wire
 CuAl aluminium wire, copper plated
 Cu/Cu double screened plain copper wire
 CuSn copper wire, tin plated

CuSt copper plated steel wire
 CuStAg silvered copper plated steel wire
 FEP fluorethylenepropylene
 GSi glass fibre braided and silicone varnish
 HDPE high-density polyethylene
 HL semiconducting layer

Screen		Jacket		Cable retention force	Recommended operating frequency range	Notes
Material	Ø mm/inches	Material	Ø mm/inches	N/lbs		
CuAg	0.90/.035	PFA	1.20/.047	13.9/3.1	1 GHz	
CuAg	1.30/.051	PVC	1.80/.071	32.7/7.3		
CuAg	1.33/.052	FEP	1.80/.071	32.7/7.3		
CuAg	1.35/.053	RADOX	1.84/.072	32.7/7.3		
CuAg	1.33/.052	PFA	1.83/.072	32.7/7.3		
CuSn	2.00/.079	PVC	2.55/.100	43.5/9.7	1 GHz	
CuAg	2.00/.079	PFA	2.60/.102	54.4/12.1		
CuAg	2.00/.079	FEP	2.50/.098	54.4/12.1		
CuAg	2.05/.080	RADOX	2.52/.099	54.4/12.1		
Cu	2.40/.095	PVC	3.15/.124	54.4/12.1		
Cu/Cu	2.0-2.5/.08 - .10	PVC	3.10/.122	119.7/26.7	5 GHz	* equivalent cable: RD 316
CuAg/CuAg	2.0-2.5/.08 - .10	UL-PVC	3.00/.118	108.8/24.3		
CuAg/CuAg	2.0-2.5/.08 - .10	FEP	3.00/.118	108.8/24.3		
CuAg/CuAg	2.0-2.5/.08 - .10	RADOX	3.10/.122	108.8/24.3		
CuAg	2.00/.079	FEP	2.54/.100	54.4/12.1	1 GHz	
CuAg	2.13/.083	RADOX	2.54/.100	54.4/12.1		
CuAg	2.00/.079	PFA	2.65/.104	54.4/12.1		
Cu	2.00/.079	PVC	2.55/.100	54.4/12.1		
CuSn	3.00/.118	PVC	3.90/.153	120.3/26.9	1 GHz	
CuSn/CuSn	2.40-2.85/.095-.112	PVC	3.60/.141	119.7/26.7	2 GHz	in acc. to BT CW 1383A-3002
Cu	2.00/.079	PVC	2.80/.110	54.4/12.1	1 GHz	
Cu	3.60/.142	PVC	5.00/.197	128.7/28.7	1 GHz	
CuAg	3.60/.142	Radox	4.95/.195	128.7/28.7		
CuSn	3.60/.142	PVC	4.95/.195	128.7/28.7		
CuAg	3.60/.142	FEP	4.30/.169	128.7/28.7		
Cu	3.60/.142	PVC	5.00/.197	128.7/28.7		
CuAg/CuAg	2.00-2.50/.08 - .10	FEP	3.00/.118	119.7/26.7	5 GHz	
CuAg/CuAg	3.6-4.25/.142-.167	FEP	4.95/.195	257.5/57.5	5 GHz	
CuAg/CuAg	3.54-4.20/.139-.165	RADOX	4.95/.195	257.5/57.5		
CuAg/CuAg	3.6-4.20/.142-.165	PVC	5.40/.213	257.5/57.5		
CuAg/CuAg	3.6-4.20/.142-.165	FEP	4.95/.195	257.5/57.5		
CuAg/CuAg	3.6-4.15/.142-.163	RADOX	5.10/.200	257.5/57.5		
Cu	3.60/.142	PVC	5.00/.197	128.7/28.7	1 GHz	
Cu	4.00/.157	PVC	5.00/.197	128.7/28.7		
CuAg/CuAg	3.6-4.2/.14-.165	PVC	5.35/.211	257.5/57.5	2 GHz	
CuAg/CuAg	4.2-4.7/.165-.185	LSFH	5.70/.224	228.0/51.3	5 GHz	

List of abbreviations

LDPE low-density polyethylene
 LSFH low smoke free halogene
 PE polyethylene
 PEX polyethylene, cross linked
 PFA perfluoralkoxy
 PTFE polytetrafluorethylene

PVC polyvinylchloride
 Radox polymere, flame retardent
 SPE foam polyethylene
 SPEX foam polyethylene, cross linked
 UL-PVC polyvinylchloride, flame retardant

FLEXIBLE CABLES (CONT.)

Screen Type	Cable group		Cable type	Ω	Centre conductor			Insulation	
	Crimp	Clamp			mm/inches	Material	Ø mm/inches	Material	Ø mm/inches
single screen	● U16	● U15	GX 04273	75	7 x 0.21/.008	Cu	0.62/.024	PEX	3.75/.148
	● U16	● U15	RG 59 B/U	75	0.58/.022	CuSt	0.58/.022	PE	3.64/.143
	● U16	● U15	RG 62 A/U	93	0.62/.024	CuSt	0.62/.024	PE/Air	3.70/.146
	● U16	● U15	RG 302/U	75	0.64/.025	CuStAg	0.64/.025	PTFE	3.70/.146
	● U17	● U15	S 04263	75	0.83/.033	Cu	0.83/.033	SPE	3.70/.146
double screen	● U18	● U18	G 04233 D	75	0.58/.022	CuSt	0.58/.022	PE	3.64/.143
	● U18	● U18	G 04273 D	75	0.58/.022	CuSt	0.58/.022	PE	3.64/.143
single screen		● U19	G 05232	50	7 x 0.50/.020	Cu	1.50/.059	PE	4.80/.189
double screen		● U20	RG 212/U	50	1.40/.055	CuAg	1.40/.055	PE	4.70/.185
single screen	● U21	● U21	G 05273-01	75	7 x 0.28/.011	Cu	0.80/.032	PE	4.80/.189
		● U22	S 05273	75	1.07/.042	Cu	1.07/.042	SPE	4.80/.189
double screen		● U23	RG 6 A/U	75	0.73/.029	CuSt	0.73/.029	PE	4.80/.189
	● U24	● U23	G 05133 D	75	0.77/.030	Cu	0.77/.030	PE	4.78/.188
double screen	● S24		S 06162 D-02	50	2.05 / .080	CuAg	2.05 / .080	SPE	5.60 / .220
	● U25		S 06132 D	50	2.17/.085	Cu	2.17/.085	SPE	6.25/.246
double screen	● S26		S 06132D-10	50	7 x 0.75/.030	CuAg	2.25/.089	SPE	5.80/.228
single screen		● U28	GX 07272	50	7 x 0.75/.030	Cu	2.25/.089	PEX	7.25/.285
		● U28	RG 165/U	50	7 x 0.82/.032	CuAg	2.46/.097	PTFE	7.25/.285
	● U29	● U28	RG 213/U	50	7 x 0.75/.030	Cu	2.25/.089	PE	7.25/.285
	● U30	● U31	S 07232	50	2.68/.106	Cu	2.68/.106	SPE	7.25/.285
		● U31	S 07232-1	50	7 x 0.95/.037	Cu	2.85/.112	SPE	7.25/.285
	● U30	● U31	SX 07272	50	2.68/.106	Cu	2.68/.106	SPEX	7.30/.287
multiple screen	● S32		S 07262 BD	50	7 x 0.95/.037	CuAg	2.85/.112	SPE	7.35/.289
	● S32		SX 07272 BD	50	7 x 0.95/.037	CuAg	2.85/.112	SPE	7.35/.289
double screen	● U32	● U33	RG 214/U	50	7 x 0.75/.030	CuAg	2.25/.089	PE	7.28/.286
	● U32	● U33	RG 214 hiflex	50	19 x 0.45/.017	CuAg	2.25/.089	PE	7.30/.287
	● U33	● U33	RG 225/U	50	7 x 0.79/.031	CuAg	2.37/.093	PTFE	7.25/.285
	● U33	● U33	RG 393/U	50	7 x 0.79/.031	CuAg	2.37/.093	PTFE	7.25/.285
	● U33	● U33	EF 393	50	7 x 0.82/.032	CuAG	2.46/.096	SPEX	7.30/.287
single screen	● U34	● U35	RG 11 A/U	75	7 x 0.40/.016	CuSn	1.20/.047	PE	7.25/.285
		● U35	RG 63 B/U	125	0.60/.024	CuSt	0.60/.024	PE/Air	7.25/.285
double screen	● U36	● U37	RG 216/U	75	7 x 0.40/.016	CuSn	1.20/.047	PE	7.25/.285
double screen		● U38	RG 217/U	50	2.70/.106	Cu	2.70/.106	PE	9.40/.370
	● S39		S 10162 B-11	50	3.78/.149	CuAl	3.78/.149	SPE	9.75/.384
	● S39		S 10172 B-11	50	3.78/.149	CuAl	3.78/.149	SPE	9.75/.384
single screen foil		● U39	G 12232	50	7 x 1.13/.044	Cu	3.39/.133	PE	11.50/.435
		● U40	S 12272-4	50	4.20/.165	CuAl	4.20/.165	SPE	11.50/.435
single screen		● U44	RG 218/U	50	5.00/.197	Cu	5.00/.197	PE	17.30/.681

List of abbreviations:

Cu plain copper wire
 CuAg silvered copper wire
 CuAg/CuAg double screened silvered copper wire
 CuAl aluminium wire, copper plated
 Cu/Cu double screened plain copper wire
 CuSn copper wire, tin plated

CuSt copper plated steel wire
 CuStAg silvered copper plated steel wire
 FEP fluorethylenepropylene
 GSi glass fibre braided and silicone varnish
 HDPE high-density polyethylene
 HL semiconducting layer

Screen		Jacket		Cable retention force	Recommended operating frequency range	Notes
Material	Ø mm/inches	Material	Ø mm/inches	N/lbs		
CuAg	4.45/.175	Radox	6.10/.240	183.7/41.0	1 GHz	
Cu	4.50/.177	PVC	6.10/.240	171.4/38.3		
Cu	4.40/.173	PVC	6.10/.240	171.4/38.3		
CuAg	4.30/.169	FEP	5.10/.201	128.7/28.7		
Cu	4.35/.171	LSFH	6.10/.240	147.1/32.9		
CuAg/CuAg	4.45-5.2/.175-.204	PVC	6.70/.264	367.3/82.0	2 GHz	
CuAg/CuAg	4.45-5.2/.175-.204	Radox	6.70/.264	367.3/82.0		
Cu	5.60/.220	PVC	7.40/.291	220.4/49.2	1 GHz	
CuAg/CuAg	5.45-6.2/.214-.244	PVC	8.45/.333	440.8/98.4	5 GHz	
Cu	5.60/.220	PE	6.80/.267	280.4/49.2	1 GHz	
Cu	5.50/.216	PE	6.90/.272	250.7/56.0		
CuAg/Cu	5.4-6.2/.212-.244	PVC	8.45/.333	440.8/98.4	2 GHz	
Cu/Cu	5.5-6.3/.216-.248	PVC	8.00/.315	477.5/106.6		
CuAg/CuAg	6.1-6.75/.24-.266	LSFH	7.90/.311	440.8/98.4	5 GHz	
CuSn/Alu/Cu/Sn/Alu	7.2-8.28/.283-.326	PVC	10.30/.406	581.8/129.9		
CuAg/CuAg	6.55/7.25 .258/.285	PVC	8.95/.352		5 GHz	
CuAg	8.15/.321	Radox	10.30/.406	423.1/94.5	1 GHz	
CuAg	8.00/.315	PTFE/GSi	10.30/.406	250.7/56.0		
Cu	8.10/.319	PVC	10.30/.406	423.1/94.5		
Cu	8.15/.321	PVC	10.30/.406	423.1/94.5		
Cu	8.15/.321	PVC	10.30/.406	423.1/94.5		
CuAg	8.10/.319	Radox	10.30/.406	423.1/94.5		
CuAg/Cu/CuSn	8.00-8.10-9.00/ .315-.319-.354	LSFH	10.80/.425	661.1/148.6	5 GHz	*
CuAg/Cu/CuSn		Radox	10.80/.425	661.1/148.6		
CuAg/CuAg	8.0-8.70/.315-.342	PVC	10.80/.425	477.5/106.6	5 GHz	
CuAg/CuAg	8.0-8.70/.315-.342	PVC	10.80/.425	477.5/106.6		
CuAg/CuAg	8.0-8.75/.315-.344	PTFE/GSi	10.90/.429	553.7/123.7		
CuAg/CuAg	8.0-8.75/.315-.344	FEP	9.90/.390	477.5/106.6		
CuAg/CuAg	8.0-8.75/.315-.344	RADOX	10.10/.397	477.5/106.6		
Cu	8.15/.321	PVC	10.30/.406	423.1/94.5	1 GHz	
Cu	8.10/.319	PVC	10.30/.406	423.1/94.5		
Cu/Cu	8.0-8.75/.32-.344	PVC	10.80/.425	587.7/131.3	5 GHz	
Cu/Cu	10.3-11.2/.406-.441	PVC	13.85/.545	952.0/212.6	5 GHz	
Cu (foil)/Cu (braid)	9.85-10.7/.388-.421	LSFH	12.9/.508	317.3/70.9	7.5 GHz	
Cu (foil)/Cu (braid)	9.85-10.7/.388-.421	PE	12.9/.508	317.3/70.9	7.5GHz	
Cu	12.40/.488	PVC	15.00/.591	634.7/141.8	1 GHz	- - - - -
Cu	12.50/.492	PE	15.00/.591	317.3/70.9	5 GHz	
Cu	18.55/.730	PVC	22.10/.870	1377.3/307.6	1 GHz	

List of abbreviations:

* double screened with helically wrapped foil

LDPE low-density polyethylene
 LSFH low smoke free halogene
 PE polyethylene
 PEX polyethylene, cross linked
 PFA perfluoralkoxy
 PTFE polytetrafluorethylene

PVC polyvinylchloride
 Radox polymere, flame retardent
 SPE foam polyethylene
 SPEX foam polyethylene, cross linked
 UL-PVC polyvinylchloride, flame retardant

CABLE GROUPS V,W: VARIOUS CABLES

Screen Type	Cable group		Cable type	Ω	Centre conductor			Insulation	
	Crimp	Clamp			mm/inches	Material	$\varnothing$ mm/inches	Material	$\varnothing$ mm/inches
symmetric screened cable	● V1	● V2	RG 108 A/U G 05730	78 95	7 x 0.32/.013	CuSn	2 x 0.96/.038	PE	2.0-4.0/.08-.16
					7 x 0.28/.011	Cu	2 x 0.84/.033	PE	1.7-4.8/.07-.19
triaxial cable		● W1	G 02332	50	7 x 0.16/.006	Cu	0.48/.019	PE	1.50/.059
triaxial cable		● W2	G 03332	50	7 x 0.31/.012	Cu	0.93/.037	PE	2.95/.116
triaxial cable		● W2	G 03333	75	7 x 0.16/.006	Cu	0.48/.019	PE	2.95/.116

SEMI-RIGID CABLES

Crimp	Cable group		Cable type	Ω	Centre conductor			Insulation	
	Soldered	Clamp			mm/inches	Material	$\varnothing$ mm/inches	Material	$\varnothing$ mm/inches
● Y3	● Y1 ● Y2 ● Y2 ● Y3 ● Y4		EZ 34	50	0.20/.008	CuStAg	0.20/.008	PTFE	0.66/.026
			EZ 47	50	0.29/.011	CuStAg	0.29/.011	PTFE	0.94/.037
● Y5	● Y5 ● Y6		Sucoform 47-Cu	50	0.31/.012	CuAg	0.31/.012	PTFE	0.94/.037
			EZ 86	50	0.51/.020	CuStAg	0.51/.020	PTFE	1.68/.066
			EZ 86-75	75	0.29/.011	CuStAg	0.29/.011	PTFE	1.73/.068
			EZ 141	50	0.92/.036	CuStAg	0.92/.036	PTFE	2.98/.117
		● Y7	EZ 141-75	75	0.51/.020	CuStAg	0.51/.020	PTFE	2.98/.117
			EZ 250	50	1.63/.064	CuAg	1.63/.064	PTFE	5.31/.209
			EZ 118TP	50	0.81/.032	CuAg	0.81/.032	PTFE	2.31/.091
			Sucoform 86	50	0.53/.021	CuStAg	0.53/.021	PTFE	1.65/.065
			Multiflex 86	50	0.47/.018	CuAg	0.47/.018	PTFE	1.48/.058
			Sucoform 141	50	0.95/.037	CuStAg	0.95/.037	PTFE	2.95/.116
			Multiflex 141	50	0.92/.037	CuAg	0.92/.037	PTFE	2.96/.117
			Sucoform 250	50	1.64/.064	CuAg	1.64/.064	PTFE	5.27/.207
	● Y14	● Y13	Sucoform 250-1	50	1.67/.065	CuAg	1.67/.065	PTFE	5.24/.206

FOAM DIELECTRIC CORRUGATED COPPER TUBE CABLES

Screen Type	Cable group		Cable type	Ω	Centre conductor		Insulation	
	Crimp	Clamp			Material	mm/inches	Material	$\varnothing$ mm/inches
corrug. copper tube cable		● M5	SUCOFEEED 1/4" HF	50	AlCu	1.90/.074	SPE	4.40/.173
		● M6	CF14-50	50	Cu	2.40/.094	SPE	6.00/.236
		● M7	SUCOFEEED 3/8" HF	50	AlCu	2.80/.110	SPE	6.90/.272
		● M8	LDF2-50 3/8"	50	AlCu	3.10/.122	SPE	8.70/.342
		—	EFX2-50 3/8"	50	AlCu	3.00/.118	SPE	8.50/.335
		● M9	SUCOFEEED 1/2" HF	50	AlCu	3.60/.142	SPE	8.70/.343
		● M12	SUCOFEEED 1/2"	50	AlCu	4.80/.189	SPE	11.90/.469
		● M23	SUCOFEEED 7/8"	50	Cu	9.00/.354	SPE	22.00/.866
		● M24	SUCOFEEED 7/8" HF	50	Cu	9.40/.370	SPE	22.40/.882
		● M25	SUCOFEEED 7/8" LA	50	Cu	9.50/.374	SPE	22.70/.894
		● M32	SUCOFEEED 1 1/4"	50	Cu	13.00/.511	SPE	32.00/1.259
		● M42	SUCOFEEED 1 5/8"	50	Cu	17.30/.681	SPE	42.00/1.654

List of abbreviations see pages 30 and 31

Screen		Jacket		Cable retention force	Recommended operating frequency range	Notes
Material	Ø mm/inches	Material	Ø mm/inches	N/lbs		
CuSn Cu	4.70/.185 5.60/.220	PVC PVC	6.00/.236 7.40/.291	110.4/24.8 220.4/49.5	—	
Cu Cu	2.00/.079 3.05/.120	PVC PVC	2.80/.110 4.25/.167	130.6/29.4	1 GHz	
Cu Cu	3.60/.142 5.75/.226	PVC PVC	5.00/.197 7.35/.289	294.3/66.2	1 GHz	
Cu Cu	3.60/.142 5.75/.226	PVC PVC	5.00/.197 7.35/.289	294.3/66.2	1 GHz	

Screen		Jacket		Cable retention force		Notes
Material	Ø mm/inches	Material	Ø mm/inches	N/lbs		
Cu	0.86/.034			23.9/5.3		
Cu	1.19/.047			41.8/9.3		
CuSn	1.19/.047			26.1/5.87		
Cu	2.20/.086			158.5/35.6		
Cu	2.20/.086			139.5/31.2		
Cu	3.58/.141			309.1/69.5		
Cu	3.58/.141			309.1/69.5		
Cu	6.35/.250			952.4/212.7		
Cu-TP	2.95/.116			246.0/54.9		
CuSn	2.20/.086			100.0/22.5		
CuAg	2.20/.086	FEP	2.65/.104	160.0/36.0		
CuSn	3.58/.141			100.0/22.5		
CuAg	3.58/.141	FEP	4.14/.163	160.0/36.0		
CuSn	6.05/.238			100.0/22.5		
CuSn	6.30/.248			100.0/22.5		

Screen		Jacket		Cable retention force		Notes
Material	Ø mm/inches	Material	Ø mm/inches	N/lbs		
Cu	6.40/.252	LDPE	7.70/.303	100.0/22.5		
Cu	7.50/.295	PE	10.00/.394	100.0/22.5		
Cu	9.50/.374	LDPE	10.80/.425	150.0/33.7		
Cu	9.70/.381	PE	11.00/.433	150.0/33.7		
Cu	9.70/.381	PE	11.20/.441	n.a.		
Cu	12.10/.476	LDPE	13.40/.528	200.0/45.0		
Cu	13.70/.539	LDPE	16.00/.630	200.0/45.0		
Cu	24.70/.972	LDPE	27.75/1.093	700.0/157.4		
Cu	25.00/.984	LDPE	27.50/1.083	700.0/157.4		
Cu	25.40/1.000	LDPE	27.90/1.098	700.0/157.4		
Cu	35.70/1.406	HDPE	39.50/1.550	> 700.0/157.4		
Cu	46.20/1.890	HDPE	50.00/1.968	> 700.0/157.4		

List of abbreviations see pages 30 and 31

CROSS REFERENCE LIST: NATIONAL STANDARDS - HUBER+SUHNER® CABLE GROUPS:

BS 2316	Group		CCTU 10-01-A	Group		VG 95216	Group	
(British Standard)	Cable entry crimp	Cable entry clamp	(French Standard)	Cable entry crimp	Cable entry clamp	(German Standard)	Cable entry crimp	Cable entry clamp
URM 43	● U7	● U7	KX 3A	● U2	● U2	T0, 3L/1	● U1	● U1
URM 67	● U29	● U28	KX 6A	● U16	● U15	T0, 5L/2	● U2	● U2
URM 72	–	● U7	KX 15	● U7	● U7	T2L/7	–	● U28
URM 76	● U7	● U7	KX 21A	● U1	● U1	P2L/7	● U29	● U28
URM 90	● U16	● U15	KX 22A	● U2	● U2			
URM 95	● U2	● U2	KX 23	● U11	● U10			
URM 102	–	● U28						
URM 110	● U1	● U1						
URM 112	● U32	● U31						



SERIES MMBX

MICRO MINIATURE BOARD CONNECTORS

DESCRIPTION

Modularity with a minimum space requirement is demanded for the existing and coming generation of systems (GSM 900 / 1800 / 1900, PCS, WCDMA, UMTS). To achieve this for all different systems, the smallest possible components must be used also for interconnections.


In order to reduce the variety of products and to achieve standardised systems (in other words: modularity), the HUBER+SUHNER Series MMBX™ (Micro Miniature Board Connector) contains a range of board and cable connectors which require a minimum of space. It offers all the necessary characteristics to obtain a unified design of the various systems.

CONTENTS

PAGE

Description	35
Interface dimensions	35
Interface dimensions in mm / inches	35
Technical data of cable connectors	37
Technical data of PCB connectors	38
Technical data of adaptors between series	39
Cable connectors	43
PCB connectors	45
Adaptors within-series	48
Tools	50

INTERFACE DIMENSIONS



INTERFACE DIMENSIONS (MM / INCHES)


Adaptors Within-Series

	min. / max. mm	min. / max. inches
T	3.70 nom.	.146 nom.
U	0.95 nom.	.037 nom.
V	0.70 nom.	.028 nom.
W	3.65 nom.	.144 nom.
X	2.05 nom.	.081 nom.
Y	0.80 nom.	.032 nom.


- [1] Slotted and flared to meet electrical and mechanical requirements
- [2] Dimension to meet electrical and mechanical requirements

IP rating (interface, mated) IP50

Jack (female)




Plug (male)



MMBX Connectors:

	min. mm	min. inches	max. mm	max. inches
A	5.00 nom.	.197 nom.	5.00 nom.	.197 nom.
B	3.68	.145	3.71	.146
C	2.25	.089	2.30	.091
D	0.98	.039	1.01	.040
E	1.85 nom.	.073 nom.	1.85 nom.	.073 nom.
F	2.10 nom.	.083 nom.	2.10 nom.	.083 nom.
G	—	—	1.80	.071
H	1.55	.061	1.75	.069
I	0.90	.035	—	—
K	0.75 nom.	.030 nom.	0.75 nom.	.030 nom.
L	0	0	—	—
M	1.45	.057	—	—
N	2.50 nom.	.098 nom.	2.50 nom.	.098 nom.
O	3.70 nom.	.146 nom.	3.70 nom.	.146 nom.
P	0.95 nom.	.037 nom.	0.95 nom.	.037 nom.
Q	1.85 nom.	.073 nom.	1.85 nom.	.073 nom.
R	0.50 nom.	.020 nom.	0.50 nom.	.020 nom.
S	0.10 nom.	.004 nom.	0.10 nom.	.004 nom.

- ① Slotted and flared to meet electrical and mechanical requirements
- ② Dimension to meet electrical and mechanical requirements



Direct interconnection with excellent electrical and mechanical properties.

TECHNICAL DATA OF CABLE CONNECTORS

ELECTRICAL DATA	CECC 22000	REQUIREMENTS
for cable groups		Y 11, U2, U4
Impedance		50 Ω
Frequency range		DC ... 12.4 GHz
Dielectric withstanding voltage (at sea level)	4.4.5	750 V rms, 50 Hz
Working voltage (at sea level) - unmated	IEC 169-1 14.6.1	250 V rms, 50 Hz (calculated)
Working voltage (at 21'000 m/70'000 ft.) - mated and unmated	Appendix C	42 VAC 50 Hz (calculated)
Insulation resistance	4.4.4	$\geq 1 \text{ G}\Omega$
Contact resistance - centre contact - outer contact	4.4.2 4.4.3	$\leq 5 \text{ m}\Omega$ $\leq 1 \text{ m}\Omega$

MECHANICAL DATA	CECC 22000	REQUIREMENTS
Engagement force	4.5.4	max. 30 N / max. 6.7 lbs
Disengagement force	4.5.4	8 - 30 N / 1.8 - 6.7 lbs
Contact captivation	4.5.2	$\geq 10 \text{ N}$ / 2.3 lbs
Cable retention force	4.5.5	see pages 28 - 34
Durability (matings)	4.7.1	100

ENVIRONMENTAL DATA	CECC 22000 TEST CONDITIONS	EQUIVALENT MIL TEST CONDITIONS
Temperature range		- 55° C ... + 155° C / - 67 °F ... + 311 °F
Climatic category	→ 55 / 155 / 21	
Thermal shock	4.6.7 → IEC 68-2-14 Na	MIL-STD-202, Method 107 G, Condition B1
Moisture resistance	4.6.6 → IEC 68-2-3 Ca	MIL-STD-202, Method 106 F
Corrosion	4.6.10 → IEC 68-2-11 Ka	MIL-STD-202, Method 101, Condition B
Vibration	4.6.3 → IEC 68-2-6 Fc	MIL-STD-202, Method 204 D, Condition A

MATERIAL DATA		
CONNECTOR PARTS	MATERIAL	PLATING
Centre contact	copper-beryllium alloy	SUCOPRO /gold
Outer contact	copper-beryllium alloy	SUCOPRO
Body	brass	SUCOPRO
Crimp ferrules	E-copper	SUCOPRO/gold
Insulators	PTFE / PFA	

TECHNICAL DATA OF PCB CONNECTORS - BOARD-TO-BOARD

ELECTRICAL DATA	CECC 22000	REQUIREMENTS	REQUIREMENTS
		Nominal PCB distance 6.7 mm / .264 in.	Nominal PCB distance 11.7 mm / .461 in.
Impedance		50 Ω	
Frequency range		DC ... 12.4 GHz	
Dielectric withstanding voltage (at sea level)	4.4.5	1 kV rms, 50 Hz	
Working voltage (at sea level)	IEC 169-1 11.6.1	$\leq$ 330 V rms, 50 Hz	
Insulation resistance	4.4.4	$\geq$ 1 G Ω	
Contact resistance			
- centre contact	4.4.2	$\leq$ 5 m Ω	
- outer contact	4.4.3	$\leq$ 1 m Ω	

MECHANICAL DATA	CECC 22000	REQUIREMENTS 6 SLOTS	REQUIREMENTS 4 SLOTS
Engagement force (Slideside)	4.5.4	< 15 N / 3.4 lbs	< 20 N / 4.5 lbs
Disengagement force (Slideside)	4.5.4	< 15 N / 3.4 lbs	< 20 N / 4.5 lbs
Contact captivation	4.5.2	10 N / 2.3 lbs	
Durability (matings)	4.7.1	100	

RETURN LOSS	REQUIREMENTS		
Nominal board-to-board distance	6.7 mm / .2638 in.	11.7 mm / .4606 in.	20.0 mm / .7874 in.
Typical return loss	board-to-board = two PCB-connector + one adaptor (without termination to PCB)		
- up to 2.5 GHz	26 dB	26 dB	26 dB
- 2.5 up to 6 GHz	25 dB	19 dB	19 dB

PROCESSING DATA	REQUIREMENTS
Adherent to the print	
- shearing	150 N / 33.7 lbs
- pulling (vertical to PCB)	150 N / 33.7 lbs

MATERIAL DATA		
CONNECTOR PARTS	MATERIAL	PLATING
Centre contact	brass	SUCOPRO / gold
Outer contact	bronze	SUCOPRO
Body	brass	SUCOPRO
Insulators	LCP / PTFE / PFA	

ENVIRONMENTAL DATA	CECC 22000 TEST CONDITIONS	EQUIVALENT MIL TEST CONDITIONS
Temperature range		- 55° C ... + 155° C / - 67 °F ... + 311 °F
Climatic category	→ 55 / 155 / 21	
Thermal shock	4.6.7 → IEC 68-2-14 Na	MIL-STD-202, Method 107 G, Condition B1
Moisture resistance	4.6.6 → IEC 68-2-3 Ca	MIL-STD-202, Method 106 F
Corrosion	4.6.10 → IEC 68-2-11 Ka	MIL-STD-202, Method 101, Condition B
Vibration	4.6.3 → IEC 68-2-6 Fc	MIL-STD-202, Method 204 D, Condition A

TECHNICAL DATA OF ADAPTORS BETWEEN SERIES

ELECTRICAL DATA	CECC 22000	REQUIREMENTS		
Impedance		50 Ω		
Frequency range		DC ... 12.4 GHz		
Typical return loss (mated pair)		DC – 2.5 GHz 32 dB	2.5 – 6 GHz 30 dB	6 – 12.4 GHz 16 dB
Dielectric withstanding voltage (at sea level)	4.4.5	1 kV rms, 50 Hz		
Working voltage (at sea level)	IEC 169-1 11.6.1	≤ 330 V rms, 50 Hz		
Insulation resistance	4.4.4	≥ 1 GΩ		
Contact resistance				
- centre contact	4.4.2	≤ 5 mΩ		
- outer contact	4.4.3	≤ 1 mΩ		

MECHANICAL DATA	CECC 22000	REQUIREMENTS
Engagement force (MMBX)	4.5.4	max. 30 N / max. 6.7 lbs
Disengagement force (MMBX)	4.5.4	8 - 30 N / 1.8 - 6.7 lbs
Durability (matings)	4.7.1	500

MATERIAL DATA		
CONNECTOR PARTS	MATERIAL	PLATING
MMBX centre contact	copper-beryllium alloy	SUCOPRO / gold
MMBX outer contact	brass / copper-beryllium	SUCOPRO
MMBX body	brass / copper-beryllium	SUCOPRO
MMBX insulators	LCP / PTFE / PFA	

ENVIRONMENTAL DATA	CECC 22000 TEST CONDITIONS	EQUIVALENT MIL TEST CONDITIONS
Temperature range		- 55° C ... + 155° C / - 67 °F ... + 311 °F
Climatic category	→ 55 / 155 / 21	
Thermal shock	4.6.7 → IEC 68-2-14 Na	MIL-STD-202, Method 107 G, Condition B1
Moisture resistance	4.6.6 → IEC 68-2-3 Ca	MIL-STD-202, Method 106 F
Corrosion	4.6.10 → IEC 68-2-11 Ka	MIL-STD-202, Method 101, Condition B
Vibration	4.6.3 → IEC 68-2-6 Fc	MIL-STD-202, Method 204 D, Condition A

Some connectors may have a specification that differs from the above mentioned data.


The products are designed and guaranteed to pass the above mentioned test procedures. Any additional or different requirement arising from specific applications or environmental conditions which is not covered by these test procedures is subject to request.

MMBX APPLICATION INSTRUCTION FOR PCB AND PANEL DISTANCES

The MMBX connector range offers a wide variety of interconnection solutions for blind mate PCB and panel applications. The formulas below provides a guideline to help to quickly determine; the board to board distance (x) for a combination of two board connectors and an adaptor, the minimum board to board or panel distance and the required adaptor length (a).

The parameters used in these formulas can be found on the MMBX connector outline drawings.

Example for board to board connection



Formula

Distance $x = a + b + c + (2 * d)$
 Min. distance $x = e + f + 0.5 \text{ mm}$
 Adapter length $a = x - b - c - (2 * d)$


Variables

x = Board to board distance
 a = adaptor length
 b = interface reference connector
 c = interface reference connector
 d = gap for adaptor movement
 e = height connector
 f = height connector

Calculation of example

Board to board distance $x = a + b + c + (2 * d) = 10 \text{ mm} + 0.6 \text{ mm} + 0.6 \text{ mm} + (2 * 0.4 \text{ mm}) = \underline{12 \text{ mm}}$
 Min. board to board distance $x = e + f + 0.5 \text{ mm} = 3.1 \text{ mm} + 4.1 \text{ mm} + 0.5 \text{ mm} = \underline{7.7 \text{ mm}}$
 Adapter length $a = x - b - c - (2 * d) = 12 \text{ mm} - 0.6 \text{ mm} - 0.6 \text{ mm} - (2 * 0.4 \text{ mm}) = \underline{10 \text{ mm}}$

Example for panel to panel connection



Note: For panel connectors the interface reference (b, c) needs to be subtracted.

Calculation of example

Panel to panel distance $x = a - b - c + (2 * d) = 4.7 \text{ mm} - 1.47 \text{ mm} - 1.47 \text{ mm} + (2 * 0.4 \text{ mm}) = \underline{2.56 \text{ mm}}$

Min. panel to panel distance $x = e + f + 0.5 \text{ mm} = 1 \text{ mm} + 1 \text{ mm} + 0.5 \text{ mm} = \underline{2.5 \text{ mm}}$

Adaptor length $a = x + b + c - (2 * d) = 2.56 \text{ mm} + 1.47 \text{ mm} + 1.47 \text{ mm} - (2 * 0.4 \text{ mm}) = \underline{4.7 \text{ mm}}$


CABLE CONNECTORS

Straight cable plugs (male)

> for HUBER+SUHNER® MULTIFLEX

> cable entry soldered

> centre contact soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction
11_MMBX-50-2-4/111_NE	84026769	Y11 (Multiflex 86)	single	27534
11_MMBX-50-2-4/111_NH	23033280	Y11 (Multiflex 86)	bulk 100 pcs.	27534

> for flexible cables

> HUBER+SUHNER® full crimp




Fig. 1




Fig. 2



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Fig.
11_MMBX-50-1-1/111_NE	23001743	U1 (EF 178)	single	27350	0.54 / A	1
11_MMBX-50-2-1/111_NE	23001745	U2 (EF 316)	single	27351	1 / A	2
11_MMBX-50-2-2/111_NE	23001744	U4 (EF 316 D)	single	27351	1 / A	2

Right angle cable plugs (male)

> for microwave cables

> cable entry soldered

> centre contact soldered




Fig. 1





Fig. 2



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Fig.
16_MMBX-50-1-2/111_NH	21000174	Y2 (EZ 47)	bulk 100 pcs.	0000247073	1
16_MMBX-50-2-4/111_NE	84026740	Y11 (Multiflex 86)	single	27533	2
16_MMBX-50-2-4/111_NH	23033281	Y11 (Multiflex 86)	bulk 100 pcs.	27533	2

- > for flexible cables
- > cable entry crimp
- > centre contact soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
16_MMBX-50-1-1/111_NE	23001748	U1 (EF 178)	single	27352	A
16_MMBX-50-2-1/111_NE	23001747	U2 (EF 316)	single	27352	A
16_MMBX-50-2-1/111_NH	84018554	U2 (EF 316)	bulk 100 pcs.	27352	A
16_MMBX-50-2-2/111_NE	23001746	U4 (EF 316 D)	single	27352	A
16_MMBX-50-2-2/111_NH	84028931	U4 (EF 316 D)	bulk 100 pcs.	27352	A

RECEPTACLES WITH SOLDER END

Receptacles, jacks (female)

- > bulkhead mounted




Fig. 1




Fig. 2




HUBER+SUHNER type	Item no.	Packaging	Assembly style	Fig.
22_MMBX-50-0-1/111_NE	23008312	single	screwed-in	1
22_MMBX-50-0-2/111_NY	84005177	bulk 100 pcs.	pressed-in	2

PCB CONNECTORS

Straight PCB plugs (male)

> surface mount type SMT



HUBER+SUHNER type	Item no.	Packaging	Soldering pad	Notes
81_MMBX-S50-0-1/111_NM	23001780	tape and reel	ML 122	
81_MMBX-S50-0-1/111_NH	23001781	bulk 100 pcs.	ML 122	
81_MMBX-S50-0-1/111_NE	23001782	single	ML 122	




Fig. 1




Fig. 2



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes	Fig.
81_MMBX-50-0-2/111_NM	23001776	tape and reel	ML 15		1
81_MMBX-50-0-2/111_NH	23001778	bulk 100 pcs.	ML 15		1
81_MMBX-50-0-2/111_NE	23001779	single	ML 15		1
81_MMBX-50-0-11/111_NM	23028072	tape and reel	ML 15		2

Straight PCB jacks (female)

> surface mount type SMT




Fig. 1




Fig. 2




Fig. 3

HUBER+SUHNER type	Item no.	Packaging	Soldering pad	Notes	Fig.
82_MMBX-S50-0-1/111_NM	23001783	tape and reel	ML 122	pull-in range 0.65 mm / .0256 in.	1
82_MMBX-S50-0-1/111_NH	23001784	bulk 100 pcs.	ML 122	pull-in range 0.65 mm / .0256 in.	1
82_MMBX-S50-0-1/111_NE	23001785	single	ML 122	pull-in range 0.65 mm / .0256 in.	1
82_MMBX-S50-0-3/111_NM	23031931	tape and reel	ML 122	pull-in range 0.95 mm / .0374 in.	2
82_MMBX-S50-0-3/111_NH	23011273	bulk 100 pcs.	ML 122	pull-in range 0.95 mm / .0374 in.	2
82_MMBX-S50-0-3/111_NE	23015527	single	ML 122	pull-in range 0.95 mm / .0374 in.	2
82_MMBX-S50-0-13/111_NM	23041511	tape and reel	ML 122	pull-in range 1.80 mm / .0709 in.	3
82_MMBX-S50-0-13/111_NH	23036608	bulk 100 pcs.	ML 122	pull-in range 1.80 mm / .0709 in.	3
82_MMBX-S50-0-13/111_NE	84032435	single	ML 122	pull-in range 1.80 mm / .0709 in.	3

Straight PCB jacks (female)




Fig. 1




Fig. 2






Fig. 3

HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes	Fig.
82_MMBX-50-0-2/111_NM	23001786	tape and reel	ML 15	pull-in range 0.65 mm / .0256 in.	1
82_MMBX-50-0-2/111_NH	23001787	bulk 100 pcs.	ML 15	pull-in range 0.65 mm / .0256 in.	1
82_MMBX-50-0-2/111_NE	23001788	single	ML 15	pull-in range 0.65 mm / .0256 in.	1
82_MMBX-50-0-4/111_NH	23013667	bulk 100 pcs.	ML 15	pull-in range 0.95 mm / .0374 in.	2
82_MMBX-50-0-14/111_NH	23038051	bulk 100 pcs.	ML 15	pull-in range 1.80 mm / .0709 in.	3
82_MMBX-50-0-14/111_NE	84032421	single	ML 15	pull-in range 1.80 mm / .0709 in.	3

Straight PCB jacks (female), edge-mount




HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
92_MMBX-550-0-12/111_NM	23038620	tape and reel	ML 147	
92_MMBX-550-0-12/111_NE	84019159	single	ML 147	

ADAPTORS WITHIN-SERIES

Straight adaptors


> plug to plug (male)



HUBER+SUHNER type	Item no.	Packaging	Board-to-board distance	Adaptor length X	Min. pull-in range
32_MMBX-50-0-1/111_NE	23001749	single	6.7 mm/.264 in.	4.7 mm/.158 in.	0.65 mm/.026 in.
32_MMBX-50-0-1/111_NY	84028418	industrial 200 pcs.	6.7 mm/.264 in.	4.7 mm/.158 in.	0.65 mm/.026 in.
32_MMBX-50-0-12/111_NH	84004734	industrial 100 pcs.	8.0 mm/.315 in.	6.0 mm/.236 in.	0.95 mm/.037 in.
32_MMBX-50-0-11/111_NE	23040373	single	9.0 mm/.354 in.	7.0 mm/.276 in.	0.95 mm/.037 in.
32_MMBX-50-0-4/111_NE	23010564	single	10.0 mm/.394 in.	8.0 mm/.315 in.	1.80 mm/.071 in.
32_MMBX-50-0-4/111_NY	23038658	industrial 300 pcs.	10.0 mm/.394 in.	8.0 mm/.315 in.	1.80 mm/.071 in.
32_MMBX-50-0-8/111_NE	23030066	single	11.65 mm/.459 in.	9.65 mm/.380 in.	1.80 mm/.071 in.
32_MMBX-50-0-13/111_NE	84031096	single	12.0 mm/.472 in.	10.0 mm/.417 in.	1.80 mm/.071 in.
32_MMBX-50-0-5/111_NE	84026915	single	14.0 mm/.551 in.	12.0 mm/.472 in.	1.80 mm/.071 in.
32_MMBX-50-0-5/111_NY	23011920	industrial 200 pcs.	14.0 mm/.551 in.	12.0 mm/.472 in.	1.80 mm/.071 in.
32_MMBX-50-0-10/111_NY	23034946	industrial 200 pcs.	15.0 mm/.591 in.	13.0 mm/.512 in.	1.80 mm/.071 in.
32_MMBX-50-0-6/111_NE	23022532	single	16.5 mm/.650 in.	14.5 mm/.571 in.	external guidance needed
32_MMBX-50-0-6/111_NH	84024341	industrial 100 pcs.	16.5 mm/.650 in.	14.5 mm/.571 in.	external guidance needed
32_MMBX-50-0-9/111_NH	23033418	industrial 100 pcs.	18.0 mm/.709 in.	16.0 mm/.630 in.	external guidance needed
32_MMBX-50-0-3/111_NE	23023073	single	20.0 mm/.787 in.	18.0 mm/.709 in.	external guidance needed
32_MMBX-50-0-15/111_NY	84033819	industrial 100 pcs.	21.2 mm/.835 in.	19.2 mm/.755 in.	external guidance needed
32_MMBX-50-0-14/111_NY	84010338	industrial 100 pcs.	32.7 mm/1.287 in.	30.7 mm/1.207 in.	external guidance needed

Bulkhead adaptors

> plug to plug (male)



HUBER+SUHNER type	Item no.	Packaging	Interface	Notes
35_MMBX-50-0-1/111_NE	23007587	single	slide-slide	
35_MMBX-50-0-1/111_NH	84015150	bulk 100 pcs.	slide-slide	

> plug to plug (male)




Fig. 1




Fig. 2

HUBER+SUHNER type	Item no.	Packaging	Interface	Notes	Fig.
35_MMBX-50-0-5/111_NY	23028242	industrial 75 pcs.	slide-slide		1
35_MMBX-U50-0-9/113_NY	84023360	industrial 50 pcs.	slide-slide	extended axial float	2

TOOLS

Adaptor assembly and disassembly tool



Fig. 1



Fig. 2

HUBER+SUHNER type	Item no.	Packaging	Operating instruction	Fig.
74_Z-0-0-437	23023494	single	27378	1
74_Z-0-0-557	84032418	single	0000246815	2



SERIES MMCX

MICRO MINIATURE CONNECTORS

DESCRIPTION

HUBER+SUHNER® MMCX connectors are intended for use in applications where the smallest dimensions have to be achieved. These connectors can be used in applications from DC to 6 GHz.

The reliable "snap-on" coupling mechanism ensures that the electrical parameters are consistently reproduced. Due to its non-slotted outer contact, the MMCX series provides a low RF-leakage.

In addition, HUBER+SUHNER SMT MMCX connectors fully meet today's SMT (Surface Mount Technology) requirements with superior design, material selection and packaging.


The HUBER+SUHNER SMT connectors are suitable to all reflow-soldered SMT-PCBs where impedance matching or screened signal transmission is necessary

CONTENTS

PAGE

Description	51
Interface dimensions	51
Interface dimensions in mm / inches	51
Technical data	52
Cable connectors	54
Receptacles with solder end	58
PCB connectors	58
MMCX "cube"-connectors	61
Packaging MMCX "cube"-connectors	62
Application notes MMCX "cube"-connectors	63
Packaging for MMCX edge mount	66
Application notes for MMCX edge mount	66

INTERFACE DIMENSIONS



INTERFACE DIMENSIONS (MM / INCHES)

	Plug		Jack	
	min.	max.	min.	max.
A	—	2.40/.094	2.41/.095	—
B	2.70/.106	—	—	2.65/.104
C	0.00/.000	0.25/.010	0.90/.035	1.20/.047
D	1.23/.048	—	0.70/.028 nom.	
E	1.58/.062	1.62/.064	1.40/.055	—
F	1.23/.048	—	3.00/.118	3.04/.120
G*	0.38/.015	0.42/.017	2.88/.113	2.92/.115
H	—	0.20/.008	1.57/.062	1.63/.064

*	Jack		
G	2.88/.113	2.90/.114	2.92/.115
I	2.34/.092	2.30/.091	2.26/.089

Note: I is related to G

IP rating (interface, mated) IP50

TECHNICAL DATA

ELECTRICAL DATA	CECC 22000	TEST REQUIREMENTS
Impedance		50 Ω
Frequency range		DC ... 6 GHz
Dielectric withstanding voltage (at sea level)	4.4.5	500 V rms, 50 Hz
Working voltage (at sea level)		≤ 170 V rms, 50 Hz
Insulation resistance	4.4.4	$\geq 10^3$ M Ω / ≥ 500 M Ω ¹⁾
Contact resistance		
- centre contact	4.4.2	≤ 5.0 m Ω / ≤ 10 m Ω ¹⁾
- outer contact	4.4.3	≤ 2.5 m Ω / ≤ 5 m Ω ¹⁾
VSWR (mated pair)		(typical values)
- up to 4 GHz	4.4.1	≤ 1.15
- 4 up to 6 GHz		≤ 1.40 for cable connectors, see table below
RF leakage (measured at 1 GHz)		
- connectors for flexible cables	4.4.8	≥ 60 dB
- connectors for semi-rigid cables		≥ 70 dB

1) valid for MMCX "Cube"-connectors only.

TYPICAL VSWR	FREQUENCY RANGE			CABLE GROUP
CONNECTOR TYPE	1 GHZ	2.5 GHZ	6 GHZ	
straight connectors	1.03	1.08	1.12	Y3, Y11
	1.04	1.08	1.12	U1
right angle connectors	1.03	1.08	1.13	Y3, Y11
	1.07	1.12	1.25	U1

Other connectors and cables on request

MECHANICAL DATA	CECC 22000	REQUIREMENTS
Engagement force	4.5.4	≤ 15 N / 3.4 lbs
Disengagement force	4.5.4	6 N ... 15 N / 1.4 lbs ... 3.4 lbs
Contact captivation	4.5.2	≥ 10 N / 2.3 lbs
Cable retention force ²⁾	4.5.5	see pages 28 – 34
Durability (matings)	4.7.1	≥ 500

2) value considers maximum load of the cables without irreversible variations of specifications.

ENVIRONMENTAL DATA	CECC 22000 TEST CONDITIONS	EQUIVALENT MIL TEST CONDITIONS
Temperature range		- 55° C ... + 155° C / - 67 °F ... + 311 °F
Climatic category	4.6.5 → 55 / 155 / 21	
Thermal shock	4.6.7 → IEC 68-2-14 Na	MIL-STD-202, Method 107, Condition F
Moisture resistance	4.6.6 → IEC 68-2-3 Ca	MIL-STD-202, Method 106
Corrosion	4.6.10 → IEC 68-2-11 Ka	Saltspray test acc. to MIL-STD-202, Method 101, Condition B
Vibration	4.6.3 → IEC 68-2-6 Fc	MIL-STD-202, Method 204, Condition C

ENVIRONMENTAL DATA FOR "CUBE"-CONNECTORS ONLY	CECC 22000 TEST CONDITIONS	EQUIVALENT MIL TEST CONDITIONS
Temperature range		- 40°C ... + 90°C / - 40 °F ... + 194 °F
Climatic category	4.6.5 → 40 / 90 / 21	
Thermal shock	4.6.7	MIL-STD-202, Method 107, - 40°C/ 40 °F and + 90°C/ + 194 °F, 30 min. each
Moisture resistance	4.6.6	MIL-STD-202, Method 103, Condition B
Vibration	4.6.3	3 cycles in 3 opposite directions 10-150 Hz, 10-60 Hz: 0.75 mm/.030 in., 60-150 Hz: 10 G
Mechanical shock	4.6.4	MIL-STD-202, Method 213, Condition B

MATERIAL DATA		
CONNECTOR PARTS	MATERIAL	PLATING
Centre contact	copper-beryllium alloy, bronze	SUCOPRO / gold
Body	brass	SUCOPRO / gold
Crimp ferrules	brass	SUCOPRO / gold
Insulators	PTFE or PFA	

MATERIAL DATA FOR "CUBE"-CONNECTORS ONLY		
CONNECTOR PARTS	MATERIAL	PLATING
Leads Contact sockets	bronze	gold
Body	LCP (liquid crystal polymer), brass	gold
Outer contact	brass	gold
Insulators	LCP (liquid crystal polymer), PTFE or PFA	

PROCESSING DATA FOR "Cube"-CONNECTORS ONLY	TEST STANDARD	REQUIREMENT
Lead free reflow process	IPC/JEDECJ-STD-020C	recommended
Adherent to the print - shearing - pulling (vertical to PCB)		25 N/5.6 lbs 50 N/11.2 lbs


Some connectors may have a specification that differs from the above mentioned data.

The products are designed and guaranteed to pass the above mentioned test procedures. Any additional or different requirement arising from specific applications or environmental conditions which is not covered by these test procedures is subject to request.

CABLE CONNECTORS


Straight cable plugs (male)

- > for semi-rigid cables
- > cable entry soldered
- > centre contact crimped




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
11_MMCX-50-1-3/111_OE	22648893	Y2 (EZ 47)	single	9078	1
11_MMCX-50-2-1/111_OE	22645297	Y3, Y11 (EZ 86)	single	9170	1
11_MMCX-50-2-1/111_OH	22649039	Y3, Y11 (EZ 86)	bulk 100 pcs.	9170	1

- > for flexible cables
- > HUBER+SUHNER® full crimp



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
11_MMCX-50-1-1/111_OE	22645298	U1 (EF 178)	single	9169	1 / 2.67
11_MMCX-50-1-1/111_OH	22651666	U1 (EF 178)	bulk 100 pcs.	9169	1 / 2.67
11_MMCX-50-1-2/111_OE	22645296	U0 (K 01152-07)	single	9169	1 / 2.67
11_MMCX-50-1-2/111_OH	84027753	U0 (K 01152-07)	bulk 100 pcs.	9169	1 / 2.67

- > for flexible cables
- > HUBER+SUHNER® full crimp



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
11_MMCX-50-2-3/111_OE	22649899	U2 (EF 316)	single	9110	1 A
11_MMCX-50-2-3/111_OH	23000258	U2 (EF 316)	bulk 100 pcs.	9110	1 A
11_MMCX-50-2-4/111_OE	22649901	U4 (EF 316 D)	single	9110	1 A

Right angle cable plugs (male)

- > for semi-rigid cables
- > cable entry soldered
- > centre contact soldered




Fig. 1





Fig. 2



MMCX


HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Fig.
16_MMCX-50-1-12/111_OE	84030531	Y2 (EZ 47)	single	0000180777	1
16_MMCX-50-1-12/111_OH	21000178	Y2 (EZ 47)	bulk 100 pcs.	0000180777	1
16_MMCX-50-2-13/111_OE	84032569	Y3, Y11 (EZ 86)	single	0000214734	2
16_MMCX-50-2-13/111_OH	84007944	Y3, Y11 (EZ 86)	bulk 100 pcs.	0000214734	2

- > for flexible cables
- > cable entry crimp
- > centre contact soldered




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
16_MMCX-50-1-1/111_OE	22645955	U1 (EF 178)	single	9175	2.67
16_MMCX-50-1-1/111_OH	22648762	U1 (EF 178)	bulk 100 pcs.	9175	2.67

- > for flexible cables
- > cable entry crimp
- > centre contact soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
16_MMCX-50-1-2/111_OE	22645956	U0 (K 01152-07)	single	9175	2.67
16_MMCX-50-1-2/111_OH	22649009	U0 (K 01152-07)	bulk 100 pcs.	9175	2.67


- > for flexible cables
- > cable entry crimp
- > centre contact soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
16_MMCX-50-1-7/111_OE	22649900	Cable: K 01252 D	single	9128	A
16_MMCX-50-1-7/111_OH	23008430	Cable: K 01252 D	bulk 100 pcs.	9128	A
16_MMCX-50-2-2/111_OE	22649374	U4 (EF 316 D)	single	9128	A
16_MMCX-50-2-2/111_OH	22651401	U4 (EF 316 D)	bulk 100 pcs.	9128	A
16_MMCX-50-2-4/111_OE	22649433	U2 (EF 316)	single	9128	A
16_MMCX-50-2-4/111_OH	22649635	U2 (EF 316)	bulk 100 pcs.	9128	A


Straight cable jacks (female)

- > for semi-rigid cables
- > cable entry soldered
- > centre contact crimped



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
21_MMCX-50-2-1/111_OE	22645290	Y3, Y11 (EZ 86)	single	9170	1


- > for flexible cables
- > HUBER+SUHNER® full crimp



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
21_MMCX-50-1-1/111_OE	22645288	U1 (EF 178)	single	9169	1 / 2.67
21_MMCX-50-1-2/111_OE	22645289	U0 (K 01152-07)	single	9169	1 / 2.67


Straight bulkhead cable jacks (female)

- > for semi-rigid cables
- > cable entry soldered
- > centre contact crimped
- > front mounting



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole	Crimp insert
24_MMCX-50-2-1/111_OE	22645954	Y3, Y11 (EZ 86)	single	9170 / ML 68	1

- > for flexible cables
- > HUBER+SUHNER® full crimp
- > front mounting




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole	Crimp insert
24_MMCX-50-1-1/111_OE	22645952	U1 (EF 178)	single	9169 / ML 68	1 / 2.67
24_MMCX-50-1-1/111_OH	23000416	U1 (EF 178)	bulk 100 pcs.	9169 / ML 68	1 / 2.67

RECEPTACLES WITH SOLDER END


Receptacles, jacks (female)

> bulkhead mounted



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
22_MMCX-50-0-1/111_OE	22645951	single	ML 68	
22_MMCX-50-0-1/111_OH	22660126	bulk 100 pcs.	ML 68	


> bulkhead mounted



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
22_MMCX-50-0-4/111_OH	22660282	bulk 100 pcs.	M 3.5 × 0.35	


PCB CONNECTORS

Straight PCB plugs (male)



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
81_MMCX-50-0-1/111_OE	22646298	single	ML 44	without stand-off


Straight PCB jacks (female)



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
82_MMCX-50-0-1/111_NE	22645958	single	ML 44	without stand-off
82_MMCX-50-0-1/111_NH	22648469	bulk 100 pcs.	ML 44	without stand-off

Jacks for horizontal applications

> edge mount



HUBER+SUHNER type	Item no.	Packaging	PCB Layout	Notes
82_MMCX-S50-0-2/111_KE	22648789	single	see application notes on page 66	
82_MMCX-S50-0-2/111_KH	22649680	bulk 100 pcs.	see application notes on page 66	
82_MMCX-S50-0-2/111_KG	22649679	tape and reel	see application notes on page 66	blister tape containing 750 pcs.
82_MMCX-S50-0-2/111_KL-1	23041776	tape and reel	see application notes on page 66	blister tape containing 1500 pcs.

Straight PCB jacks (female)




Fig. 1





Fig. 2




HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes	Fig.
82_MMCX-50-0-8/111_OE	22652153	single	ML 167	throughhole mount	1
82_MMCX-50-0-8/111_OM	22660270	tape and reel	ML 167	throughhole mount	1
82_MMCX-50-0-18/111_OM	23023564	tape and reel	ML 130	surface mount technology	2

Right angle PCB plugs (male)



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
84_MMCX-50-0-1/111_OH	22658819	bulk 100 pcs.	ML 44	without stand-off


Right angle PCB jacks (female)



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
85_MMCX-50-0-1/111_OE	22645968	single	ML 44	without stand-off
85_MMCX-50-0-1/111_OH	22646636	bulk 100 pcs.	ML 44	without stand-off

MMCX "CUBE"-CONNECTORS

Jack for straight (vertical) applications



HUBER+SUHNER type	Item no.	Packaging	PCB Layout	Notes
82_MMCX-S50-0-55/119_OM	84021645	tape and reel	see application notes on page 63	blister tape containing 1500 pcs.


Jack for right angle (horizontal) applications



HUBER+SUHNER type	Item no.	Packaging	PCB Layout	Notes
85_MMCX-S50-0-55/119_OM	84021646	tape and reel	see application notes on page 63	blister tape containing 1500 pcs.

Combination jack

for straight (vertical) or right angle (horizontal) applications



HUBER+SUHNER type	Item no.	Packaging	PCB Layout	Notes
90_MMCX-S50-0-55/119_OE	84021577	single	see application notes on page 63	
90_MMCX-S50-0-55/119_OH	84021269	bulk 100 pcs.	see application notes on page 63	

PACKAGING FOR MMCX "Cube"-CONNECTORS


Blister tape supply in accordance with IEC 286-3/EIA-481

For automated placement the connectors can be supplied on industry standard tape-and-reel. Depending on the application, they are packaged uniformly either for vertical or horizontal mounting.


Bulk supply in bags of one single or 100 pcs. (90_MMCX-S50-0-55)

This delivery form supports vertical or horizontal applications of the SMT MMCX connector.


It is suitable for manual or automated tube fed pick-and-place assembly.



1. straight (vertical) application (82_MMCX-S50-0-55)



2. right angle (horizontal) application (85_MMCX-S50-0-55)




Dimensions of blister carrier tape


The 16 mm/.63 inches blister tape is delivered on reels of 330 mm/13 inches diameter and in tough cardboard boxes.

APPLICATION NOTES FOR MMCX "Cube"-CONNECTORS

Dimensions of mated pair and clearance for mating



Vertical mounting together with a right angle cable connector (can be rotated by 360°)



Horizontal mounting together with a straight cable connector

Appropriate operation

Surface-mounted electronic components exhibit a lower adherence force to the PCB than through-hole components.

The solder joints act as a mechanical fixation to the board and also function as the electrical contact.

Therefore the following has to be considered:

- Avoid forces from the cable of the mating connector to the surface mount connector.
Fix the cable sufficiently and in several places.
- Apply only axial forces during the mating and de-mating of the connector parts.


Non-axial forces – such as improper pulling at the cable entry or the cable portion of right angle mating connector – may cause excessive torque forces, which could result in damage to the solder joints.

Recommendation:

Application of the assembly tools 74_Z00-225 or 74_Z00-272 when disengaging right angle connectors. The tool 74_Z00-272 can simultaneously be used as a mating support for straight connectors.




Warning:
force must not be applied to this region



Recommended mounting pattern for MMCX “Cube”-connectors

MATERIAL FR 4 ($\epsilon_r = 4.6$)

-  pattern
 land (free of solder mask)




Microstrip line

PCB thickness	W	A	B	C
1.0 mm / .039 in.	1.8 mm / .071 in.	2.4 mm / .094 in.	12 mm / .472 in.	4.5 mm / .177 in.
1.6 mm / .063 in.	2.8 mm / .110 in.	4.8 mm / .189 in.	16 mm / .630 in.	5.0 mm / .197 in.

MATERIAL FR 4 ($\epsilon_r = 4.6$)

-  pattern
 land (free of solder mask)



Coplanar line

PCB thickness	W
0.8 mm / .031 in.	1.85 mm / .037 in.
1.0 mm / .039 in.	1.70 mm / .067 in.
1.2 mm / .047 in.	1.60 mm / .063 in.
1.6 mm / .063 in.	1.50 mm / .059 in.

Data valid for PCB material FR 4 ($\epsilon_r = 4.6$)

Automated pick-and-place for MMCX "Cube"-connectors

The MMCX "Cube" connectors can be processed on all state-of-the-art pick-and-place machines.

Application hints:

- Position of the connectors in the carrier tape

For the uniform orientation of the connectors refer to the figures in section "Packaging" (see page 62).

- Connector pick up by suction tip

1. Vertical mounting (82_MMCX-S50-0-55)

You have the choice between the contact of the suction tip on the outer edge of the outer conductor sleeve (convenient circular or square standard tip) or the insertion of a special tip into the connector interface.

When using an insertion tip consider that the outer conductor sleeve is only centered along one axis. A chuck alignment is possible only along this axis, which however is fully sufficient.

2. Horizontal mounting (85_MMCX-S50-0-55)

The suction tip meets an even surface and can be a suitable standard one:

- Vision system alignment inspection

The optical alignment inspection of the MMCX "cube" connector is supported by its asymmetrical contour in vertical as well as horizontal applications.

- Placement

For placing the connectors, the special arrangement of the leads must be considered. When applying a suction tip, the eccentricity of the outer conductor sleeve has to be taken into account.

Soldering

MMCX "Cube" connectors are compatible with reflow soldering methods.


Infrared soldering (IR, IC - max. 260°C/500 °F, 10s) is recommended.

Lead free solder pastes (96.5% tin, 3.5% silver) can be used with a thickness of 0.20 mm/.008 inches to 0.25 mm/.010 inches if stencilled or screened in accordance with our recommended mounting pattern. The stand-off of 0.4 mm/.016 inches enables an easy visual inspection of the soldered joint.


Cleaning

The stand-off also allows effective cleaning after soldering, if necessary. It is especially advantageous when applying aqueous solutions.

Because of the material used, MMCX "cube" connectors withstand solvents such as alcohols, halogenated hydrocarbons and azeotropic solutions, as well as water mixed with alkaline saponifiers.



Recommendation for an insertion tip




PACKAGING FOR MMCX EDGE MOUNT CONNECTORS

Blister tape supply in accordance with IEC 286-2/EIA-481


For automated placement the connectors can be supplied on industry standard type-and-reel.

Bulk supply in bags of 100 pcs.

This delivery form is suitable for manual or automated tube fed pick-and-place assembly.



straight (horizontal) application




dimensions of blister carrier tape


The 16 mm/.63 inches blister tape is delivered on reels of 330 mm/13 inches diameter, in a tough cardboard box.

APPLICATION NOTES FOR MMCX EDGE MOUNT

Dimensions of mated pair and clearance for mating



Horizontal mounting together with a right angle cable connector



Horizontal mounting together with a straight cable connector


Appropriate operation for MMCX edge mount

For appropriate operation the following has to be considered:

- Avoid forces from the cable of the mating connector to the surface mount connector.
Fix the cable sufficiently and in several places.
- Apply only axial forces during the mating and demating of the connector parts.

Non-axial forces – such as improper pulling at the cable entry or the cable portion of a right angle mating connector – may cause excessive torque forces, which could result in damage to the solder joints.

For further information about soldering or cleaning, please see page 65.




Recommended mounting pattern for MMCX edge mount

Material FR 4 ($\epsilon_r = 4.6$)

pattern

land (free of solder mask)




Microstrip line

Coplanar line

PCB thickness	a	b	c	d	e	f
0.8 mm / .031 in.	1.6 / .063	1.90 / .075		1.1 / .043	1.4 / .055	1.0 / .039
1.0 mm / .039 in.	1.4 / .055	1.75 / .069	0.3 / .012	1.2 / .047	1.8 / .071	0.9 / .035
1.6 mm / .063 in.	0.8 / .031	1.55 / .061	1.6 / .063	2.3 / .091	2.8 / .110	0.4 / .016

A FURTHER HUBER+SUHNER PRODUCT!

RF Power Switch - the fast, secure plug and play solution.



Details on the RF POWER SWITCH are to be found in the brochure
Item no. 84020735. Get your copy free of charge at
www.hubersuhner.com.






SERIES MMPX
PRECISION MICRO MINIATURE SNAP CONNECTORS

DESCRIPTION	CONTENTS	PAGE
The series MMPX offers smallest dimensions and unique electrical performance up to 65 GHz - including PCB links. The interface is based on MMCX dimensions. An established snap mechanism guarantees quick and reliable matings. The electrical bandwidth from DC to 65 GHz makes MMPX very interesting for a wide range of applications. Especially for EMC critical systems MMPX provides an excellent RF leakage due to the non slotted outer contact.	Description	69
	Technical data	70
	Cable connectors	72
	Print connectors	73

IP rating (interface, mated) IP50



TECHNICAL DATA

ELECTRICAL DATA	REQUIREMENTS		
Impedance	50 Ω		
Frequency range (for interface only)	DC ... 65 GHz		
Dielectric withstanding voltage (at sea level)	500 V rms, 50 Hz		
Working voltage (at sea level)	≤ 170 V rms, 50 Hz		
Insulation resistance	≥ 1 G Ω		
Contact resistance - centre contact - outer contact	≤ 5 m Ω ≤ 2 m Ω		
Return loss, typical	see table below		
RF leakage typical (MMPX interface only)	DC – 25 GHz 85 dB	25 – 50 GHz 65 dB	50 – 65 GHz 60 dB

RETURN LOSS	FREQUENCY RANGE		
CONNECTOR TYPE	DC – 26.5 GHZ	26.5 – 50 GHZ	50 – 65 GHZ
straight cable plug (male) ¹⁾	25 dB	17.5 dB	17.5 dB
Right angle cable plug (male) ¹⁾	25 dB	20 dB	20 dB
Straight cable plug (male), precision interface (air dielectric only) ¹⁾	25 dB	25 dB	25 dB
Straight PCB jack (female), SMT-version mated with a right angle cable plug	25 dB	15 dB	10 dB ²⁾
Edge mount PCB jack (female), SMT-version mated with a straight cable plug	22 dB	20 dB	20 dB

MECHANICAL DATA	REQUIREMENTS
Engagement force	max. 30 N / 6.7 lbs (typical 20 N / 4.4 lbs.)
Disengagement force ³⁾	max. 30 N / 6.7 lbs (typical 15 N / 3.3 lbs.)
Centre contact retention force PCB connectors	connector ≥ 2 N / 0.4 lbs. assembly ≥ 7 N / 1.5 lbs.
Durability (matings)	100

PROCESSING DATA PCB CONNECTORS	REQUIREMENTS	
Adherent to the print - shearing ²⁾ - pulling (vertical to PCB) ²⁾	straight PCB jack 90 N / 20.2 lbs. 50 N / 11.2 lbs. ¹⁾	edge mount PCB jack 70 N / 15.7 lbs. no standard value available

1) mated with straight cable jack (female)

2) valid for recommended PCB structure only

3) decoupling tool MMPX shall be used (74_Z-0-0-555)!

ENVIRONMENTAL DATA	REQUIREMENTS
Temperature range	- 65° C ... + 155° C / - 85 °F ... + 311 °F
Thermal shock	assembly - 55° C + 85 °C / - 67°F ... + 185°F connector - 65° C + 155 °C / - 85°F ... + 311 °F
Mechanical shock	100 g / 6 ms - max. interruption < 1 µs
Corrosion	Saltspray test
Vibration	20 g - max. interruption < 1 µs

MATERIAL DATA		
CONNECTOR PARTS	MATERIAL	PLATING
Centre contact	beryllium-copper alloy	gold over nickel
Body	brass	SUCOPRO / gold
Outer contact - female - male	copper-beryllium alloy brass	SUCOPRO/gold
Snap ring, male interface	copper-beryllium alloy	SUCOPRO/gold
Insulators	PTFE	

MATERIAL DATA FOR PCB CONNECTORS		
CONNECTOR PARTS	MATERIAL	PLATING
Centre contacts	copper-beryllium alloy	SUCOPRO/gold
Outer contact	copper-beryllium alloy	SUCOPRO/gold
Body	brass	SUCOPRO/gold
Insulators	PTFE	


Some connectors may have a specification that differs from the above mentioned data.

The products are designed and guaranteed to pass the above mentioned test procedures. Any additional or different requirement arising from specific applications or environmental conditions which is not covered by these test procedures is subject to request.

CABLE CONNECTORS


Straight cable plugs (male)

- > for semi-rigid cables
- > cable entry soldered
- > centre contact soldered
- > decoupling tool 74_Z-0-0-555 (recommended)
- > phase matched adaptors MMPX/PC1.85 and PC1.85/PC1.85 available on request



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Notes
11_MMPX-50-2-1/111_NE	84022225	Y3 (EZ 86)	single	0000236402	precision interface, air dielectric only


- > for semi-rigid, semi-flexible and flexible cables
- > cable entry soldered
- > centre contact plugged
- > decoupling tool 74_Z-0-0-555 (recommended)
- > phase matched adaptors MMPX/PC1.85 and PC1.85/PC1.85 available on request



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Notes
11_MMPX-50-2-2/111_NE	84022228	Y3, Y11 (EZ 86)	single	0000236450	

Right angle cable plugs (male)

- > for semi-rigid, semi-flexible and flexible cables
- > cable entry soldered
- > centre contact plugged
- > decoupling tool 74_Z-0-0-555 (recommended)
- > phase matched adaptors MMPX/PC1.85 and PC1.85/PC1.85 available on request




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Notes
16_MMPX-50-2-1/111_NE	84022227	Y3, Y11 (EZ 86)	single	0000236453	

Straight cable jacks (female)

> for semi-rigid, semi-flexible and flexible cables

- > cable entry soldered
- > centre contact soldered
- > decoupling tool 74_Z-0-0-555 (recommended)
- > phase matched adaptors MMPX/PC1.85 and PC1.85/PC1.85 available on request




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Notes
21_MMPX-50-2-1/111_NE	84022226	Y3, Y11 (EZ 86)	single	0000236433	

PCB CONNECTORS

Straight PCB jacks (female)

- > surface mount type SMT
- > decoupling tool 74_Z-0-0-555 (recommended)
- > phase matched adaptors MMPX/PC1.85 and PC1.85/PC1.85 available on request




HUBER+SUHNER type	Item no.	Packaging	PCB Layout*	Notes
82_MMPX-550-0-1/111_NM	84009130	Tape		Blister tape containing 10 pcs.
82_MMPX-550-0-1/111_NM	84009131	tape and reel		Blister tape containing 750 pcs.

* PCB layouts on request. Please contact our affiliate or agent in your country.


Straight PCB jacks (female), edge-mount

- > surface mount type SMT
- > decoupling tool 74_Z-0-0-555 (recommended)
- > phase matched adaptors MMPX/PC1.85 and PC1.85/PC1.85 available on request



HUBER+SUHNER type	Item no.	Packaging	PCB Layout*	Notes
92_MMPX-S50-0-1/111_NM	84009138	Tape		Blister tape containing 10 pcs.
92_MMPX-S50-0-1/111_NM	84009140	tape and reel		Blister tape containing 500 pcs.

- > surface mount type SMT
- > extra shielded for EMF sensitive applications
- > decoupling tool 74_Z-0-0-555 (recommended)
- > phase matched adaptors MMPX/PC1.85 and PC1.85/PC1.85 available on request



HUBER+SUHNER type	Item no.	Packaging	PCB Layout*	Notes
92_MMPX-S50-0-2/111_NE	84016110	single		

* PCB layouts on request. Please contact our affiliate or agent in your country.



SERIES MCX 50 Ω MICRO MINIATURE CONNECTORS

DESCRIPTION


HUBER+SUHNER MCX micro miniature snap-on connectors offer you an excellent blend of size, weight, durability and performance for applications such as mobile and fixed telecommunications, in GPS applications and in Test+Measurement systems for testing instruments and apparatus. They are designed for frequencies up to 6 GHz and are tested according to the international standard CECC 22220. And they meet all the high requirements that micro coaxial connectors are expected to satisfy today.

CONTENT

PAGE

Description	75
Interface Dimensions	75
Interface Dimensions in mm / inches	75
Technical Data	76
Cable Connectors	78
Receptacles with solder End	82
PCB Connectors	82

INTERFACE DIMENSIONS



INTERFACE DIMENSIONS (MM / INCHES)

	Plug		Jack	
	min.	max.	min.	max.
A	3.72/.146*	3.80/.150*	3.60/.142	3.70/.146
B	2.49/.098	2.59/.102	2.80/.110	—
C	0.48/.019	0.53/.021	3.75/.148	3.85/.152
D	4.15/.163	—	4.00/.157	4.12/.162
E	0.70/.028	0.75/.030	0.75/.030	0.85/.033
F	2.80/.110	3.20/.126	2.30/.091	2.80/.110
G	0.95/.037 nom.		0.95/.037 nom.	
H	—	0.30/.012	3.42/.135	3.48/.137
I	2.00/.079	2.07/.081	1.80/.071	1.98/.078
K	2.80/.110	3.20/.126	2.60/.102	2.80/.110

* prior to slotting

Interface dimensions conformable to the Standards:

International: IEC 60169-36
Europe: CECC 22220

IP rating (interface, mated) IP50

TECHNICAL DATA

ELECTRICAL DATA	CECC 22000	TEST REQUIREMENTS
Impedance		50 Ω
Frequency range		DC ... 6 GHz
Dielectric withstanding voltage (at sea level)	4.4.5	$\geq$ 750 V rms, 50 Hz (depending on cable)
Working voltage (at sea level) - unmated		$\geq$ 170 V rms, 50 Hz (depending on cable)
Working voltage (at 21 000 m / 70 000 ft.) - unmated		$\geq$ 42 V rms, 50 Hz (depending on cable)
Insulation resistance	4.4.4	$\geq$ 10 ⁴ M Ω
Contact resistance - centre contact - outer contact	4.4.2 4.4.3	$\leq$ 5 m Ω $\leq$ 1 m Ω
RF leakage (measured at 1 GHz) - connectors for flexible cables - connectors for semi-rigid cables	4.4.8	$\geq$ 60 dB $\geq$ 70 dB

MECHANICAL DATA	CECC 22000	REQUIREMENTS
Engagement force	4.5.1	$\leq$ 25 N / 5.6 lbs
Disengagement force	4.5.1	8 N ... 20 N / 1.8 lbs ... 4.5 lbs
Contact captivation	4.5.2	$\geq$ 10 N / 2.3 lbs
Cable retention force ¹⁾	4.5.5	see pages 28 – 34
Durability (matings)	4.7.1	$\geq$ 500

1) Value considers maximum load of the cables without irreversible variations of specifications.

ENVIRONMENTAL DATA	CECC 22000	EQUIVALENT MIL TEST CONDITIONS
Temperature range		- 55° C ... + 155° C / - 67 °F ... + 311 °F
Climatic category		IEC $\rightarrow$ 55 / 155 / 21
Thermal shock	4.6.7	MIL-STD-202, Method 107, Condition F
High temperature endurance test	4.7.2	MIL-STD-202, Method 108A, Condition D
Moisture resistance	4.6.6	MIL-STD-202, Method 106
Corrosion	4.6.10	Saltspray test acc. to MIL-STD-202, Method 101, Condition B
Vibration	4.6.3	MIL-STD-202, Method 204, Condition D

MATERIAL DATA		
CONNECTOR PARTS	MATERIAL	PLATING
Pin contacts	brass	SUCOPRO / gold
Body	brass	SUCOPRO / SUCOPLATE [®] / gold
Socket contacts	copper-beryllium alloy	SUCOPRO/gold
Outer contacts - plug - jack	copper-beryllium alloy brass	SUCOPRO/gold / SUCOPLATE [®]
Crimp ferrules	copper / brass	SUCOPRO/gold
Insulators	PTFE or PFA	

Other materials and platings on request.

Some connectors may have a specification that differs from the above mentioned data.

The products are designed and guaranteed to pass the above mentioned test procedures. Any additional or different requirement arising from specific applications or environmental conditions which is not covered by these test procedures is subject to request.


CABLE CONNECTORS

Straight cable plugs (male)

> for semi-rigid cables, SUCOFORM and MULTIFLEX cables

> cable entry soldered

> centre contact soldered




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction
11_MCX-50-1-14/111_NE	23032081	Y2 (EZ 47)	single	27413
11_MCX-50-2-19/111_NH	23032147	Y3, Y11 (EZ 86)	bulk 100 pcs.	27496
11_MCX-50-3-1/111_NE	23024699	Y12 (Sucoform 141)	single	0000200108
11_MCX-50-3-1/111_NH	84006763	Y12 (Sucoform 141)	bulk 100 pcs.	0000200108

> for flexible cables

> HUBER+SUHNER® full crimp

> taper sleeves see page 406




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
11_MCX-50-1-13/133_NH	22658307	U1 (EF 178)	bulk 100 pcs.	27316	1 A
11_MCX-50-1-13/111_NH	23002830	U1 (EF 178)	bulk 100 pcs.	27316	1 A
11_MCX-50-2-15/111_NE	84018641	U4 (EF 316 D)	single	27306	1 A
11_MCX-50-2-15/111_NH	23000440	U4 (EF 316 D)	bulk 100 pcs.	27306	1 A
11_MCX-50-2-15/133_NH	23000566	U4 (EF 316 D)	bulk 100 pcs.	27306	1 A
11_MCX-50-2-16/111_NE	84022831	U2 (EF 316)	single	27306	1 A
11_MCX-50-2-16/111_NH	22658275	U2 (EF 316)	bulk 100 pcs.	27306	1 A
11_MCX-50-2-16/133_NH	23000437	U2 (EF 316)	bulk 100 pcs.	27306	1 A

Right angle cable plugs (male)

> for semi-rigid cables, SUCOFORM and MULTIFLEX cables

- > cable entry soldered
- > centre contact soldered




MCX 50

HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction
16_MCX-50-1-11/111_NE	23024700	Y2 (EZ 47)	single	27495
16_MCX-50-1-11/111_NH	23032063	Y2 (EZ 47)	bulk 100 pcs.	27495
16_MCX-50-2-104/111_NH	23032067	Y3, Y11 (EZ 86)	bulk 100 pcs.	27308
16_MCX-50-3-8/111_NH	23012471	Y5, Y12 (EZ 141)	bulk 100 pcs.	27401


> for flexible cables

- > cable entry crimp
- > centre contact soldered
- > taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
16_MCX-50-1-7/111_NH	23000443	U1 (EF 178)	bulk 100 pcs.	27319	A
16_MCX-50-1-7/133_NH	22658308	U1 (EF 178)	bulk 100 pcs.	27319	A
16_MCX-50-2-11/133_NE	22660003	U4 (EF 316 D)	single	27102	A
16_MCX-50-2-11/133_NH	22650803	U4 (EF 316 D)	bulk 100 pcs.	27102	A
16_MCX-50-2-11/111_NH	23015358	U4 (EF 316 D)	bulk 100 pcs.	27102	A
16_MCX-50-2-14/133_NE	22660002	U2 (EF 316)	single	27102	A
16_MCX-50-2-14/133_NH	22660001	U2 (EF 316)	bulk 100 pcs.	27102	A
16_MCX-50-2-14/111_NH	23000445	U2 (EF 316)	bulk 100 pcs.	27102	A


- > for flexible cables
- > low profile
- > cable entry soldered
- > centre contact soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction
16_MCX-50-2-102/111_NH	23000454	U2 (EF 316)	bulk 100 pcs.	27307

Straight cable jacks (female)

- > for flexible cables
- > HUBER+SUHNER® full crimp
- > taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
21_MCX-50-1-11/111_NE	84023972	U1 (EF 178)	single	27317	1 A
21_MCX-50-1-11/111_NH	23005297	U1 (EF 178)	bulk 100 pcs.	27317	1 A
21_MCX-50-2-12/111_NE	23032052	U4 (EF 316 D)	single	27309	1 A
21_MCX-50-2-12/133_NH	22658278	U4 (EF 316 D)	bulk 100 pcs.	27309	1 A
21_MCX-50-2-13/111_NH	23005298	U2 (EF 316)	bulk 100 pcs.	27309	1 A
21_MCX-50-2-13/133_NH	22658279	U2 (EF 316)	bulk 100 pcs.	27309	1 A

Straight bulkhead cable jacks (female)

> for semi-rigid cables, SUCOFORM and MULTIFLEX cables

> cable entry soldered

> centre contact soldered




Fig. 1




Fig. 2



MCX 50


HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole	Fig.
24_MCX-50-1-3/111_NE	22641648	Y2 (EZ 47)	single	3100 / ML 11	1
24_MCX-50-2-3/111_NE	22543580	Y3, Y11 (EZ 86)	single	3100 / ML 11	2

☐ centre contact NOT captivated

> for flexible cables

> HUBER+SUHNER® full crimp

> taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole	Crimp insert
24_MCX-50-1-13/111_NH	23005299	U1 (EF 178)	bulk 100 pcs.	27317 / ML 11	1 A
24_MCX-50-1-13/133_NH	22658310	U1 (EF 178)	bulk 100 pcs.	27317 / ML 11	1 A
24_MCX-50-2-6/111_NH	23005300	U4 (EF 316 D)	bulk 100 pcs.	27309 / ML 11	1 A
24_MCX-50-2-7/111_NH	23000468	U2 (EF 316)	bulk 100 pcs.	27309 / ML 11	1 A

RECEPTACLES WITH SOLDER END

Receptacles, jacks (female)

- > bulkhead mounted
- > front mounting




Fig. 1




Fig. 2 (press-in)



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Fig.
22_MCX-50-0-2/111_NE	22640171	single	ML 11	1
22_MCX-50-0-2/111_NH	22646960	bulk 100 pcs.	ML 11	1
22_MCX-50-0-2/133_NE	22643633	single	ML 11	1
22_MCX-50-0-2/133_NH	22644433	bulk 100 pcs.	ML 11	1
22_MCX-50-0-19/111_NH	22652984	bulk 100 pcs.	ML 103	2
22_MCX-50-0-19/133_NH	23019789	bulk 100 pcs.	ML 103	2

PCB CONNECTORS

Straight PCB plugs (male)

- > with stand-off
- > 2.54 mm / .100 in. grid




Fig. 1




Fig. 2



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Fig.
81_MCX-50-0-6/111_NE	84023713	single	ML 15	1
81_MCX-50-0-6/111_NH	23005296	bulk 100 pcs.	ML 15	1
81_MCX-50-0-9/111_NH	23026871	bulk 100 pcs.	ML 15	2

Straight PCB jacks (female)

> 2.54 mm / .100 in. grid




Fig. 1




Fig. 2




MCX 50

HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes	Fig.
82_MCX-50-0-17/111_NH	23006209	bulk 100 pcs.	ML 15	without stand-off	1
82_MCX-50-0-19/111_NE	84018352	single	ML 15	with stand-off	2
82_MCX-50-0-19/111_NH	22658305	bulk 100 pcs.	ML 15	with stand-off	2
82_MCX-50-0-19/111_NM	23000573	tape and reel	ML 15	with stand-off	2


> 1.27 mm / .05 in. grid

> space saving version




HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
82_MCX-50-0-10/111_NE	22641649	single	ML 44	without stand-off
82_MCX-50-0-10/111_NH	22651980	bulk 100 pcs.	ML 44	without stand-off

> surface mount type SMT



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
82_MCX-50-0-29/111_NE	84018482	single	ML 120	
82_MCX-50-0-29/111_NH	23001527	bulk 100 pcs.	ML 120	
82_MCX-50-0-29/111_NM	22658306	tape and reel	ML 120	


- > surface mount type SMT
- > edge mount



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
82_MCX-S50-0-22/111_NE	22651467	single	ML 121	
82_MCX-S50-0-22/111_NM	84011207	tape and reel	ML 121	


Right angle PCB jacks (female)

- > 2.54 mm / .100 in. grid



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
85_MCX-50-0-16/111_NE	84018523	single	ML 15	
85_MCX-50-0-16/111_NH	23001545	bulk 100 pcs.	ML 15	
85_MCX-50-0-16/111_NM	84030779	tape and reel	ML 15	

- > surface mount type SMT



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
85_MCX-S50-0-25/111_NH	23005091	bulk 100 pcs.	ML 123	
85_MCX-S50-0-25/111_NM	84036471	tape and reel	ML 123	



SERIES MCX 75 Ω MICRO MINIATURE CONNECTORS

DESCRIPTION


HUBER+SUHNER MCX 75 Ω connectors are derived from the MCX 50 Ω series but have a characteristic impedance of 75 Ω . They offer outstanding electrical properties up to 6 GHz and allow the transmission of digital signals with high bit rates.

CONTENTS

PAGE

Description	85
Interface Dimensions	85
Interface Dimensions in mm / inches	85
Technical Data	86
Cable Connectors	88
PCB Connectors	89

INTERFACE DIMENSIONS



INTERFACE DIMENSIONS (MM / INCHES)

	Plug		Jack	
	min.	max.	min.	max.
A	3.72/.146*	3.80/.150*	3.60/.142	3.70/.146
B	2.49/.098	2.59/.102	2.80/.110	—
C	0.48/.019	0.53/.021	3.75/.148	3.85/.152
D	4.15/.163	—	4.00/.157	4.12/.162
E	0.70/.028	0.75/.030	0.75/.030	0.85/.033
F	2.80/.110	3.20/.126	2.30/.091	2.80/.110
G	0.83/.033 nom.		0.83/.033 nom.	
H			3.42/.135	3.48/.137

* prior to slotting

Interface dimensions conformable to the Standards:

Intermateable with MCX 50 Ω connectors acc. to CECC 22220.

IP rating (interface, mated) IP50

TECHNICAL DATA

ELECTRICAL DATA	TEST REQUIREMENTS
Impedance	75 Ω
Frequency range	DC ... 6 GHz
Dielectric withstanding voltage (at sea level)	$\geq$ 500 V rms, 50 Hz (depending on cable)
Working voltage (at sea level) - unmated	$\geq$ 170 V rms, 50 Hz (depending on cable)
Working voltage (at 21 000 m / 70 000 ft.) - unmated	$\geq$ 45 V rms, 50 Hz (depending on cable)
Insulation resistance	$\geq$ 10 ³ M Ω
Contact resistance - centre contact - outer contact	$\leq$ 5.0 m Ω $\leq$ 2.5 m Ω

MECHANICAL DATA	REQUIREMENTS
Engagement force	$\leq$ 25 N / 5.6 lbs
Disengagement force	8 N ... 20 N / 1.8 lbs ... 4.5 lbs
Contact captivation	$\geq$ 10 N / 2.3 lbs
Cable retention force ¹⁾	see pages 28 – 34
Durability (matings)	$\geq$ 500

1) Value considers maximum load of the cables without irreversible variations of specifications.

ENVIRONMENTAL DATA	TEST CONDITIONS
Temperature range	- 65° C ... + 165° C / - 85°F ... + 329 °F
Climatic category	IEC → 55 / 155 / 21
Thermal shock	MIL-STD-202, Method 107, Condition F
Moisture resistance	MIL-STD-202, Method 106
Corrosion	Saltspray test acc. to MIL-STD-202, Method 101, Condition B
Vibration	MIL-STD-202, Method 204, Condition D

MATERIAL DATA		
CONNECTOR PARTS	MATERIAL	PLATING
Pin contacts	brass	SUCOPRO / gold
Body	brass	SUCOPRO / SUCOPLATE [®]
Socket contacts	copper-beryllium alloy	SUCOPRO/gold
Outer contacts (resilient)	copper-beryllium alloy	SUCOPRO/gold
Crimp ferrules	copper	SUCOPLATE [®] / SUCOPRO
Insulators	PTFE or PFA	


Some connectors may have a specification that differs from the above mentioned data.

The products are designed and guaranteed to pass the above mentioned test procedures. Any additional or different requirement arising from specific applications or environmental conditions which is not covered by these test procedures is subject to request.

CABLE CONNECTORS

Straight cable plugs (male)


- > HUBER+SUHNER® full crimp
- > taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
11_MCX-75-2-1/113_NE	22646946	U5 (RG 187 A/U)	single	9196	1 A
11_MCX-75-2-6/113_NE	22650698	R8 (K 02253 D-02)	single	9196	1 A

Right angle cable plugs (male)


- > cable entry crimp
- > centre contact soldered
- > taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
16_MCX-75-2-5/133_NH	23008072	U5 (RG 187 A/U)	bulk 100 pcs.	27383	A

Straight bulkhead cable jacks (female)

- > HUBER+SUHNER® full crimp
- > "snap-on" panel mounting
- > taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly Instruction/ Mounting Hole	Crimp insert
24_MCX-75-2-1/113_NE	22646948	U5 (RG 187 A/U)	single	9196/ML 82	1 A

PCB CONNECTORS

Straight PCB jacks (female)

> 2.54 mm / .100 in.




Fig. 1




Fig. 2




MCX 75

HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes	Fig.
82_MCX-75-0-4/111_NE	84023729	single	ML 15	without stand-off	1
82_MCX-75-0-4/111_NH	23004043	bulk 100 pcs.	ML 15	without stand-off	1
82_MCX-75-0-5/111_NH	23004046	bulk 100 pcs.	ML 15	with stand-off	2

> surface mount type SMT


> edge mount



HUBER+SUHNER type	Item no.	Packaging	Notes
82_MCX-S75-0-2/111_NE	22651011	single	
82_MCX-S75-0-2/111_NH	84020046	bulk 100 pcs.	
82_MCX-S75-0-2/111_NM	84017665	Tape and Reel	

Right angle PCB jacks (female)

> 2.54 mm / .100 in.




HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
85_MCX-75-0-1/111_NE	22649202	single	ML 15	
85_MCX-75-0-1/111_NH	22650766	bulk 100 pcs.	ML 15	

A FURTHER HUBER+SUHNER PRODUCT!

SEMPER™ – the world's first self-extinguishing lightning protector



Details on this product are to be found in the brochure
Item no. 84015766. Get your copy free of charge at
www.hubersuhner.com.





SERIES SMB SUBMINIATURE CONNECTORS


DESCRIPTION

The HUBER+SUHNER subminiature connectors Series SMB, SMC, SMS have the same basic design. They only differ with regard to their coupling mechanism. HUBER+SUHNER SMB subminiature connectors are suitable for applications from DC up to 4 GHz.

Coupling mechanism:

The SMB snap-on mechanism provides a fast and reliable connection for applications with high packing density.

INTERFACE DIMENSIONS



CONTENTS

PAGE

Description	91
Interface dimensions	91
Interface dimensions in mm / inches	91
Technical data	92
Cable connectors	94
Receptacles with solder end	97
PCB connectors	99

SMB
SMC, SMS

INTERFACE DIMENSIONS (MM / INCHES)

	Plug		Jack	
	min.	max.	min.	max.
A	—	2.06/.081	2.08/.082	—
B	0.18/.007	0.94/.037	—	0.18/.007
C	0.18/.007	—	—	0.18/.007
D	2.97/.117	—	—	2.97/.117
E	3.58/.141	—	1.32/.052	—
F	3.58/.141	—	3.66/.144	3.71/.146
G	3.05/.120 nom.		0.48/.019	0.53/.021
H	—	1.63/.064	0.00/.000	—
I	—	—	3.05/.120 nom.	
K	—	—	3.33/.131	3.58/.141
L	—	—	1.65/.065	—

Note: HUBER+SUHNER SMB jacks are intermateable with HUBER+SUHNER SMS plugs.

Interface dimensions conformable to the Standards:

International:	IEC 60169-10
Europe:	CECC 22130
USA:	MIL-C-39012 SMB Interface MIL-STD-348A/311
Great Britain:	BS 9210 N 0007 SMB
France:	NFC 93562 series KMC

IP rating (interface, mated) IP50

TECHNICAL DATA

ELECTRICAL DATA	REQUIREMENTS
Impedance	50 Ω
Frequency range	DC ... 4 GHz
Dielectric withstanding voltage (at sea level)	750 V rms, 50 Hz (depending on cable)
Working voltage (at sea level)	250 V rms for cables with 1 mm / 0.039 in. dielectric 335 V rms for cables with 2 mm / 0.078 in. dielectric
Insulation resistance	$\geq 10^4$ M Ω
Contact resistance - centre contact - outer contact	≤ 5 m Ω ≤ 2.5 m Ω
RF-leakage (measured at 1 GHz)	≥ 55 dB

MECHANICAL DATA	REQUIREMENTS
Engagement force	8 N ... 63 N / 1.8 lbs ... 14.2 lbs
Disengagement force	8 N ... 63 N / 1.8 lbs ... 14.2 lbs
Contact captivation	≥ 18 N / 4.0 lbs
Cable retention force ¹⁾	see pages 28 - 34
Durability (matings)	≥ 500

1) Value considers maximum load of the cables without irreversible variations of specifications.

ENVIRONMENTAL DATA	TEST CONDITIONS
Temperature range	- 65° C ... + 165° C / - 85 ° F ... + 329 ° F
Climatic category	IEC → 55 / 155 / 21
Thermal shock	MIL-STD-202, Method 107, Condition B
Moisture resistance	MIL-STD-202, Method 106
Corrosion	Saltspray test acc. to MIL-STD-202, Method 101, Condition B
Vibration	MIL-STD-202, Method 204, Condition D

MATERIAL DATA		
CONNECTOR PARTS	MATERIAL	PLATING
Bodies	brass	gold or SUCOPLATE®
Pin contacts	brass	gold
Socket contacts	copper-beryllium alloy	gold
Crimp ferrules	copper / brass	gold or SUCOPLATE®
Springs and washers	copper-beryllium alloy	gold or SUCOPLATE®
Insulators	PTFE or PFA	

Some connectors may have a specification that differs from the above mentioned data.


The products are designed and guaranteed to pass the above mentioned test procedures. Any additional or different requirement arising from specific applications or environmental conditions which is not covered by these test procedures is subject to request.

CABLE CONNECTORS

Straight cable plugs (male)

> for semi-rigid cables


- > open entry
- > cable entry soldered
- > centre contact crimp or soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
11_SMB-50-2-13/111_NH	22658765	Y3, Y11 (EZ 86)	bulk 100 pcs.	9002	1

> for flexible cables

- > closed entry
- > HUBER+SUHNER® full crimp
- > taper sleeves see page 406




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
11_SMB-50-1-40/111_NH	22650186	U1 (RG 178 B/U)	bulk 100 pcs.	3077	1A
11_SMB-50-2-40/111_NH	23017717	U2 (RG 316/U)	bulk 100 pcs.	3077	1A
11_SMB-50-2-41/111_NH	22650536	U4 (K 02252 D)	bulk 100 pcs.	3077	1A

Right angle cable plugs (male)

> for semi-rigid cables


- > closed entry
- > cable entry soldered
- > centre contact soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Notes
16_SMB-50-2-23/111_NE	22644079	Y3, Y11 (EZ 86)	single	9160	

> for flexible cables


- > closed entry
- > HUBER+SUHNER® full crimp
- > taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
16_SMB-50-1-40/111_NE	22648053	U1 (RG 178 B/U)	single	3096	1A
16_SMB-50-2-40/111_NH	22650695	U2 (RG 316/U)	bulk 100 pcs.	3096	1A
16_SMB-50-2-41/111_NH	22660335	U4 (K 02252 D)	bulk 100 pcs.	3096	1A

> for flexible cables


- > closed entry
- > cable entry crimp
- > centre contact soldered
- > taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
16_SMB-50-1-50/111_NE	22648056	U1 (RG 178 B/U)	single	9157	A
16_SMB-50-2-50/111_NH	23011371	U2 (RG 316/U)	bulk 100 pcs.	9157	A
16_SMB-50-2-51/111_NH	22658985	U4 (K 02252 D)	bulk 100 pcs.	9157	A


Straight cable jacks (female)

- > for semi-rigid cables
- > cable entry soldered
- > centre contact crimp or soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
21_SMB-50-2-13/111_NE	22543425	Y3, Y11 (EZ 86)	single	9002	1


- > for flexible cables
- > HUBER+SUHNER® full crimp
- > taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
21_SMB-50-1-10/111_NE	22543424	U1 (RG 178 B/U)	single	3077	1A
21_SMB-50-2-10/111_NH	22651810	U2 (RG 316/U)	bulk 100 pcs.	3077	1A
21_SMB-50-2-11/111_NE	22642407	U4 (K 02252 D)	single	3077	1A

Straight bulkhead cable jacks (female)

- > for semi-rigid cables
- > cable entry soldered
- > centre contact crimp or soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole	Crimp insert
24_SMB-50-2-13/111_NE	22640822	Y3, Y11 (EZ 86)	single	9002 / ML 11	1

☒ centre contact NOT captivated

> for flexible cables

> HUBER+SUHNER® full crimp

> rear mounting

> taper sleeves see page 406




Fig. 1




Fig. 2



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Fig.
24_SMB-50-1-10/111_NE	22543631	U1 (RG 178 B/U)	single	3077	1A	1
24_SMB-50-2-110/111_NH	22659126	U2 (RG 316/U)	bulk 100 pcs.	3077	1A	2
24_SMB-50-2-111/111_NH	22659130	U4 (K 02252 D)	bulk 100 pcs.	3077	1A	2

mounting hole ML 11


RECEPTACLES WITH SOLDER END

Receptacles, jacks (female)

> bulkhead mounted

> rear mounting


> insulating washers see page 408



HUBER+SUHNER type	Item no.	Packaging	Mounting hole
22_SMB-50-0-3/111_NE	22640207	single	ML 11


☒ centre contact NOT captivated

- > bulkhead mounted
- > hermetically sealed
- > suited for microstrip-circuits for direct soldering (250 °C / 482 ° F max.)
- > RoHS compliant alternative on request




HUBER+SUHNER type	Item no.	Packaging	Mounting hole	VSWR DC...3 GHz	3...4 GHz	Leak rate
22_SMB-50-0-5/111_NE	22640209	single	ML 90	≤ 1.2	≤ 1.4	≤ 10 ⁻⁸ Torr. l./sec.(atm cc/s)

- > bulkhead mounted
- > non protrusive
- > front mounting



HUBER+SUHNER type	Item no.	Packaging	Mounting hole
22_SMB-50-0-11/111_NE	22640210	single	ML 2

- > bulkhead mounted
- > front mounting
- > insulating washers see page 408




HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Plating body	Notes
22_SMB-50-0-2/133_NH	22651503	bulk 100 pcs.	ML 11	SUCOPLATE®	

PCB CONNECTORS


Straight PCB plugs (male)

- > open entry
- > surface mount type SMT
- > edge mount



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
81_SMB-S50-0-4/111_NM	23001011	tape and reel	ML 131	

Straight PCB jacks (female)



> with stand-off

Fig. 1

> with stand-off




Fig. 2

> without stand-off





Fig. 3

HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Plating body	Fig.	Notes
82_SMB-50-0-1/111_NH	23017254	bulk 100 pcs.	ML 15	SUCOPRO	1	2.54 mm / .100 in. grid
82_SMB-50-0-17/111_NH	23010991	bulk 100 pcs.	ML 15	SUCOPRO	2	2.54 mm / .100 in. grid
82_SMB-50-0-17/111_NM	23013254	tape and reel	ML 15	SUCOPRO	2	2.54 mm / .100 in. grid
82_SMB-50-0-19/111_NH	23011018	bulk 100 pcs.	ML 15	SUCOPRO	3	2.54 mm / .100 in. grid


> surface mount type SMT



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Plating body	Notes
82_SMB-S50-0-18/111_NH	23010995	bulk 100 pcs.	ML 122	SUCOPRO	

Right angle PCB jacks (female)

> with stand-off



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Plating body	Notes
85_SMB-Z50-0-19/111_NH	23010999	bulk 100 pcs.	ML 15	SUCOPRO	2.54 mm / .100 in. grid



SERIES SMC SUBMINIATURE CONNECTORS

DESCRIPTION

The HUBER+SUHNER SMC subminiature connector series is based on the same design as the SMB and SMS series. But due to its screw-on coupling mechanism, the HUBER+SUHNER SMC subminiature connectors are suitable for applications up to 10 GHz.

Coupling mechanism:

The SMC screw-on mechanism permits a vibration-proof connection suitable for semi-permanent connections and for use in mobile equipment with low VSWR requirements.


CONTENTS

PAGE

Description	101
Interface dimensions	101
Interface dimensions in mm / inches	101
Technical data	102
Cable connectors	104
Receptacles with solder end	107
PCB connectors	108

SMC

INTERFACE DIMENSIONS



INTERFACE DIMENSIONS (MM / INCHES)

	Plug		Jack	
	min.	max.	min.	max.
A	—	2.60/.081	2.08/.082	—
B	2.85/.112	3.40/.134	3.40/.134	—
C	—	3.40/.134	3.40/.134	—
D	2.79/.110	—	0.61/.024	—
E	0.00/.000	—	—	2.13/.084
F	—	5.92/.233	—	3.71/.146
G	3.05/.120 nom.		0.48/.019	0.53/.021
H	—	—	0.00/.000	—
I	—	—	3.05/.120 nom.	
K	—	—	5.94/.234	—

Interface dimensions conformable to the Standards:

International:	IEC 60169-9
Europe:	CECC 22140
USA:	MIL-C-39012 SMC
	Interface MIL-STD-348A/312
Great Britain:	BS 9210 N 0009 SMC
France:	NFC 93561 series KMV
Germany:	VG 95286

IP rating (interface, mated) IP50

TECHNICAL DATA

ELECTRICAL DATA	REQUIREMENTS
Impedance	50 Ω
Frequency range	DC ... 10 GHz
Dielectric withstanding voltage (at sea level)	750 V rms, 50 Hz (depending on cable)
Working voltage (at sea level)	250 V rms for cables with 1 mm / 0.039 in. dielectric 335 V rms for cables with 2 mm / 0.078 in. dielectric
Insulation resistance	$\geq 10^4$ M Ω
Contact resistance - centre contact - outer contact	≤ 5 m Ω ≤ 2.5 m Ω
RF-leakage (measured at 1 GHz)	≥ 90 dB

MECHANICAL DATA	REQUIREMENTS
Coupling nut torque - recommended - proof torque	25 Ncm ... 35 Ncm / 2.2 in. lbs ... 3.1 in. lbs 71 Ncm / 6.2 in. lbs
Coupling nut retention force	≥ 150 N / 33.72 lbs
Contact captivation	≥ 10 N / 2.25 lbs
Cable retention force ¹⁾	see pages 28 – 34
Durability (matings)	≥ 500

1) Value considers maximum load of the cables without irreversible variations of specifications.

ENVIRONMENTAL DATA	TEST CONDITIONS
Temperature range	- 65° C ... + 165° C / - 85 ° F ... + 329 ° F
Climatic category	IEC → 55 / 155 / 21
Thermal shock	MIL-STD-202, Method 107, Condition B
Moisture resistance	MIL-STD-202, Method 106
Corrosion	Saltspray test acc. to MIL-STD-202, Method 101, Condition B
Vibration	MIL-STD-202, Method 204, Condition D

MATERIAL DATA		
CONNECTOR PARTS	MATERIAL	PLATING
Bodies	brass	gold
Pins contacts	brass	gold
Socket contacts	copper-beryllium alloy	gold
Crimp ferrules	copper / brass	gold
Springs	copper-beryllium alloy	gold
Insulators	PTFE or PFA	


Some connectors may have a specification that differs from the above mentioned data.

The products are designed and guaranteed to pass the above mentioned test procedures. Any additional or different requirement arising from specific applications or environmental conditions which is not covered by these test procedures is subject to request.

CABLE CONNECTORS


Straight cable plugs (male)

- > for semi-rigid cables
- > cable entry soldered
- > centre contact soldered




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Notes
11_SMC-50-2-13/111_NH	22650675	Y3, Y11 (EZ 86)	bulk 100 pcs.	9002	

- > for flexible cables
- > cable entry HUBER+SUHNER® pressure-sleeve
- > centre contact soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Notes
11_SMC-50-1-6/111_NE	22640238	U1 (RG 178 B/U)	single	3041	
11_SMC-50-2-5/111_NE	22640246	U2 (RG 316/U)	single	3041	


- > for flexible cables
- > HUBER+SUHNER® full crimp
- > taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
11_SMC-50-1-10/111_NH	22648629	U1 (RG 178 B/U)	bulk 100 pcs.	3077	1A
11_SMC-50-2-10/111_NH	22645841	U2 (RG 316/U)	bulk 100 pcs.	3077	1A
11_SMC-50-2-10/133_NE	22641528	U2 (RG 316/U)	single	3077	1A
11_SMC-50-2-11/111_NE	22640251	U4 (K 02252 D)	single	3077	1A


Right angle cable plugs (male)

- > for semi-rigid cables
- > cable entry soldered
- > centre contact soldered




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Notes
16_SMC-50-2-25/111_NE	22644126	Y3, Y11 (EZ 86)	single	9160	
16_SMC-50-2-25/111_NH	23003713	Y3, Y11 (EZ 86)	bulk 100 pcs.	9160	

- > for flexible cables
- > cable entry HUBER+SUHNER® pressure-sleeve
- > centre contact soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Notes
16_SMC-50-2-5/111_NE	22640264	U2 (RG 316/U)	single	3039	

- > for flexible cables
- > HUBER+SUHNER® full crimp
- > taper sleeves see page 406




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
16_SMC-50-1-10/111_NH	22648283	U1 (RG 178 B/U)	bulk 100 pcs.	3096	1A
16_SMC-50-2-10/111_NH	22645323	U2 (RG 316/U)	bulk 100 pcs.	3096	1A
16_SMC-50-2-11/111_NE	22543366	U4 (K 02252 D)	single	3096	1A

> for flexible cables

> cable entry crimp

> centre contact soldered

> taper sleeves see page 406




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
16_SMC-50-1-20/111_NE	22644083	U1 (RG 178 B/U)	single	9157	A
16_SMC-50-2-20/111_NE	22643949	U2 (RG 316/U)	single	9157	A

Straight cable jacks (female)

> for flexible cables

> HUBER+SUHNER® full crimp

> taper sleeves see page 406




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
21_SMC-50-2-10/111_NE	22640279	U2 (RG 316/U)	single	3077	1 A
21_SMC-50-2-11/111_NE	22644232	U4 (K 02252 D)	single	3077	1 A

Straight bulkhead cable jacks (female)

> for semi-rigid cables


> cable entry soldered

> centre contact soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Mounting hole
24_SMC-50-2-13/111_NH	22650209	Y3, Y11 (EZ 86)	bulk 100 pcs.	9002	ML 11

- > for flexible cables
- > HUBER+SUHNER® full crimp
- > rear mounting
- > taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Mounting hole	Crimp insert
24_SMC-50-1-10/111_NH	22648484	U1 (RG 178 B/U)	bulk 100 pcs.	3077	ML 11	1 A
24_SMC-50-2-110/111_NH	22660135	U2 (RG 316/U)	bulk 100 pcs.	3077	ML 11	1 A

RECEPTACLES WITH SOLDER END

Receptacles, jacks (female)

- > bulkhead mounted
- > insulating washers see page 408




Fig. 1




Fig. 2


HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Fig.	Notes
22_SMC-50-0-2/111_NE	22640281	single	ML 11	1	front mounting
22_SMC-50-0-3/111_NE	22640282	single	ML 11	2	rear mounting
22_SMC-50-0-3/133_NE	22641428	single	ML 11	2	rear mounting

☐ centre contact NOT captivated

PCB CONNECTORS

Straight PCB plugs (male)


> 2.54 mm / .100 in. grid



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
81_SMC-50-0-1/111_NE	22640312	single	ML 15	without stand-off

Straight PCB jacks (female)


> 2.54 mm / .100 in. grid



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
82_SMC-50-0-1/111_NH	22646201	bulk 100 pcs.	ML 15	with stand-off

Right angle PCB jacks (female)

> 2.54 mm / .100 in. grid



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
85_SMC-50-0-1/111_NE	22640326	single	ML 15	with stand-off
85_SMC-50-0-1/111_NH	22652987	bulk 100 pcs.	ML 15	with stand-off
85_SMC-50-0-1/133_NE	22642472	single	ML 15	with stand-off



SERIES SMS, SUBMINIATURE CONNECTORS


DESCRIPTION

HUBER+SUHNER SMS connectors are used in applications requiring rapid connection and disconnection, even where space is limited. The small physical size of the connector allows a high packing density to be achieved. These connectors are suitable for applications up to 4 GHz.

The SMB, SMC and SMS series have an identical inner construction, but a different coupling mechanism.

In accordance with the international specifications, plugs are fitted with female center contacts and jacks with male center contacts. To increase the voltage rating, all insulators overlap.

INTERFACE DIMENSIONS



CONTENTS

PAGE

Description	109
Interface dimensions	109
Interface dimensions in mm / inches	109
Technical data	110
Cable connectors	112
Receptacles with solder end	113
PCB connectors	113

INTERFACE DIMENSIONS (MM / INCHES)

	Plug		Jack	
	min.	max.	min.	max.
A	—	2.06/.081	2.08/.082	—
B	2.85/.112	3.40/.134	3.40/.134	—
C	—	3.40/.134	3.40/.134	—
D	2.79/.110	—	0.61/.024	—
E	0.00/.000	—	—	2.13/.084
F	—	5.20/.205	3.66/.144	3.71/.146
G	3.05/.120 nom.		0.48/.019	0.53/.021
H	—	—	0.00/.000	—
I	—	—	3.05/.120 nom.	
K	—	—	5.30/.209	—

Note: HUBER+SUHNER SMS plugs are intermateable with HUBER+SUHNER SMB jacks without any restrictions.

IP rating (interface, mated) IP50

TECHNICAL DATA

ELECTRICAL DATA	REQUIREMENTS
Impedance	50 Ω
Frequency range	DC ... 4 GHz
Dielectric withstanding voltage (at sea level)	750 V rms, 50 Hz (depending on cable)
Working voltage (at sea level)	250 V rms for cables with 1 mm / 0.039 in. dielectric 335 V rms for cables with 2 mm / 0.078 in. dielectric
Insulation resistance	$\geq 10^4$ M Ω
Contact resistance - centre contact - outer contact	≤ 5 m Ω ≤ 2.5 m Ω
RF-leakage (measured at 1 GHz)	≥ 55 dB

MECHANICAL DATA	REQUIREMENTS
Engagement force	typ. 8 N / 1.8 lbs
Disengagement force	typ. 5 N / 1.1 lbs
Contact captivation	≥ 10 N / 2.25 lbs
Cable retention force ¹⁾	see pages 28 - 34
Durability (matings)	≥ 500

1) Value considers maximum load of the cables without irreversible variations of specifications.

ENVIRONMENTAL DATA	TEST CONDITIONS
Temperature range	- 65° C ... + 165° C / - 85 ° F ... + 329 ° F
Climatic category	IEC → 55 / 155 / 21
Thermal shock	MIL-STD-202, Method 107, Condition B
Moisture resistance	MIL-STD-202, Method 106
Corrosion	Saltspray test acc. to MIL-STD-202, Method 101, Condition B
Vibration	MIL-STD-202, Method 204, Condition D

MATERIAL DATA		
CONNECTOR PARTS	MATERIAL	PLATING
Bodies	brass	gold
Pins contacts	brass	gold
Socket contacts	copper-beryllium alloy	gold
Crimp ferrules	copper / brass	gold
Springs	copper-beryllium alloy	gold
Insulators	PTFE or PFA	

Some connectors may have a specification that differs from the above mentioned data.

The products are designed and guaranteed to pass the above mentioned test procedures. Any additional or different requirement arising from specific applications or environmental conditions which is not covered by these test procedures is subject to request.

CABLE CONNECTORS


Straight cable plugs (male)

> for flexible cables

> closed entry

> HUBER+SUHNER® full crimp

> taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
11_SMS-50-1-10/111_NE	22543572	U1 (RG 178 B/U)	single	3077	1 A
11_SMS-50-2-110/111_NH	23011901	U2 (RG 316/U)	bulk 100 pcs.	3077	1 A


Right angle cable plugs (male)

> for flexible cables

> open entry

> HUBER+SUHNER® full crimp

> taper sleeves see page 406




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
16_SMS-50-1-10/111_NH	22649894	U1 (RG 178 B/U)	bulk 100 pcs.	3096	1 A
16_SMS-50-2-10/111_NE	22543574	U2 (RG 316/U)	single	3096	1 A

Straight cable jacks (female)

> for flexible cables

> HUBER+SUHNER® full crimp

> taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Notes
21_SMB-50-1-10/111_NE	22543424	U1 (RG 178 B/U)	single	3077	1 A	*
21_SMB-50-2-10/111_NH	22651810	U2 (RG 316/U)	bulk 100 pcs.	3077	1 A	*


* intermateable with SMS plug without any restrictions

☒ centre contact NOT captivated

RECEPTACLES WITH SOLDER END

Receptacles, plugs (male)

- > open entry
- > bulkhead mounted
- > front mounting



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Crimp insert
12_SMS-50-0-3/133_NH	22651812	bulk 100 pcs.	ML 11	without panel seal

Receptacles, jacks (female)

- > bulkhead mounted
- > insulating washers see page 408




Fig. 1




Fig. 2




HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes	Fig.
22_SMB-50-0-2/111_NE	22640206	single	ML 11	front mounting, intermateable with SMS plug without any restrictions	1
22_SMB-50-0-3/111_NE	22640207	single	ML 11	rear mounting, intermateable with SMS plug without any restrictions	2

PCB CONNECTORS

Straight PCB plugs (male)


- > open entry
- > 2.54 mm / .100 in. grid



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
81_SMS-50-0-1/111_NH	22650093	bulk 100 pcs.	ML 15	without stand-off

Straight PCB jacks (female)


- > with stand-off
- > 2.54 mm / .100 in. grid



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
82_SMB-50-0-1/111_NH	22645143	bulk 100 pcs.	ML 15	intermateable with SMS plug without any restrictions

Right angle PCB plugs (male)


- > open entry
- > with stand-off
- > 2.54 mm / .100 in. grid



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
84_SMS-50-0-1/111_NE	22640377	single	ML 15	

Right angle PCB jacks (female)

- > 2.54 mm / .100 in. grid
- > with stand-off



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
85_SMB-50-0-1/111_NH	22645989	bulk 100 pcs.	ML 15	intermateable with SMS plug without any restrictions



SERIES SMA, SUBMINIATURE CONNECTORS

DESCRIPTION

HUBER+SUHNER SMA connectors are precision connectors for microwave applications up to 18 GHz. They distinguish themselves through their high mechanical strength, high durability, high reliability and low VSWR.

SMA launchers are the preferred connection element for varied microwave circuits. There is a huge variety of applications for HUBER+SUHNER SMA connectors, such as mobile communication, test & measurement, instruments, avionics, etc.


CONTENTS

PAGE

Description	115
Interface dimensions	115
Interface dimensions in mm / inches	115
Standards	116
Technical data	116
Cable connectors	118
Receptacles with solder end	128
Receptacles with coaxial end	130
Stripline launchers	131
Microstrip launchers	133
Connectors with hermetic seal	133
PCB connectors	135
Protective caps and shorts	136
SMA Launchers with Transition Pins	137

SMA
PC3.5/SK

INTERFACE DIMENSIONS



INTERFACE DIMENSIONS (MM / INCHES)

	Plug		Jack	
	min.	max.	min.	max.
A	—	4.59/.181	4.59/.181	—
B	0.00/.000	0.25/.010	0.00/.000	0.25/.010
C	0.00/.000	0.25/.010	0.00/.000	0.25/.010
D	—	2.54/.100	2.67/.105	—
E	1.24/.049	1.29/.051	1.24/.049	1.29/.051
F	0.38/.015	1.14/.045	1.88/.074	1.98/.078
G	—	3.43/.135	0.38/.015	1.14/.045
H	0.90/.036	0.94/.037	5.28/.208	5.49/.216
I	—	—	4.32/.170	—
K	—	—	5.54/.218	—

IP rating (interface, mated) IP68

Interface dimensions conformable to the Standards:

International: **IEC 60169-15**
 Europe: **CECC 22110**
 USA: **MIL-C-39012, SMA**
Interface MIL-STD-348a/310

GB: **BS 9210 N 0006**
 F: **NF-C-93563 (KMR)**

TECHNICAL DATA

ELECTRICAL DATA		MIL-C-39012			
Cable type		semi-rigid		flexible	
Cable dielectric diameter (mm/in.)		1.5 / .066	3 / .117	1.5 / .066	3 / .117
Impedance		50 Ω			
Frequency range for interface		DC ... 18 GHz			
VSWR (typical value)		see table below			
RF-leakage measured at 3 GHz (f in GHz)	3.26	$\geq 100 \text{ dB-f}$		$\geq 60 \text{ dB}$	
Dielectric withstanding voltage (at sea level, in V rms, 50 Hz)	3.17	1000	1500	750	1000
Working voltage (at sea level, in V rms, 50 Hz)		335	500	250	335
Corona extinction voltage (at 21 000 m/70 000 ft., in V rms, 50 Hz)	3.22	250	375	190	250
Working voltage (at 21 000 m/70 000 ft., in V rms, 50 Hz)		85	125	65	85
RF withstanding voltage at 5 MHz (V rms)	3.23	670	1000	500	670
Insulation resistance	3.11	$\geq 5 \cdot 10^3 \text{ M}\Omega$			
Contact resistance - centre contact - outer contact	3.16	$\leq 3 \text{ m}\Omega$ $\leq 2.5 \text{ m}\Omega$			

TYPICAL VSWR	FREQUENCY RANGE					CABLE GROUP
CONNECTOR TYPE	1 GHz	2.5 GHz	5 GHz	12.4 GHz	18 GHz	
straight connectors	1.03	1.03	1.03	1.07	1.08	Y3, Y11
	1.03	1.03	1.04	1.07	1.15	Y5, Y12
	1.05	1.07	1.08			U2, U4
	1.04	1.05	1.07			U7, U9
right angle connectors	1.03	1.05	1.10	1.25		Y3, Y11
	1.03	1.05	1.08	1.17		Y5, Y12
	1.05	1.07	1.11			U2, U4
	1.03	1.05	1.07			U7, U9

MECHANICAL DATA	MIL-C-39012	
Recommended coupling nut torque		standard: 0.8 Nm ... 1.1 Nm / 7.1 in. lbs. ... 9.7 in. lbs brass: 0.45 Nm / 4.0 in. lbs
Coupling nut retention force	3.25	$\geq 270 \text{ N} / 60.7 \text{ lbs}$
Contact captivation - axial	3.12	$\geq 27 \text{ N} / 6.1 \text{ lbs}$
Cable retention force ¹⁾		see pages 28 – 34
Durability (matings)		≤ 500

1) Value considers maximum load of the cables without irreversible variations of specifications.

ENVIRONMENTAL DATA	TEST CONDITIONS
Temperature range	- 65°C ... + 165°C / - 85 °F ... + 329 °F
Climatic category	IEC → 55/155/21
Thermal shock	MIL-STD-202, Method 107, Condition B
Moisture resistance	MIL-STD-202, Method 106
Corrosion	Saltspray test acc. to MIL-STD-202, Method 101, Condition B
Vibration	MIL-STD-202, Method 204, Condition D
Shock	MIL-STD-202, Method 213, Condition I

MATERIAL DATA		
CONNECTOR PART	MATERIAL	PLATING
Bodies, outer contacts	copper-beryllium alloy stainless steel brass spring bronze	gold passivated SUCOPLATE®, gold gold
Pin contacts	copper-beryllium alloy, brass	gold
Socket contacts	copper-beryllium alloy spring bronze	gold
Crimp ferrules	copper, brass	gold
Insulators	PTFE or PFA	
Gaskets	silicone rubber	

Some connectors may have a specification that differs from the above mentioned data.


The products are designed and guaranteed to pass the above mentioned test procedures. Any additional or different requirement arising from specific applications or environmental conditions which is not covered by these test procedures is subject to request.

CABLE CONNECTORS

Straight cable plugs (male)

> for semi-rigid cables

- > with pin and insulator
- > cable entry soldered
- > centre contact soldered
- > compound 74_Z-0-116 needed
(see page 398)



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Plating body
11_SMA-50-1-1/111_NE	22642387	Y1 (EZ 34)	single	9118	gold
11_SMA-50-1-2/111_NE	22642388	Y2 (EZ 47)	single	9119	gold

> for semi-rigid cables

- > with pin and insulator
- > cable entry soldered
- > centre contact soldered




Fig. 1




Fig. 2




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Plating body	Fig.
11_SMA-50-2-15/111_NH	22645898	Y3, Y11 (EZ 86)	bulk 100 pcs.	9056	gold	1
11_SMA-50-2-29/119_NH	22660366	Y3, Y11 (EZ 86)	bulk 100 pcs.	27334	stainless steel ²⁾	2 ¹⁾
11_SMA-50-2-65/119_NH	22645366	Y3, Y11 (EZ 86)	bulk 100 pcs.	9056	stainless steel ²⁾	1

1) centre contact plugged-in

2) cable entry CuBe/gold

> for semi-rigid cables

- > without pin and insulator
- > cable entry soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Plating body	Notes
11_SMA-50-3-14/-11_NH	22644467	Y5 (EZ 141)	bulk 100 pcs.	9055	gold	26.5 GHz
11_SMA-50-3-64/-19_NH	22649224	Y5 (EZ 141)	bulk 100 pcs.	9055	stainless steel ²⁾	26.5 GHz

2) cable entry CuBe/gold

☒ centre contact NOT captivated

> for semi-rigid cables

- > with pin and insulator
- > cable entry soldered
- > centre contact soldered




Fig. 1




Fig. 2




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Plating body	Fig.
11_SMA-50-3-15/111_NH	22651601	Y5, Y12 (EZ 141)	bulk 100 pcs.	9056	gold	1
11_SMA-50-3-65/119_NH	22646570	Y5, Y12 (EZ 141)	bulk 100 pcs.	9056	stainless steel ²⁾	1
11_SMA-50-3-39/111_YH	23026120	Y5, Y12 (EZ 141)	bulk 100 pcs.	150012	SUCOPRO	2 ¹⁾

1) centre contact plugged-in

2) cable entry CuBe/gold

> for semi-rigid cables

- > without pin and insulator
- > cable entry soldered
- > short version




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Plating body	Notes
11_SMA-50-3-16/-11_NH	22644470	Y5 (EZ 141)	bulk 100 pcs.	9055	gold	26.5 GHz
11_SMA-50-3-42/-33_NH	22646128	Y5 (EZ 141)	bulk 100 pcs.	9055	SUCOPLATE ^{®1)}	26.5 GHz
11_SMA-50-3-66/-19_NH	22645207	Y5 (EZ 141)	bulk 100 pcs.	9055	stainless steel ²⁾	26.5 GHz

1) use torque wrench 74_Z-0-0-79

2) cable entry CuBe/gold

> for flexible cables

- > cable entry clamp
- > centre contact soldered




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Plating body
11_SMA-50-3-7/111_NE	22640050	U7 (RG 58 C/U)	single	3071	gold
11_SMA-50-3-8/111_NH	22648630	U10 (RG 223/U)	bulk 100 pcs.	3071	gold
11_SMA-50-3-10/111_NE	22640053	U10 (RG 223/U)	single	3071	gold

☐ centre contact NOT captivated

> for flexible cables

- > cable entry crimp
- > centre contact soldered
- > taper sleeves see page 406




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Plating body	Crimp insert
11_SMA-50-1-4/111_NE	22645871	U1 (RG 178 B/U)	single	27061	gold	A
11_SMA-50-2-5/111_NH	22646312	U2 (RG 316/U)	bulk 100 pcs.	27266	gold	A
11_SMA-50-2-6/111_NH	22650740	U4 (K 02252 D)	bulk 100 pcs.	27266	gold	A
11_SMA-50-2-27/111_NH	22652923	U2 (RG 316/U)	bulk 100 pcs.	27164	gold	1 A ¹⁾
11_SMA-50-2-41/133_NH	22652160	U4 (K 02252 D)	bulk 100 pcs.	3069	SUCOPLATE ^{®2)}	A
11_SMA-50-2-42/133_NH	22648783	U2 (RG 316/U)	bulk 100 pcs.	27266	SUCOPLATE ^{®2)}	A
11_SMA-50-2-55/199_NE	22641377	U2 (RG 316/U)	single	3069	stainless steel	A
11_SMA-50-2-56/199_NH	22651486	U4 (K 02252 D)	bulk 100 pcs.	3069	stainless steel	A

1) HUBER+SUHNER[®] full crimp

2) use torque wrench 74_Z-0-79

> for flexible cables

- > cable entry crimp
- > centre contact soldered
- > taper sleeves see page 406




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Plating body	Crimp insert
11_SMA-50-3-5/111_NE	22640048	U7 (RG 58 C/U)	single	3069	gold	B
11_SMA-50-3-6/111_NH	22650739	U9, 11 (RG 400/U)	bulk 100 pcs.	3069	gold	B
11_SMA-50-3-45/133_NH	22645987	U7 (RG 58 C/U)	bulk 100 pcs.	3069	SUCOPLATE ^{®1)}	B
11_SMA-50-3-46/133_NH	22651819	U9, 11 (RG 400/U)	bulk 100 pcs.	3069	SUCOPLATE ^{®1)}	B
11_SMA-50-3-55/199_NE	22641371	U7 (RG 58 C/U)	single	3069	stainless steel	B
11_SMA-50-3-56/199_NH	22648300	U9, 11 (RG 400/U)	bulk 100 pcs.	3069	stainless steel	B

1) use torque wrench 74_Z-0-79

Right angle cable plugs (male)

- > for semi-rigid cables
- > cable entry soldered
- > centre contact soldered




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Plating body	Notes
16_SMA-50-2-43/133_NE	22641953	Y3, Y11 (EZ 86)	single	3068	SUCOPLATE® ¹⁾	
16_SMA-50-2-53/119_NH	22646639	Y3, Y11 (EZ 86)	bulk 100 pcs.	3068	stainless steel ²⁾	
16_SMA-50-2-103/111_NH	22652924	Y3, Y11 (EZ 86)	bulk 100 pcs.	3068	gold	

1) use torque wrench 74_Z-0-0-79

2) cable entry CuBe/gold


- > for semi-rigid cables
- > cable entry soldered
- > centre contact soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Plating body	Notes
16_SMA-50-3-3/111_NH	22646569	Y5, Y12 (EZ 141)	bulk 100 pcs.	3068	gold	
16_SMA-50-3-43/133_NE	22642241	Y5, Y12 (EZ 141)	single	3070	SUCOPLATE® ¹⁾	


1) use torque wrench 74_Z-0-0-79

- > for flexible cables
- > cable entry crimp
- > centre contact soldered
- > taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Plating body	Crimp insert
16_SMA-50-1-1/111_NH	22660358	U1 (RG 178 B/U)	bulk 100 pcs.	3070	gold	A
16_SMA-50-2-105/111_NH	22651456	U2 (RG 316/U)	bulk 100 pcs.	3070	gold	A
16_SMA-50-2-106/111_NH	22651458	U4 (K 02252 D)	bulk 100 pcs.	3070	gold	A
16_SMA-50-2-141/133_NH	22651997	U4 (K 02252 D)	bulk 100 pcs.	3070	SUCOPLATE® ¹⁾	A
16_SMA-50-2-145/133_NH	22652929	U2 (RG 316/U)	bulk 100 pcs.	3070	SUCOPLATE® ¹⁾	A

- > for flexible cables
- > cable entry crimp
- > centre contact soldered
- > taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Plating body	Crimp insert
16_SMA-50-3-105/111_NH	22651800	U7 (RG 58 C/U)	bulk 100 pcs.	3070	gold	B
16_SMA-50-3-106/111_NH	22650545	U9, 11 (RG 400/U)	bulk 100 pcs.	3070	gold	B
16_SMA-50-3-145/133_NE	22651584	U7 (RG 58 C/U)	single	3070	SUCOPLATE® ¹⁾	B
16_SMA-50-3-146/133_NE	22649909	U9, 11 (RG 400/U)	single	3070	SUCOPLATE® ¹⁾	B

1) use torque wrench 74_Z00-79

Straight cable jacks (female)

- > for semi-rigid cables
- > cable entry soldered
- > centre contact soldered




Fig. 1





Fig. 2



HUBER+SUHNER type	Item no.	Cable group (example)		Packaging	Assembly instruction	Plating body	Fig.
21_SMA-50-1-1/111_NE	22642385	Y1	(EZ 34)	single	9118	gold	1
21_SMA-50-1-2/111_NE	22642386	Y2	(EZ 47)	single	9119	gold	1
21_SMA-50-2-15/111_NH 	22652141	Y3, Y11	(EZ 86)	bulk 100 pcs.	9057	gold	2

- > for semi-rigid cables
- > cable entry soldered
- > centre contact plugged-in




HUBER+SUHNER type	Item no.	Cable group (example)		Packaging	Assembly instruction	Plating body	Notes
21_SMA-50-3-47/111_YE	23025549	Y5	(EZ 141)	bulk 100 pcs.	150012	SUCOPRO	

 centre contact NOT captivated

> for flexible cables


- > cable entry crimp
- > centre contact soldered
- > taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)		Packaging	Assembly instruction	Plating body	Crimp insert
21_SMA-50-2-5/111_NE	22640077	U2	(RG 316/U)	single	3069	gold	A
21_SMA-50-2-6/111_NH	22651818	U4	(K 02252 D)	bulk 100 pcs.	3069	gold	A

> for flexible cables

- > cable entry crimp
- > centre contact soldered
- > taper sleeves see page 406




HUBER+SUHNER type	Item no.	Cable group (example)		Packaging	Assembly instruction	Plating body	Crimp insert
21_SMA-50-3-5/111_NE	22640081	U7	(RG 58 C/U)	single	3069	gold	B
21_SMA-50-3-6/111_NE	22640082	U9, 11	(RG 400/U)	single	3069	gold	B

Straight bulkhead cable jacks (female)

> for semi-rigid cables

- > cable entry soldered
- > centre contact soldered
- > with panel seal
- > insulating washers see page 408




HUBER+SUHNER type	Item no.	Cable group (example)		Packaging	Assembly instruction	Plating body	Mounting hole
24_SMA-50-2-15/111_NH	22645490	Y3, Y11	(EZ 86)	bulk 100 pcs.	9057	gold	ML 35

☒ centre contact NOT captivated

> for semi-rigid cables


- > cable entry soldered
- > centre contact soldered
- > with panel seal
- > insulating washers see page 408



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Plating body	Mounting hole
24_SMA-50-3-15/111_NH	22645259	Y5, Y12 (EZ 141)	bulk 100 pcs.	9057	gold	ML 35

> for flexible cables

- > cable entry crimp
- > centre contact soldered
- > with panel seal
- > taper sleeves see page 406




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly Instruction/ Mounting Hole	Plating body	Crimp insert
24_SMA-50-2-13/111_NH	22651719	U4 (K 02252 D)	bulk 100 pcs.	3069 / ML 20	gold	A
24_SMA-50-2-14/111_NH	22651747	U2 (RG 316/U)	bulk 100 pcs.	3069 / ML 20	gold	A
24_SMA-50-2-45/133_NH	22652352	U4 (K 02252 D)	bulk 100 pcs.	3069 / ML 20	SUCOPLATE® ¹⁾	A
24_SMA-50-2-45/133_UH	22648472	U4 (K 02252 D)	bulk 100 pcs.	3069 / ML 20	SUCOPLATE® ¹⁾	A
24_SMA-50-2-46/133_NH	22646565	U2 (RG 316/U)	bulk 100 pcs.	3069 / ML 20	SUCOPLATE® ¹⁾	A

1) use torque wrench 74_Z-0-0-79

☒ centre contact NOT captivated

- > for flexible cables
- > cable entry crimp
- > centre contact soldered
- > taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly Instruction/ Mounting Hole	Plating body	Crimp insert
24_SMA-50-3-42/133_NE	22641358	U9 (RG 223/U)	single	3072 / ML 20	SUCOPLATE®1)	B

1) use torque wrench 74_Z-0-0-79

Straight panel cable jacks (female)

- > for semi-rigid cables
- > cable entry soldered
- > centre contact soldered




Fig. 1




Fig. 2



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole	Plating body	Fig.
25_SMA-50-1-2/111_NE	22642390	Y2 (EZ 47)	single	9119 / ML 19	gold	1
25_SMA-50-1-4/111_NE	22642391	Y2 (EZ 47)	single	9119	gold	2

- > for semi-rigid cables
- > cable entry soldered
- > centre contact soldered




Fig. 1




Fig. 2

HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole	Plating body	Fig.
25_SMA-50-2-15/111_NE	22544551	Y3, Y11 (EZ 86)	single	9057 / ML 19	gold	1
25_SMA-50-2-25/111_NE	22641493	Y3, Y11 (EZ 86)	single	9057	gold	2

- > for semi-rigid cables
- > cable entry soldered
- > centre contact soldered




Fig. 1





Fig. 2

HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole	Plating body	Fig.
25_SMA-50-3-15/111_NH	22644717	Y5, Y12 (EZ 141)	bulk 100 pcs.	9057 / ML 19	gold	1
25_SMA-50-3-25/111_NH	22646563	Y5, Y12 (EZ 141)	bulk 100 pcs.	9057	gold	2

☒ centre contact NOT captivated

- > for flexible cables
- > cable entry crimp
- > centre contact soldered
- > square flange
- > taper sleeves see page 406




HUBER+SUHNER type	Item no.	Cable group (example)		Packaging	Assembly instruction/ Mounting hole	Plating body	Crimp insert
25_SMA-50-2-5/111_NH	22650755	U2	(RG 316/U)	bulk 100 pcs.	3072 / ML 19	gold	A
25_SMA-50-2-6/111_NE	22640113	U4	(K 02252 D)	single	3072 / ML 19	gold	A
25_SMA-50-2-46/133_NE	22642246	U4	(K 02252 D)	single	3072 / ML 19	SUCOPLATE® ¹⁾	A

1) use torque wrench 74_Z-0-0-79

RECEPTACLES WITH SOLDER END

Receptacles, jacks (female)


- > bulkhead mounted
- > with panel seal



HUBER+SUHNER type	Item no.	Packaging	Plating body	Mounting hole	Notes
22_SMA-50-0-1/111_NE	22640087	single	gold	ML 20	rear mounting


Receptacles, jacks (female)

- > rear mounting
- > without panel seal
- > insulating washers see page 408




HUBER+SUHNER type	Item no.	Packaging	Plating body	Mounting hole	Notes
22_SMA-50-0-4/111_NH	22649418	bulk 100 pcs.	gold	ML 35	
22_SMA-50-0-44/133_NE	22643518	single	SUCOPLATE®	ML 35	use torque wrench 74_Z0-0-79
22_SMA-50-0-203/111_NH	22652012	bulk 100 pcs.	gold	ML 35	

- > panel mounted



HUBER+SUHNER type	Item no.	Packaging	Plating body	Notes
23_SMA-50-0-1/111_NH	22651409	bulk 100 pcs.	gold	
23_SMA-50-0-44/133_NH	22652098	bulk 100 pcs.	SUCOPLATE®	use torque wrench 74_Z0-0-79
23_SMA-50-0-51/199_NE	22543948	single	stainless steel	

- > panel mounted



HUBER+SUHNER type	Item no.	Packaging	Plating body	Notes
23_SMA-50-0-11/111_NE	22640095	single	gold	
23_SMA-50-0-41/133_NH	22644383	bulk 100 pcs.	SUCOPLATE®	use torque wrench 74_Z0-0-79
23_SMA-50-0-61/199_NE	22544796	single	stainless steel	

- > bulkhead mounted
- > without panel seal
- > insulating washers see page 408



> panel mounted




- > bulkhead mounted



HUBER+SUHNER® SMA

Receptacles, jacks (female)

> panel mounted



HUBER+SUHNER type	Item no.	Packaging	Plating body	Notes
23_SMA-50-0-21/111_NE	22640101	single	gold	flush dielectric



SMA




Fig. 1





Fig. 2

HUBER+SUHNER type	Item no.	Packaging	Plating body	Notes	Fig.
23_SMA-50-0-3/111_NE	22640092	single	gold	extended dielectric	1
23_SMA-50-0-13/111_NH	22658873	bulk 100 pcs.	gold	extended dielectric	2
23_SMA-50-0-53/199_NE	22641394	single	stainless steel	extended dielectric	1

STRIPLINE LAUNCHERS

Panel launchers, male


> tab contact



HUBER+SUHNER type	Item no.	Packaging	Plating body	Notes
13_SMA-50-0-2/111_NE	22640056	single	gold	flush dielectric

Panel launchers, male

> tab contact




HUBER+SUHNER type	Item no.	Packaging	Plating body	Notes
13_SMA-50-0-141/133_NH	22649018	bulk 100 pcs.	SUCOPLATE® 1)	flush dielectric

1) use torque wrench 74_Z-0-0-79


Panel launchers, female

> tab contact



HUBER+SUHNER type	Item no.	Packaging	Plating body	Notes
23_SMA-50-0-2/111_NE	22640091	single	gold	flush dielectric
23_SMA-50-0-52/199_NE	22543487	single	stainless steel	flush dielectric

> tab contact




HUBER+SUHNER type	Item no.	Packaging	Plating body	Notes
23_SMA-50-0-12/111_NE	22640096	single	gold	flush dielectric
23_SMA-50-0-62/199_NE	22544779	single	stainless steel	flush dielectric

MICROSTRIP LAUNCHERS

Panel launchers, female

> tab contact, offset



HUBER+SUHNER type	Item no.	Packaging	Plating body	Notes
23_SMA-50-0-4/111_NE	22640093	single	gold	flush dielectric

CONNECTORS WITH HERMETIC SEAL


All hermetic seal SMA connectors use precision glass to metal seals, which are soldered into the connector body.

Caution: max. soldering temperature for hermetic seal SMA connectors is 250°C / 482 °F.

Receptacle, male, hermetic seal

> “Spark Plug” with metal ring seal


> RoHs compliant alternative on request



HUBER+SUHNER type	Item no.	Packaging	Plating body	Mounting hole	Notes
12_SMA-50-0-110/111_NE	22652315	single	gold	ML 42	pressure max. 200 N/cm ² (290 psi)

Receptacle, female, hermetic seal

- > "Spark Plug" with metal ring seal
- > RoHS compliant alternative on request




HUBER+SUHNER type	Item no.	Packaging	Plating body	Mounting hole	Notes
22_SMA-50-0-10/111_NE	22641291	single	gold	ML 42	pressure max. 200 N/cm ² (290 psi)

For type 12_SMA-50-0-110 (see previous page) and 22_SMA-50-0-10 (see above):
 Use assembly tool 74_Z-0-0-75 and torque wrench 74_Z-0-0-80!
 The specified torque of 200 Ncm (17.7 in. lbs) results in a leakage rate of 10⁻⁸ Torr l/sec. (atm cc/s) maximum.

Receptacles, jacks (female)

- > bulkhead mounted
- > with panel seal
- > RoHS compliant alternative on request




HUBER+SUHNER type	Item no.	Packaging	Plating body	Mounting hole	Notes
22_SMA-50-0-12/111_NY	22641293	75 pcs.	gold	ML 98	pressure max. 200 N/cm ² (290 psi) ¹⁾

1) leak rate 10⁻⁶ Torr l/sec.(atm cc/s) max.

tap drill 74_Z-0-0-24

Receptacles, female, hermetic seal

- > bulkhead mounted for direct soldering
- > supplied with separate insulating bushing
- > RoHS compliant alternative on request



HUBER+SUHNER type	Item no.	Packaging	Plating body	Mounting hole	Notes
22_SMA-50-0-15/111_NE	22544588	single	gold	ML 96	pressure max. 200 N/cm ² (290 psi) ¹⁾


1) leak rate 10⁻⁸ Torr l/sec.(atm cc/s) max.

soldering temperature 250 °C / 482 °F max.

PCB CONNECTORS


Straight PCB jacks (female)

> without stand-off



HUBER+SUHNER type	Item no.	Packaging	Plating body	Mounting hole	Notes
82_SMA-50-0-1/111_NH	22644334	bulk 100 pcs.	gold	ML 41	


> edge mount



HUBER+SUHNER type	Item no.	Packaging	Plating body	Mounting hole	Notes
82_SMA-50-0-45/111_NE	22652330	single	gold	ML 132	


Right angle PCB jacks (female)

> without stand-off



HUBER+SUHNER type	Item no.	Packaging	Plating body	Mounting hole	Notes
85_SMA-50-0-101/111_NH	22652140	bulk 100 pcs.	gold	ML 41	


> with stand-off



HUBER+SUHNER type	Item no.	Packaging	Plating body	Mounting hole	Notes
85_SMA-50-0-144/111_YH	23000527	bulk 100 pcs.	SUCOPLATE®	ML 41	



PROTECTIVE CAPS AND SHORTS

Cap with chain for jacks



HUBER+SUHNER type	Item no.	Packaging	Plating body	Notes
62_SMA-0-0-1/-11_NE	22640159	single	gold	non-shorting, humidity sealed
62_SMA-0-0-51/-99_NE	22644252	single	stainless steel	non-shorting, humidity sealed

Shorting Caps




HUBER+SUHNER type	Item no.	Packaging	Plating body	Notes
64_SMA-0-0-1/111_NE	22640161	single	gold	SMA plug, humidity sealed

SMA LAUNCHERS WITH TRANSITION PINS

SMA launchers have interchangeable transition pins and insulators. This design offers many advantages as:

- connector replacement without disturbing the electronic circuit
- improved mechanical performance
- greater design flexibility (mechanical and electrical)
- reduced inventory costs

The launchers accept transition pins with a diameter of 0.92 mm/.036 in. Connectors and pins have to be ordered separately. All parts conform to MIL C-83517. Connector housings are available with recessed or flush rear contact. The PTFE dielectric is always flush with the connector flange back.



Tab contact




Fig. 1





Fig. 2

HUBER+SUHNER type	Item no.	Packaging	Plating body	Fig.	Notes
23_SMA-0-165/199_NE	22644159	single	stainless steel	1	flush design
23_SMA-0-166/199_NE	22644160	single	stainless steel	2	flush design
23_SMA-0-167/199_NE	22644155	single	stainless steel	1	recessed design
23_SMA-0-168/199_NE	22644156	single	stainless steel	2	recessed design

Transition pins for flush launchers


Tab contact



HUBER+SUHNER type	Item no.	Packaging	Plating	Notes
73_Z-0-0-138/1-_UZ	22644145	10 pins	gold	


Transition pins for recessed launchers

Pin contact and insulator




HUBER+SUHNER type	Item no.	Packaging	Plating	Notes
73_Z-0-0-136/1-_UZ	22644151	10 pins and insulators	gold	

Pin contact



HUBER+SUHNER type	Item no.	Packaging	Plating	Notes
73_Z-0-0-141/1-_UZ	22644147	10 pins	gold	

Tab contact



HUBER+SUHNER type	Item no.	Packaging	Plating	Notes
73_Z-0-0-142/1-_UZ	22644148	10 pins	gold	

Slotted contact



HUBER+SUHNER type	Item no.	Packaging	Plating	Notes
73_Z-0-0-151/1-_UZ	22644143	10 pins	gold	


SMA

A FURTHER HUBER+SUHNER PRODUCT!

RF microwave cables and assemblies



Details on our RF cable assemblies are to be found in the general catalogue, Item no. 23012500. Get your copy free of charge at www.hubersuhner.com.





SERIES PC 3.5

PRECISION SUBMINIATURE CONNECTORS

DESCRIPTION


HUBER+SUHNER PC 3.5 connectors are precision connectors for use in microwave applications up to 33 GHz. They are especially suitable for use with semi-rigid cables and microwave components. They are **inter-mateable with SMA and SK connectors**. Due to an air dielectric interface and the more durable construction a superior repeatability further enhances the performance.

CONTENTS

PAGE

Description	141
Interface dimensions	141
Interface dimensions in mm / inches	141
Technical data	142
Cable connectors	144
Connectors with Interchangeable transition pins	145

INTERFACE DIMENSIONS



INTERFACE DIMENSIONS (MM / INCHES)

	Plug		Jack	
	min.	max.	min.	max.
A	4.55/.179	4.58/.180	4.60/.181	4.63/.182
B	0.00/.000	0.08/.003	0.00/.000	0.08/.003
C	2.03/.080	2.29/.090	2.79/.110	3.18/.125
D	3.49/.138	3.51/.138	3.49/.138	3.51/.138
E	2.36/.093	3.56/.135	1.88/.074	1.98/.078
F	1.51/.060	1.52/.060	1.51/.060	1.52/.060
G	0.38/.015	1.14/.045	3.35/.132	4.62/.182
H	0.92/.036	0.93/.037	0.38/.015	1.14/.045
I	—	—	5.30/.209	5.40/.213
K	—	—	5.54/.218	—

Interface dimensions conformable to the Standards:

International: IEC 60169-23

IP rating (interface, mated) IP68

TECHNICAL DATA

ELECTRICAL DATA	REQUIREMENTS
Impedance	50 Ω
Frequency range	DC ... 33 GHz
Dielectric withstanding voltage (at sea level) - RG 405/U - RG 402/U	750 V rms, 50 Hz 1000 V rms, 50 Hz
Working voltage (at sea level) - RG 405/U - RG 402/U	≤ 250 V rms, 50 Hz ≤ 335 V rms, 50 Hz
Insulation resistance	$\geq 5 \cdot 10^3$ M Ω
Contact resistance - centre contact - outer contact	≤ 3 m Ω ≤ 2 m Ω
RF-leakage	≥ 100 dB - f (GHz) dB
VSWR (typical values) - RG 405/U - RG 402/U - adaptors	≤ 1.13 up to 26.5 GHz ≤ 1.10 up to 26.5 GHz ≤ 1.08 up to 18 GHz / ≤ 1.15 up to 26.5 GHz

MECHANICAL DATA	REQUIREMENTS
Coupling nut torque - recommended - proof torque	0.80 Nm ... 1.10 Nm / 7.1 in. lbs ... 9.7 in. lbs 1.70 Nm / 15.0 in. lbs
Coupling nut retention force	≥ 270 N / 60.7 lbs
Contact captivation	≥ 27 N / 6.1 lbs
Cable retention force ¹⁾	see pages 28 – 34
Durability (matings)	≥ 500

1) Value considers maximum load of the cables without irreversible variations of specifications.

ENVIRONMENTAL DATA	TEST CONDITIONS
Temperature range	- 65°C ... + 90°C / - 85 °F ... + 194 °F
Thermal shock	MIL-STD-202, Method 107, Condition B
Moisture resistance	MIL-STD-202, Method 106
Corrosion	Saltspray test acc. to MIL-STD-202, Method 101, Condition B
Vibration	MIL-STD-202, Method 204, Condition D
Shock	MIL-STD-202, Method 213, Condition I

MATERIAL DATA		
CONNECTOR PART	MATERIAL	PLATING
Bodies	stainless steel	passivated
Cable entries	brass	gold
Centre contacts	copper-beryllium alloy	gold
Support beads	polystyrene, crosslinked	
Gaskets	silicone rubber	

Some connectors may have a specification that differs from the above mentioned data.

The products are designed and guaranteed to pass the above mentioned test procedures. Any additional or different requirement arising from specific applications or environmental conditions which is not covered by these test procedures is subject to request.

CABLE CONNECTORS

Straight cable plugs (male)

- > for semi-rigid cables
- > cable entry soldered
- > centre contact plugged-in




Fig. 1




Fig. 2



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Fig.	Notes
11_PC35-50-2-4/199_UE	84009440	Y3, Y11 (EZ 86)	single	0000215467	1	
11_PC35-50-3-4/199_UE	84009380	Y5, Y12 (EZ 141)	single	0000215467	2	

Straight cable jacks (female)

- > for semi-rigid cables
- > cable entry soldered
- > centre contact plugged-in




Fig. 1




Fig. 2



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Fig.	Notes
21_PC35-50-2-4/199_UE	84009419	Y3, Y11 (EZ 86)	single	0000215467	1	
21_PC35-50-3-3/199_UE	84009382	Y5, Y12 (EZ 141)	single	0000215467	2	

Straight bulkhead cable jacks (female)

- > for semi-rigid cables
- > bulkhead mounted
- > cable entry soldered
- > centre contact plugged-in
- > with panel seal




Fig. 1




Fig. 2

HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Fig.	Mounting hole
24_PC35-50-2-2/199_UE	84009405	Y3, Y11 (EZ 86)	single	0000215467	1	ML 35
24_PC35-50-3-2/199_UE	84009383	Y5, Y12 (EZ 141)	single	0000215467	2	ML 35

CONNECTORS WITH INTERCHANGEABLE TRANSITION PINS

Flange mount, jacks (female)

- > panel mounted





Fig. 1





Fig. 2

HUBER+SUHNER type	Item no.	Packaging	Flange type	Fig.	Notes
23_PC35-50-0-51/199_UE	22644918	single	square	1	
23_PC35-50-0-53/199_UE	22644910	single	square	2	

> panel mounted




HUBER+SUHNER type	Item no.	Packaging	Flange type	Notes
23_PC35-50-0-54/199_UE	22644911	single	2-hole	

Transition Pins


for PC 3.5 connectors with interchangeable contact pins

Pin contact




HUBER+SUHNER type	Item no.	Packaging	Plating	Notes
73_Z-0-0-168	22644927	10 pins	gold	

Tab contact



HUBER+SUHNER type	Item no.	Packaging	Plating	Notes
73_Z-0-0-169	22644931	10 pins	gold	

Tab contact



HUBER+SUHNER type	Item no.	Packaging	Plating	Notes
73_Z-0-0-170	22644932	10 pins	gold	



SERIES SK, PRECISION SUBMINIATURE CONNECTORS

DESCRIPTION


HUBER+SUHNER SK connectors are precision connectors for microwave applications up to 40 GHz. They are **intermateable with series SMA and PC 3.5**. They have a high mechanical stability and an excellent repeatability. The shortened male pin ensures a non-destructive mating process. The glass beads, when used in conjunction with the SK launchers, enable the connectors to be replaced without disturbing the hermetic seal. For a mechanical decoupling between glass bead and internal microwave circuit, stress relief contacts are available.

CONTENTS

PAGE

Description	147
Interface Dimensions in mm / inches	147
Technical Data	148
Cable Connectors	149
Launchers	150
Accessories	151

INTERFACE DIMENSIONS



INTERFACE DIMENSIONS (MM / INCHES)

	Plug		Jack	
	min.	max.	min.	max.
A	4.53/.178	4.57/.180	4.60/.181	4.64/.183
B	0.00/.000	0.13/.005	0.00/.000	0.13/.005
C	1.55/.061	1.65/.065	2.80/.110	—
D	2.89/.114	2.95/.116	2.89/.114	2.95/.116
E	—	3.28/.129	1.88/.074	1.98/.078
F	0.91/.036	0.94/.037	5.90/.232	—
G	—	—	4.40/.173	—
H	—	—	0.70/.028	0.90/.036
I	—	—	5.30/.208	5.40/.213

IP rating (interface, mated) IP68

TECHNICAL DATA

ELECTRICAL DATA	REQUIREMENTS
Impedance	50 Ω
Frequency range	DC ... 40 GHz
Dielectric withstanding voltage (at sea level)	750 V rms, 50 Hz
Working voltage (at sea level) mated / unmated	≤ 250 V rms, 50 Hz
Insulation resistance	$\geq 5 \cdot 10^3$ M Ω
Contact resistance - centre contact - outer contact	≤ 3 m Ω ≤ 2 m Ω
VSWR (typical values) - cable connectors (cable assembly with 2 connectors) - launchers	≤ 1.37 DC ... 40 GHz ≤ 1.43 DC ... 40 GHz

MECHANICAL DATA	REQUIREMENTS
Coupling nut torque - recommended - proof torque	1.30 Nm / 11.47 in. lbs 1.70 Nm / 15.0 in. lbs
Contact captivation	≥ 22 N / 4.9 lbs
Durability (matings)	≥ 500

ENVIRONMENTAL DATA	TEST CONDITIONS
Temperature range	- 55°C ... + 125°C / - 67°F ... + 257°F
Thermal shock	MIL-STD-202, Method 107, Condition B
Vibration	MIL-STD-202, Method 204, Condition D

MATERIAL DATA		
CONNECTOR PART	MATERIAL	PLATING
Bodies, cable connectors	copper-beryllium alloy / stainless steel	gold
Bodies, receptacles	stainless steel / copper alloy	passivated / gold
Centre contacts	copper-beryllium alloy	gold
Support beads	PPO (polyphenylene oxide)	

Some connectors may have a specification that differs from the above mentioned data.

The products are designed and guaranteed to pass the above mentioned test procedures. Any additional or different requirement arising from specific applications or environmental conditions which is not covered by these test procedures is subject to request.

CABLE CONNECTORS

Straight cable plugs (male)

> for semi-rigid cables




Fig. 1




Fig. 2




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Fig.	Notes
11_SK-50-2-56/119_NE	84013230	Y3, Y11 (EZ 86)	single	27445	1	plug
21_SK-50-2-58/199_NE	84019664	Y3, Y11 (EZ 86)	single	0000234990	2	jack

Straight bulkhead cable jacks (female)

> for semi-rigid cables

> with panel seal



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole
24_SK-50-2-55/1-_NE	84016419	Y10 (EZ 118-TP)	single	0000229976 / ML 35

LAUNCHERS

"Sparkplug" Launchers




Fig. 1




Fig. 2



HUBER+SUHNER type	Item no.	Packaging	Assembly instruction	Mounting hole	Fig.	Notes
12_SK-50-0-51/199_NE	22645974	single	9181	ML 75	1	plug
22_SK-50-0-51/199_NE	22645975	single	9181	ML 75	2	jack

Panel launchers (male)




Fig. 1






Fig. 2



HUBER+SUHNER type	Item no.	Packaging	Assembly instruction	Mounting hole	Flange type	Fig.	Notes
13_SK-50-0-51/199_NE	22645978	single	9182	ML 77	square	1	
13_SK-50-0-52/199_NE	22645976	single	9182	ML 78	2-hole	2	

Panel launchers (female)




Fig. 1







Fig. 2



HUBER+SUHNER type	Item no.	Packaging	Assembly instruction	Mounting hole	Flange type	Fig.	Notes
23_SK-50-0-51/199_NE	22645979	single	9182	ML 77	square	1	
23_SK-50-0-52/199_NE	22645977	single	9182	ML 78	2-hole	2	


ACCESSORIES

Glass bead for 12 SK, 13 SK, 22 SK, 23 SK launchers (package with 1 piece)



HUBER+SUHNER® TYPE
73_Z-0-0-203/11-_NE
Item no. 22645983

Microstrip stress relief contacts (package with 100 pieces)



HUBER+SUHNER® TYPE
73_Z-0-0-204/1-_NH
Item no. 22645980

SK

A FURTHER HUBER+SUHNER PRODUCT GROUP!

RF test and measurement components



Details on this product range are to be found in the Test and Measurement general catalogue, Item no. 23012791. Get your copy free of charge at www.hubersuhner.com.





SERIES 1.0/2.3, INSERTS ACCORDING TO DIN 41626/2

DESCRIPTION


HUBER+SUHNER Coaxial "Inserts" 1.0/2.3 are suitable for the insertion of mixed layout connectors DIN 41612 (pattern M). These inserts feature a slide-on coupling mechanism, which ensures a short connect-disconnect time. Impedance accuracy, fast and easy assembly as well as high reproducibility due to the full crimp cable entry are typical characteristics of these H+S connectors. The 1.0/2.3 inserts are suitable for applications up to 4 GHz.

CONTENTS

PAGE

Description	153
Interface dimensions	153
Interface dimensions in mm / inches	153
Technical data	154
Cable connectors	154
PCB connectors	156

INTERFACE DIMENSIONS



INTERFACE DIMENSIONS (MM / INCHES)

	Plug		Jack	
	min.	max.	min.	max.
A	5.40/.213	5.70/.224	4.50/.177	—
B	—	1.15/.045	1.15/.045	1.45/.057
C	5.20/.205	5.50/.217	5.80/.228	5.90/.232
D	3.05/.120	3.20/.126	6.40/.252	6.50/.256
E	9.25/.364	9.35/.368	9.50/.374	9.60/.378
F	2.22/.087	2.40/.094	2.22/.087	2.40/.094
G	4.76/.187	4.79/.189	4.76/.187	4.79/.189
H	—	6.00/.236	—	6.00/.236
I	4.20/.165	4.28/.169	4.03/.159	4.15/.163
K	4.66/.183	4.78/.188	4.72/.186	4.75/.187
L	1.00/.039 nom.		1.00/.039 nom.	
M	0.48/.019	0.52/.020	0.50/.020	0.60/.024
N	—	—	3.00/.118	3.06/.120

Interface dimensions conformable to the Standards:

Germany: DIN 41626/2

IP rating (interface, mated) IP50

1.0/2.3
QLA

TECHNICAL DATA

ELECTRICAL DATA	REQUIREMENTS
Impedance	50 Ω
Frequency range	DC ... 4 GHz
Dielectric withstanding voltage (at sea level)	750 V rms, 50 Hz (depending on cable)
Working voltage (at sea level)	250 V rms, 50 Hz (depending on cable)
Insulation resistance	$\geq 200 \text{ M}\Omega$
Contact resistance	
- centre contact	$\leq 10 \text{ m}\Omega$
- outer contact	$\leq 3 \text{ m}\Omega$

MECHANICAL DATA	REQUIREMENTS
Engagement force	$\leq 10 \text{ N} / 2.3 \text{ lbs}$
Disengagement force	$\leq 10 \text{ N} / 2.3 \text{ lbs}$
Contact captivation	$\geq 10 \text{ N}$
Cable retention force ¹⁾	see pages 28 - 34
Durability (matings)	≥ 500

1) Value considers maximum load of the cables without irreversible variations of specifications.


ENVIRONMENTAL DATA	TEST CONDITIONS
Temperature range	- 55°C ... + 125°C / - 67 °F ... + 257 °F
Climatic category	IEC → 50/125/56
Moisture resistance	MIL-STD-202, Method 106
Corrosion	Saltspray test acc. to MIL-STD-202, Method 101, Condition B
Vibration	MIL-STD-202, Method 204, Condition A

MATERIAL DATA		
CONNECTOR PARTS	MATERIAL	PLATING
Bodies	brass	SUCOPLATE® / gold
Outer contacts	copper-beryllium alloy, brass	gold / SUCOPRO
Pin contacts	brass	gold / SUCOPRO
Socket contacts	copper-beryllium alloy	gold / SUCOPRO
Crimp ferrules	copper	SUCOPLATE® / gold
Insulators	PTFE or PFA	

Some connectors may have a specification that differs from the above mentioned data.

The products are designed and guaranteed to pass the above mentioned test procedures. Any additional or different requirement arising from specific applications or environmental conditions which is not covered by these test procedures is subject to request.


Typical application



CABLE CONNECTORS

Straight cable plugs (male)


- > HUBER+SUHNER® full crimp
- > removal tool see page 392



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
11_1023-C50-2-2/111_NE	22648559	U4 (K 02252 D)	single	9191	1 A
11_1023-C50-2-2/111_NH	22649631	U4 (K 02252 D)	bulk 100 pcs.	9191	1 A
11_1023-C50-2-3/111_NE	22648780	U2 (RG 316/U)	single	9191	1 A
11_1023-C50-2-3/111_NH	22649007	U2 (RG 316/U)	bulk 100 pcs.	9191	1 A

Straight cable jacks (female)

- > HUBER+SUHNER® full crimp
- > removal tool see page 392




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
21_1023-C50-2-2/111_NE	22648560	U4 (K 02252 D)	single	9191	1 A
21_1023-C50-2-3/111_NE	22648790	U2 (RG 316/U)	single	9191	1 A

PCB CONNECTORS

Right angle PCB jacks (female)

- > removal tool see page 392



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
85_1023-C50-0-1/111_NE	22648561	single	ML 15	



SERIES QLA 00, SUBMINIATURE COAXIAL CONNECTORS

DESCRIPTION

The QLA 00 series contains connectors with a quick latch coupling mechanism: connection is achieved by simply pushing the plug into the jack. 3 latching springs automatically engage, thereby securing the mated connectors against axial and rotational forces. No twisting action is required. The connectors are easily released by slightly pulling back the outer sleeve of the plug. This coupling mechanism provides a fast and reliable connection for applications up to 1.4 GHz.

Compatibility


All connectors of the series QLA 00 are without any restrictions intermateable with Lemo series 00.250.

CONTENTS

PAGE

Description	157
Interface dimensions	157
Interface dimensions in mm / inches	157
Standards	157
Technical data	158
Cable connectors	160
Receptacles with solder end	163
PCB connectors	164
Shorting plugs	164

INTERFACE DIMENSIONS



INTERFACE DIMENSIONS (MM / INCHES)

	Plug		Jack	
	min.	max.	min.	max.
A	4.96/.195	5.03/.198	5.05/.199	5.11/.201
B	3.38/.133	3.44/.135	3.50/.138*	3.55/.140*
C	3.93/.155	4.08/.161	3.73/.147	3.86/.152
D	3.55/.140	—	—	3.48/.137
E	0.95/.037 nom.		1.24/.049 nom.	
F	4.00/.157	4.16/.164	4.23/.167	4.88/.192
G	2.10/0.83	2.16/.085	1.95/.077	2.03/.080
H	—	1.32/.052	—	3.30/.130
I	0.69/.027	0.72/.028	2.35/.093	2.90/.114

* prior to slotting

Interface dimensions conformable to the Standards:

NIM-CAMAC-Standard CD/N549

IP rating (interface, mated) IP50

QLA

TECHNICAL DATA

ELECTRICAL DATA	REQUIREMENTS
Impedance	50 Ω
Frequency range	DC ... 1.4 GHz
Dielectric withstanding voltage (at sea level)	1.5 kV, 50 Hz
Working voltage (at sea level) - unmated - mated	≤ 300 V rms, 50 Hz ≤ 500 V rms, 50 Hz
Insulation resistance	$\geq 10^6$ M Ω
Contact resistance - centre contact - outer contact	≤ 4 m Ω ≤ 2 m Ω
VSWR (typical value for mated connector pair) 11 QLA - 21 QLA	DC ... 300 MHz = 1.15 300 MHz - 1.4 GHz = 1.20
RF-leakage (measured at 500 MHz)	≥ 80 dB

MECHANICAL DATA	REQUIREMENTS
Engagement force	typ. 2 N / .45 lbs
Disengagement force	typ. 5 N / 1.1 lbs
Contact captivation	≥ 20 N / 4.5 lbs
Cable retention force ¹⁾	see pages 28 - 34
Durability (matings)	$\geq 10\,000$

1) Value considers maximum load of the cables without irreversible variations of specifications.

ENVIRONMENTAL DATA	TEST CONDITIONS
Temperature range	- 55°C ... + 150°C / - 67 °F ... + 302 °F
Thermal shock	MIL-STD-202, Method 107, Condition B
Moisture resistance	MIL-STD-202, Method 106
Corrosion	Saltspray test acc. to MIL-STD-202, Method 101, Condition B
Vibration	MIL-STD-202, Method 204, Condition D
Shock	MIL-STD-202, Method 213, Condition I

MATERIAL DATA		
CONNECTOR PARTS	MATERIAL	PLATING
Bodies	brass, annealed	nickel
Pin contacts	brass, annealed	gold
Socket contacts	copper-beryllium alloy	gold
Crimp ferrules	copper	SUCOPLATE®
Insulators	PTFE or PFA	


Some connectors may have a specification that differs from the above mentioned data.

The products are designed and guaranteed to pass the above mentioned test procedures. Any additional or different requirement arising from specific applications or environmental conditions which is not covered by these test procedures is subject to request.

CABLE CONNECTORS


Straight cable plugs (male)

- > for flexible cables
- > cable entry clamp
- > centre contact soldered




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Notes
11_QLA-01-2-11/122_NE	22544536	U2 (EF 316)	single	9008	

- > for flexible cables
- > HUBER+SUHNER® full crimp



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
11_QLA-01-1-8/122_NE	22641146	U1 (EF 178)	single	9007	1 A
11_QLA-01-2-8/122_NE	22544043	U2 (EF 316)	single	9007	1 A
11_QLA-01-2-8/122_NH	22544042	U2 (EF 316)	bulk 100 pcs.	9007	1 A
11_QLA-01-2-9/122_NH	22648228	U4 (EF 316 D)	bulk 100 pcs.	9007	1 A
11_QLA-01-2-13/122_NH	22644547	U3 (G 01130 HT)	bulk 100 pcs.	27020	1 A

- > for flexible cables
- > HUBER+SUHNER® full crimp




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
11_QLA-01-3-1/122_NE	22641313	U7 (RG 58 C/U)	single	3015	2 B
11_QLA-01-3-2/122_NE	22643326	U9 (RG 223/U)	single	3015	2 B

Right angle cable plugs (male)

> for flexible cables

- > cable entry crimp
- > centre contact soldered




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
16_QLA-01-1-1/122_NE	22640011	U1 (EF 178)	single	3091	A
16_QLA-01-2-1/122_NE	22640013	U2 (EF 316)	single	3091	A
16_QLA-01-2-13/122_NE	22544279	U3 (G 01130 HT)	single	3091	A
16_QLA-01-2-4/122_NE	22640015	U4 (EF 316 D)	single	3091	A
16_QLA-01-2-4/122_NH	22646619	U4 (EF 316 D)	bulk 100 pcs.	3091	A

Straight cable jacks (female)

> for flexible cables


- > cable entry crimp
- > centre contact soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
21_QLA-01-2-1/112_NE	22640019	U2 (EF 316)	single	3089	A
21_QLA-01-2-1/112_NH	22651746	U2 (EF 316)	bulk 100 pcs.	3089	A

> for flexible cables


- > HUBER+SUHNER® full crimp



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
21_QLA-01-2-5/112_NH	22652371	U2 (EF 316)	bulk 100 pcs.	27158	1 A


Straight bulkhead cable jacks (female)

- > for semi-rigid cables
- > cable entry soldered
- > centre contact plugged-in




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole
24_QLA-01-2-5/112_NH	23002772	Y11,Y3 (Sucoform 86)	bulk 100 pcs.	27362 / ML 20

- > for flexible cables
- > cable entry clamp
- > centre contact soldered




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly Instruction/ Mounting Hole	Notes
24_QLA-01-1-11/112_NE	22642297	U1 (EF 178)	single	9008/ML 99	max. cable diameter 2.10 mm/.093 in.
24_QLA-01-2-11/112_NE	22544535	U2 (EF 316)	single	9008/ML 99	max. cable diameter 2.90 mm/.114 in.

- > for flexible cables
- > cable entry clamp
- > centre contact soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly Instruction/ Mounting Hole	Notes
24_QLA-01-1-12/112_NH	22659147	U1 (RG 178 B/U)	bulk 100 pcs.	9008/ML 23	max. cable diameter 2.10 mm/.093 in.

- > for flexible cables
- > cable entry crimp
- > centre contact soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly Instruction/ Mounting Hole	Crimp insert
24_QLA-01-2-1/112_NE	22640026	U2 (RG 316/U)	single	3089/ML 99	A

RECEPTACLES WITH SOLDER END

Receptacles, jacks (female)

- > bulkhead mounted




Fig. 1





Fig. 2

HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Fig.	Crimp insert
22_QLA-01-0-1/112_NE	22640023	single	ML 23	1	assembly tool 74_Z-0-0-25 required
22_QLA-01-0-1/112_NH	22646308	bulk 100 pcs.	ML 23	1	assembly tool 74_Z-0-0-25 required
22_QLA-01-0-2/112_NE	22640024	single	ML 99	2	counter sunk from rear


PCB CONNECTORS

Straight PCB jacks (female)




HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
82_QLA-01-0-2/112_NE	22543414	single	ML 97	without stand-off

Right angle PCB jacks (female)



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
85_QLA-01-0-2/112_NE	22640039	single	ML 97	without stand-off
85_QLA-01-0-2/110_NH	22646483	bulk 100 pcs.	ML 97	without stand-off
85_QLA-01-0-2/122_NE	22651770	single	ML 97	without stand-off

SHORTING PLUGS



HUBER+SUHNER type	Item no.	Packaging	Notes
64_QLA-01-0-1/122_NE	22640035	single	



SERIES BMA, SUBMINIATURE BLIND MATE CONNECTORS

DESCRIPTION

HUBER+SUHNER BMA blind mate connectors open up special dimensions in microwave applications up to 18 GHz. HUBER+SUHNER offers a range of connectors for fixed as well as "floating" configurations with any axial or radial misalignment taken out by the outer contact of the jacks.


The BMA series presents an outstanding range of products featuring high reliability and ease of assembly.

CONTENTS

PAGE

Description	165
Interface Dimensions	165
Interface Dimensions in mm / inches	165
Compatibility	165
Technical Data	166
BMA Connector Applications	168
Cable Connectors	171
Receptacles with Solder-in Hermetic Seal	174
Receptacles with Solder End	175
PCB Connectors	176

INTERFACE DIMENSIONS



INTERFACE DIMENSIONS (MM / INCHES)

	Plug		Jack	
	min.	max.	min.	max.
A	4.09 / .161 nom		1.78 / .070 nom.	
B	4.88 / .192 nom.		4.09 / .161 nom.	
C	5.31/.209	5.35/.211	—	5.08/.200
D	7.62 / .300 nom.		5.71/.225	—
E	5.03/.198	—	7.37/.290	—
F	3.25/.128	—	3.05/.120	3.23/.127
G	2.29 / .090 nom.		—	5.03/.198
H	0.90/.035	0.94/.037		
I	1.78 / .070 nom.			

Interface dimensions conformable to the Standards:

USA: MIL-STD-348A/321

COMPATIBILITY

The HUBER+SUHNER range of BMA connectors is fully compatible with the OSP connector series.

IP rating (interface, mated) IP60

BMA

TECHNICAL DATA

ELECTRICAL DATA	REQUIREMENTS	
Cable type	.086" Semi-Rigid	.141" Semi-Rigid
Impedance	50 Ω	
Frequency range	DC ... 18 GHz	
Dielectric withstanding voltage (at sea level)	1.5 kV rms, 50 Hz	1.0 kV rms, 50 Hz
Insulation resistance	$\geq 5 \cdot 10^3 \text{ M}\Omega$	
Contact resistance	$\leq 2 \text{ m}\Omega$	
- centre contact	$\leq 2 \text{ m}\Omega$	
- outer contact	$\leq 2 \text{ m}\Omega$	
VSWR (typical values)	(mated connector pair)	(mated connector pair)
- DC ... 18 GHz	$\leq 1.02 + 0.005 f \text{ (GHz)}$	$\leq 1.05 + 0.005 f \text{ (GHz)}$
RF-leakage interface only (fully mated)	$\geq 90 \text{ dB} - f \text{ (GHz)}^1$	
RF-testing voltage (at sea level)	1.0 kV rms, 5 MHz	670 V rms, 5 MHz
Admissible power (at sea level and room temperature)	$\leq 300 \text{ W at } 3 \text{ GHz}$	

1) measured at interface with reference planes being in true alignment

MECHANICAL DATA	REQUIREMENTS
Engagement force	$\leq 13.5 \text{ N}$
Disengagement force	$\geq 2 \text{ N}$
Contact captivation	$\geq 27 \text{ N} / 6.1 \text{ lbs}$
Cable retention force ¹⁾	see pages 28 - 34
Durability (matings)	≥ 1000

1) Value considers maximum load of the cables without irreversible variations of specifications.

ENVIRONMENTAL DATA	TEST CONDITIONS
Temperature range	- 65°C ... + 125°C / - 85 °F ... + 257 °F
Thermal shock	MIL-STD-202, Method 107, Condition B
Moisture resistance	MIL-STD-202, Method 106
Corrosion	Saltspray test acc. to MIL-STD-202, Method 101, Condition B
Vibration	MIL-STD-202, Method 204, Condition D
Shock	MIL-STD-202, Method 213, Condition I

MATERIAL DATA		
CONNECTOR PARTS	MATERIAL	PLATING
Bodies	copper-beryllium alloy stainless steel	gold
Pin contacts	copper-beryllium alloy	gold
Spring basket	copper-beryllium alloy	gold
Springs (floating connectors)	stainless steel	
Insulators	PTFE or PFA	
Gaskets	EPDM, 40 shore A	

Some connectors may have a specification that differs from the above mentioned data.

The products are designed and guaranteed to pass the above mentioned test procedures. Any additional or different requirement arising from specific applications or environmental conditions which is not covered by these test procedures is subject to request.

BMA CONNECTOR APPLICATIONS

Quick and reliable engagement and disengagement of multiple microwave transmission lines, high packaging density of flexible and rigid coaxial lines and cable free connection of modules to motherboard are some needs of modern microwave systems.

HUBER+SUHNER BMA connectors offer an economical solution for the most demanding interconnector applications found today in civil and military microwave circuits. To help ensure a problem free, reliable long term operation the following guidelines should be used.


Assembly hints

Radial and axial misalignments can be accommodated with the spring outer contacts of the HUBER+SUHNER BMA connector.

These misalignments are due to the build up of tolerances with the major contributions coming from: Axial direction, mounting plate distances and plate distortions. Radial direction: mounting hole positions and concentricity, plate distortion and misalignment.

For recommended mounting hole sizes see page 412.

Rigid mounting




Maximum misalignment

Axial: 0.38 mm / .015 in. *

Radial: 0.20 mm / .008 in.

* For applications with reduced return loss specifications
0.76 mm / .030 in. is allowable.


Hole dimensions



To avoid tolerances build up all mounting holes must be tolerated from a single datum point.

It is also important that both of the mounting plates are properly affixed and correctly positioned.

Float mounting




The increased tolerance correction of the connector is achieved by using an extra spring system.

This allows the centre assembly of the connector to move freely within the flange body.

Recommended maximum tolerances:

Axial: 1.52 mm / .060 in.

Radial: 0.51 mm / .020 in.



The adjacent diagram shows the relationship between the connector preloading force and the separation distance "L" between the mounting reference planes for a typical connector pair (25_BMA-50-3-2 and 14_BMA-50-3-2).

To ensure optimum contact under extreme radial misalignment the following points must be considered:

A:

The maximum misalignment tolerances must not be exceeded. Any possible bending of the mounting plate due to the spring preloading of the individual connectors must be taken into account.

If distortion occurs the following steps should be taken to minimize the effect:

- re-dimensioning
- bracing of the mounting plate
- reduction of maximum connector preloading force which will result in the limitation of length L.

B:

A minimum preloading force of 16 N must be ensured for each connector pair so that the maximum engaging force will be exceeded. This represents the upper limit of separation. For the example above this is a length L of maximum 10.65 mm / .419 in.


Data on other connector combinations available on request.

For the dimensioning of the holes the same points must be considered as for the rigid mounting.

Mounting plate bending

For an array of BMA connectors to be mounted on a chassis, the forces on the connectors must be taken into account and in the case of a floating assembly the preloading forces must be considered.

For a simplified calculation the mounting plate can be considered as a beam under deflection, thus the bending is:



Legend:

D	deflection = $\frac{n \cdot F \cdot l^3}{384 E \cdot I}$
E	modulus of elasticity aluminium: $E = 70'000 \text{ N/mm}^2$ steel: $E = 210'000 \text{ N/mm}^2$
F	preloading force
I	moment of beam = $\frac{w \cdot t^3}{12}$
l	length of panel
n	number of connectors
t	thickness of panel
w	width of panel

Example:

4 connectors of type 25_BMA-50-3-2 (preloading force $F = 20 \text{ N}$ each):

$E = 70'000 \text{ N/mm}^2$ (aluminium chassis)

thickness of panel (t) 2 mm

width of panel (w) 20 mm

length of panel (l) 80 mm

$$I = \frac{20\text{mm} \cdot (2\text{mm})^3}{12} = 13.33\text{mm}^4$$

$$D = \frac{4 \cdot 20\text{N} \cdot (80\text{mm})^3}{384 \cdot 70'000 \frac{\text{N}}{\text{mm}^2} \cdot 13.33\text{mm}^4} = 0.11\text{mm}$$

CABLE CONNECTORS

Straight bulkhead cable plugs (male)

- > for semi-rigid cables
- > cable entry soldered
- > bulkhead mounted, rigid
- > body material: CuBe, gold plated




Fig. 1




Fig. 2




Fig. 3

HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Mounting hole	Fig.
14_BMA-50-1-15/111_NE	22646663	Y2 (EZ 47)	single	27180	ML 56	1
14_BMA-50-2-2/111_NE	22645600	Y3, Y11 (EZ 86)	single	9171	ML 56	2
14_BMA-50-3-2/111_NE	22645601	Y5, Y12 (EZ 141)	single	9171	ML 56	3

> for flexible cables

- > cable entry crimp
- > bulkhead mounted, rigid
- > body material: stainless steel




Fig. 1




Fig. 2


HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Mounting hole	Crimp insert	Fig.
14_BMA-50-2-3/199_NE	22645614	U2 (RG 316/U)	single	9172	ML 56	A ¹⁾	1
14_BMA-50-3-3/199_NE	22645615	U9, 11 (RG 400/U)	single	9173	ML 56	B ²⁾	2

1) MIL insert M22520/5-03A can also be used

2) MIL insert M22520/5-05A can also be used

Straight panel cable plugs (male)

- > for semi-rigid cables
- > cable entry soldered
- > 2-hole mounted
- > body material: CuBe, gold plated



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Notes
15_BMA-50-1-15/111_NE	22649704	Y2 (EZ 47)	single	27180	

Straight bulkhead cable jacks (female)

- > for semi-rigid cables
- > cable entry soldered
- > snap-in, floating
- > body material: CuBe, gold plated




Fig. 1




Fig. 2

Connector fixed into mounting panel with snap-in mechanism.
Recommended removal tool: 74_Z-0-0-213

HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole	Fig.
24_BMA-50-2-4/111_NE	22645606	Y3, Y11 (EZ 86)	single	9171 / ML 66	1
24_BMA-50-3-4/111_NE	22645607	Y5, Y12 (EZ 141)	single	9171 / ML 66	2

It is recommended to use a service loop to facilitate the float features of the connector

> for flexible cables

- > cable entry crimp
- > snap-in, floating
- > body material: stainless steel




Fig. 1




Fig. 2

Connector fixed into mounting panel with snap-in mechanism.
Recommended removal tool: 74_Z-0-213

HUBER+SUHRNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole	Crimp insert	Fig.
24_BMA-50-2-5/119_NE	22645620	U2 (RG 316/U)	single	9172 / ML 66	A ¹⁾	1
24_BMA-50-3-5/119_NE	22645621	U9, 11 (RG 400/U)	single	9173 / ML 66	B ²⁾	2

1) MIL insert M22520/5-03A can also be used

2) MIL insert M22520/5-05A can also be used

Straight panel cable jacks (female)

> for semi-rigid cables

- > cable entry soldered
- > flange mount, floating




Fig. 1




Fig. 2

A = min. 2.1 mm/.083 in. axial range of spring

B = min. 0.5 mm/.020 in. radial misalignment

Outer connector body and flange of stainless steel, inner
floating part of gold plated CuBe

HUBER+SUHRNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole	Fig.
25_BMA-50-2-2/119_NE	22645604	Y3, Y11 (EZ 86)	single	9171 / ML 58	1
25_BMA-50-3-2/119_NE	22645605	Y5, Y12 (EZ 141)	single	9171 / ML 58	2

It is recommended to use a service loop to facilitate the float features of the connector

- > for flexible cables
- > cable entry crimp
- > flange mount, floating




Fig. 1

A = min. 2.1 mm/.083 in. axial range of spring

B = min. 0.5 mm/.020 in. radial misalignment




Fig. 2

Outer connector body and flange of stainless steel, inner floating part of gold plated CuBe

HUBER+SUHRNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole	Crimp insert	Fig.
25_BMA-50-2-3/119_NE	22645618	U2 (RG 316/U)	single	9172 / ML 58	A ¹⁾	1
25_BMA-50-3-3/119_NE	22645619	U9, 11 (RG 400/U)	single	9173 / ML 58	B ²⁾	2


1) MIL insert M22520/5-03A can also be used

2) MIL insert M22520/5-05A can also be used

RECEPTACLES WITH SOLDER-IN HERMETIC SEAL

Receptacles, plugs (male)

- > bulkhead mounted
- > threaded installation
- > body material: stainless steel




HUBER+SUHRNER type	Item no.	Packaging	Mounting hole	Suitable ¹⁾ glass-bead	Notes
12_BMA-50-0-3/199 NE	22645636	single	ML 61	73 Z-0-0-198	

Use tool 74_Z-0-0-215 with torque wrench 74_Z-0-0-214 for mounting. For fixturing hermetic seal while soldering, fixture 74_Z-0-0-211 is recommended.

1) see page 411

Receptacles, jacks (female)

- > bulkhead mounted
- > threaded installation
- > body material: stainless steel



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Suitable ¹⁾ glass-bead	Notes
22_BMA-50-0-3/199_NE	22645637	single	ML 61	73 Z-0-0-198	


1) see page 411

Use torque wrench 74_Z-0-0-214 for mounting. For fixturing hermetic seal while soldering, fixture 74_Z-0-0-211 is recommended.

RECEPTACLES WITH SOLDER END


Receptacles, plugs (male)

- > panel mounted
- > body material: stainless steel




HUBER+SUHNER type	Item no.	Packaging	Flange type	Notes
13_BMA-50-0-1/199_NE	22645622	single	square	with extended dielectric

- > panel mounted
- > body material: stainless steel



HUBER+SUHNER type	Item no.	Packaging	Flange type	Notes
13_BMA-50-0-13/199_NE	22660107	single	square	with extended dielectric


- > panel mounted
- > body material: stainless steel



HUBER+SUHNER type	Item no.	Packaging	Flange type	Notes
13_BMA-50-0-2/199_NE	22645623	single	2-hole	with extended dielectric

Receptacles, jacks (female)

- > panel mounted
- > body material: stainless steel




HUBER+SUHNER type	Item no.	Packaging	Flange type	Notes
23_BMA-50-0-1/199_NE	22645624	single	square	with extended dielectric

PCB CONNECTORS

Straight PCB plugs (male)


- > body material: CuBe, gold plated



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
81_BMA-50-0-1/111_NE	22645630	single	ML 41	

Straight PCB jacks (female)

> body material: CuBe, gold plated




HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
82_BMA-50-0-1/111_NE	22645631	single	ML 41	

A FURTHER HUBER+SUHNER PRODUCT!

RF corrugated cable assemblies LISCA



Details on this product are to be found in the brochure,
Item no. 23035388. Get your copy free of charge at
www.hubersuhner.com.





SERIES QMA, SUBMINIATURE CONNECTORS

DESCRIPTION

HUBER+SUHNER QMA coaxial connectors are available with 50 Ω impedance. The frequency range extends to 18 GHz, depending on the connector and cable type, however most of the QMA connectors are Return Loss optimised for frequencies up to 6 GHz. The interface is based on the SMA dimension, but, instead of a threaded coupling mechanism, a new snap-lock mechanism is used.

The QMA interface has a very similar performance to the SMA, but in addition it offers an easier, faster and safer coupling operation, helping the customers to save significantly time during production of their systems.

The packaging density of QMA is increased compared to SMA connectors thanks to the fact that no torque spanner is required to fasten the coupling nut.

QMA is not intermateable with SMA.

CONTENT


PAGE

Description	179
Interface dimensions	179
Features of QMA connectors	179
Technical data	180
Cable connectors	181
Receptacles with solder end	185
PCB connectors	187
QMA-calibration	189

INTERFACE DIMENSIONS (COMPARED TO SMA)

FEATURES OF QMA CONNECTORS

QMA
QN



- > Cycle time improvement for making RF connections (10 times faster to mount than threaded connectors)
- > No torque required
- > Higher packaging density
- > Free-rotating connection when mated
- > Eliminates loosening problems associated with threaded connectors
- > Same performance as SMA up to 6 GHz

HUBER+SUHNER QMA - the cost effective solution for advanced RF interconnections!

IP rating (interface, mated) IP50*

* IP68 variant available

TECHNICAL DATA

ELECTRICAL DATA	REQUIREMENTS
Impedance	50 Ω
Frequency range	DC to 6 GHz optimized DC to 18 GHz working range [interface]
Dielectric withstanding voltage (at sea level)	1000 V rms, 50 Hz
Working voltage (at sea level)	≤ 480 V rms, 50 Hz
Insulation resistance	$\geq 5 \cdot 10^3$ M Ω
Contact resistance - centre contact - outer contact	≤ 3 m Ω ≤ 2.5 m Ω
RF-leakage	0 ... 3 GHz ≥ -80 dB; 3 ... 6 GHz ≥ -70 dB
Return loss (typical)	DC - 3 GHz ≥ 32 dB; 3 to 6 GHz ≥ 25 dB

MECHANICAL DATA	REQUIREMENTS
Engagement force (typical)	25 N
Disengagement force (typical)	20 N
Retention force for interface	≥ 60 N
Durability (matings)	≥ 100
Distance between connectors	12.4 mm / .49 in. minimum

ENVIRONMENTAL DATA	TEST CONDITIONS
Temperature range	-40°C ... +85°C / -40°F ... +185°F
Thermal shock	IEC 60169-1 16.4 (-40° C / +85° C)
Corrosion	IEC 60169-1 16.7 (48 hrs)
Vibration	IEC-68-2-64 random, 5-20 Hz: 1.29 (m/s ²) ² /Hz 20-500 Hz: -3dB/octave
Damp heat - steady state	IEC 60169-1 16.3 (96 hrs)

MATERIAL DATA		
CONNECTOR PART	MATERIAL	PLATING
Bodies	brass	SUCOPLATE®
Solder bodies	brass	SUCOPRO
Pin contacts	brass	SUCOPRO
Socket contacts	spring bronze	SUCOPRO
Outer contacts	spring bronze	SUCOPLATE®
Insulators	PTFE or PFA	
Crimp ferrules	copper	SUCOPLATE®

Some connectors may have a specification that differs from the above mentioned data.

The products are designed and guaranteed to pass the above mentioned test procedures. Any additional or different requirement arising from specific applications or environmental conditions which is not covered by these test procedures is subject to request.


CABLE CONNECTORS

Straight cable plugs (male)

> for semi-rigid cables, SUCOFORM and MULTIFLEX cables

> cable entry soldered

> centre contact plugged-in




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Notes
11_QMA-50-2-3/133_NE	23017704	Y11,Y3 (Sucoform 86)	single	27428	
11_QMA-50-2-3/133_NH	23017705	Y11,Y3 (Sucoform 86)	bulk 100 pcs.	27428	

> for semi-rigid cables, SUCOFORM and MULTIFLEX cables

> cable entry soldered


> centre contact plugged-in



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Notes
11_QMA-50-3-3/133_NE	23017695	Y12 (Sucoform 141)	single	27428	
11_QMA-50-3-3/133_NH	23017696	Y12 (Sucoform 141)	bulk 100 pcs.	27428	

> for flexible cables

> HUBER+SUHNER® full crimp




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
11_QMA-50-2-1/133_NE	23017700	U4 (K 02252 D)	single	27427	1 A
11_QMA-50-2-1/133_NH	23017701	U4 (K 02252 D)	bulk 100 pcs.	27427	1 A
11_QMA-50-2-2/133_NE	23017720	U2 (RG 316/U)	single	27427	1 A
11_QMA-50-2-2/133_NH	23017721	U2 (RG 316/U)	bulk 100 pcs.	27427	1 A

> for flexible cables

> cable entry crimp

> centre contact soldered




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
11_QMA-50-3-1/133_NE	23017697	U9,U11 (RG 400/U)	single	27429	B
11_QMA-50-3-1/133_NH	23017698	U9,U11 (RG 400/U)	bulk 100 pcs.	27429	B
11_QMA-50-3-2/133_NE	23017702	U7 (RG 58 C/U)	single	27429	B
11_QMA-50-3-2/133_NH	23017703	U7 (RG 58 C/U)	bulk 100 pcs.	27429	B

Right angle cable plugs (male)

> for semi-rigid cables, SUCOFORM and MULTIFLEX cables

> cable entry soldered

> centre contact soldered




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Notes
16_QMA-50-2-3/133_NE	23017666	Y11,Y3 (Sucoform 86)	single	27444	
16_QMA-50-2-3/133_NH	23017667	Y11,Y3 (Sucoform 86)	bulk 100 pcs.	27444	

> for semi-rigid cables, SUCOFORM and MULTIFLEX cables

> cable entry soldered

> centre contact soldered




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Notes
16_QMA-50-3-3/133_NE	23017693	Y5, Y12 (Sucoform 141)	single	27444	
16_QMA-50-3-3/133_NH	23017694	Y5, Y12 (Sucoform 141)	bulk 100 pcs.	27444	

> for flexible cables

> cable entry crimp

> centre contact soldered




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
16_QMA-50-2-1/133_NE	23017654	U4 (K 02252 D)	single	27443	A
16_QMA-50-2-1/133_NH	23017644	U4 (K 02252 D)	bulk 100 pcs.	27443	A
16_QMA-50-2-2/133_NE	23017657	U2 (RG 316/U)	single	27443	A
16_QMA-50-2-2/133_NH	23017658	U2 (RG 316/U)	bulk 100 pcs.	27443	A


> for flexible cables

> cable entry crimp

> centre contact soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
16_QMA-50-3-1/133_NE	23017686	U9, 11 (RG 400/U)	single	27443	B
16_QMA-50-3-1/133_NH	23017687	U9, 11 (RG 400/U)	bulk 100 pcs.	27443	B
16_QMA-50-3-2/133_NE	23017691	U7 (RG 58 C/U)	single	27443	B
16_QMA-50-3-2/133_NH	23017692	U7 (RG 58 C/U)	bulk 100 pcs.	27443	B




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
16_QMA-50-4-1/133_NH	23012849	S16 (S 04262 D)	bulk 100 pcs.	27405	C

Straight bulkhead cable jacks (female)

> for semi-rigid cables, SUCOFORM and MULTIFLEX cables


- > cable entry soldered
- > centre contact plugged-in
- > with panel seal



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly Instruction/ Mounting Hole	Notes
24_QMA-50-2-1/111_NE	23017742	Y11,Y3 (Sucoform 86)	single	27428 / ML 20	
24_QMA-50-2-1/111_NH	23017743	Y11,Y3 (Sucoform 86)	bulk 100 pcs.	27428 / ML 20	

> for semi-rigid cables, SUCOFORM and MULTIFLEX cables


- > cable entry soldered
- > centre contact plugged-in
- > with panel seal



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly Instruction/ Mounting Hole	Notes
24_QMA-50-3-3/111_NE	23017683	Y5, Y12 (Sucoform 141)	single	27428 / ML 20	
24_QMA-50-3-3/111_NH	23017684	Y5, Y12 (Sucoform 141)	bulk 100 pcs.	27428 / ML 20	

> for flexible cables


- > cable entry crimp
- > centre contact soldered
- > with panel seal



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly Instruction/ Mounting Hole	Crimp insert
24_QMA-50-2-2/133_NE	23017829	U4 (K 02252 D)	single	27429 / ML 20	A
24_QMA-50-2-2/133_NH	23017830	U4 (K 02252 D)	bulk 100 pcs.	27429 / ML 20	A
24_QMA-50-2-3/133_NE	23017837	U2 (RG 316/U)	single	27429 / ML 20	A
24_QMA-50-2-3/133_NH	23017838	U2 (RG 316/U)	bulk 100 pcs.	27429 / ML 20	A

> for flexible cables

- > cable entry crimp
- > centre contact soldered
- > with panel seal




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly Instruction/ Mounting Hole	Crimp insert
24_QMA-50-3-1/133_NE	23017822	U9, 11 (RG 400/U)	single	27429 / ML 20	B
24_QMA-50-3-1/133_NH	23017823	U9, 11 (RG 400/U)	bulk 100 pcs.	27429 / ML 20	B
24_QMA-50-3-2/133_NE	23017795	U7 (RG 58 C/U)	single	27429 / ML 20	B
24_QMA-50-3-2/133_NH	23017796	U7 (RG 58 C/U)	bulk 100 pcs.	27429 / ML 20	B

RECEPTACLES WITH SOLDER END

Receptacles, jacks (female)


- > bulkhead mounted
- > press-in chassis mount



QMA


HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
22_QMA-50-0-7/111_NH	84009240	bulk 100 pcs.	ML 143	press-in
22_QMA-50-0-7/133_NF	84001926	bulk 50 pcs.	ML 143	press-in

- > bulkhead mounted
- > without panel seal





HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
22_QMA-50-0-3/133_NH	23018585	bulk 100 pcs.	ML 20	flush dielectric

- > bulkhead mounted
- > without panel seal





HUBER+SUHNER type	Item no.	Packaging	Notes
22_QMA-50-0-4/133_NH	23022628	bulk 100 pcs.	extended dielectric

- > panel mounted
- > 2-hole flange



HUBER+SUHNER type	Item no.	Packaging	Notes
23_QMA-50-0-2/111_NH	23024985	bulk 100 pcs.	extended dielectric

- > panel mounted
- > 4-hole flange




HUBER+SUHNER type	Item no.	Packaging	Notes
23_QMA-50-0-3/111_NH	23025007	bulk 100 pcs.	extended dielectric

PCB CONNECTORS


Straight PCB jacks (female)

> with stand-off



HUBER+SUHNER type	Item no.	Packaging	PCB Layout	Notes
82_QMA-50-0-3/111_NH	23017656	bulk 100 pcs.	ML 41	


> surface mount type SMT



HUBER+SUHNER type	Item no.	Packaging	PCB Layout	Notes
82_QMA-550-0-2/111_NH	23017631	bulk 100 pcs.	ML 136	



Right angle PCB jacks (female)

> surface mount type SMT (with positioning pin)



HUBER+SUHNER type	Item no.	Packaging	PCB Layout	Notes
85_QMA-550-0-2/111_NM	23021299	tape and reel	ML 137	



> with stand-off



HUBER+SUHNER type	Item no.	Packaging	PCB Layout	Notes
85_QMA-50-0-3/111_NH	23021463	bulk 100 pcs.	ML 41	

> surface mount type SMT

> bulkhead mounted




HUBER+SUHNER type	Item no.	Packaging	PCB Layout	Notes
85_QMA-S50-0-5/111_NM	84002573	tape and reel	ML 137	

QMA-CALIBRATION WITH ADAPTOR SWAPPING METHOD

For return Loss/VSWR measurement of QMA connectors, HUBER+SUHNER recommends the following calibration method:

1. Calibration with PC3.5 to PC3.5 calibration adaptors (SMA calibration)

Adaptors: 31_PC35-50-0-2/199_NE (Item no. 23020456) or
32_PC35-50-0-2/199_NE (Item no. 23020457) or
33_PC35-50-0-2/199_NE (Item no. 23020453) see all three adaptors on page 338



2. Exchanging of the calibration adaptors with the required QMA adaptors

31_PC35-QMA-50-1/199_NE (Item no. 23017468) see page 376 or
32_PC35-QMA-50-1/1-NE (Item no. 23017489) see page 376 or
33_PC35-QMA-50-1/199_NE (Item no. 23017467) see page 376 or
33_QMA-PC35-50-1/1-NE (Item no. 23017488) see page 376



QMA


Thanks to the same electrical length and the same return loss behaviour of all these adaptors, the adaptor swapping method can be used (same dimensions of all electrical relevant piece parts in these adaptors).

A FURTHER HUBER+SUHNER PRODUCT!

Waterproof QMA RF connector



Details on this product are to be found in the brochure,
Item no. 84032821. Get your copy free of charge at
www.hubersuhner.com.



SERIES QN, COAXIAL CONNECTORS

DESCRIPTION

HUBER+SUHNER QN coaxial connectors are available with 50 Ω impedance. The frequency range extends to 11 GHz, depending on the connector and cable type, however most of the QN connectors are Return Loss optimised for frequencies up to 6 GHz. The interface is based on the inner dimensions of the N connector, but, instead of a threaded coupling mechanism, a new snap-lock mechanism is used.

The QN interface has a very similar performance to the N, but in addition it offers an easier, faster and safer coupling operation, helping the customers to save significantly time during production of their systems.

The packaging density of QN increased compared to N thanks to the fact that no torque spanner is required to fasten the coupling nut. Additionally the outer dimensions of QN are smaller than N, leading to the advantage that TNC-size flanges can be used at QN connectors.


CONTENT

PAGE

Description	191
Interface dimensions	191
Features of QN connectors	191
Technical data	192
Cable connectors	194
Receptacles with solder end	197
QN-calibration	198

INTERFACE DIMENSIONS (COMPARED TO N)

FEATURES OF QN CONNECTORS



- > Cycle time improvement for making RF connections (10 times faster to mount than threaded connectors)
- > No torque required
- > Higher packaging density
- > Free-rotating connection when mated
- > Eliminates loosening problems associated with threaded connectors
- > Same performance as N
- > Best intermodulation performance thanks to the unique interface design

HUBER+SUHNER QN - the cost effective solution for advanced RF interconnections !

IP rating (interface, mated) IP68

TECHNICAL DATA

ELECTRICAL DATA	REQUIREMENTS	
Impedance	50 Ω	
Frequency range	DC to 6 GHz (optimized)	DC to 11 GHz (working range)
Dielectric withstanding voltage (at sea level, in V rms, 50 Hz)	2500	
Working voltage (at sea level, in V rms, 50 Hz)	≤ 1000	
Insulation resistance	$\geq 5 \cdot 10^3 \text{ M}\Omega$	
Contact resistance		
- centre contact	$\leq 1.5 \text{ m}\Omega$	
- outer contact	$\leq 1.5 \text{ m}\Omega$	
RF-leakage	100 MHz to 3 GHz $\geq -90 \text{ dB}$	
Return loss (typical)	DC - 3 GHz $\geq 32 \text{ dB}$; 3 to 6 GHz $\geq 25 \text{ dB}$; 6 to 11 GHz $\geq 20 \text{ dB}$	
Intermodulation	better -155 dBc (2 x 43 dBm carrier)	

MECHANICAL DATA	REQUIREMENTS
Durability (matings)	≥ 100
Engagement force (typical)	30 N
Disengagement force (typical)	30 N
Retention force for interface	$\geq 450 \text{ N}$
Bending moment admissible (interface)	$\leq 10 \text{ Nm}$
Contact captivation	$\geq 28 \text{ N}$

1) Value considers maximum load of the cables without irreversible variations of specifications.

ENVIRONMENTAL DATA	TEST CONDITIONS
Temperature range	- 40°C ... + 125°C / - 40 °F ... + 257 °F
Climatic category	40 / 125 / 21 (IEC 60169_1 16.2)
Moisture resistance	MIL-STD-202 F, Method 106 F
Corrosion	Saltspray test acc. to MIL-STD-202 F, Method 101 D, Condition B
Vibration	IEC-1169-1 paragraph 9.3.3. (10-500 Hz; 5g)
Shock	MIL-STD-202 F, Method 213, Condition I
Rapid change of temperature	IEC 60169-1 16.4 (-40° C ... + 125° C / - 40 °F ... + 257 °F)

MATERIAL DATA		
CONNECTOR PART	MATERIAL	PLATING
Bodies	brass	SUCOPLATE®
Pin contacts	brass	SUCOPRO
Socket contacts	spring bronze	SUCOPRO
Insulators	typ.: PTFE or PFA	
Contact washer	spring bronze or copper beryllium	SUCOPRO


Some connectors may have a specification that differs from the above mentioned data.

The products are designed and guaranteed to pass the above mentioned test procedures. Any additional or different requirement arising from specific applications or environmental conditions which is not covered by these test procedures is subject to request.

CABLE CONNECTORS


Straight cable plugs (male)

- > for semi-rigid cables, SUCOFORM and MULTIFLEX cables
- > cable entry soldered
- > centre contact plugged-in




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Notes
11_QN-50-3-3/113_NE	23033393	Y5, Y12 (SM 141)	single	27502	

- > for flexible cables
- > HUBER+SUHNER® full crimp



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
11_QN-50-3-1/133_NE	23033391	U9 (EF 142)	single	27500	2B
11_QN-50-3-2/133_NE	23033392	U7 (RG 58 C/U)	single	27501	2B

- > for flexible cables
- > HUBER+SUHNER® full crimp




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
11_QN-50-7-1/133_NE	23033394	U32 (RG 214/U)	single	27503	3D
11_QN-50-7-2/133_NE	23033395	U33 (EF 393)	single	27504	2.5D
11_QN-50-7-3/133_NE	23033396	U29 (RG 213/U)	single	27505	3D

Right angle cable plugs (male)

> for semi-rigid cables, SUCOFORM and MULTIFLEX cables

> cable entry soldered

> centre contact soldered




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Notes
16_QN-50-3-3/13_NE	23033268	Y5, Y12 (SM 141)	single	27508	

> for flexible cables

> cable entry crimp

> centre contact soldered




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
16_QN-50-3-1/133_NE	23033267	U11 (EF 400)	single	27506	B
16_QN-50-3-2/133_NE	23033398	U7 (RG 58 C/U)	single	27507	B
16_QN-50-4-1/133_NE	23033078	S16 (S 04262 D)	single	27509	C

> for flexible cables

> cable entry crimp


> centre contact soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
16_QN-50-7-1/133_NE	23032410	U32,U33 (EF 393)	single	27510	D
16_QN-50-7-2/133_NE	23033399	U29 (RG 213/U)	single	27511	D


Straight bulkhead cable jacks (female)

- > for semi-rigid cables, SUCOFORM and MULTIFLEX cables
- > cable entry soldered
- > centre contact plugged-in




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Mounting hole
24_QN-50-3-3/13_NE	23033423	Y5, Y12 (SM 141)	single	27514	ML 112

- > for flexible cables
- > HUBER+SUHNER® full crimp



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole	Crimp insert
24_QN-50-3-1/133_NE	23033400	U9 (EF 142)	single	27512 / ML 112	2B
24_QN-50-3-2/133_NE	23033402	U7 (RG 58 C/U)	single	27513 / ML 112	2B

- > for flexible cables
- > HUBER+SUHNER® full crimp




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole	Crimp insert
24_QN-50-7-1/133_NE	23033403	U33 (EF 393)	single	27515 / ML 112	2.5D
24_QN-50-7-2/133_NE	23033404	U32 (RG 214/U)	single	27516 / ML 112	3D
24_QN-50-7-3/133_NE	23033405	U29 (RG 213/U)	single	27517 / ML 112	3D

RECEPTACLES WITH SOLDER END


Receptacles, jacks (female)

- > bulkhead mounted
- > press-in chassis mount



HUBER+SUHNER type	Item no.	Packaging	Notes
22_QN-50-0-1/133_NE	23033237	single	press-in
22_QN-50-0-1/133_NY	23033904	bulk 100 pcs.	press-in

- > panel mounted




HUBER+SUHNER type	Item no.	Packaging	Notes
23_QN-50-0-1/133_NE	23033251	single	flange with same dimensions as TNC
23_QN-50-0-1/133_NY	23033252	bulk 100 pcs.	flange with same dimensions as TNC

QN-CALIBRATION WITH ADAPTOR SWAPPING METHOD

For return Loss/VSWR measurement of QN connectors, HUBER+SUHNER recommends the following calibration method:


1. Calibration with PC7 to PC7 calibration adaptors (PC7 calibration)

Adaptors: 32_PC7-U50-0-1/1_NE (Item no. 23032719) and
33_PC7-U50-0-1/1_NE (Item no. 23032721)




Alternative calibration with N to PC7 calibration adaptors (N calibration)

Adaptors: 32_N-PC7-50-6/1_NE (Item no. 23032917) see page 373 or
33_PC7-N-50-6/1_NE (Item no. 23032916) see page 374



2. Exchanging of the calibration adaptors with the required QN adaptors

32_PC7-QN-50-1/1_NE (Item no. 23032720) see page 377 or
33_PC7-QN-50-1/1_NE (Item no. 23032722) see page 377



Thanks to the same electrical length and the same return loss behaviour of all these adaptors, the adaptor swapping method can be used (same dimensions of all electrical relevant piece parts in these adaptors).



SERIES BNC 50 Ω, COAXIAL MINIATURE CONNECTORS

DESCRIPTION

HUBER+SUHNER BNC is still one of the most popular connector series, featuring a two stud bayonet coupling mechanism, which is particularly useful for frequently coupled and uncoupled RF connections with frequencies up to 4 GHz.

Compatibility


50 Ω BNC connectors and 75 Ω BNC connectors are intermateable without any restrictions.

CONTENTS

PAGE

Description	199
Interface dimensions	199
Interface dimensions in mm / inches	199
Technical data	200
Cable connectors	202
Receptacles with solder end	211
PCB connectors	215
Protective caps and shorts	216

INTERFACE DIMENSIONS



INTERFACE DIMENSIONS (MM / INCHES)

	Plug		Jack	
	min.	max.	min.	max.
A	4.83/.190	—	—	4.72/.186
B	5.33/.210	5.84/.230	4.72/.186	5.23/.206
C	5.28/.208	5.79/.228	4.78/.188	5.28/.208
D	2.06/.081	2.21/.087	2.06/.081	2.21/.087
E	9.78/.385	9.91/.390	9.60/.378	9.70/.382
F	1.98/.078	—	4.95/.195	—
G	1.32/.052	1.37/.054	8.31/.327	8.51/.335
H	0.08/.003	—	8.10/.319	8.15/.321
I	—	—	10.52/.414	—

Interface dimensions conformable to the Standards:

International:	IEC 61169-8
Europe:	CECC 22120
USA:	MIL-C- 39012, BNC Interface MIL-STD-348A/301
Great Britain:	BS 9210 N 004

IP rating (interface, mated) IP64

BNC

TECHNICAL DATA

ELECTRICAL DATA	REQUIREMENTS
Impedance	50 Ω
Frequency range (for connector interface)	DC ... 4 GHz
Dielectric withstanding voltage (at sea level)	1.5 kV rms, 50 Hz (depending on cable)
Working voltage (at sea level)	500 V rms, 50 Hz (depending on cable)
Insulation resistance	$\geq 5 \cdot 10^3 \text{ M}\Omega$
Contact resistance - centre contact - outer contact	$\leq 1.5 \text{ m}\Omega$ $\leq 1 \text{ m}\Omega$
RF-leakage (between 2 ÷ 3 GHz)	$\geq 55 \text{ dB}$

MECHANICAL DATA	REQUIREMENTS
Coupling nut torque	7 Ncm ... 28 Ncm / 0.6 in. lbs ... 2.5 in. lbs
Coupling nut retention force	$\geq 450 \text{ N} / 101.2 \text{ lbs}$
Contact captivation	$\geq 27 \text{ N} / 6.1 \text{ lbs}$
Cable retention force ¹⁾	see pages 28 - 34
Durability (matings)	≥ 500

1) Value considers maximum load of the cables without irreversible variations of specifications.

ENVIRONMENTAL DATA	TEST CONDITIONS
Temperature range	- 65°C ... + 165°C / - 85 °F ... + 329 °F
Climatic category	IEC → 55/155/21
Thermal shock	MIL-STD-202, Method 107, Condition B
Moisture resistance	MIL-STD-202, Method 106
Corrosion	Salt spray test acc. to MIL-STD-202, Method 101, Condition B
Vibration	MIL-STD-202, Method 204, Condition B
Shock	MIL-STD-202, Method 213, Condition G

MATERIAL DATA		
CONNECTOR PART	MATERIAL	PLATING
Bodies	brass	SUCOPLATE® / SUCOPRO
Pin contacts	brass	gold / SUCOPRO
Socket contacts	copper-beryllium alloy copper alloy	gold / SUCOPRO
Crimp ferrules	copper brass	SUCOPLATE®
Insulators	PTFE or PFA	
Gaskets	silicone rubber	

Some connectors may have a specification that differs from the above mentioned data.

The products are designed and guaranteed to pass the above mentioned test procedures. Any additional or different requirement arising from specific applications or environmental conditions which is not covered by these test procedures is subject to request.

CABLE CONNECTORS

Straight cable plugs (male)

- > for semi-rigid cables
- > cable entry soldered
- > centre contact soldered




Fig. 1





Fig. 2



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Fig.	Notes
11_BNC-50-2-20/103_NE	22641778	Y3, Y11 (EZ 86)	single	9100	1	
11_BNC-50-3-54/103_NE	22540108	Y5, Y12 (EZ 141)	single	9106	2	


- > for flexible cables
- > cable entry clamp
- > centre contact soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Notes
11_BNC-50-1-1/133_NE	22540021	U1 (RG 178 B/U)	single	3005	
11_BNC-50-2-1/133_NE	22540029	U2 (RG 316/U)	single	3005	
11_BNC-50-3-1/133_NE	22540045	U7, 10 (RG 58C/U)	single	3004	
11_BNC-50-3-5/133_NE	22540054	U7, 10 (RG 58C/U)	single	3005	

☒ centre contact NOT captivated

- > for flexible cables
- > cable entry clamp
- > centre contact soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Notes
11_BNC-50-7-1/133_NE	22540145	U28 (RG 213/U)	single	3008	
11_BNC-50-7-2/133_NE	22540149	U33 (RG 214/U)	single	3008	

- > for flexible cables
- > HUBER+SUHNER® full crimp
- > taper sleeves see page 406




Fig. 1





Fig. 2



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Fig.
11_BNC-50-1-5/133_NE	22641759	U1 (RG 178 B/U)	single	9068	1 A	1
11_BNC-50-2-13/133_NE	22543749	U2 (RG 316/U)	single	9068	1 A	1
11_BNC-50-2-13/133_NH	22644716	U2 (RG 316/U)	bulk 100 pcs.	9068	1 A	1
11_BNC-50-2-14/133_NE	22641683	U4 (K 02252 D)	single	9068	1 A	1
11_BNC-50-2-14/133_NH	22649839	U4 (K 02252 D)	bulk 100 pcs.	9068	1 A	1
11_BNC-50-2-16/133_NE	22544026	U3 (G 01130 HT)	single	9068	1 A	1
11_BNC-50-2-16/133_NH	22648466	U3 (G 01130 HT)	bulk 100 pcs.	9068	1 A	1
11_BNC-50-3-4/133_NE	22540052	U7 (RG 58 C/U)	single	3015	2 B	2
11_BNC-50-3-4/133_NH	22641268	U7 (RG 58 C/U)	bulk 100 pcs.	3015	2 B	2
11_BNC-50-3-16/133_NE	22540071	U9 (RG 223/U)	single	3015	2 B	2
11_BNC-50-3-16/133_NH	22652130	U9 (RG 223/U)	bulk 100 pcs.	3015	2 B	2
11_BNC-50-3-36/133_NE	22540089	U13 (G 03130-HT)	single	27057	2 C	2
11_BNC-50-3-52/133_NE	22645522	U11 (RG 400/U)	single	3015	2 B	2
11_BNC-50-3-52/133_NH	22652006	U11 (RG 400/U)	bulk 100 pcs.	3015	2 B	2
11_BNC-50-3-58/133_NE	22641576	U8 (S 03232-1)	single	3015	2 B	2
11_BNC-50-3-58/133_NH	23008429	U8 (S 03232-1)	bulk 100 pcs.	3015	2 B	2
11_BNC-50-4-4/133_NE	22540115	U16 (RG 59 B/U)	single	3015	2 C	2
11_BNC-50-4-4/133_NH	22648238	U16 (RG 59 B/U)	bulk 100 pcs.	3015	2C	2
11_BNC-50-4-23/133_NE	22543958	U16 (RG 62 A/U)	single	9098	2 C	2


- > for flexible cables
- > HUBER+SUHNER® full crimp
- > taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
11_BNC-50-7-6/133_NE	22640863	U32 (RG 214/U)	single	3061	3 D
11_BNC-50-7-7/133_NE	22543766	U29 (RG 213/U)	single	3061	3 D


Right angle cable plugs (male)

- > for flexible cables
- > cable entry clamp



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Notes
16_BNC-50-2-9/133_NE	84013192	U2 (RG 316/U)	single	3024	
16_BNC-50-3-25/133_NE	84013233	U7, 10 (RG 58C/U)	single	3024	

- > for flexible cables
- > cable entry clamp



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Notes
16_BNC-50-7-6/133_NE	22651588	U28 (RG 213/U) U33 (RG 214/U)	single	27121	

- > for flexible cables
- > cable entry crimp
- > centre contact soldered
- > taper sleeves see page 406




Fig. 1





Fig. 2



BNC 50

HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Fig.
16_BNC-50-2-3/133_NE	22540168	U2 (RG 316/U)	single	3079	A	1
16_BNC-50-2-3/133_NH	22648628	U2 (RG 316/U)	bulk 100 pcs.	3079	A	1
16_BNC-50-2-5/133_NE	22540169	U4 (K 02252 D)	single	3079	A	1
16_BNC-50-2-5/133_NH	22650221	U4 (K 02252 D)	bulk 100 pcs.	3079	A	1
16_BNC-50-3-5/133_NE	22540185	U7 (RG 58 C/U)	single	3058	B	2
16_BNC-50-3-7/133_NE	22540192	U9, 11 (RG 400/U)	single	3058	B	2
16_BNC-50-3-7/133_NH	22650222	U9, 11 (RG 400/U)	bulk 100 pcs.	3058	B	2


- > for flexible cables
- > HUBER+SUHNER® full crimp
- > taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
16_BNC-50-3-13/133_NE	22540198	U7 (RG 58 C/U)	single	3015	2 B

Straight cable jacks (female)

- > for flexible cables
- > cable entry clamp



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Notes
21_BNC-50-2-1/133_NE	22540228	U2 (RG 316/U)	single	3005	
21_BNC-50-3-12/133_NE	22540263	U7, 10 (RG 58C/U)	single	3005	

> for flexible cables

> HUBER+SUHNER® full crimp

> taper sleeves see page 406




Fig. 1




Fig. 2

HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Fig.
21_BNC-50-1-4/133_NE	22641777	U1 (RG 178 B/U)	single	9068	1 A	1
21_BNC-50-2-9/133_NE	22641732	U2 (RG 316/U)	single	9068	1 A	1
21_BNC-50-2-10/133_NE	22641779	U4 (K 02252 D)	single	9068	1 A	1
21_BNC-50-3-2/133_NE	22540242	U7 (RG 58 C/U)	single	3015	2 B	2
21_BNC-50-3-9/133_NE	22540255	U9 (RG 223/U)	single	3015	2 B	2

Straight bulkhead cable jacks (female)

> for semi-rigid cables

> cable entry soldered

> insulating washers see page 408

> with panel seal




Fig. 1




Fig. 2


HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Mounting hole	Fig.
24_BNC-50-2-20/133_NE	22641886	Y3, Y11 (EZ 86)	single	9100	ML 4	1
24_BNC-50-3-33/133_NE	22641923	Y5, Y12 (EZ 141)	single	9005	ML 4	2

> for flexible cables

> cable entry clamp

> with panel seal

> insulating washers see page 408



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Mounting hole
24_BNC-50-1-1/133_NE	22540362	U1 (RG 178 B/U)	single	3005	ML 4
24_BNC-50-2-1/133_NE	22540365	U2 (RG 316/U)	single	3005	ML 4
24_BNC-50-3-5/133_NE	22540385	U7, 10 (RG 58C/U)	single	3005	ML 4

> for flexible cables

> HUBER+SUHNER® full crimp

> with panel seal

> insulating washers see page 408

> taper sleeves see page 406




Fig. 1





Fig. 2

HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole	Crimp insert	Fig.
24_BNC-50-1-6/133_NE	22641781	U1 (RG 178 B/U)	single	9068 / ML 4	1 A	1
24_BNC-50-1-6/133_NH	84011438	U1 (RG 178 B/U)	bulk 100 pcs.	9068 / ML 4	1 A	1
24_BNC-50-2-13/133_NE	22641731	U2 (RG 316/U)	single	9068 / ML 4	1 A	1
24_BNC-50-2-13/133_NH	22645373	U2 (RG 316/U)	bulk 100 pcs.	9068 / ML 4	1 A	1
24_BNC-50-2-14/133_NE	22641783	U4 (K 02252 D)	single	9068 / ML 4	1 A	1
24_BNC-50-2-14/133_NH	22652154	U4 (K 02252 D)	bulk 100 pcs.	9068 / ML 4	1 A	1
24_BNC-50-3-1/133_NE	22540378	U7 (RG 58 C/U)	single	3015 / ML 4	2 B	2
24_BNC-50-3-8/133_NE	22540389	U9 (RG 223/U)	single	3015 / ML 4	2 B	2
24_BNC-50-3-25/133_NE	22658913	U11 (RG 400/U)	single	3015 / ML 4	2 B	2
24_BNC-50-3-25/133_NH	22660362	U11 (RG 400/U)	bulk 100 pcs.	3015 / ML 4	2 B	2

> for flexible cables


- > HUBER+SUHNER® full crimp
- > taper sleeves see page 406
- > front mounting
- > without panel seal



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole	Crimp insert
24_BNC-50-2-29/133_NE	22648682	U2 (RG 316/U)	single	9068 / ML 3	1 A

> for flexible cables

- > HUBER+SUHNER® full crimp
- > with panel seal
- > insulating washers see page 408
- > taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole	Crimp insert
24_BNC-50-7-3/133_NE	22540415	U29 (RG 213/U)	single	9121 / ML 4	3 D

Straight panel cable jacks (female)

> for flexible cables

- > HUBER+SUHNER® full crimp
- > fastening screws see page 407
- > taper sleeves see page 406




Fig. 1





Fig. 2

HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole	Crimp insert	Fig.
25_BNC-50-2-13/133_NE	22641919	U2 (RG 316/U)	single	9068 / ML 8	1 A	2 *
25_BNC-50-2-14/133_NE	22641924	U2 (RG 316/U)	single	9068 / ML 8	1 A	1
25_BNC-50-2-16/133_NE	22641795	U4 (K 02252 D)	single	9068 / ML 8	1 A	1

* mounting also possible with screws ISO M 2.5

> for flexible cables

- > HUBER+SUHNER® full crimp
- > fastening screws see page 407
- > taper sleeves see page 406




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole	Crimp insert	Notes
25_BNC-50-3-13/133_NE	22540463	U7 (RG 58 C/U)	single	3015 / ML 8	2 B	*

* mounting also possible with screws ISO M 2.5

RECEPTACLES WITH SOLDER END

Receptacles, plugs (male)

- > bulkhead mounted
- > insulating washers see page 408
- > solder tags see page 409



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Panel thickness	Notes
12_BNC-50-0-1/133_NE	22540154	single	ML 2	max. 3.5 mm	with panel seal

Receptacles, jacks (female)

- > bulkhead mounted
- > insulating washers see page 408
- > solder tags see page 409




Fig. 1




Fig. 2

HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Fig.	Notes
22_BNC-50-0-2/133_NE	22540293	single	ML 102	1	insulated mounting / *
22_BNC-50-0-3/133_NE	22540301	single	ML 1	2	with panel seal
22_BNC-50-0-3/133_NH	22645500	bulk 100 pcs.	ML 1	2	with panel seal

* equipped with insulating washers 77_Z0-0-2 (not protected against rotation)

Receptacles, jacks (female)

- > bulkhead mounted
- > insulating washers see page 408
- > solder tags see page 409




Fig. 1




Fig. 2

H+S type	Item no.	Packaging	Mounting hole	Fig.	Notes
22_BNC-50-0-4/133_NE	22540303	single	ML 3	1	not suitable for insulated mounting
22_BNC-50-0-5/133_NE	22540308	single	ML 2	2	suitable for insulated mounting
22_BNC-50-0-5/133_NH	22650242	bulk 100 pcs.	ML 2	2	suitable for insulated mounting

- > bulkhead mounted
- > insulating washers see page 408
- > solder tags see page 409




Fig. 1




Fig. 2


H+S type	Item no.	Packaging	Mounting hole	Fig.	Notes
22_BNC-50-0-16/133_NE	22540314	single	ML 2	1	suitable for insulated mounting
22_BNC-50-0-24/100_NE**	22540321	single	ML 2	2	hermetically sealed / body silver plated*

* leak rate 10^{-6} Torr l/sec.(atm cc/s) max.

** RoHS compliant alternative on request


Receptacles, plugs (male)

- > panel mounted
- > fastening screws see page 407



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
13_BNC-50-0-1/133_NE	22543470	single	ML 6	mounting also possible with screws ISO M 2.5


- > panel mounted
- > fastening screws see page 407



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
13_BNC-50-0-2/133_NE	22540160	single	ML 5	suitable for SUCOBOX® applications, see page 410


Receptacles, jacks (female)

- > panel mounted
- > fastening screws see page 407




HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
23_BNC-50-0-2/133_NE	22540333	single	ML 5	suitable for SUCOBOX® applications, see page 410

- > panel mounted
- > fastening screws see page 407



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
23_BNC-50-0-12/133_NE	22540349	single	ML 6	mounting also possible with screws ISO M 2.5


- > panel mounted
- > fastening screws see page 407



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
23_BNC-50-0-16/133_NE	22540355	single	ML 6	


Right angle receptacles, jack (female)

- > bulkhead mounted
- > with panel seal
- > insulating washers see page 408




HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
27_BNC-50-0-1/133_NE	22540492	single	ML 2	

- > panel mounted
- > fastening screws see page 407




HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
28_BNC-50-0-2/133_NE	22540500	single	ML 6	fastening hole d = 3.1 mm / .12 in.

Straight PCB jacks (female)




HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
82_BNC-50-0-1/133_NE	22645779	single	ML 49	
82_BNC-50-0-1/133_NH	22543974	bulk 100 pcs.	ML 49	
82_BNC-50-0-1/111_NH	23012124	bulk 100 pcs.	ML 49	Plating body: SUCOPRO



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
85_BNC-50-0-1/133_NE	22540736	single	ML 49	
85_BNC-50-0-1/111_NE	23022540	single	ML 49	Plating body: SUCOPRO


PROTECTIVE CAPS AND SHORTS

> protective cap for plugs (males)



HUBER+SUHNER type	Item no.	Packaging	Notes
61_BNC-0-0-1/-33_E	22540660	single	with chain and loop

> for jacks (females)



HUBER+SUHNER type	Item no.	Packaging	Notes
62_BNC-0-0-1/-33_E	22540666	single	protective cap with chain
64_BNC-50-0-1/133_NE	22540681	single	short circuit with chain

> protective caps for jacks (females)




Fig. 1




Fig. 2



HUBER+SUHNER type	Item no.	Packaging	Fig.	Notes
62_BNC-0-0-2/-_H	22540667	bulk 100 pcs.	1	made of plastic
62_BNC-0-0-3/-33_E	22540669	single	2	

SERIES BNC 75 Ω , COAXIAL MINIATURE CONNECTORS

DESCRIPTION

HUBER+SUHNER BNC Series featuring a two stud bayonet coupling mechanism which is particularly useful for frequently coupled and uncoupled RF connections. At frequencies up to 1 GHz the small impedance deviation is negligible for any application. A typical VSWR of 1.15 at 1 GHz is achieved.

Compatibility


75 Ω BNC connectors and 50 Ω BNC connectors are intermateable without any restrictions.

CONTENTS

PAGE

Description	217
Interface dimensions	217
Interface dimensions in mm / inches	217
Technical data	218
Cable connectors	220
Receptacles with solder end	225
PCB connectors	226
Protective caps and shorts	227

INTERFACE DIMENSIONS



INTERFACE DIMENSIONS (MM / INCHES)

	Plug		Jack	
	min.	max.	min.	max.
A	4.83/.190	4.97/.196	—	4.72/.186
B	5.28/.208	5.79/.228	4.72/.186	5.23/.206
C	9.78/.385	9.91/.390	1.50/.059 nom.	
D	1.32/.052	1.37/.054	2.10/.827 nom.	
E	0.08/.003	1.02/.040	9.60/.378	9.70/.382
F	—	—	4.95/.195	—
G	—	—	8.35/.328	8.48/.334
H	—	—	8.10/.319	8.15/.321
I	—	—	10.60/.417	—

Interface dimensions conformable to the Standards:

International: IEC 61169-8

IP rating (interface, mated) IP64

TECHNICAL DATA

ELECTRICAL DATA	REQUIREMENTS
Impedance	75 Ω
Frequency range	DC ... 1 GHz
Dielectric withstanding voltage (at sea level)	1.5 kV rms, 50 Hz (depending on cable)
Working voltage (at sea level)	500 V rms, 50 Hz (depending on cable)
Insulation resistance	$\geq 5 \cdot 10^3 \text{ M}\Omega$
Contact resistance - centre contact - outer contact	$\leq 1.5 \text{ m}\Omega$ $\leq 1 \text{ m}\Omega$
RF-leakage (measured at 1 GHz)	$\geq 55 \text{ dB}$

MECHANICAL DATA	REQUIREMENTS
Coupling nut torque	7 Ncm ... 28 Ncm / 0.6 in. lbs ... 2.5 in. lbs
Coupling nut retention force	$\geq 450 \text{ N} / 101.2 \text{ lbs}$
Contact captivation	$\geq 27 \text{ N} / 6.1 \text{ lbs}$
Cable retention force ¹⁾	see pages 28 – 34
Durability (matings)	≥ 500

1) Value considers maximum load of the cables without irreversible variations of specifications.

ENVIRONMENTAL DATA	TEST CONDITIONS
Temperature range	- 65°C ... + 165°C / - 85 °F ... + 329 °F
Climatic category	IEC → 55/155/21
Thermal shock	MIL-STD-202, Method 107, Condition B
Moisture resistance	MIL-STD-202, Method 106
Corrosion	Saltspray test acc. to MIL-STD-202, Method 101, Condition B
Vibration	MIL-STD-202, Method 204, Condition B
Shock	MIL-STD-202, Method 213, Condition G

MATERIAL DATA		
CONNECTOR PARTS	MATERIAL	PLATING
Bodies	brass	SUCOPLATE®
Pin contacts	brass	gold / SUCOPRO
Socket contacts	copper-beryllium alloy	gold / SUCOPRO
Crimp ferrules	copper brass	SUCOPLATE®
Insulators	PTFE or PFA	
Gaskets	silicone rubber	


Some connectors may have a specification that differs from the above mentioned data.

The products are designed and guaranteed to pass the above mentioned test procedures. Any additional or different requirement arising from specific applications or environmental conditions which is not covered by these test procedures is subject to request.

CABLE CONNECTORS


Straight cable plugs (male)

- > for flexible cables
- > cable entry clamp
- > centre contact soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Notes
11_BNC-75-2-1/133_NE	22543768	U5 (RG 187 A/U)	single	3005	
11_BNC-75-2-12/133_NE	22544277	U6 (G 03133-06)	single	3005	

- > for flexible cables
- > cable entry clamp
- > centre contact soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Notes
11_BNC-75-3-11/133_NE	22540711	U14 (G 03233 D)	single	3005	
11_BNC-75-4-3/133_NE	22540758	U15 (RG 59 B/U)	single	3005	

> for flexible cables

> HUBER+SUHNER® full crimp

> taper sleeves see page 406




Fig. 1




Fig. 2




Fig. 3




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Fig.
11_BNC-75-2-15/133_NE	22641685	U5 (RG 187 A/U)	single	9068	1 A	1
11_BNC-75-2-15/133_NH	22644586	U5 (RG 187 A/U)	bulk 100 pcs.	9068	1 A	1
11_BNC-75-2-18/133_NE	22643710	S5 (S 02223-02)	single	9068	1 A	1
11_BNC-75-2-18/133_NH	22644587	S5 (S 02223-02)	bulk 100 pcs.	9068	1 A	1
11_BNC-75-2-21/133_NE	22644358	R6 (G 02133 D-05)	single	27001	1/4.95	2
11_BNC-75-2-21/133_NH	22650676	R6 (G 02133 D-05)	bulk 100 pcs.	27001	1/4.95	2
11_BNC-75-3-8/133_NE	22540707	U12 (G 03233)	single	3015	2 B	3
11_BNC-75-3-9/133_NE	22540709	U14 (G 03233 D)	single	3015	2 B	3
11_BNC-75-4-4/133_NE	22540761	U16 (RG 59 B/U)	single	3015	2 C	3
11_BNC-75-4-4/133_NH	22544846	U16 (RG 59 B/U)	bulk 100 pcs.	3015	2 C	3
11_BNC-75-4-6/133_NE	22540765	U18 (G 04233 D)	single	3015	2 C	3
11_BNC-75-4-6/133_NH	22540766	U18 (G 04233 D)	bulk 100 pcs.	3015	2 C	3
11_BNC-75-4-30/133_NE	22544636	U17 (S 04233)	single	3015	2 C	3
11_BNC-75-5-6/133_NE	22540799	U24 (G 05133 D)	single	3015	76_Z-0-5-21	3

> for flexible cables

> HUBER+SUHNER® full crimp

> taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
11_BNC-75-7-5/133_NE	22540811	U34 (RG 11 A/U)	single	9120	2 D
11_BNC-75-7-6/133_NE	22543960	U36 (RG 216/U)	single	9120	2 D

Right angle cable plugs (male)

- > for flexible cables
- > cable entry crimp
- > centre contact soldered
- > taper sleeves see page 406




Fig. 1





Fig. 2



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Fig.
16_BNC-75-2-3/133_NE	22540820	U5 (RG 187 A/U)	single	3079	A	1
16_BNC-75-2-3/133_NH	22649038	U5 (RG 187 A/U)	bulk 100 pcs.	3079	A	1
16_BNC-75-2-5/133_NE	22642801	R6 (G 02133 D-05)	single	27100	4.95	2

- > for flexible cables
- > cable entry crimp
- > centre contact soldered
- > taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
16_BNC-75-3-4/133_NE	22543781	U14 (G 03233 D)	single	3058	B
16_BNC-75-4-4/133_NE	22540840	U16 (RG 59 B/U)	single	3058	C
16_BNC-75-4-5/133_NE	22540842	U18 (G 04233 D)	single	3058	C

Straight cable jacks (female)

> for flexible cables

> HUBER+SUHNER® full crimp

> taper sleeves see page 406




Fig. 1




Fig. 2

HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Fig.
21_BNC-75-2-5/133_NE	22641780	U5 (RG 187 A/U)	single	9068	1 A	1
21_BNC-75-2-5/133_NH	22645904	U5 (RG 187 A/U)	bulk 100 pcs.	9068	1 A	1
21_BNC-75-2-7/133_NE	22643853	S5 (S 02223-02)	single	9068	1 A	1
21_BNC-75-4-4/133_NE	22540872	U16 (RG 59 B/U)	single	3015	2 C	2
21_BNC-75-4-5/133_NE	22540874	U18 (G 04233 D)	single	3015	2 C	2

Straight bulkhead cable jacks (female)


> for flexible cables

> HUBER+SUHNER® full crimp

> with panel seal

> insulating washers see page 408

> taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
24_BNC-75-2-6/133_NE	22641786	U5 (RG 187 A/U)	single	9068	1 A
24_BNC-75-2-6/133_NH	22644569	U5 (RG 187 A/U)	bulk 100 pcs.	9068	1 A
24_BNC-75-2-12/133_NE	22643854	S5 (S 02223-02)	single	9068	1 A

mounting hole ML 4

BNC 75


> for flexible cables

> HUBER+SUHNER® full crimp

> with panel seal

> insulating washers see page 408

> taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
24_BNC-75-2-15/133_NE	22644339	R6 (G 02133 D-05)	single	27001	1 / 4.95
24_BNC-75-2-15/133_NH	22651492	R6 (G 02133 D-05)	bulk 100 pcs.	27001	1 / 4.95
24_BNC-75-3-4/133_NE	22540917	U12 (G 03233)	single	3015	2 B
24_BNC-75-3-5/133_NE	22540920	U14 (G 03233 D)	single	3015	2 B
24_BNC-75-4-3/133_NE	22540930	U16 (RG 59 B/U)	single	3015	2 C
24_BNC-75-4-4/133_NE	22540932	U18 (G 04233 D)	single	3015	2 C
24_BNC-75-4-15/133_NE	22641769	U17 (S 04233)	single	3015	2 C

mounting hole ML 4

Straight panel cable jacks (female)

> for flexible cables

> HUBER+SUHNER® full crimp

> fastening screws see page 407

> taper sleeves see page 406




Fig. 1




Fig. 2

HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Fig.
25_BNC-75-2-7/133_NE	22641790	U5 (RG 187 A/U)	single	9068	1 A	1
25_BNC-75-2-8/133_NE	22641791	U5 (RG 187 A/U)	single	9068	1 A	2*


* mounting also possible with screws ISO M 2.5

mounting hole ML 8

RECEPTACLES WITH SOLDER END


Receptacles, jacks (female)

- > bulkhead mounted
- > with panel seal
- > solder tags see page 409
- > insulating washers see page 408




HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
22_BNC-75-0-1/133_NE	22540883	single	ML 1	

- > bulkhead mounted
- > solder tags see page 409
- > insulating washers see page 408



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
22_BNC-75-0-4/133NE	22540889	single	ML 2	without panel seal


- > panel mounted
- > fastening screws see page 407



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
23_BNC-75-0-10/133_NE	22540906	single	ML 6	


PCB CONNECTORS

Straight PCB jacks (female)



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
82_BNC-75-0-2/122_NE	22643586	single	ML 49	Plating Body: nickel
82_BNC-75-0-2/122_NH	22646624	bulk 100 pcs.	ML 49	Plating Body: nickel


Right angle PCB jacks (female)



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
85_BNC-75-0-1/133_NE	22641623	single	ML 49	
85_BNC-75-0-1/133_NH	22646488	bulk 100 pcs.	ML 49	


PROTECTIVE CAPS AND SHORTS

> protective cap for plugs (males)



HUBER+SUHNER type	Item no.	Packaging	Notes
61_BNC-0-0-1/-33_E	22540660	single	with chain and loop

> protective cap for jacks (females)



HUBER+SUHNER type	Item no.	Packaging	Notes
62_BNC-0-0-1/-33_E	22540666	single	with chainp

> protective caps for jacks (females)





Fig. 1

Fig. 2


HUBER+SUHNER type	Item no.	Packaging	Fig.	Notes
62_BNC-0-0-2/-_H	22540667	bulk 100 pcs.	1	made of plastic
62_BNC-0-0-3/-33_E	22540669	single	2	

A FURTHER HUBER+SUHNER PRODUCT GROUP!

RF and microwave components



Details on this product range are to be found in the brochure ,
Item no. 23038050. Get your copy free of charge at
www.hubersuhner.com.





SERIES TNC 50 Ω, COAXIAL MINIATURE CONNECTORS

DESCRIPTION

HUBER+SUHNER TNC connectors are threaded RF connectors applicable from DC up to 11 GHz. Precision designs using a dielectric bead are suitable for use up to 18 GHz. The threaded coupling mechanism improves control over the interface dimensions and allows them to be used under a higher environmental load than BNC, especially under a high vibration load.

Compatibility


50 Ω TNC connectors and 75 Ω TNC connectors are intermateable without restrictions.

CONTENTS

PAGE

Description	229
Interface dimensions	229
Interface dimensions in mm / inches	229
Technical data	230
Cable connectors	232
Receptacles with solder end	239
Protective caps and shorts	241

INTERFACE DIMENSIONS



INTERFACE DIMENSIONS (MM / INCHES)

	Plug		Jack	
	min.	max.	min.	max.
A	4.83/.190	—	—	4.72/.186
B	5.33/.210	5.84/.230	4.72/.186	5.23/.206
C	5.28/.208	5.79/.228	4.78/.188	5.28/.208
D	2.06/.081	2.21/.087	2.06/.081	2.21/.087
E	1.98/.078	—	4.95/.195	—
F	1.32/.052	1.37/.054	9.60/.378	9.70/.382
G	0.08/.003	—	8.31/.327	8.51/.335
H	—	—	8.10/.319	8.15/.321
I	—	—	10.52/.414	—

Interface dimensions conformable to the Standards:

International: IEC 60169-17
Europe: CECC 22 200
USA: MIL-C-39012
TNC-Interface MIL-STD-348A/313

IP rating (interface, mated) IP68

TNC

TECHNICAL DATA

ELECTRICAL DATA	REQUIREMENTS
Impedance	50 Ω
Frequency range	DC ... 11 GHz
Dielectric withstanding voltage (at sea level)	1.5 kV rms, 50 Hz (depending on cable)
Working voltage (at sea level) - unmated	500 V rms, 50 Hz (depending on cable)
Insulation resistance	$\geq 5 \cdot 10^3 \text{ M}\Omega$
Contact resistance - centre contact - outer contact	$\leq 1.5 \text{ m}\Omega$ $\leq 1 \text{ m}\Omega$
RF-leakage (between 2 ÷ 3 GHz)	$\geq 60 \text{ dB}$

MECHANICAL DATA	REQUIREMENTS
Coupling nut torque - recommended - proof torque	46 Ncm ... 69 Ncm / 4.1 in. lbs ... 6.1 in. lbs 170 Ncm / 15.0 in. lbs
Coupling nut retention force	$\geq 450 \text{ N} / 101.2 \text{ lbs}$
Contact captivation	$\geq 27 \text{ N} / 6.1 \text{ lbs}$
Cable retention force ¹⁾	see pages 28 - 34
Durability (matings)	≥ 500

1) Value considers maximum load of the cables without irreversible variations of specifications.

ENVIRONMENTAL DATA	TEST CONDITIONS
Temperature range	- 65°C ... + 165°C / - 85 °F ... + 329 °F
Climatic category	IEC → 55/155/21
Thermal shock	MIL-STD-202, Method 107, Condition B
Moisture resistance	MIL-STD-202, Method 106
Corrosion	Saltspray test acc. to MIL-STD-202, Method 101, Condition B
Vibration	MIL-STD-202, Method 204, Condition B
Shock	MIL-STD-202, Method 213, Condition G

MATERIAL DATA		
CONNECTOR PART	MATERIAL	PLATING
Bodies	brass	SUCOPLATE®
Pin contacts	brass	gold / SUCOPRO
Socket contacts	copper-beryllium alloy copper alloy	gold / SUCOPRO
Crimp ferrules	copper brass	SUCOPLATE®
Insulators	PTFE or PFA	
Gaskets	silicone rubber	

Some connectors may have a specification that differs from the above mentioned data.

The products are designed and guaranteed to pass the above mentioned test procedures. Any additional or different requirement arising from specific applications or environmental conditions which is not covered by these test procedures is subject to request.

CABLE CONNECTORS

Straight cable plugs (male)

- > for semi-rigid cables
- > cable entry soldered
- > centre contact soldered




Fig. 1





Fig. 2

HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Fig.	Notes
11_TNC-50-2-20/103_NE	22642519	Y3, Y11 (EZ 86)	single	9100	1	
11_TNC-50-3-29/103_NE	22641997	Y5, Y12 (EZ 141)	single	9106	2	outer contact silver
11_TNC-50-3-29/113_NE	22544841	Y5, Y12 (EZ 141)	single	9106	2	outer contact gold

- > for flexible cables
- > cable entry clamp
- > centre contact soldered




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Notes
11_TNC-50-2-1/133_NE	22640783	U2 (RG 316/U)	single	3005	
11_TNC-50-3-5/133_NE	22640798	U7, 10 (RG 58C/U)	single	3005	
11_TNC-50-3-6/133_NE	22543475	U7, 10 (RG 58C/U)	single	3004	

☐ centre contact NOT captivated

> for flexible cables

- > cable entry clamp
- > centre contact soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Notes
11_TNC-50-7-2/133_NE	22640466	U28 (RG 213/U) U33 (RG 214/U)	single	3008	

> for flexible cables

- > HUBER+SUHNER® full crimp
- > taper sleeves see page 406

3 security holes Ø 1/.039 DIA.




Fig. 1

3 security holes Ø 1/.039 DIA.




Fig. 2



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Fig.
11_TNC-50-2-112/133_NE	23001710	U2 (RG 316/U)	single	27215	1 A	1
11_TNC-50-2-113/133_NE	23001711	U4 (K 02252 D)	single	27215	1 A	1
11_TNC-50-3-115/133_NE	23001712	U9 (RG 223/U)	single	3015	2 B	2
11_TNC-50-3-115/133_NH	23001713	U9 (RG 223/U)	bulk 100 pcs.	3015	2 B	2
11_TNC-50-3-116/133_NE	23001714	U7 (RG 58 C/U)	single	3015	2 B	2
11_TNC-50-3-117/133_NE	23010015	U11 (RG 400/U)	single	3015	2 B	2

Right angle cable plugs (male)

- > for flexible cables
- > cable entry clamp
- > centre contact soldered




Fig. 1





Fig. 2




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Fig.	Notes
16_TNC-50-2-10/133_NE	8403229	U2 (RG 316/U)	single	3024	1	
16_TNC-50-3-28/133_NE	84012481	U7, 10 (RG 58C/U)	single	3024	1	
16_TNC-50-7-4/133_NE	22651587	U28 (RG 213/U) U33 (RG 214/U)	single	3003	2	

- > for flexible cables
- > cable entry crimp
- > centre contact soldered
- > taper sleeves see page 406




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
16_TNC-50-2-119/133_NE	23010087	U2 (RG 316/U)	single	27216	A
16_TNC-50-2-7/133_NE	23001716	U4 (K 02252 D)	single	27216	A

- > for flexible cables
- > HUBER+SUHNER® full crimp
- > taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
16_TNC-50-3-13/133_NE	22640492	U7 (RG 58 C/U)	single	3015	2 B
16_TNC-50-3-18/133_NE	22543606	U9 (RG 223/U)	single	3015	2 B


- > for flexible cables
- > cable entry clamp
- > centre contact soldered
- > taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
16_TNC-50-3-111/133_NE	23001717	U9 (RG 223/U)	single	27218	B
16_TNC-50-3-112/133_NE	23010115	U7 (RG 58 C/U)	single	27218	B
16_TNC-50-4-115/133_NE	23001718	S16 (S 04262 D)	single	27219	C
16_TNC-50-4-115/133_NH	22658175	S16 (S 04262 D)	bulk 100 pcs.	27219	C



Straight cable jacks (female)

- > for flexible cables
- > cable entry clamp
- > centre contact soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Notes
21_TNC-50-2-2/133_NE	22640515	U2 (RG 316/U)	single	3005	
21_TNC-50-3-4/133_NE	22640523	U7, 10 (RG 58C/U)	single	3005	

- > for flexible cables
- > HUBER+SUHNER® full crimp
- > taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
21_TNC-50-3-31/133_NE	84016544	U7 (RG 58 C/U)	single	0000231215	2 B
21_TNC-50-3-32/133_NE	84016601	U9 (RG 223/U)	single	0000231453	2 B

Straight bulkhead cable jacks (female)

- > for semi-rigid cables
- > cable entry soldered
- > with panel seal
- > insulating washers see page 408




Fig. 1





Fig. 2



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Mounting hole	Fig.
24_TNC-50-2-31/133_NE	23001721	Y3, Y11 (EZ 86)	single	27269	ML 4	1
24_TNC-50-3-30/133_NH	23001723	Y5, Y12 (EZ 141)	bulk 100 pcs.	27220	ML 4	2

- > for flexible cables
- > cable entry clamp
- > centre contact soldered
- > with panel seal
- > insulating washers see page 408



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole
24_TNC-50-2-1/133_NE	22543398	U2 (RG 316/U)	single	3005 / ML 4

☒ centre contact NOT captivated

> for flexible cables

> HUBER+SUHNER® full crimp

> with panel seal

> taper sleeves see page 406

> insulating washers see page 408




Fig. 1




Fig. 2

HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole	Crimp insert	Fig.
24_TNC-50-2-27/133_NE	23001719	U2 (RG 316/U)	single	9068 / ML 4	1 A	1
24_TNC-50-2-29/133_NH	23001720	U4 (K 02252 D)	bulk 100 pcs.	9068 / ML 4	1 A	1
24_TNC-50-3-21/133_NE	23001722	U9 (RG 223/U)	single	27221 / ML 4	2 B	2
24_TNC-50-3-23/133_NE	23010150	U7 (RG 58 C/U)	single	27221 / ML 4	2 B	2


Straight panel cable jacks (female)

> for flexible cables

> cable entry clamp

> centre contact soldered

> fastening screws see page 407



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole
25_TNC-50-2-1/133_NE	22640578	U2 (RG 316/U)	single	3005 / ML 8
25_TNC-50-3-9/133_NE	22643707	U7, 10 (RG 58C/U)	single	3005 / ML 8

- > for flexible cables
- > HUBER+SUHNER® full crimp
- > fastening screws see page 407
- > taper sleeves see page 406




Fig. 1




Fig. 2


HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Mounting hole	Crimp insert	Fig.
25_TNC-50-2-19/133_NE	84016723	U2 (RG 316/U)	single	ML 8	1 A	1
25_TNC-50-3-19/133_NE	84016722	U7 (RG 58 C/U)	single	ML 8	2 B	2 *

* mounting also possible with screws ISO M 2.5

RECEPTACLES WITH SOLDER END

Receptacles, plugs (male)

- > bulkhead mounted
- > with panel seal
- > insulating washers see page 408
- > solder tags see page 409



TNC 50

HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
12_TNC-50-0-1/133_NE	22640467	single	ML 2	

Receptacles, jacks (female)

- > bulkhead mounted
- > insulating washers see page 408
- > solder tags see page 409




Fig. 1





Fig. 2


HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Fig.	Notes
22_TNC-50-0-1/133_NE	22640537	single	ML 1	1	with panel seal
22_TNC-50-0-2/133_NE	22640539	single	ML 2	2	

- > panel mounted
- > fastening screws see page 407



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
23_TNC-50-0-2/133_NE	22640549	single	ML 6	
23_TNC-50-0-2/133_NH	22644322	bulk 100 pcs.	ML 6	


- > panel mounted
- > fastening screws see page 407



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
23_TNC-50-0-6/133_NE	22640551	single	ML 5	suitable for SUCOBOX® applications, see page 410

Right angle receptacles, jack (female)


- > bulkhead mounted
- > with panel seal
- > insulating washers see page 408
- > solder tags see page 409



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
27_TNC-50-0-1/133_NE	22543405	single	ML 2	


PROTECTIVE CAPS AND SHORTS

- > protective cap for plugs



HUBER+SUHNER type	Item no.	Packaging	Notes
61_TNC-0-0-1/-33_E	22640661	single	with chain

- > protective cap for jacks



HUBER+SUHNER type	Item no.	Packaging	Notes
62_TNC-0-0-1/-33_E	22640665	single	with chain

A FURTHER HUBER+SUHNER PRODUCT!

SUCOTEST™ 18 A test assemblies for harsh environments



Details on this product are to be found in the brochure,
Item no. 84017528. Get your copy free of charge at
www.hubersuhner.com.



SERIES TNC 75 Ω , COAXIAL MINIATURE CONNECTORS

DESCRIPTION

Within the internationally standardized TNC mating face dimensions a perfect 75 Ω characteristic impedance cannot be realized. However, at frequencies up to 1 GHz the small impedance deviation is negligible for practical applications. A typical VSWR of 1.15 at 1 GHz is achieved. The threaded coupling mechanism allows them to be used under higher environmental load than BNC.

Compatibility


75 Ω TNC connectors and 50 Ω TNC connectors are intermateable without restrictions.

CONTENTS

PAGE

Description	243
Interface Dimensions	243
Interface Dimensions in mm / inches	243
Technical Data	244
Cable Connectors	246
Protective Caps	247

INTERFACE DIMENSIONS



INTERFACE DIMENSIONS (MM / INCHES)

	Plug		Jack	
	min.	max.	min.	max.
A	4.83/.190	4.97/.196	—	4.72/.186
B	5.28/.208	5.79/.228	4.72/.186	5.23/.206
C	1.32/.052	1.37/.054	1.50 / .059 nom.	
D	0.08/.003	1.02/.040	2.10 / .827 nom.	
E	—	—	4.95/.195	—
F	—	—	9.60/.378	9.70/.382
G	—	—	8.35/.328	8.48/.334
H	—	—	8.10/.319	8.15/.321
I	—	—	10.60/.417	—

Interface dimensions conformable to the Standards:

(based on
IEC 60169-17 and
IEC 60169-8, Annex A)

IP rating (interface, mated) IP68

TECHNICAL DATA

ELECTRICAL DATA	REQUIREMENTS
Impedance	75 Ω
Frequency range	DC ... 1 GHz
Dielectric withstanding voltage (at sea level)	1.5 kV rms, 50 Hz (depending on cable)
Working voltage (at sea level) - unmated	500 V rms, 50 Hz (depending on cable)
Insulation resistance	$\geq 5 \cdot 10^3 \text{ M}\Omega$
Contact resistance - centre contact - outer contact	$\leq 1.5 \text{ m}\Omega$ $\leq 1 \text{ m}\Omega$
RF-leakage (measured at 1 GHz)	$\geq 60 \text{ dB}$

MECHANICAL DATA	REQUIREMENTS
Coupling nut torque - recommended - proof torque	46 Ncm ... 69 Ncm / 4.1 in. lbs ... 6.1 in. lbs 170 Ncm / 15.0 in. lbs
Coupling nut retention force	$\geq 450 \text{ N} / 101.2 \text{ lbs}$
Contact captivation	$\geq 27 \text{ N} / 6.1 \text{ lbs}$
Cable retention force ¹⁾	see pages 28 - 34
Durability (matings)	≥ 500

1) Value considers maximum load of the cables without irreversible variations of specifications.

ENVIRONMENTAL DATA	TEST CONDITIONS
Temperature range	- 65°C ... + 165°C / - 85 °F ... + 329 °F
Climatic category	IEC → 55/155/21
Thermal shock	MIL-STD-202, Method 107, Condition B
Moisture resistance	MIL-STD-202, Method 106
Corrosion	Saltspray test acc. to MIL-STD-202, Method 101, Condition B
Vibration	MIL-STD-202, Method 204, Condition B
Shock	MIL-STD-202, Method 213, Condition G

MATERIAL DATA		
CONNECTOR PART	MATERIAL	PLATING
Bodies	brass	SUCOPLATE®
Pin contacts	brass	gold / SUCOPRO
Socket contacts	copper-beryllium alloy copper alloy	gold / SUCOPRO
Crimp ferrules	copper brass	SUCOPLATE®
Insulators, standard version	PTFE or PFA	
Gaskets	silicone rubber	


Some connectors may have a specification that differs from the above mentioned data.

The products are designed and guaranteed to pass the above mentioned test procedures. Any additional or different requirement arising from specific applications or environmental conditions which is not covered by these test procedures is subject to request.

CABLE CONNECTORS


Straight cable plugs (male)

- > for flexible cables
- > cable entry clamp
- > centre contact soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Notes
11_TNC-75-4-2/133_NE	22543477	U15 (RG 59 B/U)	single	3005	


- > for flexible cables
- > HUBER+SUHNER® full crimp
- > taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
11_TNC-75-4-4/133_NE	22543478	U16 (RG 59 B/U)	single	3015	2 C
11_TNC-75-4-9/133_NE	22642678	U18 (G 04233 D)	single	3015	2 C
11_TNC-75-4-30/133_NE	22642503	U17 (S 04233)	single	3015	2 C

Right angle cable plugs (male)


- > for flexible cables
- > cable entry clamp
- > centre contact soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Notes
16_TNC-75-4-2/133_NE	22641402	U15 (RG 59 B/U)	single	3024	

Straight bulkhead cable jacks (female)


- > for flexible cables
- > HUBER+SUHNER® full crimp
- > with panel seal
- > taper sleeves see page 406
- > insulating washers see page 408



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole	Crimp insert
24_TNC-75-4-8/133_NE	22544140	U16 (RG 59 B/U)	single	3015 / ML 4	2 C


PROTECTIVE CAPS

- > protective cap for plugs



HUBER+SUHNER type	Item no.	Packaging	Notes
61_TNC-0-0-1/-33_E	22640661	single	with chain


- > protective cap for jacks



HUBER+SUHNER type	Item no.	Packaging	Notes
62_TNC-0-0-1/-33_E	22640665	single	with chain

A FURTHER HUBER+SUHNER PRODUCT GROUP!

RF coaxial cables



Details on this product are to be found in the general catalogue,
Item no. 644817. Get your copy free of charge at www.hubersuhner.com.





SERIES BNO TWINAXIAL MINIATURE CONNECTORS

DESCRIPTION

HUBER+SUHNER BNO twin connectors are two pin bayonet coupled (same bayonet locking mechanism as BNC) connectors for use with balanced twin-conductor cables with 75 Ω to 130 Ω impedance. They have polarized contacts and are not inter-mateable with BNC.


The HUBER+SUHNER BNO twin connectors are suitable for applications up to 200 MHz (i.e. computer networks and process control).

CONTENTS

PAGE

Description	249
Interface dimensions	249
Interface dimensions in mm / inches	249
Technical data	250
Cable connectors	252
Receptacles with solder end	253

INTERFACE DIMENSIONS



INTERFACE DIMENSIONS (MM / INCHES)

	Plug		Jack	
	min.	max.	min.	max.
A	9.78/.385	9.91/.390	9.60/.378	9.70/.382
B	0.89/.035	1.65/.065	4.34/.171	5.08/.200
C	0.81/.032	1.80/.071	3.96/.156	5.08/.200
D	0.71/.028	1.07/.042	4.78/.188	5.23/.206
E	3.14/.124	3.26/.128	3.14/.124	3.26/.128
F	—	—	8.10/.319	8.15/.321
G	—	—	10.52/.414	—
H	—	—	8.36/.329	8.46/.333

Interface dimensions conformable to the Standards:

International: IEC 60169-22

IP rating (interface, mated) IP64

BNO
BNT

TECHNICAL DATA

ELECTRICAL DATA	REQUIREMENTS
Impedance	not defined
Frequency range (for connector interface)	DC ... 200 MHz
Dielectric withstanding voltage (at sea level)	1.5 kV rms, 50 Hz between any two contacts
Insulation resistance	$\geq 10^4 \text{ M}\Omega$
Contact resistance - centre contact - outer contact	$\leq 2 \text{ m}\Omega$ $\leq 2 \text{ m}\Omega$

MECHANICAL DATA	REQUIREMENTS
Coupling nut torque	7 Ncm ... 28 Ncm / 0.6 in. lbs ... 2.5 in. lbs
Coupling nut retention force	$\geq 450 \text{ N} / 101.2 \text{ lbs}$
Cable retention force ¹⁾	see pages 28 – 34
Durability (matings)	≥ 500

1) Value considers maximum load of the cables without irreversible variations of specifications.

ENVIRONMENTAL DATA	TEST CONDITIONS
Temperature range	- 50°C ... + 125°C / - 58 °F ... + 257 °F
Climatic category	IEC → 50/125/21
Thermal shock	MIL-STD-202, Method 107, Condition B
Moisture resistance	MIL-STD-202, Method 106
Corrosion	Saltspray test acc. to MIL-STD-202, Method 101, Condition B
Vibration	MIL-STD-202, Method 204, Condition B
Shock	MIL-STD-202, Method 213, Condition G

MATERIAL DATA		
CONNECTOR PARTS	MATERIAL	PLATING
Bodies	brass	SUCOPLATE®
Pin contacts	brass	gold
Socket contacts	copper-beryllium alloy	gold
Crimp ferrules	copper	SUCOPLATE®
Insulators	ETFE (Tefzel)	
Gaskets	silicone rubber	


Some connectors may have a specification that differs from the above mentioned data.

The products are designed and guaranteed to pass the above mentioned test procedures. Any additional or different requirement arising from specific applications or environmental conditions which is not covered by these test procedures is subject to request.

CABLE CONNECTORS

Straight cable plugs (male)


- > cable entry crimp
- > centre contact crimp or soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
11_BNO-0-4-1/133_NE	22541080	V1 (RG 108A/U)	single	3083	76_Z-0-4-8
11_BNO-0-4-1/133_NH	22649903	V1 (RG 108A/U)	bulk 100 pcs.	3083	76_Z-0-4-8

Right angle cable plugs (male)


- > cable entry crimp
- > centre contact soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
16_BNO-0-4-1/133_NE	22643456	V1 (RG 108A/U)	single	9042	C


Straight cable jacks (female)

- > cable entry crimp
- > centre contact crimp or soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
21_BNO-0-4-1/133_NE	22541081	V1 (RG 108A/U)	single	3083	76_Z-0-4-8

- > cable entry crimp
- > centre contact crimp or soldered



RECEPTACLES WITH SOLDER END

- > bulkhead mounted
- > without panel seal
- > front mounting




Fig. 1




Fig. 2

BNO

- > panel mounted
- > fastening screws see page 407




Fig. 1




Fig. 2

HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Fig.	Notes
23_BNO-0-0-1/133_NE	22543389	single	ML 6	1	flange with 4 threads*
23_BNO-0-0-2/133_NE	22541085	single	ML 6	2	flange with 4 holes

* mounting also possible with screws ISO M 2.5



SERIES BNT TRIAXIAL MINIATURE CONNECTORS

DESCRIPTION

HUBER+SUHNER BNT triaxial connectors are RF connectors with a bayonet coupling mechanism and three concentric contacts (inner conductor, inner screen and outer screen) for triaxial cables.

HUBER+SUHNER BNT connectors are interchangeable with BNC connectors, but the inner conductor and outer screen are connected only.


BNT connectors are suitable for applications up to 3 GHz (inner coaxial line).

CONTENTS

PAGE

Description	255
Interface dimensions	255
Interface dimensions in mm / inches	255
Technical data	256
Cable connectors	258
Receptacles with solder end	259

INTERFACE DIMENSIONS



INTERFACE DIMENSIONS (MM / INCHES)

	Plug		Jack	
	min.	max.	min.	max.
A	4.85/.191	4.90/.193	4.95/.195*	5.05/.199*
B	0.00/.000	0.40/.016	0.10/.004	—
C	0.50/.020 nom.		0.20/.008 nom.	
D	0.60/.024 nom.		4.90/.193 nom.	
E	5.30/.209	—	5.00/.197	—
F	1.43/.056	1.47/.058	1.70/.067	1.75/.069
G	1.32/.052	1.37/.054	10.52/.414	—
H	9.78/.385	9.91/.390	8.10/.319	8.15/.321
I	—	—	9.60/.378	9.70/.382
K	—	—	0.20/.008 nom.	
L	—	—	8.31/.327	8.51/.335

* prior to slotting

IP rating (interface, mated) IP64

TECHNICAL DATA

ELECTRICAL DATA	REQUIREMENTS
Impedance	50 Ω (between centre contact and first outer contact)
Frequency range	DC ... 3 GHz (inner coaxial line)
Dielectric withstanding voltage (at sea level) - centre contact/inner screen - between screens	1 kV rms, 50 Hz 400 V rms, 50 Hz
Insulation resistance - centre contact/inner screen - between screens	$\geq 5 \cdot 10^3 \text{ M}\Omega$ $\geq 5 \cdot 10^2 \text{ M}\Omega$
Contact resistance - centre contact - inner screen - outer screen	$\leq 1.5 \text{ m}\Omega$ $\leq 1 \text{ m}\Omega$ $\leq 1.5 \text{ m}\Omega$

MECHANICAL DATA	REQUIREMENTS
Coupling nut torque	7 Ncm ... 28 Ncm / 0.6 in. lbs ... 2.5 in. lbs
Coupling nut retention force	$\geq 450 \text{ N}$ / 101.2 lbs
Contact captivation	$\geq 27 \text{ N}$ / 6.1 lbs
Cable retention force ¹⁾	see pages 28 – 34
Durability (matings)	≥ 500

1) Value considers maximum load of the cables without irreversible variations of specifications.

ENVIRONMENTAL DATA	TEST CONDITIONS
Temperature range	- 50°C ... + 125°C / - 58 °F ... + 257 °F
Climatic category	IEC → 50/125/21
Thermal shock	MIL-STD-202, Method 107, Condition B
Moisture resistance	MIL-STD-202, Method 106
Corrosion	Saltspray test acc. to MIL-STD-202, Method 101, Condition B
Vibration	MIL-STD-202, Method 204, Condition B
Shock	MIL-STD-202, Method 213, Condition G

MATERIAL DATA		
CONNECTOR PARTS	MATERIAL	PLATING
Bodies	brass	SUCOPLATE®
Pin contacts	brass	gold
Socket contacts	copper-beryllium alloy	gold
1 st outer contact	brass	silver / SUCOPLATE®
Crimp ferrules	copper	SUCOPLATE®
Insulators	PTFE or PFA	
Gaskets	silicone rubber	


Some connectors may have a specification that differs from the above mentioned data.

The products are designed and guaranteed to pass the above mentioned test procedures. Any additional or different requirement arising from specific applications or environmental conditions which is not covered by these test procedures is subject to request.

CABLE CONNECTORS

Straight cable plugs (male)


> cable entry clamp



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction
11_BNT-50-2-1/103_NE	22541057	W1 (G 02332)	single	3082
11_BNT-50-3-1/103_NE	22541058	W2 (G 03332)	single	3082
11_BNT-50-4-1/103_NE	22541061	(UR 114)	single	3082

Straight bulkhead cable jacks (female)

- > cable entry clamp
- > with panel seal



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Mounting hole
24_BNT-50-2-1/103_NE	22541075	W1 (G 02332)	single	3082	ML 4
24_BNT-50-3-1/103_NE	22541077	W2 (G 03332)	single	3082	ML 4

☒ centre contact NOT captivated

RECEPTACLES WITH SOLDER END

Receptacles, jacks (female)

- > bulkhead mounted
- > without panel seal
- > front mounting




Fig. 1




Fig. 2

HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Fig.	Notes
22_BNT-50-0-1/103_NE	22541069	single	ML 3	1	
22_BNT-50-0-2/103_NE	22541070	single	ML 2	2	

Flange mount, jacks (female)

- > panel mounted
- > fastening screws see page 407




Fig. 1





Fig. 2

HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Fig.	Notes
23_BNT-50-0-1/103_NE	22544850	single	ML 6	1	flange with 4 threads *
23_BNT-50-0-2/103_NE	22541073	single	ML 6	2	flange with 4 holes


* mounting also possible with screws ISO M 2.5

A FURTHER HUBER+SUHNER PRODUCT GROUP!

SENCITY® broadband antennas for indoor applications



Details on this product are to be found in the brochure,
Item no. 84001364. Get your copy free of charge at
www.hubersuhner.com.





SERIES SHV, HIGH VOLTAGE CONNECTORS

DESCRIPTION

HUBER+SUHNER SHV (Safe High Voltage) connectors provide more secure handling: center contacts are well recessed to prevent shock hazards in unmated condition. All inner contacts are fully captivated and will withstand axial forces of 100 N minimum. When mating a connector pair the outer conductor contact is made prior to the inner conductor contacts.


SHV connectors are suitable for all high voltage applications up to 5 kV DC or 3.5 kV rms. These connectors are typically used in nuclear instruments or test and measurement equipment. Voltages are valid for both, the mated and the unmated condition.

CONTENTS

PAGE

Description	261
Interface dimensions	261
Interface dimensions in mm / inches	261
Technical data	262
Cable connectors	264
Receptacles with solder end	265

INTERFACE DIMENSIONS



INTERFACE DIMENSIONS (MM / INCHES)

	Plug		Jack	
	min.	max.	min.	max.
A	4.57/.180	4.72/.186	4.83/.190	4.98/.196
B	9.78/.385	9.91/.390	9.60/.378	9.70/.382
C	2.06/.081	—	2.06/.081	—
D	5.44/.214	—	5.26/.207	5.44/.214
E	1.17/.046	1.63/.064	1.55/.061	1.98/.078
F	4.42/.174	—	3.30/.130	—
G	15.90/.626	16.10/.634	15.90/.626	16.00/.630
H	—	—	11.59/.456	12.70/.500
I	—	—	1.32/.052	1.37/.054
K	—	—	10.85/.427	—
L	—	—	1.63/.064	2.18/.086

Interface dimensions conformable to the Standards:

International: IEC 60498, NIM ND-545
USA: MIL-STD-348A/314
ANSI N 24.4

IP rating (interface, mated) IP64

SHV
MHV

TECHNICAL DATA

ELECTRICAL DATA	REQUIREMENTS
Impedance	50 Ω
Frequency range	DC ... 300 MHz
Dielectric withstanding voltage (at sea level)	5.0 kV rms, 50 Hz (depending on cable)
Working voltage (at sea level)	3.5 V rms, 50 Hz (depending on cable)
Insulation resistance	$\geq 10^6$ M Ω
Contact resistance - centre contact - outer contact	≤ 2 m Ω ≤ 1.5 m Ω
Corona extinction voltage (at 21000 m)	≥ 350 V rms, 50 Hz (depending on cable)
Current rating, continuous	≤ 10 A

MECHANICAL DATA	REQUIREMENTS
Coupling nut torque	7 Ncm ... 28 Ncm / 0.6 in. lbs ... 2.5 in. lbs
Coupling nut retention force	≥ 450 N / 101.2 lbs
Contact captivation	≥ 27 N / 6.1 lbs
Cable retention force ¹⁾	see pages 28 - 34
Durability (matings)	≥ 500

1) Value considers maximum load of the cables without irreversible variations of specifications.

ENVIRONMENTAL DATA	TEST CONDITIONS (PTFE)	TEST CONDITIONS (POLYSTYROL)
Temperature range	- 65°C ... + 165°C / - 85 °F ... + 329 °F	- 55°C ... + 100°C / - 67 °F ... + 212 °F
Climatic category	IEC $\rightarrow$ 55/155/21	
Thermal shock	MIL-STD-202, Method 107, Condition B	
Moisture resistance	MIL-STD-202, Method 103, Condition B	
Corrosion	Saltspray test acc. to MIL-STD-202, Method 101, Condition B	
Vibration	MIL-STD-202, Method 204, Condition A	
Shock	MIL-STD-202, Method 213, Condition I	
Radiation resistance (with polystyrene dielectric)	$\geq 10^9$ rad	

MATERIAL DATA		
CONNECTOR PARTS	MATERIAL	PLATING
Bodies	brass	SUCOPLATE®
Pin contacts	brass	gold
Socket contacts	copper-beryllium alloy	gold
Crimp ferrules	copper	SUCOPLATE®
Insulators	PTFE or PFA	
Insulators (radiation resistant types)	polystyrol, crosslinked	

Some connectors may have a specification that differs from the above mentioned data.


The products are designed and guaranteed to pass the above mentioned test procedures. Any additional or different requirement arising from specific applications or environmental conditions which is not covered by these test procedures is subject to request.

CABLE CONNECTORS

Straight cable plugs (male)


> HUBER+SUHNER® full crimp

> taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
11_SHV-50-3-1/133_NE	22541987	U7 (RG 58 C/U)	single	3092	2 B
11_SHV-50-4-1/133_NE	22541992	U16 (RG 59 B/U)	single	3092	2 C

> cable entry clamp




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Notes
11_SHV-50-3-10/133_NE	22541990	U7 (RG 58 C/U)	single	3094	
11_SHV-50-4-10/133_NE	22541996	U15 (RG 59 B/U)	single	3094	

Straight cable jacks (female)

> HUBER+SUHNER® full crimp


> taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert
21_SHV-50-3-1/133_NE	22541998	U7 (RG 58 C/U)	single	3092	2 B
21_SHV-50-4-1/133_NE	22542001	U16 (RG 59 B/U)	single	3092	2 C

Straight bulkhead cable jacks (female)

- > HUBER+SUHNER® full crimp
- > with panel seal
- > taper sleeves see page 406




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole	Crimp insert
24_SHV-50-3-1/133_NE	22641281	U7 (RG 58 C/U)	single	3092 / ML 4	2 B
24_SHV-50-4-1/133_NE	22544592	U16 (RG 59 B/U)	single	3092 / ML 4	2 C

RECEPTACLES WITH SOLDER END


Receptacles, jacks (female)

- > bulkhead mounted
- > without panel seal




HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Insulator	Notes
22_SHV-50-0-2/133_NE	22544054	single	ML 2	PTFE	
22_SHV-50-0-6/133_NE	22542007	single	ML 2	polystyrol	radiation resistant

- > bulkhead mounted
- > hermetically sealed




HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Plating body	Notes
22_SHV-50-0-3/100_NE *	22543968	single	ML 4	silver	leak rate 10 ⁻⁶ Torr l/sec.(atm cc/s)

- > panel mounted
- > fastening screws see page 407



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
23_SHV-50-0-1/133_NE	22542008	single	ML 106	mounting also possible with screws ISO M 2.5

- > panel mounted
- > fastening screws see page 407



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
23_SHV-50-0-2/133_NE	22542010	single	ML 106	

* RoHS compliant alternative on request



SERIES MHV (H4) HIGH VOLTAGE CONNECTORS

DESCRIPTION

HUBER+SUHNER MHV connectors are coaxial miniature high voltage (MHV = Miniature High Voltage) connectors with 5 kV rms test voltage (mated pairs). The MHV connectors have a working voltage up to 1.6 kV rms in mated condition and are suitable for applications up to 300 MHz. MHV connectors are of similar design to BNC connectors but the insulators protrude over the outer contacts to give a degree of contact-voltage proof when unmated.


However, if a high degree of protection in the unmated condition is required, use of series SHV is recommended.

CONTENTS

PAGE

Description	267
Interface dimensions	267
Interface dimensions in mm / inches	267
Technical data	268
Cable connectors	270
Receptacles with solder end	271

INTERFACE DIMENSIONS



INTERFACE DIMENSIONS (MM / INCHES)

	Plug		Jack	
	min.	max.	min.	max.
A	4.83/.190	—	—	4.72/.186
B	9.78/.385	9.91/.390	9.60/.378	9.70/.382
C	7.18/.283	—	—	7.11/.280
D	8.10/.319	—	—	8.05/.317
E	—	2.31/.091	2.06/.081	2.31/.091
F	—	2.18/.086	2.18/.086	—
G	1.32/.052	1.37/.054	8.31/.327	8.51/.335
H	—	—	10.52/.414	—
I	—	—	6.86/.270	—

IP rating (interface, mated) IP64

TECHNICAL DATA

ELECTRICAL DATA	REQUIREMENTS
Impedance	50 Ω
Frequency range	DC ... 300 MHz
Dielectric withstanding voltage (at sea level)	5.0 kV rms, 50 Hz (depending on cable)
Working voltage (at sea level)	1.6 V rms, 50 Hz (depending on cable)
Insulation resistance	$\geq 5 \cdot 10^6 \text{ M}\Omega$
Contact resistance - centre contact - outer contact	$\leq 2 \text{ m}\Omega$ $\leq 1 \text{ m}\Omega$
Corona extinction voltage (at 21000 m)	$\geq 300 \text{ V rms}$, 50 Hz (depending on cable)
Current rating, continuous	$\leq 10 \text{ A}$

MECHANICAL DATA	REQUIREMENTS
Coupling nut torque	7 Ncm ... 28 Ncm / 0.6 in. lbs ... 2.5 in. lbs
Coupling nut retention force	$\geq 450 \text{ N}$ / 101.2 lbs
Contact captivation	$\geq 15 \text{ N}$ / 6.1 lbs
Cable retention force ¹⁾	see pages 28 - 34
Durability (matings)	≥ 500

1) Value considers maximum load of the cables without irreversible variations of specifications.

ENVIRONMENTAL DATA	TEST CONDITIONS
Temperature range	- 65°C ... + 165°C / - 85 °F ... + 329 °F
Climatic category	IEC → 55/155/21
Thermal shock	MIL-STD-202, Method 107, Condition B
Moisture resistance	MIL-STD-202, Method 106
Corrosion	Saltspray test acc. to MIL-STD-202, Method 101, Condition B
Vibration	MIL-STD-202, Method 204, Condition B

MATERIAL DATA		
CONNECTOR PARTS	MATERIAL	PLATING
Bodies	brass	SUCOPLATE®
Pin contacts	brass	gold
Socket contacts	copper-beryllium alloy	gold
Crimp ferrules	copper	SUCOPLATE®
Insulators	PTFE or PFA	


Some connectors may have a specification that differs from the above mentioned data.

The products are designed and guaranteed to pass the above mentioned test procedures. Any additional or different requirement arising from specific applications or environmental conditions which is not covered by these test procedures is subject to request.

CABLE CONNECTORS

Straight cable plugs (male)

> cable entry clamp



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Notes
11_H4-50-3-1/133_NE	22541732	U7 (RG 58 C/U)	single	3012	
11_H4-50-4-1/133_NE	22541742	U15 (RG 59 B/U)	single	3012	

> cable entry crimp

> taper sleeves see page 406




Fig. 1





Fig. 2



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Fig.
11_H4-50-3-3/133_NE	22541737	U7 (RG 58 C/U)	single	3078	B	1
11_H4-50-4-4/133_NE	22543809	U16 (RG 59 B/U)	single	3078	C	2

Straight cable jacks (female)

> cable entry clamp




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Notes
21_H4-50-3-1/133_NE	22541756	U7 (RG 58 C/U)	single	3012	

☐ centre contact NOT captivated

Straight bulkhead cable jacks (female)

- > cable entry clamp
- > with panel seal




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole
24_H4-50-3-1/133_NE	22541784	U7 (RG 58 C/U)	single	3012 / ML 4

RECEPTACLES WITH SOLDER END


Receptacles, jacks (female)

- > bulkhead mounted
- > with panel seal



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
22_H4-50-0-1/133_NE	22652095	single	ML 1	

- > bulkhead mounted
- > hermetically sealed




HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Plating body	Notes
22_H4-50-0-6/100_NE *	22541764	single	ML 4	silver	leak rate 10 ⁻⁶ Torr l/sec.(atm cc/s) max.

☐ centre contact NOT captivated
* RoHs compliant alternative on request

Receptacles, plugs (male)

> bulkhead mounted



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes
12_H4-50-0-1/133_NE	22543467	single	ML 2	with panel seal

Flange mount, jacks (female)

- > panel mounted
- > fastening screws see page 407




Fig. 1




Fig. 2

HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Notes	Fig.
23_H4-50-0-7/133_NE	22541776	single	ML 6	mounting also possible with screws ISO M 2.5	1
23_H4-50-0-8/133_NE	22541779	single	ML 6		2



SERIES N 50 Ω, COAXIAL CONNECTORS

DESCRIPTION

HUBER+SUHNER N connectors are available with 50 Ω and 75 Ω impedance. The frequency range extends to 18 GHz, depending on the connector and cable type. The screw-type coupling mechanism provides a sturdy and reliable connection.


HUBER+SUHNER N connectors are available for flexible cables, for semi-rigid cables and for corrugated copper tube cables.

Cable entries: clamp, crimp and solder types available, as well as HUBER+SUHNER QUICK-FIT for corrugated copper tube cables.

Compatibility

Inner conductors of N 75 Ω connectors have a smaller diameter than those of the 50 Ω version. Therefore 50 Ω and 75 Ω connectors must not be mated with each other.

INTERFACE DIMENSIONS



CONTENTS

PAGE

Description	273
Interface dimensions	273
Interface dimensions in mm / inches	273
Technical data	274
Cable connectors	277
Receptacles with solder end	293
Stripline launchers	296
Protective caps	297
HUBER+SUHNER QUICK-FIT	323

INTERFACE DIMENSIONS (MM / INCHES)

	Plug		Jack	
	min.	max.	min.	max.
A	—	8.38/.330	8.03/.316	8.13/.320
B	5.33/.210	5.84/.230	4.75/.187	5.26/.207
C	—	3.15/.124	—	3.15/.124
D	16.00/.630	—	—	15.93/.627
E	1.60/.063	1.68/.066	5.33/.210	—
F	—	—	9.04/.356	9.19/.362
G	—	—	6.76/.266	—
H	—	—	10.72/.422	—

Interface dimensions conformable to the Standards:

International:	IEC 61169-16
Europe:	CECC 22 210
USA:	MIL-STD-348A/304


IP rating (interface, mated) IP68

TECHNICAL DATA

ELECTRICAL DATA	REQUIREMENTS
Impedance	50 Ω
Frequency range - flexible cables - semi-rigid cables	DC ... 11 GHz DC ... 18 GHz
Dielectric withstanding voltage (at sea level)	2.5 kV rms, 50 Hz
Working voltage (at sea level)	≤ 1.0 kV rms, 50 Hz
Insulation resistance	$\geq 5 \cdot 10^3$ M Ω
Contact resistance - centre contact - outer contact	≤ 1.0 m Ω ≤ 1.0 m Ω
RF-leakage (between 2 ÷ 3 GHz)	≥ 90 dB
VSWR	see table below

TYPICAL VSWR *	FREQUENCY RANGE					CABLE GROUP
CONNECTOR TYPE	1 GHz	2.5 GHz	5 GHz	12.4 GHz	18 GHz	
straight connectors	1.04	1.05	1.08			M6
	1.03	1.04	1.06	1.12		Y5, Y12
	1.03	1.04	1.05	1.07	1.09	Y5, Y12
	1.03	1.04	1.05	1.08	1.12	Y7
	1.05	1.09	1.17			U7, U9
	1.04	1.06	1.12			U28, U29, U32, U33
	1.03	1.05	1.14			S24
	1.03	1.05	1.10			S39
right angle connectors	1.04	1.05	1.08			M6
	1.04	1.05	1.06	1.12		Y5, Y12
	1.05	1.10	1.20			U7, U9
	1.08	1.10	1.12			U28, U29, U32, U33

* Values which can be achieved when connectors are perfectly fixed onto cable.



MECHANICAL DATA	REQUIREMENTS					
Coupling nut torque						
- recommended	0.68 Nm ... 1.13 Nm / 6.0 ... 10.0 in. lbs					
- proof torque	1.70 Nm / 15.0 in. lbs					
Coupling nut retention force	≥ 450 N / 101.2 lbs					
Contact captivation	≥ 28 N / 6.3 lbs					
Cable retention force ¹⁾	see pages 28 - 34					
Durability (matings)	≥ 500					
- recommended torque for connectors with profile HEX19 (HEX18) coupling nut	Matings	500	250	100	60	30
	Torque	1 Nm	2 Nm	3 Nm	4 Nm	5 Nm

1) value considers maximum load of the cables without irreversible variations of specifications.

ENVIRONMENTAL DATA	TEST CONDITIONS
Temperature range	- 65°C ... + 165°C / - 85 °F ... + 329 °F
Climatic category	IEC → 55/155/21
Thermal shock	MIL-STD-202, Method 107, Condition B
Moisture resistance	MIL-STD-202, Method 106
Corrosion	Saltspray test acc. to MIL-STD-202, Method 101, Condition B
Vibration	MIL-STD-202, Method 204, Condition B
Shock	MIL-STD-202, Method 213, Condition I

MATERIAL DATA		
CONNECTOR PART	MATERIAL	PLATING
Bodies	brass	SUCOPLATE®
Pin contacts	brass	gold / SUCOPRO
Outer contact, slotted	spring bronze	SUCOPLATE®
Female contacts	copper-beryllium alloy; spring bronze	gold / SUCOPRO
Crimp ferrules	copper	SUCOPLATE®
Insulators, standard version	PTFE or PFA	
Gaskets	silicone rubber	

Some connectors may have a specification that differs from the above mentioned data.

The products are designed and guaranteed to pass the above mentioned test procedures. Any additional or different requirement arising from specific applications or environmental conditions which is not covered by these test procedures is subject to request.

CABLE CONNECTORS

Straight cable plugs (male)

- > for semi-rigid cables
- > cable entry soldered
- > centre contact soldered




Fig. 1





Fig. 2



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Weight	Fig.
11_N-50-2-15/113_UE	22660315	Y3, Y11 (EZ 86)	single	3095	25.6 g/0.90 oz.	1
11_N-50-3-13/113_NE	22542083	Y5, Y12 (EZ 141)	single	3095	29.0 g/1.02 oz.	2

- > for SUCOFORM cables
- > cable entry soldered
- > centre contact soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Weight	Fig.
11_N-50-5-18/103_NH	84008445	Y13 (Sucoform 250-01)	bulk 100 pcs.	0000215552	21.9 g/0.77 oz.	1

> for semi-rigid cables

- > cable entry soldered (Fig. 1)
- > cable entry clamp (Fig. 2)
- > centre contact plugged-in
- > frequency range: DC - 18 GHz




Fig. 1





Fig. 2

HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Weight	Fig.
11_N-50-3-51/133_NE	22543919	Y5, Y12 (EZ 141)	single	9006	43.0 g/1.51 oz.	1 *
11_N-50-5-39/133_NE	22642481	Y7 (EZ 250)	single	9089	51.0 g/1.79 oz.	2

* stainless steel

> for flexible cables

- > cable entry clamp
- > centre contact soldered




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Weight
11_N-50-2-1/133_NE	22544030	U2 (RG 316/U)	single	3017	38.0 g/1.33 oz.
11_N-50-2-2/133_NE	22643807	U4 (K 02252 D)	single	3017	38.0 g/1.33 oz.
11_N-50-3-5/133_NE	22542073	U7, 10 (RG 58C/U)	single	3017	36.0 g/1.26 oz.

Precision Connector - low VSWR

> for flexible cables

- > cable entry clamp
- > centre contact soldered
- > VSWR: DC-4 GHz ≤ 1.10 4-10 GHz ≤ 1.20 10-12.4 GHz ≤ 1.25




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Weight
11_N-50-3-54/133_NE	22642009	RG 223/U only	single	9099	32.0 g/1.12 oz.

Cable groups see page 28

Assembly tools see page 385

Mounting holes see page 412


- > for flexible cables
- > cable entry clamp
- > centre contact soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Weight
11_N-50-7-5/133_NE	22542117	U33, 28 (RG 214/U)	single	3007	51.0 g/1.79 oz.
11_N-50-7-6/133_NE	22542120	U33, 28 (RG 214/U)	single	3008	51.0 g/1.79 oz.

☒ centre contact NOT captivated

- for flexible cables
- HUBER+SUHNER® full crimp
- taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight
11_N-50-2-11/133_NH	22658813	U2 (RG 316/U)	bulk 100 pcs.	9068	1 A	26.5 g/0.93 oz.
11_N-50-2-16/133_NE	23014128	U4 (K 02252 D)	single	9068	1 A	25.4 g/0.89 oz.

- > for flexible cables
- > HUBER+SUHNER® full crimp
- > taper sleeves see page 406




Fig. 1




Fig. 2




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight	Fig.
11_N-50-3-28/133_NE	22642842	U7 (RG 58 C/U)	single	3015	2 B	23.0 g/0.81 oz.	1
11_N-50-3-29/133_NE	22642843	U9 (RG 223/U)	single	3015	2 B	23.0 g/0.81 oz.	1
11_N-50-3-31/133_NE	22648829	U11 (RG 400/U)	single	3015	2 B	28.0 g/0.98 oz.	1
11_N-50-3-31/133_NH	22650658	U11 (RG 400/U)	bulk 100 pcs.	3015	2 B	28.0 g/0.98 oz.	1
11_N-50-4-63/133_NE	22652069	S16 (S 04262 D)	single	3015	2 C	27.3 g/0.96 oz.	1
11_N-50-6-1/133_NE	22642488	U25 (S 06132D)	single	27035	3 D	34.0 g/1.19 oz.	2

> for flexible cables

> HUBER+SUHNER® full crimp

> taper sleeves see page 406




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight
11_N-50-6-5/133_NE	22648674	S26 (S 06132 D-10)	single	27082	3/8.65	31.0 g/1.09 oz.

> for flexible cables

> cable entry crimp

> centre contact plugged-in

> taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight
11_N-50-6-10/133_NH	22660330	S24 (S 06162 D-02)	bulk 100 pcs.	27091	8.65	29.5 g/1.03 oz.

> for flexible cables

> HUBER+SUHNER® full crimp

> taper sleeves see page 406




Fig. 1




Fig. 2





Fig. 3

HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight	Fig.
11_N-50-7-33/133_NE	22641614	U30 (S 07232)	single	9067	4 D	39.0 g/1.37 oz.	1
11_N-50-7-43/133_NE	22642844	U29 (RG 213/U)	single	3061	3 D	28.0 g/0.98 oz.	2
11_N-50-7-44/133_NE	22642845	U32 (RG 214/U)	single	3061	3 D	28.0 g/0.98 oz.	2
11_N-50-7-49/133_NE	22652111	S32 (S 07262 BD)	single	9067	4 D	40.0 g/1.40 oz.	3
11_N-50-7-61/133_NE	22651793	U33 (RG 393/U)	single	27070	2.5 D	28.5 g/1.00 oz.	2


- > for flexible cables
- > cable entry crimp
- > centre contact plugged-in
- > degree of protection IP 67



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight
11_N-50-10-5/103_UV	23002543	S39 (S 10162 B-11)	bulk 20 pcs.	27356	12.4	37.8 g/1.32 oz.

Right angle cable plugs (male)

- > for semi-rigid cables
- > cable entry soldered
- > centre contact soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Weight
16_N-50-3-15/133_NE	22648832	Y5 (EZ 141)	single	9200	29.1 g/1.02 oz.

- > for flexible cables
- > cable entry clamp
- > centre contact soldered




Fig. 1




Fig. 2

HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Weight	Fig.
16_N-50-3-103/133_NE	22651610	U10, U7 (RG 223/U)	single	27060	37.0 g/1.30 oz.	1
16_N-50-7-26/133_NE	22650825	U28, U33 (RG 213/U)	single	27121	65.0 g/2.28 oz.	2

- > for flexible cables
- > cable entry crimp
- > centre contact soldered
- > taper sleeves see page 406




Fig. 1





Fig. 2

HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight	Fig.
16_N-50-3-26/133_NE	22642846	U7 (RG 58 C/U)	single	3058	B	27.0 g/0.95 oz.	1
16_N-50-3-27/133_NE	22642847	U9 (RG 223/U)	single	3058	B	27.0 g/0.95 oz.	1
16_N-50-3-27/133_NH	22650168	U9 (RG 223/U)	bulk 100 pcs.	3058	B	27.0 g/0.95 oz.	1
16_N-50-7-30/133_NE	22642848	U29 (RG 213/U)	single	3076	D	42.0 g/1.47 oz.	2
16_N-50-7-31/133_NE	22642849	U32 (RG 214/U)	single	3076	D	42.0 g/1.47 oz.	2

> for flexible cables


- > cable entry crimp
- > centre contact soldered
- > taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight
16_N-50-4-14/133_NE	23015067	S16 (S 04262 D)	single	3058	C	31.7 g/1.11 oz.

> for flexible cables


- > cable entry crimp
- > centre contact soldered
- > taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight
16_N-50-7-22/133_NE	22651794	S32 (S 07262 BD)	single	9094	D	50.0 g/1.75 oz.

> for flexible cables

- > cable entry crimp
- > centre contact soldered
- > degree of protection IP 67
- > taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight
16_N-50-10-1/103_UV	23002552	S39 (S 10162 B-11)	bulk 20 pcs.	27357	12.4	50.0 g/1.75 oz. *

* centre contact not nickel underplated

> for flexible cables

> HUBER+SUHNER® full crimp

> taper sleeves see page 406




Fig. 1




Fig. 2




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight	Fig.
16_N-50-6-8/133_NE	22651496	S26 (S 06132 D-10)	single	27082	3/8.65	63.0 g/2.21 oz.	1
16_N-50-7-28/133_NE	22652040	U33 (RG 393/U)	single	27064	4 D	63.6 g/2.23 oz.	2
16_N-50-7-29/133_NE	22651494	U29 (RG 213/U)	single	9009	3 D	65.0 g/2.28 oz.	2
16_N-50-7-36/133_NE	22651495	U32 (RG 214/U)	single	9009	3 D	66.0 g/2.31 oz.	2

Straight cable jacks (female)

> for semi-rigid cables

> cable entry soldered

> centre contact soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Frequency range	Weight
21_N-50-2-14/133_NE	22642666	Y3, Y11 (EZ 86)	single	9073	DC-18 GHz	38.0 g/1.33 oz.
21_N-50-3-11/133_NE	22543921	Y5, Y12 (EZ 141)	single	9005	DC-12.4 GHz	38.0 g/1.33 oz.

☐ centre contact NOT captivated

> for flexible cables

> cable entry clamp

> centre contact soldered




Fig. 1




Fig. 2



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Weight	Fig.
21_N-50-3-5/133_NE	22543504	U10, U7 (RG 223/U)	single	3017	38.0 g/1.33 oz.	1
21_N-50-7-8/133_NE	22542254	U28, U33 (RG 213/U)	single	3008	50.0 g/1.75 oz.	2

> for flexible cables

> HUBER+SUHNER® full crimp

> taper sleeves see page 406




Fig. 1





Fig. 2



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight	Fig.
21_N-50-3-7/133_NE	22542229	U7 (RG 58 C/U)	single	3063	2 B	36.0 g/1.26 oz.	1
21_N-50-3-8/133_NE	22542231	U9 (RG 223/U)	single	3063	2 B	36.0 g/1.26 oz.	1
21_N-50-3-12/133_NE	22651795	U11 (RG 400/U)	single	3063	2 B	35.0 g/1.12 oz.	1
21_N-50-7-13/133_NE	22542257	U29 (RG 213/U)	single	3061	3 D	38.0 g/1.33 oz.	2
21_N-50-7-14/133_NE	22542258	U32 (RG 214/U)	single	3061	3 D	37.0 g/1.30 oz.	2

> for flexible cables


- > HUBER+SUHNER® full crimp
- > taper sleeves see page 406
- > degree of protection IP 66



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight
21_N-50-7-20/133_NE	22651796	S32 (S 07262 BD)	single	9067	4 D	37.0 g/1.30 oz.

> for flexible cables

- > cable entry crimp
- > centre contact plugged-in
- > degree of protection IP 67




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight
21_N-50-10-1/133_UF	23003072	S39 .. (S 10162 B-11)	bulk 50 pcs.	27356	12.4	38.1 g/1.33 oz. *

* centre contact not nickel underplated

Straight bulkhead cable jacks (female)

> for semi-rigid cables

- > cable entry soldered
- > centre contact soldered
- > with panel seal
- > insulating washers see page 408




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Frequency range	Weight
24_N-50-2-14/133_NE	22544637	Y3, Y11 (EZ 86)	single	9073	DC-12.4 GHz	39.0 g/1.37 oz.
24_N-50-3-14/133_NE	22542300	Y5, Y12 (EZ 141)	single	9005	DC-12.4 GHz	39.0 g/1.37 oz.

mounting hole ML 12

> for semi-rigid cables

- > cable entry soldered
- > centre contact plugged-in
- > body material: stainless steel
- > with panel seal
- > insulating washers see page 408




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Frequency range	Weight
24_N-50-3-51/19_NE	22642344	Y5, Y12 (EZ 141)	single	9006	DC-18 GHz	45.0 g/1.58 oz.

mounting hole ML 12

> for flexible cables

- > cable entry clamp
- > centre contact soldered
- > with panel seal
- > insulating washers see page 408



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole	Weight
24_N-50-2-1/133_NE	22641239	U2 (RG 316/U)	single	9150 / ML 12	42.0 g/1.47 oz.

> for flexible cables

- > cable entry clamp
- > centre contact soldered
- > with panel seal
- > insulating washers see page 408




Fig. 1




Fig. 2

HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole	Weight	Fig.
24_N-50-3-10/133_NE	22542295	U7, 10 (RG 58C/U)	single	9150 / ML 12	41.0 g/1.44 oz.	1
24_N-50-7-8/133_NE	22542323	U33, 28 (RG 214/U)	single	3008 / ML 12	53.0 g/1.86 oz.	2

> for flexible cables

- > HUBER+SUHNER® full crimp
- > taper sleeves see page 406
- > insulating washers see page 408




Fig. 1




Fig. 2




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight	Fig.
24_N-50-2-4/133_NE	22650170	U2 (RG 316/U)	single	9068	1 A	35.2 g/1.23 oz.	1
24_N-50-2-117/133_NE	22660124	U4 (K 02252 D)	single	9068	1 A	36.1 g/1.26 oz.	1
24_N-50-4-17/133_UE	22651789	S16 (S 04262 D)	single	3063	2 C	37.3 g/1.31 oz.	2 *

* has to be crimped with large crimp tool or table press!
centre contact not nickel underplated

mounting hole ML 12

> for flexible cables

- > HUBER+SUHNER® full crimp
- > taper sleeves see page 406
- > insulating washers see page 408




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight
24_N-50-3-11/133_NE	22542296	U7 (RG 58 C/U)	single	3063	2 B	38.0 g/1.33 oz. *
24_N-50-3-12/133_NE	22542297	U9 (RG 223/U)	single	3063	2 B	38.0 g/1.33 oz. *

* has to be crimped with large crimp tool or table press!

mounting hole ML 12

> for flexible cables

- > HUBER+SUHNER® full crimp
- > taper sleeves see page 406
- > insulating washers see page 408




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight
24_N-50-7-14/133_NE	22542326	U29 (RG 213/U)	single	3061	3 D	40.0 g/1.40 oz.
24_N-50-7-15/133_NE	22542327	U32 (RG 214/U)	single	3061	3 D	40.0 g/1.40 oz.

mounting hole ML 12

> for flexible cables

- > HUBER+SUHNER® full crimp
- > taper sleeves see page 406
- > insulating washers see page 408



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight
24_N-50-7-24/133_NE	22649912	U33 (RG 393/U)	single	27064	3 D	39.3 g/1.38 oz.

mounting hole ML 12

Straight panel cable jacks (female)

- > for semi-rigid cables
- > cable entry soldered
- > centre contact soldered
- > fastening screws see page 407




Fig. 1





Fig. 2

HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Frequency range	Weight	Fig.
25_N-50-2-14/133_NE	22641303	Y3, Y11 (EZ 86)	single	9073	DC-12.4 GHz	42 g/1.47 oz.	1
25_N-50-3-9/133_NE	22543952	Y5, Y12 (EZ 141)	single	9005	DC-12.4 GHz	42 g/1.47 oz.	2

mounting hole ML 14


- > for flexible cables
- > cable entry clamp
- > centre contact soldered
- > fastening screws see page 407



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole	Weight
25_N-50-2-2/133_NE	22542332	U2 (RG 316/U)	single	3017 / ML 14	45.0 g/1.58 oz.
25_N-50-3-4/133_NE	22542342	U7, 10 (RG 58C/U)	single	3017 / ML 14	44.0 g/1.54 oz.

☒ centre contact NOT captivated

- > for flexible cables
- > cable entry clamp
- > centre contact soldered
- > fastening screws see page 407



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole	Weight
25_N-50-7-8/133_NE	22542366	U33, 28 (RG 214/U)	single	3008 / ML 18	55.0 g/1.93 oz.

- > for flexible cables
- > HUBER+SUHNER® full crimp
- > fastening screws see page 407
- > taper sleeves see page 406




Fig. 1




Fig. 2

HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight	Fig.
25_N-50-2-9/133_NE	22651072	U2 (RG 316/U)	single	3068	1 A	34.5 g/1.21 oz.	1
25_N-50-2-10/133_NE	22651054	U4 (K 02252 D)	single	3068	1 A	38.6 g/1.35 oz.	2

mounting hole ML 14

> for flexible cables

- > HUBER+SUHNER® full crimp
- > fastening screws see page 407
- > taper sleeves see page 406




Fig. 1





Fig. 2

HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight	Fig.
25_N-50-3-6/133_NE	22542346	U7 (RG 58 C/U)	single	3063	2 B	39.0 g/1.37 oz.	1
25_N-50-3-7/133_NE	22542348	U9 (RG 223/U)	single	3063	2 B	39.0 g/1.37 oz.	1
25_N-50-3-20/133_NE	22649913	U11 (RG 400/U)	single	3063	2 B	37.0 g/1.30 oz.	2

mounting hole ML 14

> for flexible cables

- > HUBER+SUHNER® full crimp
- > fastening screws see page 407
- > taper sleeves see page 406




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight
25_N-50-7-13/133_NE	22542369	U29 (RG 213/U)	single	3061	3 D	42.0 g/1.47 oz.
25_N-50-7-14/133_NE	22542370	U32 (RG 214/U)	single	3061	3 D	42.0 g/1.47 oz.

mounting hole ML 14

RECEPTACLES WITH SOLDER END

Receptacles, plugs (male)


- > panel mounted
- > fastening screws see page 407



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Weight
13_N-50-0-1/133_NE	22542173	single	ML 16	46.0 g/1.61 oz.

Receptacles, jacks (female)

- > panel mounted
- > fastening screws see page 407



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Weight
23_N-50-0-1/133_NE	22542272	single	ML 17	31.0 g/1.09 oz.

- > bulkhead mounted
- > solder tags see page 409
- > with panel seal
- > insulating washers see page 408




Fig. 1





Fig. 2

HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Weight	Notes	Fig.
22_N-50-0-2/133_NE	22542265	single	ML 12	47.0 g/1.65 oz.		1
22_N-50-0-3/133_NE	22644425	single	ML 12	47.0 g/1.65 oz.	hermetically sealed *	2

* leak rate 10⁻⁶ Torr l/sec.(atm cc/s) max.
 * RoHs compliant alternative on request


- > bulkhead mounted



HUBER+SUHNER type	Item no.	Packaging	Weight	Notes
22_N-50-0-23/133_NF	22651448	bulk 50 pcs.	20.8 g/0.73 oz.	without nut and washer (direct screw into panel, thread M14x1)

Receptacles, plugs (male)


- > panel mounted
- > extended dielectric
- > fastening screws included



HUBER+SUHNER type	Item no.	Packaging	Weight	Notes
13_N-50-0-30/133_NE	22642831	single	30.0 g/1.05 oz.	SMA flange size


Receptacles, jacks (female)

- > panel mounted
- > extended dielectric
- > fastening screws see page 407




HUBER+SUHNER type	Item no.	Packaging	Weight	Notes
23_N-50-0-30/133_NE	22642835	single	14.0 g/0.49 oz.	SMA flange size

- > panel mounted
- > solder pot terminal
- > flush dielectric
- > fastening screws see page 407




HUBER+SUHNER type	Item no.	Packaging	Weight	Notes
23_N-50-0-23/133_NE	22544751	single	24.0 g/0.84 oz.	

- > end of center pin slotted
- > panel mounted
- > flush dielectric
- > fastening screws see page 407



HUBER+SUHNER type	Item no.	Packaging	Weight	Notes
23_N-50-0-69/133_NX	22648797	bulk 150 pcs.	27.9 g/0.89 oz.	

- > panel mounted
- > solder pot terminal
- > flush dielectric
- > fastening screws see page 407




HUBER+SUHNER type	Item no.	Packaging	Weight	Notes
23_N-50-0-31/133_NE	22642836	single	13.6 g/0.48 oz.	SMA flange size

STRIPLINE LAUNCHERS

Receptacles, plugs (male)

- > panel mounted
- > tab contact
- > flush dielectric
- > fastening screws see page 407



HUBER+SUHNER type	Item no.	Packaging	Weight	Notes
13_N-50-0-33/133_NE	22642834	single	36.0 g/1.26 oz.	

Receptacles, jacks (female)

- > panel mounted
- > tab contact
- > flush dielectric
- > fastening screws see page 407




Fig. 1




Fig. 2

HUBER+SUHNER type	Item no.	Packaging	Weight	Notes	Fig.
23_N-50-0-16/133_NE	22641166	single	13.5 g/0.47 oz.	SMA flange size	1
23_N-50-0-33/133_NE	22642837	single	24.5 g/0.86 oz.		2

PROTECTIVE CAPS

- > suitable for N50 Ω and N75 Ω
- > with chain




Fig. 1





Fig. 2




HUBER+SUHNER type	Item no.	Packaging	Weight	Notes	Fig.
61_N-0-0-1/-3_E	22542452	single	16.0 g/0.56 oz.	for plugs	1
62_N-0-0-1/-3_E	22543433	single	15.0 g/0.53 oz.	for jacks	2

A FURTHER HUBER+SUHNER PRODUCT GROUP!

Low smoke, free of halogen coaxial cables



Details on this product are to be found in the brochure, Item no. 23032234 (in English only). Get your copy free of charge at **www.hubersuhner.com**.





SERIES N 75 Ω, COAXIAL CONNECTORS

DESCRIPTION

HUBER+SUHRNER N connectors are available with 50 Ω and 75 Ω impedance. The HUBER+SUHRNER N-75 Ω connectors are suitable for applications up to 1.5 GHz. The screw-type coupling mechanism provides a sturdy and reliable connection.

Compatibility


Center conductors of N 75 Ω connectors have a smaller diameter than those of the 50 Ω version. Therefore 50 Ω and 75 Ω connectors must not be mated with each other.

CONTENTS

PAGE

Description	299
Interface dimensions	299
Interface dimensions in mm / inches	299
Technical data	300
Cable connectors	302
Receptacles with solder end	304

INTERFACE DIMENSIONS



INTERFACE DIMENSIONS (MM / INCHES)

	Plug		Jack	
	min.	max.	min.	max.
A	—	8.38/.330	8.03/.316	8.13/.320
B	5.33/.210	5.84/.230	4.75/.187	5.26/.207
C	—	2.00/.079	—	2.00/.079
D	16.00/.630	—	—	15.93/.627
E	1.00/.039	1.05/.041	5.33/.210	—
F	—	—	9.04/.356	9.19/.362
G	—	—	6.76/.266	—
H	—	—	10.72/.422	—

IP rating (interface, mated) IP68

N 75

TECHNICAL DATA

ELECTRICAL DATA	REQUIREMENTS
Impedance	75 Ω
Frequency range	DC ... 1.5 GHz
Dielectric withstanding voltage (at sea level)	2.5 kV rms, 50 Hz
Working voltage (at sea level)	≤ 1.0 kV rms, 50 Hz
Insulation resistance	$\geq 5 \cdot 10^3$ M Ω
Contact resistance - centre contact - outer contact	≤ 1.0 m Ω ≤ 1.0 m Ω
RF-leakage (measured at 1 GHz)	≥ 90 dB

MECHANICAL DATA	REQUIREMENTS
Coupling nut torque - recommended - proof torque	0.68 Nm ... 1.13 Nm / 6.0 ... 10.0 in. lbs 1.70 Nm / 15.0 in. lbs
Coupling nut retention force	≥ 450 N / 101.2 lbs
Contact captivation	≥ 28 N / 6.3 lbs
Cable retention force ¹⁾	see pages 28 – 34
Durability (matings)	≥ 500

1) Angabe berücksichtigt die maximale Belastbarkeit des Kabels ohne irreversible, die Funktion beeinträchtigende Veränderung

ENVIRONMENTAL DATA	TEST CONDITIONS
Temperature range	- 65°C ... + 165°C / - 85 °F ... + 329 °F
Climatic category	IEC → 55/155/21
Thermal shock	MIL-STD-202, Method 107, Condition B
Moisture resistance	MIL-STD-202, Method 106
Corrosion	Saltspray test acc. to MIL-STD-202, Method 101, Condition B
Vibration	MIL-STD-202, Method 204, Condition B
Shock	MIL-STD-202, Method 213, Condition I

MATERIAL DATA		
CONNECTOR PART	MATERIAL	PLATING
Bodies	brass	SUCOPLATE®
Pin contacts	brass	gold / SUCOPRO
Outer contact, slotted	spring bronze	SUCOPLATE®
Female contacts	copper-beryllium alloy; spring bronze	gold / SUCOPRO
Crimp ferrules	copper	SUCOPLATE®
Insulators, standard version	PTFE or PFA	
Gaskets	silicone rubber	

Some connectors may have a specification that differs from the above mentioned data.

The products are designed and guaranteed to pass the above mentioned test procedures. Any additional or different requirement arising from specific applications or environmental conditions which is not covered by these test procedures is subject to request.

CABLE CONNECTORS

Straight cable plugs (male)

> for flexible cables

- > cable entry clamp
- > centre contact soldered




Fig. 1




Fig. 2



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Weight	Fig.
11_N-75-4-3/133_NE	22542467	U15 (RG 59 B/U)	single	27042	34.0 g/1.19 oz	1
11_N-75-4-6/133_NE	22542475	U18 (G 04233 D)	single	27042	34.0 g/1.19 oz	1
11_N-75-5-2/133_NE	22542484	U23 (RG 6 A/U)	single	3045	54.0 g/1.89 oz	2
11_N-75-7-4/133_NE	22542497	U37, 35 (RG 216/U)	single	3008	48.0 g/1.68 oz.	2

> for flexible cables

- > HUBER+SUHNER® full crimp
- > taper sleeves see page 406




Fig. 1





Fig. 2



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight	Fig.
11_N-75-4-8/133_NE	22542477	U16 (RG 59 B/U)	single	3063	2 C	30.0 g/1.05 oz.	1
11_N-75-4-9/133_NE	22542478	U18 (G 04233 D)	single	3063	2 C	30.0 g/1.05 oz.	1
11_N-75-7-16/133_NE	22542511	U34 (RG 11 A/U)	single	3061	2 D	32.0 g/1.12 oz.	2
11_N-75-7-18/133_NE	22542512	U36 (RG 216/U)	single	3061	2 D	32.0 g/1.12 oz.	2

Straight cable jacks (female)


- > for flexible cables
- > HUBER+SUHNER® full crimp
- > taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight
21_N-75-4-8/133_NE	22640810	U16 (RG 59 B/U)	single	3063	2 C	34.0 g/1.19 oz

Straight bulkhead cable jacks (female)

- > for flexible cables
- > cable entry clamp
- > centre contact soldered
- > with panel seal
- > insulating washers see page 408




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole	Weight
24_N-75-4-2/133_NE	22543628	U15 (RG 59 B/U)	single	27042 / ML 12	40.0 g/1.40 oz.

RECEPTACLES WITH SOLDER END

Flange mount, plugs (male)


- > panel mounted
- > fastening screws see page 407



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Weight
13_N-75-0-1/133_NE	22542522	single	ML 16	45.0 g/1.58 oz.

Flange mount, jacks (female)

- > panel mounted
- > fastening screws see page 407



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Weight
23_N-75-0-1/133_NE	22542575	single	ML 17	30.0 g/1.05 oz.



SERIES 7/16 COAXIAL CONNECTORS

DESCRIPTION

HUBER+SUHNER 7/16 connectors are mechanically very rugged coaxial connectors with screw lock. They have a characteristic impedance of $50\ \Omega$ and are applicable with excellent electrical properties up to 7.5 GHz.

Transmission of medium to high power in transmitting stations and low loss transmission of received signals such as in mobile phone base stations are typical applications.


For these purposes low intermodulation product and water-proof types are also available.

CONTENTS

PAGE

Description	305
Interface dimensions	305
Interface dimensions in mm / inches	305
Standards	306
Technical data	306
Cable connectors	309
7/16 combination system	317
Receptacles with solder end	320
HUBER+SUHNER QUICK-FIT (Series 7/16 and N)	323

INTERFACE DIMENSIONS



INTERFACE DIMENSIONS (MM / INCHES)

	Plug		Jack	
	min.	max.	min.	max.
A	M29 × 1.5		M29 × 1.5	
B	20.60/.811	21.40/.843	—	—
C	18.03/.710	18.21/.717	—	—
D	4.96/.195	5.04/.198	—	—
E	15.85/.624	16.25/.640	15.85/.624	16.25/.640
F	7.00/.276 nom.		7.00/.276 nom.	
G	1.40/.055	1.60/.063	—	—
H	1.47/.058	1.77/.070	—	—
I	7.00/.276	8.00/.315	—	—
K	—	—	10.00/.394	—
L	—	4.50/.177	—	—
M	7.00/.276	9.00/.354	—	—
N	—	—	22.10/.870	22.90/.902
P	—	—	0.50/.020	0.70/.028
Q	—	—	1.77/.070	2.07/.082
R	—	—	5.00/.197	—
S	—	—	8.10/.319	—
T	—	—	—	18.50/.728*
U	—	—	—	18.00/.709

* prior to slotting

IP rating (interface, mated) IP68

**Interface dimensions conformable to
the Standards:**

International **IEC 61169-4**
Europe: **CECC 22 190**
Germany **DIN 47223, VG 95250**


TECHNICAL DATA

ELECTRICAL DATA	REQUIREMENTS	
Impedance	50 Ω	
Frequency range	DC ... 7.5 GHz	combination types: DC - 1 GHz
Dielectric withstanding voltage (at sea level) - combination system	4.0 kV rms, 50 Hz 2.5 kV rms, 50 Hz	
Working voltage (at sea level) - combination system	≤ 2.5 kV rms, 50 Hz ≤ 1.0 kV rms, 50 Hz	
Insulation resistance	$\geq 10^4$ M Ω	
Contact resistance - centre contact - outer contact	≤ 0.4 m Ω ≤ 1.5 m Ω	
RF-leakage (at 1 GHz)	≥ 128 dB	
VSWR	see table below	

TYPICAL VSWR *	FREQUENCY RANGE			CABLE GROUP
CONNECTOR TYPE	1 GHz	2.5 GHz	5 GHz	
straight connectors	1.04	1.05	1.12	M5, M7
	1.05	1.07	1.10	U29, U32
	1.03	1.05	1.10	S39
right angle connectors	1.04	1.05	1.12	M5, M7

* Values which can be achieved when connectors are perfectly fixed onto the cable.

Other connectors and cables on request



MECHANICAL DATA	REQUIREMENTS
Coupling nut torque - recommended - proof torque	25 Nm ... 30 Nm / 221 in. lbs ... 260 in. lbs 35 Nm / 310 in. lbs
Coupling nut retention force	≥ 1000 N / 225.0 lbs
Contact captivation	≥ 200 N / 45.0 lbs
Cable retention force ¹⁾	see pages 28 - 34
Durability (matings)	≥ 500

1) Value considers maximum load of the cables without irreversible variations of specifications.

ENVIRONMENTAL DATA	CECC 22190 TEST CONDITIONS	EQUIVALENT MIL TEST CONDITIONS
Temperature range		- 65°C ... + 165°C / - 85 °F ... + 329 °F
Climatic category	4.6.5 → 55/155/56	
Corrosion (mated connectors)	4.6.10 → IEC-68-2-11 Ka	Saltspray test acc. to MIL-STD-202, Method 101, Condition B
Vibration	4.6.3 → IEC 68-2-6 Fc	

MATERIAL DATA		
CONNECTOR PART	MATERIAL	PLATING
Bodies	brass	SUCOPLATE®
Pin contacts	brass	silver
Outer contacts, jacks Socket contact	spring bronze	silver
Crimp ferrules	copper	SUCOPLATE®
Insulators, standard version	PTFE or PFA	
Gaskets	silicone rubber	


Some connectors may have a specification that differs from the above mentioned data.

The products are designed and guaranteed to pass the above mentioned test procedures. Any additional or different requirement arising from specific applications or environmental conditions which is not covered by these test procedures is subject to request.

CABLE CONNECTORS


Straight cable plugs (male)

- > for corrugated cables
- > cable entry clamp
- > centre contact soldered
- > degree of protection IP 68




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Weight
11_716-50-5-4/003_-Z	23003412	M5 (SUCOFEED ¼" HF)	bulk 10 pcs.	27297	149 g / 5.25 oz.

- > for SUCOFORM cables
- > cable entry soldered
- > centre contact soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Weight
11_716-50-5-6/003_-Y	84008435	Y13 (Sucoform 250-01)	bulk 10 pcs.	0000215393	75 g / 2.65 oz.

- > for flexible cables
- > cable entry crimp
- > centre contact plugged




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight
11_716-50-6-3/003_-E	22652341	S24 (S 06162 D-02)	single	27330	8.65	86 g / 3.01 oz.

> for flexible cables

> cable entry HUBER+SUHNER® pressure-sleeve

> centre contact soldered




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Weight
11_716-50-7-3/003_E	22544075	U28 (RG 213/U)	single	9018	105 g/3.68 oz.
11_716-50-7-4/003_E	22544076	U33 (RG 214/U)	single	9018	100 g/3.50 oz.

> for corrugated cables

> cable entry soldered

> centre contact soldered

> degree of protection IP 66




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Weight
11_716-50-7-20/003_Z	22658154	M7 (SUCOFEED 3/8" HF)	bulk 10 pcs.	27186	115 g/4.05 oz.

> for flexible cables


> HUBER+SUHNER® full crimp

> taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight
11_716-50-7-1/003_E	22544073	U29 (RG 213/U)	single	9017	3 D	85 g/2.98 oz.
11_716-50-7-2/003_E	22544074	U32 (RG 214/U)	single	9017	3 D	85 g/2.98 oz.


- > for flexible cables
- > cable entry crimp
- > centre contact soldered



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight
11_716-50-7-14/003_E	22646908	S32 (S 07262 BD)	single	27003	D	91 g/3.19 oz. *

* types available with additional sealing ferrule (IP67)


- > for flexible cables
- > cable entry crimp
- > centre contact plugged-in
- > degree of protection IP 67



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight
11_716-50-10-3/003_Z	23002520	S39 (S 10172 B-11)	bulk 10 pcs.	27354	12.4	100 g/3.52 oz.

Right angle cable plugs (male)

- > for corrugated cables
- > cable entry clamp
- > centre contact soldered
- > degree of protection IP 68



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Weight
16_716-50-5-2/003_Z	23016774	M5 (SUCCOFEEED 1/4" HF)	bulk 10 pcs.	27369	150 g/5.25 oz.

- > for flexible cables
- > cable entry crimp
- > centre contact soldered




Fig. 1





Fig. 2 PE insulator



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight	Fig.
16_716-50-7-10/003_E	22658839	U33 (RG 393/U) U32 (RG 214/U)	single	9087	D	103 g/3.61 oz.	1
16_716-50-7-11/003_E	22649421	S32 (S 07262 BD)	single	9094	D	154 g/5.39 oz.	2*

* types available with additional sealing ferrule (IP67)


- > for corrugated cables
- > cable entry soldered
- > centre contact soldered
- > degree of protection IP 66



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Weight
16_716-50-7-20/003_Z	22658147	M7 (SUCOFED 3/8"HF)	bulk 10 pcs.	27187	114 g/4.02 oz.


Straight cable jacks (female)

- > for corrugated cables
- > cable entry clamp
- > centre contact soldered
- > degree of protection IP 68




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Weight
21_716-50-5-400/003_Z	23011950	M5 (SUCOFEED 1/4"HF)	bulk 10 pcs.	27297	140 g / 4.90 oz.

- > for flexible cables
- > HUBER+SUHNER® full crimp
- > taper sleeves see page 406



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight
21_716-50-7-1/003_E	22544092	U29 (RG 213/U)	single	9017	3 D	90 g/3.15 oz.
21_716-50-7-2/003_E	22544093	U32 (RG 214/U)	single	9017	3 D	90 g/3.15 oz.

- > for flexible cables
- > cable entry crimp
- > centre contact soldered




HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight
21_716-50-7-11/003_E	22648494	S32 (S 07262 BD)	single	27003	D	97 g/3.40 oz. *

* types available with additional sealing ferrule (IP67)

Cable groups see page 28	Assembly tools see page 385	Mounting holes see page 412
--------------------------	-----------------------------	-----------------------------


- > for flexible cables
- > cable entry crimp
- > centre contact plugged-in
- > degree of protection IP 67



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight
21_716-50-10-1/003_Z	23002535	S39 (S 10162 B-11)	bulk 10 pcs.	27354	12.4	85 g/2.99 oz.

Straight bulkhead cable jacks (female)


- > for corrugated cables
- > cable entry clamp
- > centre contact soldered
- > degree of protection IP 68



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole	Weight
24_716-50-5-400/003_Z	22658272	M5 (SUCOFEEED 1/4"HF)	bulk 10 pcs.	27297 / ML 110	171 g/6.03 oz.

Straight panel cable jacks (female)



- > for SUCOFORM cables
- > cable entry soldered
- > centre contact plugged



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Mounting hole	Weight
25_716-50-5-7/00_-E	23011905	Y13 (Sucoform 250)	single	27117	ML 27	110 g/3.85 oz.

mounting hole ML 27


- > for flexible cables
- > cable entry crimp
- > centre contact plugged



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight
25_716-50-6-2/003_-V	22652322	S24 (S 06162 D-02)	bulk 20 pcs.	27330	8.65	110 g/3.85 oz.

> for flexible cables

- > cable entry crimp
- > centre contact soldered
- > degree of protection IP 66





HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Weight
25_716-50-7-11/003_E	22649423	S32 (S 07262 BD)	single	27003	D	112 g/3.92 oz.

mounting hole ML 27

> for corrugated cables


- > cable entry soldered
- > centre contact soldered
- > degree of protection IP 66



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole	Weight
25_716-50-7-21/003_Z	23000282	M7 (SUCOFEED 3/8" HF)	bulk 10 pcs.	27188 / ML 27	106 g/3.73 oz.

Right angle bulkhead cable jacks (female)

- > for corrugated cables
- > cable entry clamp
- > centre contact soldered
- > degree of protection IP 68



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction/ Mounting hole	Weight
29_716-50-5-400/003_-Z	22658301	M5 (SUCCOFEED 1/4"HF)	bulk 10 pcs.	27315 / ML 110	171 g/6.03 oz.


7/16 COMBINATION SYSTEM

The HUBER+SUHNER 7/16 combination system enables efficient, low cost and flexible stocking of 7/16 cable connectors. The 11 basic parts can be combined to obtain 48 different cable connector types for almost all coaxial cables with 2.95 mm (.116 in.), 4.7 mm (.185 in.) or 7.25 mm (.285 in.) dielectric diameter. The cable entries are available with both crimp type or pressure-sleeve (no special tools) cable attachment.

Centre conductors are soldered. All cable entries can be used together with any of the combi-heads. Taper sleeves can be supplied for the crimp type cable entries. Straight or right angle configurations are possible with the same sub-assemblies. All types have 50 Ω impedance and are suitable for frequencies up to 1 GHz. The working voltage is limited to 1.0 kV rms.


Combi-heads

- > plug (male)




HUBER+SUHNER type	Item no.	Packaging	Weight	Notes
11_716-50-0-2/003_-E	22641432	single	100 g/3.50 oz.	cable entries see page 319/320

> jack (female)




HUBER+SUHNER type	Item no.	Packaging	Weight	Notes
21_716-50-0-2/003_E	22641433	single	103 g/3.61 oz.	cable entries see page 319/320

> bulkhead jack (female)



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Weight	Notes
24_716-50-0-1/003_E	22650517	single	ML 110	126 g/4.44 oz.	cable entries see page 319/320

> panel jack (female)



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Weight	Notes
25_716-50-0-2/003_E	22641434	single	ML 27	124 g/4.34 oz.	cable entries see page 319/320

Cable entries (for use with all combi-heads)

> cable entry crimp

> taper sleeves see page 406




Fig. 1




Fig. 2

HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Crimp insert	Fig.
71_Z-0-3-21/-33_E	22641435	U7 (RG 58 C/U)	single	9084	B	1
71_Z-0-3-22/-33_E	22641436	U9 (RG 223/U)	single	9084	B	1
71_Z-0-7-21/-33_E	22641440	U29 (RG 213/U)	single	9087	D	2
71_Z-0-7-22/-33_E	22641441	U32 (RG 214/U)	single	9087	D	2

> cable entry pressure sleeve




Fig. 1





Fig. 2

HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	fig.
71_Z-0-3-24/-33_E	22641438	U7, 10 (RG 58C/U)	single	9085	1
71_Z-0-7-23/-33_E	22641442	U28 (RG 213/U)	single	9088	2
71_Z-0-7-24/-33_E	22641443	U33 (RG 214/U)	single	9088	2

RECEPTACLES WITH SOLDER END

Receptacles, plugs (male)

- > panel mounted
- > fastening screws see page 407
- > flange with O-ring
- > centre contact captivated for torque



HUBER+SUHNER type	Item no.	Packaging	Weight	Notes
13_716-50-0-4/003_V	22658959	bulk 20 pcs.	98 g/6.00 oz.	centre conductor with threaded stud M3

Receptacles, jacks (female)

- > panel mounted
- > fastening screws see page 407




Fig. 1





Fig. 2



HUBER+SUHNER type	Item no.	Packaging	Mounting hole	Weight	Notes	Fig.
23_716-50-0-1/003_E	22544102	single	ML 27	75 g/2.65 oz.	centre conductor with threaded stud M3	1
23_716-50-0-57/003_V	23015661	bulk 20 pcs.		80 g/2.80 oz.	centre conductor with threaded stud M3	2


PROTECTIVE CAPS

- > protective cap for plug
- > made of plastic



HUBER+SUHNER type	Item no.	Packaging	Notes
61_716-0-0-3/_-H	23005876	bulk 100 pcs.	

- > protective cap for jack
- > made of plastic



HUBER+SUHNER type	Item no.	Packaging	Notes
62_716-0-0-4/_-H	23005877	bulk 100 pcs.	water protection according to IP 68

A FURTHER HUBER+SUHNER PRODUCT GROUP!

RF power splitters



Details on this product are to be found in the catalogue, Item no. 23041087 (in English only). Get your copy free of charge at **www.hubersuhner.com**.





HUBER+SUHNER® QUICK-FIT COAXIAL CONNECTORS

DESCRIPTION

HUBER+SUHNER QUICK-FIT connectors are world-wide approved N and 7/16 connectors for foam dielectric corrugated copper tube cables. They offer a greatly simplified and economic approach to cable preparation and assembly. The product line meets the requirements of multi-carrier, high-channel-count transceivers such as base stations of today's mobile communication infrastructure networks.

The cable entries support standard foam dielectric corrugated copper tube cables $1/2''$, $7/8''$, $1 1/4''$ and $1 5/8''$ and $1/2''$ highflex SUCOFEEED as well as equivalent products from Andrew, RFS (Kabelmetal) and NK-Cables.

CONTENTS

PAGE

Description	323
Features	323
Applications	323
Technical data	324
Series 7/16	325
Series N	328

FEATURES

- **low, stable and reproducible PIM (Passive Intermodulation Product)**
 - typically -165 dBc
 - excellent performance under mechanical stress and severe environmental conditions
- **safe assembly process performance**
 - in-field termination with reproducible electrical performance
- **quick and easy assembly**
 - 2 main connector parts, 4 steps in less than 4 minutes
- **high IP rating**
 - IP 68
- **cable multi-brand compatibility**

APPLICATIONS

- **antenna links and internal connections of mobile phone base stations**
- **jumper cables and feeder lines**
- **Radio in the Local Loop (RLL) and WiMAX base stations**
- **in general radio transceivers with high requirements for low attenuation, PIM and VSWR**

TECHNICAL DATA

ELECTRICAL DATA	REQUIREMENTS
Impedance	50 Ω
Frequency range (for connector interface)	N: DC ... 11 GHz 7/16: DC ... 7.5 GHz
VSWR	≤ 1.06 (RL ≥ 30 dB); $f \leq 2.5$ GHz
VSWR for types marked with (R)	≤ 1.06 (RL ≥ 30 dB); $f \leq 2.0$ GHz
PIM ¹⁾	better than -155 dBc

¹⁾ Carrier to 3rd order intermodulation product ratio with 2 x 20 W (43 dBm) carrier power, $f \leq 1.88$ GHz

MECHANICAL DATA	REQUIREMENTS
Coupling nut torque	N: 0.68 ... 1.13 Nm / 0.49 ... 0.82 ft lb. 7/16: 25 ... 30 Nm / 18.05 .. 21.66 ft lb.
Recommended coupling nut torque	N: 3 Nm / 2.2 ft lb. with 100 matings max
Coupling nut retention force	N: ≥ 450 N / 101.2 lbs. 7/16: ≥ 1000 N / 225.0 lbs.
Centre contact	captivated
Durability (matings)	≥ 500

ENVIRONMENTAL DATA	REQUIREMENTS
Temperature range	- 40°C ... + 85°C / - 40 °F ... + 185 °F
IP rating	IP 68 (acc. to IEC 60529)


MATERIAL DATA		
CONNECTOR PART	MATERIAL	PLATING
Cable entry	brass	SUCOPLATE®
Connector head	brass	silver
Outer contact	brass	
Centre contact	spring bronze	
Insulators	PTFE or PFA	
Gaskets	rubber	

Some connectors may have a specification that differs from the above mentioned data.

The products are designed and guaranteed to pass the above mentioned test procedures. Any additional or different requirement arising from specific applications or environmental conditions which is not covered by these test procedures is subject to request.

SERIES 7/16

Straight cable plugs (male)



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Weight
11_716-50-9-9/003_E	22660309	M9 (SUCCOFEED_1/2_HF)	single	0000179418	126 g/4.41 oz.




Fig. 1




Fig. 2




Fig. 3




Fig. 4



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Weight	Fig.
11_716-50-12-10/003_E	22658311	M12 (SUCCOFEED_1/2)	single	0000179113	169 g/5.92 oz.	1
11_716-50-23-10/003_E	23000309	M23 (SUCCOFEED_7/8)	single	0000180164	327 g/11.4 oz.	2
11_716-50-23-13/003_E	84017916	M25(SUCCOFEED_7/8_LA)	single	0000243692	333 g/11.7 oz.	3
11_716-50-23-14/003_E	84018237	M24(SUCCOFEED_7/8_HF)	single	0000233737	333 g/11.7 oz.	4

Straight cable plugs (male)




Fig. 1




Fig. 2

HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Weight	Fig.
11_716-50-32-2/003_Y	22658187	M32 (SUCCOFEED_1_1/4)	single	0000179128	1016 g/35.6 oz.	1 (R)
11_716-50-42-2/003_Y	22658185	M42 (SUCCOFEED_1_5/8)	single	0000179128	1298 g/45.4 oz.	2 (R)

(R) see VSWR on page 324

Right angle cable plugs (male)




Fig. 1





Fig. 2

HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Weight	Fig.
16_716-50-9-5/003_E	23007298	M9 (SUCCOFEED_1/2_HF)	single	0000179418	180 g/6.30 oz.	1
16_716-50-12-11/003_E	23011827	M12 (SUCCOFEED_1/2)	single	0000179113	223 g/7.8 oz.	2

Straight cable jacks (female)



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Weight
21_716-50-9-9/003_E	23660310	M9 (SUCCOFEED_1/2_HF)	single	0000179418	120 g/4.20 oz.




Fig. 1




Fig. 2




Fig. 3




Fig. 4



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Weight	Fig.
21_716-50-12-10/003_E	22658313	M12 (SUCCOFEED_1/2)	single	0000179113	153 g/5.36 oz.	1
21_716-50-23-10/003_E	23000310	M23 (SUCCOFEED_7/8)	single	0000180164	315 g/11.0 oz.	2
21_716-50-23-12/003_E	84018251	M24(SUCCOFEED_7/8_HF)	single	0000233737	318 g/11.2 oz.	3
21_716-50-23-13/003_E	84022255	M25(SUCCOFEED_7/8_LA)	single	0000243692	318 g/11.2 oz.	4

Straight cable jacks (female)




Fig. 1





Fig. 2

HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Weight	Fig.
21_716-50-32-2/003_Y	22658188	M32 (SUCOFEED_1_1/4)	single	0000179128	1011 g/35.4 oz.	1 (R)
21_716-50-42-2/003_Y	22658186	M42 (SUCOFEED_1_5/8)	single	0000179128	1291 g/45.2 oz.	2 (R)

(R) see VSWR on page 324

SERIES N

Straight cable plugs (male)



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Weight
11_N-50-9-9/003_E	22660311	M9 (SUCOFEED_1/2_HF)	single	0000179418	112 g/3.92 oz.

Straight cable plugs (male)




Fig. 1




Fig. 2




Fig. 3

HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Weight	Fig.
11_N-50-12-10/003_E	22658314	M12 (SUCOFEED_1/2)	single	0000179113	143 g/5.00 oz.	1
11_N-50-23-10/003_E	23000308	M23 (SUCOFEED_7/8)	single	0000180164	305 g/10.7 oz.	2
11_N-50-23-11/003_E	84018250	M24(SUCOFEED_7/8_HF)	single	0000233737	312 g/11.0 oz.	3




Fig. 1




Fig. 2

HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Weight	Fig.
11_N-50-32-2/003_Y	22658189	M32 (SUCOFEED_1_1/4)	single	0000179128	990 g/34.7 oz.	1 (R)
11_N-50-42-2/003_Y	22658191	M42 (SUCOFEED_1_5/8)	single	0000179128	1285 g/45.0 oz.	2 (R)

(R) see VSWR on page 324

QUICK
FIT

Right angle cable plugs (male)




Fig. 1





Fig. 2

HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Weight	Fig.
16_N-50-9-6/003_E	23007299	M9 (SUCOFEED_1/2_HF)	single	0000179418	164 g/5.75 oz.	1
16_N-50-12-9/003_E	23011828	M12 (SUCOFEED_1/2)	single	0000179113	208 g/7.30 oz.	2

Straight cable jacks (female)



HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Weight
21_N-50-9-9/003_E	22660312	M9 (SUCOFEED_1/2_HF)	single	0000179418	113 g/3.96 oz.

Straight cable jacks (female)




Fig. 1




Fig. 2




Fig. 3

HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Weight	Fig.
21_N-50-12-10/003_E	22658315	M12 (SUCOFEED_1/2)	single	0000179113	142 g/4.97 oz.	1
21_N-50-23-10/003_E	23000307	M23 (SUCOFEED_7/8)	single	0000180164	300 g/10.5 oz.	2
21_N-50-23-11/003_E	84018249	M24(SUCOFEED_7/8_HF)	single	0000233737	313 g/11.0 oz.	3




Fig. 1





Fig. 2

HUBER+SUHNER type	Item no.	Cable group (example)	Packaging	Assembly instruction	Weight	Fig.
21_N-50-32-2/003_Y	22658190	M32 (SUCOFEED_1_1/4)	single	0000179128	989 g/34.6 oz.	1 (R)
21_N-50-42-2/003_Y	22658192	M42 (SUCOFEED_1_5/8)	single	0000179128	1279 g/44.8 oz.	2 (R)


(R) see VSWR on page 324

A FURTHER HUBER+SUHNER PRODUCT!

SMART QUICK-FIT connectors



Details on this product are to be found in the brochure, Item no. 84028926 (in English only). Get your copy free of charge at **www.hubersuhner.com**.



ADAPTORS

ADAPTORS WITHIN SERIES

HUBER+SUHNER is manufacturing a wide range of adaptors within series. Please find hereafter a selection of them.

If the requested type is not mentioned, please do not hesitate to contact the Sales Department of our Subsidiary or Agent in your country.




ADAPTORS WITHIN SERIES

MMCX	H+S type Item no.	31_MMCX-50-0-1/111_OE 22645960
------	----------------------	-----------------------------------

jack/jack (f)

Packaging single

Material: brass/gold




VSWR: DC - 3 GHz: ≤ 1.10
3 - 6 GHz: ≤ 1.28

MMCX	H+S type Item no.	34_MMCX-50-0-1/111_OE 22650516
------	----------------------	-----------------------------------

jack/jack (f)

Packaging single

Material: brass/gold
Mounting hole ML 88




VSWR DC - 1.5 GHz ≤ 1.06
1.5 - 6 GHz ≤ 1.22

MCX 50Ω	H+S type Item no.	31_MCX-50-0-1/111_NE 22543558
---------	----------------------	----------------------------------

jack/jack (f)

Packaging single

Material: brass/gold




VSWR DC - 1 GHz ≤ 1.05
1 - 6 GHz ≤ 1.22

MCX 50Ω	H+S type Item no.	32_MCX-50-0-3/111_NE 22653002
---------	----------------------	----------------------------------

plug/plug (m)

Packaging single

Material: brass/gold




VSWR DC - 1.5 GHz ≤ 1.06
1.5 - 6 GHz ≤ 1.22

MCX 50Ω	H+S type Item no.	34_MCX-50-0-2/111_NE 22649868
---------	----------------------	----------------------------------

jack/jack (f)

Packaging single

Material: brass/gold
Mounting hole ML 89




VSWR DC - 1.5 GHz ≤ 1.06
1.5 - 6 GHz ≤ 1.22


MCX 75Ω	H+S type Item no.	34_MCX-75-0-1/111_NE 22649382
---------	----------------------	----------------------------------


jack/jack (f)


Packaging single


Material: brass/gold
Mounting hole ML 35





SMB	H+S type Item no.	31_SMB-50-0-1/111_NE 22640221
jack/jack (f)		
Packaging	single	
Material:	brass/gold	
		
VSWR	DC - 4 GHz 1.03 + 0.08 f	


SMB	H+S type Item no.	46_SMB-50-0-2/111_NE 22640228
3 jacks (f)		
Packaging	single	
Material:	brass/gold	
		
VSWR	DC - 4 GHz 1.03 + 0.08 f	


SMB	H+S type Item no.	32_SMB-50-0-1/111_NE 22640222
plug/plug (m)	open entry	
Packaging	single	
Material:	brass/gold	
		
VSWR	DC - 1.5 GHz 1.03 + 0.18 f	1.5 - 4 GHz ≤ 1.30

SMC	H+S type Item no.	31_SMC-50-0-1/111_NE 22640300
jack/jack (f)		
Packaging	single	
Material:	brass/gold	
		
VSWR	DC-10 GHz ≤ 1.08 + 0.15 f	

SMB	H+S type Item no.	34_SMB-50-0-2/111_NE 22640224
jack/jack (f)		
Packaging	single	
Material:	brass/gold	
Mounting hole	ML 11	
		
VSWR	DC - 2 GHz 1.04 + 0.1 f	2 - 4 GHz ≤ 1.24

SMC	H+S type Item no.	32_SMC-50-0-1/111_NE 22543822
plug/plug (m)		
Packaging	single	
Material:	brass/gold	
		
VSWR	DC-10 GHz ≤ 1.08 + 0.10 f	

SMB	H+S type Item no.	43_SMB-50-0-2/111_NE 22640226
1 plug (m), 2 jacks (f)	open entry	
Packaging	single	
Material:	brass/gold	
		
VSWR	DC-10 GHz ≤ 1.03 + 0.08 f	

SMC	H+S type Item no.	34_SMC-50-0-2/111_NE 22640302
jack/jack (f)		
Packaging	single	
Material:	brass/gold	
Mounting hole	ML 11	
		
VSWR	DC-10 GHz ≤ 1.03 + 0.08 f	

SMC	H+S type Item no.	43_SMC-50-0-2/111_NE 22640305
1 plug (m), 2 jacks (f) Packaging	single	
Material:	brass/gold	

SMA	H+S type Item no.	32_SMA-50-0-1/111_NE 22640151
plug/plug (m)	single	
Packaging	single	
Material:	CuBe/gold	

VSWR DC-18 GHz
 $\leq 1.05 + 0.005 f$

SMC	H+S type Item no.	46_SMC-50-0-2/111_NE 22640307
3 jacks (f)	single	
Packaging	single	
Material:	brass/gold	

SMA	H+S type Item no.	32_SMA-50-0-52/199_NE 22643689
plug/plug (m)	single	
Packaging	single	
Material:	stainless steel	

VSWR DC-18 GHz
 $\leq 1.05 + 0.005 f$

SMA	H+S type Item no.	31_SMA-50-0-1/111_NE 22640150
jack/jack (f)	single	
Packaging	single	
Material:	CuBe/gold	

VSWR DC-18 GHz
 $\leq 1.05 + 0.005 f$

SMA	H+S type Item no.	33_SMA-50-0-1/111_NE 22641119
plug/jack(m/f)	single	
Packaging	single	
Material:	CuBe/gold	

VSWR DC-18 GHz
 $\leq 1.05 + 0.005 f$

SMA	H+S type Item no.	31_SMA-50-0-51/199_NE 22641486
jack/jack (f)	single	
Packaging	single	
Material:	stainless steel	

VSWR DC-18 GHz
 $\leq 1.05 + 0.005 f$

SMA	H+S type Item no.	33_SMA-50-0-51/199_NE 22644253
plug/jack (m/f)	single	
Packaging	single	
Material:	stainless steel	

VSWR DC-18 GHz
 $\leq 1.05 + 0.005 f$

SMA	H+S type Item no.	34_SMA-50-0-1/111_NH 22649842
jack/jack (f)		
Packaging	bulk 100 pcs.	
Material:	CuBe/gold	
Mounting hole	ML 35	
VSWR	DC-18 GHz	$\leq 1.05 + 0.005 f$

SMA	H+S type Item no.	46_SMA-50-0-1/111_NE 22543357
3 jacks (f)		
Packaging	single	
Material:	CuBe/gold	

SMA	H+S type Item no.	34_SMA-50-0-51/199_NE 22544823
jack/jack (f)		
Packaging	single	
Material:	stainless steel	
Mounting hole	ML 35	
VSWR	DC-18 GHz	$\leq 1.05 + 0.005 f$


SMA	H+S type Item no.	53_SMA-50-0-51/199_NE 22642655
plug/jack (m/f)		
Packaging	single	
Material:	stainless steel	
VSWR	DC - 14 GHz	14 - 18 GHz
	$\leq 1.02 + 0.03 f$	≤ 1.92


SMA	H+S type Item no.	34_SMA-50-0-3/111_NE 22641297
jack/jack (f)	hermet. sealed	
Packaging	single	
Material:	CuBe/gold	
Mounting hole	ML 38	
Leak rate	10 ⁻⁶ Torr 1/sec.	
RoHS compliant alternative on request	(atm cc/s)	
VSWR	DC - 3 GHz	3 - 7 GHz
	≤ 1.1	≤ 1.2
		7 - 18 GHz
		≤ 1.3


PC3.5	H+S type Item no.	31_PC35-50-0-1/199_UE 22644360
jack/jack (f)		
Packaging	single	
Material:	stainless steel	
Electrical length	14.1 +/- 0.1 mm	
VSWR	DC - 18 GHz	18 - 26.5 GHz
	≤ 1.08	≤ 1.15


SMA	H+S type Item no.	43_SMA-50-0-1/111_NE 22543356
1 plug (m), 2 jacks (f)		
Packaging	single	
Material:	CuBe/gold	


PC3.5	H+S type Item no.	32_PC35-50-0-1/199_UE 22644361
plug/plug (m)		
Packaging	single	
Material:	stainless steel	
Electrical length	14.1 +/- 0.1 mm	
VSWR	DC - 18 GHz	18 - 26.5 GHz
	≤ 1.08	≤ 1.15


PC3.5	H+S type Item no.	33_PC35-50-0-1/199_UE 22644362
plug/jack (m/f)		
Packaging	single	
Material:	stainless steel	
Electrical length	14.1 +/- 0.1 mm	
VSWR	DC - 18 GHz ≤ 1.08	18 - 26.5 GHz ≤ 1.15


PC3.5	H+S type Item no.	33_PC35-50-0-2/199_NE 23020453
plug/jack(m/f)		
Packaging	single	
Material:	stainless steel	
Electrical length	25.4 +/- 2.6 mm	
Note	Adaptor for QMA calibration	
VSWR	DC - 1.5 GHz ≤ 1.036	1.5 - 6 ≤ 1.065 6 - 18 GHz ≤ 1.22


PC3.5	H+S type Item no.	39_PC35-50-0-1/199_UE 23003664
plug/jack (m/f)		
Packaging	single	
Material:	stainless steel	
VSWR	DC - 4 GHz ≤ 1.03	4 - 10 10 - 16 16 - 26.5 GHz ≤ 1.07 ≤ 1.12 ≤ 1.22

SK	H+S type Item no.	31_SK-50-0-1/199_NE 23004726
jack/jack (f)		
Packaging	single	
Material:	stainless steel	
Electrical length	16.1 +/- 0.1 mm	
VSWR	DC - 40 GHz ≤ 1.20	

PC3.5	H+S type Item no.	31_PC35-50-0-2/199_NE 23020456
jack/jack (f)		
Packaging	single	
Material:	stainless steel	
Electrical length	25.4 +/- 2.6 mm	
Note	Adaptor for QMA calibration	
VSWR	DC - 1.5 GHz ≤ 1.036	1.5 - 6 6 - 18 GHz ≤ 1.065 ≤ 1.22

SK	H+S type Item no.	32_SK-50-0-1/199_NE 23004727
plug/plug (m)		
Packaging	single	
Material:	stainless steel	
Electrical length	16.1 +/- 0.1 mm	
VSWR	DC - 40 GHz ≤ 1.20	

PC3.5	H+S type Item no.	32_PC35-50-0-2/199_NE 23020457
plug/plug (m)		
Packaging	single	
Material:	stainless steel	
Electrical length	25.4 +/- 2.6 mm	
Note	Adaptor for QMA calibration	
VSWR	DC - 1.5 GHz ≤ 1.036	1.5 - 6 6 - 18 GHz ≤ 1.065 ≤ 1.22


SK	H+S type Item no.	33_SK-50-0-1/199_NE 23004728
plug/jack (m/f)		
Packaging	single	
Material:	stainless steel	
Electrical length	16.1 +/- 0.1 mm	
VSWR	DC - 40 GHz ≤ 1.20	

SK	H+S type	34_SK-50-0-51/199_NE
	Item no.	22658969

jack/jack (f)

Packaging single

Material: stainless steel
Mounting hole ML 35




VSWR DC - 40 GHz
≤ 1.02 + 0.01

QLA	H+S type	45_QLA-01-0-1/112_NE
	Item no.	22640033

2 jacks (f)
1 plug (m)
Packaging

single

Material: brass/nickel




QLA	H+S type	31_QLA-01-0-1/112_NE
	Item no.	22640028

jack/jack (f)

Packaging single

Material: brass/nickel




QLA	H+S type	53_QLA-01-0-1/112_NE
	Item no.	22640034

plug/jack (m/f)

Packaging single

Material: brass/nickel




QLA	H+S type	34_QLA-01-0-2/112_NE
	Item no.	22640031

jack/jack (f)

Packaging single

Material: brass/nickel
Mounting hole ML 99




Note ML 99

QMA	H+S type	31_QMA-50-0-1/199_NE
	Item no.	23023171

jack/jack (f)

Packaging single

Material: stainless steel




VSWR DC - 1.5 GHz
≤ 1.036 1.5 - 6 GHz
≤ 1.065

QLA	H+S type	43_QLA-01-0-1/112_NE
	Item no.	22640032

2 jacks (f)
1 plug (m)
Packaging

single

Material: brass/nickel




QMA	H+S type	32_QMA-50-0-1/1-NE
	Item no.	23023199

plug/plug (m)

Packaging single

Material: stainless steel




VSWR DC - 1.5 GHz
≤ 1.036 1.5 - 6 GHz
≤ 1.065

QMA H+S type 33_QMA-50-0-1/1_NE
Item no. 23023287

plug/jack (m/f)

Packaging single

Material: stainless steel




VSWR DC - 1.5 GHz ≤ 1.036 1.5 - 6 GHz ≤ 1.065

BNC 50 Ω H+S type 31_BNC-50-0-1/133_NE
Item no. 22540540

jack/jack (f)

Packaging single

Material: brass/SUCO*




VSWR DC - 4 GHz ≤ 1.06 + 0.04 f

BNC 50 Ω H+S type 32_BNC-50-0-1/133_NE
Item no. 22540565

plug/plug (m)

Packaging single

Material: brass/SUCO*




VSWR DC - 4 GHz ≤ 1.06 + 0.04 f

BNC 50 Ω H+S type 34_BNC-50-0-1/133_NE
Item no. 22540627

jack/jack (f)

Packaging single

Material: brass/SUCO*
Mounting hole ML 4




VSWR DC - 1.5 GHz ≤ 1.04 1.5 - 4 GHz ≤ 1.08 + 0.10 f

BNC 50 Ω H+S type 34_BNC-50-0-1/133_UE
Item no. 22652148

jack/jack (f)

Packaging single

Material: brass/SUCO*
Mounting hole ML 4




VSWR DC - 1.5 GHz ≤ 1.04 1.5 - 4 GHz ≤ 1.08 + 0.10 f

BNC 50 Ω H+S type 34_BNC-50-0-2/133_NE
Item no. 22540629

jack/jack (f)

for insulated mounting
single

Material: brass/SUCO*
Mounting hole ML 22



VSWR DC - 1.5 GHz ≤ 1.04 1.5 - 4 GHz ≤ 1.08 + 0.10 f


BNC 50 Ω H+S type 34_BNC-50-0-6/100_NE
Item no. 22540631

jack/jack (f)

hermet.sealed

Packaging single

Material: CuBe/silver
Mounting hole ML 4
Leak rate 10⁻⁶ Torr 1/sec.
RoHS compliant alternative on request




VSWR DC - 4 GHz ≤ 1.90

BNC 50 Ω H+S type 37_BNC-50-0-1/133_NE
Item no. 22540635

jack/jack (f)

Packaging single

Material: brass/SUCO*
Mounting hole ML 10




VSWR DC - 4 GHz ≤ 1.06 + 0.04 f

jack/jack (f)

Packaging single

Material: brass/SUCO*
Mounting hole ML 10




VSWR DC - 4 GHz ≤ 1.06 + 0.04 f

BNC 50 Ω H+S type
Item no. 37_BNC-50-0-2/133_NE
22540638

jack/jack (f)

Packaging single

Material: brass/SUCO*
Mounting hole ML 10




VSWR DC - 4 GHz
≤ 1.06 + 0.04 f

BNC 50 Ω H+S type
Item no. 53_BNC-50-0-1/133_NE
22540657

plug/jack (m/f)

Packaging single

Material: brass/SUCO*




VSWR DC - 4 GHz
≤ 1.06 + 0.04 f

BNC 50 Ω H+S type
Item no. 43_BNC-50-0-1/133_NE
22540644

2 jacks (female)
1 plug (male)
Packaging single

Material: brass/SUCO*




BNC 75 Ω H+S type
Item no. 31_BNC-75-0-1/133_NE
22541003

jack/jack (f)

Packaging single


Material: brass/SUCO*



BNC 50 Ω H+S type
Item no. 45_BNC-50-0-2/133_NE
22652370

2 jacks (female)
1 plug (male)
Packaging single

Material: brass/SUCO*




BNC 75 Ω H+S type
Item no. 32_BNC-75-0-1/133_NE
22541016

plug/plug (m)

Packaging single

Material: brass/SUCO*




BNC 50 Ω H+S type
Item no. 46_BNC-50-0-1/133_NE
22540649

3 jacks (female)

Packaging single

Material: brass/SUCO*




BNC 75 Ω H+S type
Item no. 34_BNC-75-0-1/133_NE
22541040

jack/jack (f)

Packaging single


Material: brass/SUCO*
Mounting hole ML 4



BNC 75 Ω H+S type
Item no. 34_BNC-75-0-2/133_NE
22541042

jack/jack (f)
Packaging
Material:
Mounting hole

for insulated
mounting
single
brass/SUCO*
ML 22




BNC 75 Ω H+S type
Item no. 45_BNC-75-0-1/133_NE
22541050

2 jacks (female)
1 plug (male)
Packaging
Material:

single


brass/SUCO*



BNC 75 Ω H+S type
Item no. 37_BNC-75-0-1/133_NE
22541045

jack/jack (f)
Packaging
Material:
Mounting hole

single
brass/SUCO*
ML 10




BNC 75 Ω H+S type
Item no. 46_BNC-75-0-1/133_NE
22541053

3 jacks (female)
Packaging
Material:

single


brass/SUCO*



BNC 75 Ω H+S type
Item no. 37_BNC-75-0-2/133_NE
22541047

jack/jack (f)
Packaging
Material:
Mounting hole

single
brass/SUCO*
ML 10




BNC 75 Ω H+S type
Item no. 53_BNC-75-0-1/133_NE
22541055

plug/jack (m/f)
Packaging
Material:

single


brass/SUCO*



BNC 75 Ω H+S type
Item no. 43_BNC-75-0-1/133_NE
22541049

2 jacks (female)
1 plug (male)
Packaging
Material:

single
brass/SUCO*




TNC 50 Ω H+S type
Item no. 31_TNC-50-0-1/133_NE
22640623

jack/jack (f)
Packaging
Material:

single

brass/SUCO*




VSWR
DC - 11 GHz
≤ 1.06 + 0.15 f

TNC 50 Ω H+S type
Item no. **32_TNC-50-0-1/133_NE**
22543407

plug/plug (m)

Packaging single

Material: brass/SUCO*




VSWR DC - 11 GHz
≤ 1.03 + 0.025 f

TNC 50 Ω H+S type
Item no. **37_TNC-50-0-1/133_NE**
22640646

jack/jack (f)

Packaging single

Material: brass/SUCO*
Mounting hole ML 8




VSWR DC - 9 GHz 9 - 11 GHz
≤ 1.09 + 0.16 f ≤ 2.53

TNC 50 Ω H+S type
Item no. **33_TNC-50-0-1/133_NE**
22543649

plug/jack(m/f)

Packaging single

Material: brass/SUCO*




VSWR DC - 11 GHz
≤ 1.10 + 0.027 f

TNC 50 Ω H+S type
Item no. **37_TNC-50-0-2/133_NE**
22640648

jack/jack (f)

Packaging single

Material: brass/SUCO*
Mounting hole ML 8




VSWR DC - 9 GHz 9 - 11 GHz
≤ 1.09 + 0.16 f ≤ 2.53

TNC 50 Ω H+S type
Item no. **34_TNC-50-0-1/133_NE**
22640643

jack/jack (f)

Packaging single

Material: brass/SUCO*
Mounting hole ML 4




VSWR DC - 2 GHz 2 - 8 GHz 8 - 11 GHz
≤ 1.05 ≤ 1.50 ≤ 1.90

TNC 50 Ω H+S type
Item no. **43_TNC-50-0-1/133_NE**
22640651

2 jacks (female)
1 plug (male)

Packaging single

Material: brass/SUCO*




TNC 50 Ω H+S type
Item no. **34_TNC-50-0-4/133_NE**
22658794

jack/jack (f)

Packaging single

Material: brass/SUCO*
Mounting hole ML 4




VSWR DC - 8 GHz
≤ 1.07 + 0.01 f

TNC 50 Ω H+S type
Item no. **46_TNC-50-0-1/133_NE**
22640655

3 jacks (female)

Packaging single

Material: brass/SUCO*




TNC 50 Ω	H+S type	53_TNC-50-0-1/133_NE
	Item no.	22640659

plug/jack (m/f)

Packaging single

Material: brass/SUCO*



VSWR DC - 5 GHz
≤ 1.03 + 0.11 f


5 - 11 GHz
≤ 1.58

N 50 Ω	H+S type	32_N-50-0-1/133_NE
	Item no.	22542398

plug/plug (m)

Packaging single

Material: brass/SUCO*



VSWR DC - 9 GHz
≤ 1.06 + 0.04 f


9 - 12 GHz
≤ 1.40

TNC 50 Ω	H+S type	53_TNC-50-0-1/133_UH
	Item no.	22646963

plug/jack (m/f)

Packaging bulk 100 pcs.

Material: brass/SUCO*



VSWR DC - 5 GHz
≤ 1.03 + 0.11 f

5 - 11 GHz
≤ 1.58


N 50 Ω	H+S type	32_N-50-0-51/193_NE
	Item no.	22652113

plug/plug (m)

Packaging single

Material: stainless steel

Note Precision adapter




VSWR DC - 18 GHz
≤ 1.03 + 0.01 f

N 50 Ω	H+S type	31_N-50-0-2/133_NE
	Item no.	22542382

jack/jack (f)

Packaging single

Material: brass/SUCO*




VSWR DC - 12.4 GHz
≤ 1.17 + 0.15 f

N 50 Ω	H+S type	33_N-50-0-7/133_NE
	Item no.	23014355

plug/jack(m/f)

Packaging single

Material: brass/SUCO*



VSWR DC - 18 GHz
≤ 1.03 + 0.05 f


N 50 Ω	H+S type	31_N-50-0-51/199_NE
	Item no.	22652112

jack/jack (f)

Packaging single

Material: stainless steel

Note Precision adapter



VSWR DC - 18 GHz
≤ 1.03 + 0.01 f


N 50 Ω	H+S type	33_N-50-0-51/193_NE
	Item no.	22652114

plug/jack(m/f)

Packaging single


Material: stainless steel

Note Precision adapter




VSWR DC - 18 GHz
≤ 1.03 + 0.01 f


N 50 Ω	H+S type Item no.	33_N-50-0-52/199_UE 22648921
plug/jack(m/f)	quick connect (male side)	
Packaging	single	
Material:	stainless steel	
Note	Precision adapter	
VSUR	DC - 18 GHz ≤ 1.03 + 0.01 f	




N 50 Ω	H+S type Item no.	34_N-50-0-51/193_NE 22544593
jack/jack (f)		
Packaging	single	
Material:	stainless steel	
Mounting hole	ML 12	
Note	Precision adapter	
VSUR	DC - 18 GHz ≤ 1.03 + 0.01 f	




N 50 Ω	H+S type Item no.	34_N-50-0-1/133_NE 22542435
jack/jack (f)		
Packaging	single	
Material:	brass/SUCO*	
Mounting hole	ML 12	
VSUR	DC - 2 GHz ≤ 1.06	2 - 12.4 GHz ≤ 1.06 + 0.17 f




N 50 Ω	H+S type Item no.	37_N-50-0-1/133_NE 22542437
jack/jack (f)		
Packaging	single	
Material:	brass/SUCO*	
Mounting hole	ML 14	
VSUR	DC - 12.4 GHz ≤ 1.19 + 0.06 f	




N 50 Ω	H+S type Item no.	34_N-50-0-1/133_UE 22651817
jack/jack (f)		
Packaging	single	
Material:	brass/SUCO*	
Mounting hole	ML 12	
VSUR	DC - 2 GHz ≤ 1.06	2 - 12.4 GHz ≤ 1.06 + 0.17 f




N 50 Ω	H+S type Item no.	43_N-50-0-1/133_NE 22542442
2 jacks (female) 1 plug (male)		
Packaging	single	
Material:	brass/SUCO*	
VSUR		



N 50 Ω	H+S type Item no.	34_N-50-0-3/133_NE 22642946
jack/jack (f)	hermet.sealed	
Packaging	single	
Material:	brass/SUCO*	
Mounting hole	ML 12	
Leak rate	10 ⁻⁶ Torr l/sec.	
RoHS compliant alternative on request	(atm cc/s)	
VSUR	DC - 12.4 GHz ≤ 1.08 + 0.13 f	



N 50 Ω	H+S type Item no.	46_N-50-0-1/133_NE 22542445
3 jacks (female)		
Packaging	single	
Material:	brass/SUCO*	
VSUR		




N 50 Ω H+S type
Item no. **46_N-50-0-1/133_UE**
22658682

3 jacks (female)

Packaging single

Material: brass/SUCO*




N 75 Ω H+S type
Item no. **32_N-75-0-1/133_NE**
22542618

plug/plug (m)

Packaging single

Material: brass/SUCO*




N 50 Ω H+S type
Item no. **53_N-50-0-4/133_NE**
22651447

plug/jack (m/f)

Packaging single

Material: brass/SUCO*




N 75 Ω H+S type
Item no. **34_N-75-0-1/133_NE**
22542631

jack/jack (f)

Packaging single

Material: brass/SUCO*
Mounting hole ML 12




N 50 Ω H+S type
Item no. **53_N-50-0-4/133_UE**
22658908

plug/jack (m/f)

Packaging single

Material: brass/SUCO*




N 75 Ω H+S type
Item no. **37_N-75-0-1/133_NE**
22542633

jack/jack (f)

Packaging single

Material: brass/SUCO*
Mounting hole ML 14




N 75 Ω H+S type
Item no. **31_N-75-0-2/133_NE**
22542612

jack/jack (f)

Packaging single

Material: brass/SUCO*




N 75 Ω H+S type
Item no. **53_N-75-0-4/133_NE**
22651799

plug/jack (m/f)

Packaging single

Material: brass/SUCO*




7/16 H+S type
Item no. 31_716-50-0-1/003_E
22544117

jack/jack (f)

Packaging single

Material: brass/SUCO*




VSWR DC - 3 GHz ≤ 1.03 3 - 7.5 GHz $\leq 1.03 + 0.01 f$

7/16 H+S type
Item no. 34_716-50-0-2/003_E
22652004

jack/jack (f)

Packaging single

Material: brass/SUCO*
Mounting hole ML 29




VSWR 2 GHz > 1.10 4 GHz > 1.15 6 GHz > 1.25 7.5 GHz > 1.30

7/16 H+S type
Item no. 32_716-50-0-1/003_E
22544118

plug/plug (m)

Packaging single

Material: brass/silver




VSWR DC - 2 GHz ≤ 1.02 2 - 4 GHz ≤ 1.03 4 - 6 GHz ≤ 1.04

7/16 H+S type
Item no. 37_716-50-0-1/003_E
22544122

jack/jack (f)

Packaging single

Material: brass/SUCO*
Mounting hole ML 28




VSWR DC - 3 GHz > 1.03 3 - 7.5 GHz $> 1.03 + 0.001f$

7/16 H+S type
Item no. 33_716-50-0-1/003_E
22651577

plug/jack (m/f)

Packaging single

Material: brass/silver




VSWR DC - 2 GHz ≤ 1.02 2 - 4 GHz ≤ 1.03 4 - 6 GHz ≤ 1.04

7/16 H+S type
Item no. 43_716-50-0-1/003_NE
22544572

2 jacks (female)
1 plug (male)

Packaging single

Material: brass/SUCO*




7/16 H+S type
Item no. 34_716-50-0-1/003_E
22544120

jack/jack (f)

Packaging single

Material: brass/SUCO*
Mounting hole ML 29




VSWR DC - 4 GHz $\leq 1.02 + 0.05 f$ 4 - 7.5 GHz ≤ 1.22

7/16 H+S type
Item no. 46_716-50-0-1/003_NE
22643266

3 jacks (female)

Packaging single

Material: brass/SUCO*




7/16	H+S type	53_716-50-0-1/003_NE
	Item no.	22641259

plug/jack (m/f)

Packaging single

Material: brass/SUCO*



VSWR DC - 7.5 GHz
 $\leq 1.02 + 0.025 f$

ADAPTORS

ADAPTORS BETWEEN SERIES

HUBER+SUHNER is manufacturing a wide range of adaptors between series. Please find hereafter a selection of them.

If the requested type is not mentioned, please do not hesitate to contact the Sales Department of our Subsidiary or Agent in your country.



ADAPTORS "BETWEEN SERIES"

		BMA		BNC		MCX		MMBX		MMCX		N		PC3.5	
		plug	jack	plug	jack	plug	jack	plug	jack	plug	jack	plug	jack	plug	jack
BMA	plug														
	jack														
BNC	plug					16	17/18			10/14	11/12	24/25	26/27		
	jack					19/20	15/21			13	9	28/29	22/23 30		
MCX	plug			16	19/20							65	66		
	jack			17/18	15/21							67/68	63/64/69		
MMBX	plug														
	jack														
MMCX	plug			10/14	13										
	jack			11/12	9										
N	plug			24/25	28/29	65	67/68								
	jack			26/27	22/23 30	66	63/64 69								
PC3.5	plug														
	jack														
QLA	plug				32										
	jack			31	33							75			
QMA	plug														
	jack														
QN	plug											77	106		107
	jack												76		
SMA	plug	2/6	4	35	37	71	73	55	57	60	62	79	81/84		
	jack	3/7	1/5/8	36	34/38	72	70	56	54	61	59	80	78/82/83		
SMB	plug			40	42							86	88		
	jack			41	39/43							87	85/89/90		
SMC	plug			45	47							92	94		
	jack			46	44							93	91/95		
TNC	plug			49	51/52							97	99/100		
	jack			50	48/53		74		58			98	96		
7/16	plug											102	104		
	jack											103	101/105		

FINDING THE RIGHT ADAPTOR


In the tables on this spread you find the most frequently used HUBER+SUHNER adaptors.

Note:

The VSWR values stated for the "Between Series" Adaptors on the next pages are typical values!

Example:

Adaptor BNC plug - N jack



		QLA		QMA		QN		SMA		SMB		SMC		TNC		7/16	
		plug	jack	plug	jack	plug	jack	plug	jack	plug	jack	plug	jack	plug	jack	plug	jack
BMA	plug							2/6	3/7								
	jack							4	1/5/8								
BNC	plug		31					35	36	40	41	45	46	49	50		
	jack	32	33					37	34/38	42	39/43	47	44	51/52	48/53		
MCX	plug							71	72								
	jack							73	70						74		
MMBX	plug							55	56								
	jack							57	54						58		
MMCX	plug							60	61								
	jack							62	59								
N	plug		75			77		79	80	86	87	92	93	97	98	102	103
	jack					106	76	81/84	78/82 83	88	85/89 90	94	91/95	99 100	96	104	101 105
PC3.5	plug																
	jack					107											
QLA	plug																
	jack																
QMA	plug								108/109								
	jack							110									
QN	plug																
	jack																
SMA	plug										112			115	116		
	jack									113	111			117	114		
SMB	plug								113						118		
	jack							112	111								
SMC	plug																
	jack																
TNC	plug								117/119								
	jack							116		118							
7/16	plug																
	jack																

Number 26 indicates where to look for the required type. On the following pages you will find the sketches and descriptions of all types in numeric order. If you go to number 26 you find the following information:

26

**H+S type
Item No.**

**33_BNC-N-50-1/133_NE
22540608**

**BNC
N**


**plug (m)
jack (f)**

Packaging

single

Material:
BNC
N


brass/SUCO*
brass/SUCO*





Adapt.


Material and plating descriptions may refer to the connector housing or outer contact.


SUCO* = SUCOPLATE®
SUPR** = SUCOPRO


1	H+S type Item no.	31_BMA-SMA-50-1/1-9_UE 22645642
BMA SMA	jack (f) jack (f)	
Packaging	single	
Material	stainless steel	
BMA	stainless steel	
SMA	stainless steel	
VSWR:	DC - 9 GHz: $\leq 1.04 + 0.02f$	


5	H+S type Item no.	34_BMA-SMA-50-2/1-UE 22645650
BMA SMA	jack (f) jack (f)	
Packaging	single	
Material	stainless steel	
BMA	stainless steel	
SMA	stainless steel	
Mounting hole	ML 56	
VSWR:	DC - 18 GHz: $\leq 1.05 + 0.005f$	


2	H+S type Item no.	32_BMA-SMA-50-1/199_UE 22645643
BMA SMA	plug (m) plug (m)	
Packaging	single	
Material	stainless steel	
BMA	stainless steel	
SMA	stainless steel	
VSWR:	DC - 9 GHz: $\leq 1.067 + 0.017f$ 9 - 18 GHz: ≤ 1.22	

6	H+S type Item no.	35_BMA-SMA-50-1/193_UE 22645647
BMA SMA	plug (m) plug (m)	
Packaging	single	
Material	stainless steel	
BMA	stainless steel	
SMA	stainless steel	
Mounting hole	ML 56	
VSWR:	DC - 18 GHz: $\leq 1.05 + 0.005f$	

3	H+S type Item no.	33_BMA-SMA-50-1/199_UE 22645644
BMA SMA	plug (m) jack (f)	
Packaging	single	
Material	stainless steel	
BMA	stainless steel	
SMA	stainless steel	
VSWR:	DC - 18 GHz: $\leq 1.06 + 0.009f$	

7	H+S type Item no.	36_BMA-SMA-50-1/199_UE 22645651
BMA SMA	plug (m) jack (f)	
Packaging	single	
Material	stainless steel	
BMA	stainless steel	
SMA	stainless steel	
Mounting hole	ML 56	
VSWR:	DC - 18 GHz: $\leq 1.03 + 0.015f$	

4	H+S type Item no.	33_SMA-BMA-50-1/1-9_UE 22645645
SMA BMA	plug (m) jack (f)	
Packaging	single	
Material	stainless steel	
SMA	stainless steel	
BMA	stainless steel	
VSWR:	DC - 18 GHz: $\leq 1.06 + 0.009f$	

8	H+S type Item no.	37_BMA-SMA-50-1/1-UE 22645649
BMA SMA	jack (f) jack (f)	
Packaging	single	
Material	stainless steel	
BMA	stainless steel	
SMA	stainless steel	
Mounting Hole	ML 58	
VSWR:	DC - 9 GHz: $\leq 1.07 + 0.017f$ 9 - 18 GHz: ≤ 1.22	

9	H+S type Item no.	31_BNC-MMCX-50-1/1-UE 22645963
BNC MMCX	jack (f) jack (f)	
Packaging	single	
Material BNC MMCX	brass/SUCO* brass/gold	
VSWR:	DC - 4 GHz: $\leq 1.05 + 0.04f$	

13	H+S type Item no.	33_MMCX-BNC-50-1/111_UE 22645966
MMCX BNC	plug (m) jack (f)	
Packaging	single	
Material MMCX BNC	brass/gold brass/SUCO*	
VSWR:	DC - 4 GHz: $\leq 1.05 + 0.04f$	

10	H+S type Item no.	32_BNC-MMCX-50-1/1-UE 22645959
BNC MMCX	plug (m) plug (m)	
Packaging	single	
Material BNC MMCX	brass/SUCO* brass/gold	
VSWR:	DC - 4 GHz: $\leq 1.03 + 0.05f$	

14	H+S type Item no.	35_BNC-MMCX-50-2/1-NE 23005885
BNC MMCX	plug (m) plug (m)	
Packaging	single	
Material BNC MMCX Mounting hole	brass/SUCO* brass/gold ML 2	
VSWR:	DC - 1 GHz: ≤ 1.03 ; 1 - 3 GHz: $\leq 0.935 + 0.095 f$; 3 - 4 GHz: ≤ 1.22	


11	H+S type Item no.	33_BNC-MMCX-50-1/1-NE 22652907
BNC MMCX	plug (m) jack (f)	
Packaging	single	
Material BNC MMCX	brass/SUCO* brass/gold	
VSWR:	DC - 4 GHz: $\leq 1.03 + 0.05f$	

15	H+S type Item no.	31_BNC-MCX-50-1/1-UE 22543639
BNC MCX	jack (f) jack (f)	
Packaging	single	
Material BNC MCX	brass/SUCO* brass/gold	
VSWR:	DC - 2 GHz: $\leq 1.03 + 0.13f$ 2 - 4 GHz: ≤ 1.29	


12	H+S type Item no.	33_BNC-MMCX-50-1/1-UE 22645964
BNC MMCX	plug (m) jack (f)	
Packaging	single	
Material BNC MMCX	brass/SUCO* brass/SUCO*	
VSWR:	DC - 4 GHz: $\leq 1.05 + 0.025 f$	

16	H+S type Item no.	32_BNC-MCX-50-1/1-UE 22543567
BNC MCX	plug (m) plug (m)	
Packaging	single	
Material BNC MCX	brass/SUCO* CuBe/gold	
VSWR:	DC - 2 GHz: $\leq 1.04 + 0.09f$ 2 - 4 GHz: ≤ 1.22	


17	H+S type Item no.	33_BNC-MCX-50-1/1-UE 22543829
BNC MCX	plug (m) jack (f)	
Packaging	single	
Material: BNC MCX	brass/SUCO* brass/gold	
VSWR:	DC - 4 GHz: ≤ 1.20	




21	H+S type Item no.	34_BNC-MCX-50-2/133_UE 22644912
BNC MCX	jack (f) jack (f)	
Packaging	single	
Material: BNC MCX Mounting hole	brass/SUCO* brass/SUCO* ML 2	
VSWR:	DC - 4 GHz: $\leq 1.03 + 0.04f$	




18	H+S type Item no.	33_BNC-MCX-75-1/1-NE 22649213
BNC MCX	plug (m) jack (f)	
Packaging	single	
Material: BNC MCX	brass/SUCO* brass/gold	




22	H+S type Item no.	31_BNC-N-50-1/133_UE 22540549
BNC N	jack (f) jack (f)	
Packaging	single	
Material: BNC N	brass/SUCO* brass/SUCO*	
VSWR:	DC - 4 GHz: ≤ 1.22	




19	H+S type Item no.	33_MCX-BNC-50-1/1-UE 22543585
MCX BNC	plug (m) jack (f)	
Packaging	single	
Material: MCX BNC	CuBe/gold brass/SUCO*	
VSWR:	DC - 1 GHz: ≤ 1.04 ; 1 - 4 GHz: ≤ 1.22	




23	H+S type Item no.	31_BNC-N-75-1/133_UE 22543640
BNC N	jack (f) jack (f)	
Packaging	single	
Material: BNC N	brass/SUCO* brass/SUCO*	




20	H+S type Item no.	33_MCX-BNC-75-1/1-NE 22649211
MCX BNC	plug (m) jack (f)	
Packaging	single	
Material: MCX BNC	CuBe/gold brass/SUCO*	




24	H+S type Item no.	32_BNC-N-50-1/133_UE 22540571
BNC N	plug (m) plug (m)	
Packaging	single	
Material: BNC N	brass/SUCO* brass/SUCO*	
VSWR:	DC - 4 GHz: $\leq 1.06 + 0.4f$	




25	H+S type Item no.	32_BNC-N-75-1/133_UE 22541022
BNC N	plug (m) plug (m)	
Packaging	single	
Material: BNC N	brass/SUCO* brass/SUCO*	




29	H+S type Item no.	33_N-BNC-75-1/133_UE 22542622
N BNC	plug (m) jack (f)	
Packaging	single	
Material: N BNC	brass/SUCO* brass/SUCO*	




26	H+S type Item no.	33_BNC-N-50-1/133_NE 22540608
BNC N	plug (m) jack (f)	
Packaging	single	
Material: BNC N	brass/SUCO* brass/SUCO*	
VSWR:	DC - 4 GHz: ≤ 1.04 + 0.025f	




30	H+S type Item no.	34_BNC-N-50-1/133_UE 22651055
BNC N	jack (f) jack (f)	
Packaging	single	
Material: BNC N Mounting hole	brass/SUCO* brass/SUCO* ML 12	
VSWR:	DC - 4 GHz: ≤ 1.22	




27	H+S type Item no.	33_BNC-N-75-1/133_UE 22541034
BNC N	plug (m) jack (f)	
Packaging	single	
Material: BNC N	brass/SUCO* brass/SUCO*	




31	H+S type Item no.	33_BNC-QLA-01-1/1-NE 22540624
BNC QLA 00	plug (m) jack (f)	
Packaging	single	
Material: BNC QLA 00	brass/nickel brass/nickel	




28	H+S type Item no.	33_N-BNC-50-1/133_UE 22542414
N BNC	plug (m) jack (f)	
Packaging	single	
Material: N BNC	brass/SUCO* brass/SUCO*	
VSWR:	DC - 4 GHz: ≤ 1.22	




32	H+S type Item no.	33_QLA-BNC-01-1/1-NE 22640029
QLA 00 BNC	plug (m) jack (f)	
Packaging	single	
Material: QLA 00 BNC	brass/nickel brass/SUCO*	



33	H+S type Item no.	34_BNC-QLA-01-1/1-UE 22640971
BNC QLA 00	jack (f) jack (f)	
Packaging	single	
Material: BNC QLA 00 Mounting hole	brass/SUCO* brass/SUCO* ML 2	




37	H+S type Item no.	33_SMA-BNC-50-1/1-NE 22640153
SMA BNC	plug (m) jack (f)	
Packaging	single	
Material: SMA BNC	CuBe/gold brass/SUCO*	




VSWR: DC - 4 GHz: $\leq 1.05 + 0.037f$

34	H+S type Item no.	31_BNC-SMA-50-1/1-UE 22540551
BNC SMA	jack (f) jack (f)	
Packaging	single	
Material: BNC SMA	brass/SUCO* CuBe/gold	




VSWR: DC - 4 GHz: $\leq 1.06 - 0.04f$

38	H+S type Item no.	34_BNC-SMA-50-2/1-UE 22640153
BNC SMA	jack (f) jack (f)	
Packaging	single	
Material: BNC SMA Mounting hole	brass/SUCO* CuBe/gold ML 4	




VSWR: DC - 4 GHz: $\leq 1.06 + 0.03f$

35	H+S type Item no.	32_BNC-SMA-50-1/1-UE 22540572
BNC SMA	plug (m) plug (m)	
Packaging	single	
Material: BNC SMA	brass/SUCO* CuBe/gold	




VSWR: DC - 4 GHz: $\leq 1.03 + 0.03f$

39	H+S type Item no.	31_BNC-SMB-50-2/1-UE 22540553
BNC SMB	jack (f) jack (f)	
Packaging	single	
Material: BNC SMB	brass/SUCO* brass/gold	




VSWR: DC - 2 GHz: $\leq 1.03 + 0.095f$
2 - 4 GHz: ≤ 1.22

36	H+S type Item no.	33_BNC-SMA-50-1/1-UE 22540610
BNC SMA	plug (m) jack (f)	
Packaging	single	
Material: BNC SMA	brass/SUCO* CuBe/gold	





VSWR: DC - 4 GHz: $\leq 1.03 + 0.03f$


40	H+S type Item no.	32_BNC-SMB-50-2/1-UE 22540574
BNC SMB	plug (m) plug (m)	
Packaging	single	
Material: BNC SMB	brass/SUCO* brass/gold	





VSWR: DC - 4 GHz: ≤ 1.12


41	H+S type Item no.	33_BNC-SMB-50-2/1-_UE 22540612
BNC SMB	plug (m) jack (f)	
Packaging	single	
Material: BNC SMB	brass/SUCO* brass/gold	
VSWR:	DC - 4 GHz: $\leq 1.06 + 0.04f$	


45	H+S type Item no.	32_BNC-SMC-50-2/1-_NE 22540576
BNC SMC	plug (m) plug (m)	
Packaging	single	
Material: BNC SMC	brass/SUCO* brass/gold	
VSWR:	DC - 4 GHz: ≤ 1.15	


42	H+S type Item no.	33_SMB-BNC-50-2/1-_UE 22640396
SMB BNC	plug (m) jack (f)	
Packaging	single	
Material: SMB BNC	brass/gold brass/SUCO*	
VSWR:	DC - 4 GHz: $\leq 1.05 + 0.075f$	


46	H+S type Item no.	33_BNC-SMC-50-2/1-_NE 22540616
BNC SMC	plug (m) jack (f)	
Packaging	single	
Material: BNC SMC	brass/SUCO* brass/gold	
VSWR:	DC - 4 GHz: ≤ 1.22	


43	H+S type Item no.	34_BNC-SMB-50-1/133_NH 23001709
BNC SMB	jack (f) jack (f)	
Packaging	bulk 100 pcs.	
Material: BNC SMB Mounting hole	brass/SUCO* brass/SUCO* ML 4	
VSWR:	DC - 2 GHz: ≤ 1.065 2 - 4 GHz: $\leq 0.8 + 0.13f$	


47	H+S type Item no.	33_SMC-BNC-50-2/1-_NE 22640405
SMC BNC	plug (m) jack (f)	
Packaging	single	
Material: SMC BNC	brass/gold brass/SUCO*	
VSWR:	DC - 2 GHz: $\leq 1.03 + 0.095f$ 2 - 4 GHz: ≥ 1.22	


44	H+S type Item no.	31_BNC-SMC-50-2/1-_NE 22540555
BNC SMC	jack (f) jack (f)	
Packaging	single	
Material: BNC SMC	brass/SUCO* brass/gold	
VSWR:	DC - 4 GHz: ≤ 1.22	


48	H+S type Item no.	31_BNC-TNC-50-1/133_UE 22540559
BNC TNC	jack (f) jack (f)	
Packaging	single	
Material: BNC TNC	brass/SUCO* brass/SUCO*	
VSWR:	DC - 4 GHz: ≤ 1.22	


49	H+S type Item no.	32_BNC-TNC-50-1/133_NE 22540582
BNC TNC	plug (m) plug (m)	
Packaging	single	
Material: BNC TNC	brass/SUCO* brass/SUCO*	
VSWR:	DC - 4 GHz: ≤ 1.22	


53	H+S type Item no.	37_BNC-TNC-50-1/133_UE 22540639
BNC TNC	jack (f) jack (f)	
Packaging	single	
Material: BNC TNC	brass/SUCO* brass/SUCO*	
VSWR:	DC - 4 GHz: ≤ 1.22	


50	H+S type Item no.	33_BNC-TNC-50-1/133_NE 22540614
BNC TNC	plug (m) jack (f)	
Packaging	single	
Material: BNC TNC	brass/SUCO* brass/SUCO*	
VSWR:	DC - 4 GHz: ≤ 1.22	

54	H+S type Item no.	31_MMBX-SMA-50-1/111_NE 23004933
MMBX SMA	jack (f) jack (f)	
Packaging	single	
Material: MMBX SMA	brass/SUPR** CuBe/SUPR**	
VSWR:	DC - 2.5 GHz: ≤ 1.05; 2.5 - 6 GHz: ≤ 1.06 6 - 12.4 GHz: ≤ 1.35	

51	H+S type Item no.	33_TNC-BNC-50-1/133_NE 22640631
TNC BNC	plug (m) jack (f)	
Packaging	single	
Material: TNC BNC	brass/SUCO* brass/SUCO*	
VSWR:	DC - 4 GHz: ≤ 1.22	

55	H+S type Item no.	32_MMBX-SMA-50-1/119_NE 23004934
MMBX SMA	plug (m) plug (m)	
Packaging	single	
Material: MMBX SMA	CuBe/SUPR** CuBe/SUPR**	
VSWR:	DC - 2.5 GHz: ≤ 1.05; 2.5 - 6 GHz: ≤ 1.06 6 - 12.4 GHz: ≤ 1.35	

52	H+S type Item no.	33_TNC-BNC-75-1/133_UE 22640759
TNC BNC	plug (m) jack (f)	
Packaging	single	
Material: TNC BNC	brass/SUCO* brass/SUCO*	


56	H+S type Item no.	33_MMBX-SMA-50-1/111_NE 23004937
MMBX SMA	plug (m) jack (f)	
Packaging	single	
Material: MMBX SMA	CuBe/SUPR** CuBe/SUPR**	
VSWR:	DC - 2.5 GHz: ≤ 1.05; 2.5 - 6 GHz: ≤ 1.06 6 - 12.4 GHz: ≤ 1.35	

57 H+S type 33_SMA-MMBX-50-1/119_NE
Item no. 23004935

SMA plug (m)
MMBX jack (f)

Packaging single

Material:
SMA CuBe/SUPR**
MMBX brass/SUPR**




VSWR: DC - 2.5 GHz: ≤ 1.05 ; 2.5 - 6 GHz: ≤ 1.06
6 - 12.4 GHz: ≤ 1.35

61 H+S type 33_MMCX-SMA-50-1/111_UE
Item no. 22645970

MMCX plug (m)
SMA jack (f)

Packaging single

Material:
MMCX brass/gold
SMA CuBe/gold




VSWR: DC - 2.5 GHz: ≤ 1.10
2.5 - 6 GHz: ≤ 1.18

58 H+S type 34_MMBX-TNC-50-1/1-3_NE
Item no. 23014297

MMBX jack (f)
TNC jack (f)

Packaging single

Material:
MMBX brass/SUCO*
TNC brass/SUCO*




VSWR: DC - 5 GHz: ≤ 1.3

62 H+S type 33_SMA-MMCX-50-1/111_NE
Item no. 22645969

SMA plug (m)
MMCX jack (f)

Packaging single

Material:
SMA CuBe/gold
MMCX brass/gold




VSWR: DC - 2.5 GHz: ≤ 1.10
2.5 - 6 GHz: ≤ 1.18

59 H+S type 31_MMCX-SMA-50-1/111_OE
Item no. 22645961

MMCX jack (f)
SMA jack (f)

Packaging single

Material:
MMCX brass/gold
SMA CuBe/gold




VSWR: DC - 2.5 GHz: ≤ 1.10
2.5 - 6 GHz: ≤ 1.18

63 H+S type 31_MCX-N-50-1/1-UE
Item no. 22640172

MCX jack (f)
N jack (f)

Packaging single

Material:
MCX brass/gold
N brass/SUCO*




VSWR: DC - 6 GHz: $\leq 1.03 + 0.05f$

60 H+S type 32_MMCX-SMA-50-1/111_OE
Item no. 22645967

MMCX plug (m)
SMA plug (m)

Packaging single

Material:
MMCX brass/gold
SMA CuBe/gold




VSWR: DC - 2.5 GHz: ≤ 1.10
2.5 - 6 GHz: ≤ 1.18

64 H+S type 31_MCX-N-75-10/133_NE
Item no. 22651488


MCX jack (f)
N jack (f)


Packaging single


Material:
MCX CuBe/SUCO*
N brass/SUCO*





VSWR: DC - 3 GHz: ≤ 1.07


65	H+S type Item no.	32_MCX-N-50-1/1-UE 22543584
MCX N	plug (m) plug (m)	
Packaging	single	
Material: MCX N	CuBe/gold brass/SUCO*	
VSWR:	DC - 6 GHz: $\leq 1.03 + 0.05f$	


69	H+S type Item no.	34_MCX-N-50-1/133_UE 22646217
MCX N	jack (f) jack (f)	
Packaging	single	
Material: MCX N	brass/SUCO* brass/SUCO*	
Mounting hole:	ML 4	
VSWR:	DC - 6 GHz: $\leq 1.03 + 0.03f$	


66	H+S type Item no.	33_MCX-N-50-1/1-UE 22543586
MCX N	plug (m) jack (f)	
Packaging	single	
Material: MCX N	CuBe/gold brass/SUCO*	
VSWR:	DC - 6 GHz: $\leq 1.03 + 0.035f$	


70	H+S type Item no.	31_MCX-SMA-50-1/111_NE 22645485
MCX SMA	jack (f) jack (f)	
Packaging	single	
Material: MCX SMA	brass/gold CuBe/gold	
VSWR:	DC - 6 GHz: $\leq 1.03 - 0.03f$	


67	H+S type Item no.	33_N-MCX-50-1/1-UE 22543796
N MCX	plug (m) jack (f)	
Packaging	single	
Material: N MCX	brass/SUCO* brass/gold	
VSWR:	DC - 6 GHz: $\leq 1.03 + 0.03f$	


71	H+S type Item no.	32_MCX-SMA-50-1/111_NE 22645486
MCX SMA	plug (m) plug (m)	
Packaging	single	
Material: MCX SMA	brass/gold CuBe/gold	
VSWR:	DC - 6 GHz: $\leq 1.03 + 0.03f$	


68	H+S type Item no.	33_N-MCX-75-1/1-NE 22649214
N MCX	plug (m) jack (f)	
Packaging	single	
Material: N MCX	brass/SUCO* brass/gold	


72	H+S type Item no.	33_MCX-SMA-50-1/111_UE 22645487
MCX SMA	plug (m) jack (f)	
Packaging	single	
Material: MCX SMA	CuBe/gold CuBe/gold	
VSWR:	DC - 6 GHz: $\leq 1.03 + 0.03f$	


73	H+S type Item no.	33_SMA-MCX-50-1/111_NE 22645488
SMA MCX	plug (m) jack (f)	
Packaging	single	
Material: SMA MCX	CuBe/gold brass/gold	
VSWR:	DC - 6 GHz: $\leq 1.03 + 0.03f$	


77	H+S type Item no.	32_N-QN-50-1/133_NE 23033962
N QN	plug (m) plug (m)	
Packaging	single	
Material: N QN	brass/SUCO* brass/SUCO*	
VSWR:	DC - 4 GHz: ≤ 1.035 ; 4 - 8 GHz: ≤ 1.06 8 - 10 GHz: ≤ 1.22	


74	H+S type Item no.	34_MCX-TNC-50-1/133_UE 22641905
MCX TNC	jack (f) jack (f)	
Packaging	single	
Material: MCX TNC Mounting hole	brass/SUCO* brass/SUCO* ML 2	
VSWR:	DC - 6 GHz: $\leq 1.07 + 0.07f$	

78	H+S type Item no.	31_N-SMA-50-1/1-UE 22542386
N SMA	jack (f) jack (f)	
Packaging	single	
Material: N SMA	brass/SUCO* CuBe/gold	
VSWR:	DC - 12.4 GHz: $\leq 1.05 + 0.015f$	

75	H+S type Item no.	33_N-QLA-01-1/1-NE 22542431
N QLA 00	plug (m) jack (f)	
Packaging	single	
Material: N QLA 00	brass/SUCO* brass/nickel	

79	H+S type Item no.	32_N-SMA-50-1/11-NE 22542399
N SMA	plug (m) plug (m)	
Packaging	single	
Material: N SMA	brass/SUCO* CuBe/gold	
VSWR:	DC - 12.4 GHz: $\leq 1.05 + 0.017f$	

76	H+S type Item no.	31_N-QN-50-1/133_NE 84016830
N QN	jack (f) jack (f)	
Packaging	single	
Material: N QN	brass/SUCO* brass/SUCO*	
VSWR:	DC - 2 GHz: 1.05 2 - 6 GHz: 1.3 6 - 11 GHz: 1.5	

80	H+S type Item no.	33_N-SMA-50-1/113_UE 22542421
N SMA	plug (m) jack (f)	
Packaging	single	
Material: N SMA	brass/SUCO* CuBe/gold	
VSWR:	DC - 12.4 GHz: $\leq 1.05 + 0.015f$	


85	H+S type Item no.	31_N-SMB-50-1/1-UE 22542387
N SMB	jack (f) jack (f)	
Packaging	single	
Material:		
N SMB	brass/SUCO* brass/gold	
VSWR:	DC - 3 GHz: $\leq 1.03 + 0.08f$ 3 - 4 GHz: ≤ 1.27	

86	H+S type Item no.	32_N-SMB-50-1/1-UE 22542400
N SMB	plug (m) plug (m)	
Packaging	single	
Material:		
N	brass/SUCO*	
SMB	brass/gold	
VSWR:0	DC - 4 GHz: $\leq 1.03 + 0.04f$	


87	H+S type	33_N-SMB-50-1/1-UE
	Item no.	22542422
N	plug (m)	
SMB	jack (f)	
Packaging	single	
Material:		
N	brass/SUCO*	
SMB	brass/gold	
VSWR:	DC - 3 GHz: $\leq 1.03 + 0.08f$	
	3 - 4 GHz: ≤ 1.27	

88	H+S type	33_SMB-N-50-1/1-UE
	Item no.	22640394
SMB	plug (m)	
N	jack (f)	
Packaging	single	
Material:		
SMB	brass/gold	
N	brass/SUCO*	
VSWR:	DC - 4 GHz: $\leq 1.06 + 0.04f$	


97	H+S type Item no.	32_N-TNC-50-1/-_UE 22542406
N TNC	plug (m) plug (m)	
Packaging	single	
Material: N TNC	brass/SUCO* brass/SUCO*	
VSUR:	DC - 11 GHz: $\leq 1.06 + 0.11f$	




101	H+S type Item no.	31_N-716-50-1/-_UE 22640869
N 7/16	jack (f) jack (f)	
Packaging	single	
Material: N 7/16	brass/SUCO* brass/SUCO*	
VSUR:	DC - 7.5 GHz: $\leq 1.03 + 0.02f$	




98	H+S type Item no.	33_N-TNC-50-1/133_NE 22542427
N TNC	plug (m) jack (f)	
Packaging	single	
Material: N TNC	brass/SUCO* brass/SUCO*	
VSUR:	DC - 11 GHz: $\leq 1.13 + 0.02f$	




102	H+S type Item no.	32_N-716-50-1/-_NE 22544576
N 7/16	plug (m) plug (m)	
Packaging	single	
Material: N 7/16	brass/SUCO* brass/silver	
VSUR:	DC - 7.5 GHz: $\leq 1.03 + 0.02f$	




99	H+S type Item no.	33_TNC-N-50-1/133_UE 22640637
TNC N	plug (m) jack (f)	
Packaging	single	
Material: TNC N	brass/SUCO* brass/SUCO*	
VSUR:	DC - 3 GHz: ≤ 1.05 ; 3 - 5.5 GHz: ≤ 1.18 5.5 - 11 GHz: ≤ 2.00	




103	H+S type Item no.	33_N-716-50-1/-_UE 22641229
N 7/16	plug (m) jack (f)	
Packaging	single	
Material: N 7/16	brass/SUCO* brass/silver	
VSUR:	DC - 7.5 GHz: $\leq 1.03 + 0.02f$	





100	H+S type Item no.	33_TNC-N-75-1/133_UE 22658811
TNC N	plug (m) jack (f)	
Packaging	single	
Material: TNC N	brass/SUCO* brass/SUCO*	
VSUR:	DC - 7.5 GHz: $\leq 1.03 + 0.02f$	





104	H+S type Item no.	33_716-N-50-1/-_UE 22544119
7/16 N	plug (m) jack (f)	
Packaging	single	
Material: 7/16 N	brass/silver brass/SUCO*	
VSUR:	DC - 7.5 GHz: $\leq 1.03 + 0.02f$	





105	H+S type Item no.	37_N-716-50-1/003_E 23001317
N 7/16	jack (f) jack (f)	
Packaging	single	
Material:	brass/silver brass/silver ML 27	
VSWR:	DC - 7.5 GHz: $\leq 1.03 + 0.02f$	


109	H+S type Item no.	39_QMA-SMA-U50-1/11_NE 23022741
QMA SMA	plug (m) jack (f)	
Packaging	single	
Material:	stainless steel CuBe/SUPR**	ML 58
VSWR:	DC - 2 GHz: ≤ 1.04 ; 2 - 4 GHz: ≤ 1.05 4 - 6 GHz: ≤ 1.08	


106	H+S type Item no.	33_QN-N-50-1/133_NE 23036033
QN N	plug (m) jack (f)	
Packaging	single	
Material:	brass/SUCO* brass/SUCO*	
VSWR:	DC - 1 GHz: 1.02 1 - 2.5 GHz: 1.04 2.5 - 11 GHz: 1.15	


110	H+S type Item no.	33_SMA-QMA-50-1/133_NE 84012204
SMA QMA	plug (m) jack (f)	
Packaging	single	
Material:	brass/SUCO* brass/SUCO*	
VSWR:	DC - 4 GHz: 1.05 4 - 6 GHz: 1.17	


107	H+S type Item no.	39_QN-PC35-U50-1/19_NE 23033936
QN PC35	plug (m) jack (f)	
Packaging	single	
Material:	stainless steel stainless steel	
VSWR:	DC - 2.5 GHz: ≤ 1.035 ; 2.5 - 6 GHz: ≤ 1.12 6 - 11 GHz: ≤ 1.22	


111	H+S type Item no.	31_SMA-SMB-50-1/111_UE 22641728
SMA SMB	jack (f) jack (f)	
Packaging	single	
Material:	CuBe/gold brass/gold	
VSWR:	DC - 4 GHz: $\leq 1.05 + 0.04f$	


108	H+S type Item no.	33_QMA-SMA-50-1/133_NE 84014876
QMA SMA	plug (m) jack (f)	
Packaging	single	
Material:	brass/SUCO* brass/SUCO*	
VSWR:	DC - 4 GHz: 1.05 4 - 6 GHz: 1.17	


112	H+S type Item no.	33_SMA-SMB-50-1/111_NE 22658917
SMA SMB	plug (m) jack (f)	
Packaging	single	
Material:	brass/gold brass/gold	
VSWR:	DC - 4 GHz: $\leq 1.05 + 0.04 f$ 4 - 7 GHz: ≤ 1.21	


113	H+S type Item no.	33_SMB-SMA-50-1/111_UE 22641727
SMB SMA	plug (m) jack (f)	
Packaging	single	
Material: SMB SMA	brass/gold CuBe/gold	
VSWR:	DC - 4 GHz:	$\leq 1.05 + 0.04f$

117	H+S type Item no.	33_TNC-SMA-50-1/1_UE 22640940
TNC SMA	plug (m) jack (f)	
Packaging	single	
Material: TNC SMA	brass/SUCO* CuBe/gold	
VSWR:	DC - 2 GHz:	≤ 1.05 ; 2 - 4 GHz: ≤ 1.10
	4 - 8 GHz:	≤ 1.20 ; 8 - 10 GHz: ≤ 1.30

114	H+S type Item no.	31_SMA-TNC-50-1/1_UE 22640941
SMA TNC	jack (f) jack (f)	
Packaging	single	
Material: SMA TNC	CuBe/gold brass/SUCO*	
VSWR:	DC - 1 GHz:	≤ 1.05 ; 1 - 2 GHz: ≤ 1.10
	2 - 6 GHz:	≤ 1.20 ; 6 - 10 GHz: ≤ 1.30

118	H+S type Item no.	33_SMB-TNC-50-2/1_UE 22640400
SMB TNC	plug (m) jack (f)	
Packaging	single	
Material: SMB TNC	brass/gold brass/SUCO*	
VSWR:	DC - 4 GHz:	$\leq 1.1 + 0.065f$

115	H+S type Item no.	32_SMA-TNC-50-1/1_UE 22640938
SMA TNC	plug (m) plug (m)	
Packaging	single	
Material: SMA TNC	CuBe/gold brass/SUCO*	
VSWR:	DC - 2 GHz:	≤ 1.05 ; 2 - 4 GHz: ≤ 1.10
	4 - 8 GHz:	≤ 1.20 ; 8 - 11 GHz: ≤ 1.30

116	H+S type Item no.	33_SMA-TNC-50-1/1_NE 22640939
SMA TNC	plug (m) jack (f)	
Packaging	single	
Material: SMA TNC	CuBe/gold brass/SUCO*	
VSWR:	DC - 6 GHz:	$\leq 1.03 + 0.05f$
	6 - 11 GHz:	≤ 1.33

ADAPTORS

SPECIAL ADAPTORS

As an addition to the adaptors mentioned on the previous pages, we also provide various types of adaptors for Test&Measurement applications, which you will find on the following pages.



PRECISION ADAPTORS



QUICK-MATE ADAPTORS



PIM ADAPTORS


PRESICION ADAPTORS


		BNC		MMCX		MCX		SMPX		SK		QN		N	
		plug	jack	plug	jack	plug	jack	plug	jack	plug	jack	plug	jack	plug	jack
BNC	plug													201	202
	jack													203	200
MMCX	plug														
	jack														
MCX	plug														
	jack														
SMPX	plug										277				
	jack									274/275 276	271/272 273				
SK	plug								274/275 276						
	jack							277	271/272 273						
QN	plug														
	jack														
N	plug	201	203												
	jack	202	200												
PC24	plug									268	269				265
	jack									270	267			266	
PC35	plug					207	209							224	226/227
	jack					208	206							225	223
PC7		204	205									257	258	228/229	230/231 232
QMA	plug														234
	jack													235	233
SMA	plug			211	213									238	241 242
	jack			212	210									239/240	236/237 243
TNC	plug													245	247
	jack													246	244
41/95	plug													215	216
	jack													217	214
7/16	plug													220	222
	jack													221	219


Note:


The VSWR values stated for the precision Adaptors on the next pages are typical values!


		PC24		PC35		PC7	QMA		SMA		TNC		41/95		7/16	
		plug	jack	plug	jack		plug	jack	plug	jack	plug	jack	plug	jack	plug	jack
BNC	plug					204										
	jack					205										
MMCX	plug								211	212						
	jack								213	210						
MCX	plug			207	208											
	jack			209	206											
SMPX	plug															
	jack															
SK	plug	268	270													
	jack	267	269													
QN	plug					257										
	jack					258										
N	plug		266	224	225	228/229		235	238	239 240	245	246	215	217	220	221
	jack	265		226 227	223	230/231 232	234	233	241 242	236/237 243	247	244	216	214	222	219
PC24	plug															
	jack															
PC35	plug					248/255	250	251								
	jack					256	252	249								
PC7				248 255	256				259	260	261 262	263 264			253	254
QMA	plug			250	252											
	jack			251	249											
SMA	plug					259										
	jack					260										
TNC	plug					261/262										
	jack					263/264										
41/95	plug															218
	jack															
7/16	plug					253										
	jack					254							218			


200	H+S type Item no.	31_BNC-N-50-51/1-UE 22544049
BNC N	jack (f) jack (f)	
Packaging	single	
Material: BNC N	stainless steel stainless steel	
VSWR:	DC - 4 GHz: $\leq 1.05 + 0.01f$	


204	H+S type Item no.	32_BNC-PC7-50-1/1-UE 22544047
BNC PC7	plug (m)	
Packaging	single	
Material: BNC PC7	stainless steel brass/gold	
VSWR:	DC - 4 GHz: $\leq 1.02 + 0.006f$	


201	H+S type Item no.	32_BNC-N-50-51/1-UE 22544051
BNC N	plug (m) plug (m)	
Packaging	single	
Material: BNC N	stainless steel stainless steel	
VSWR:	DC - 4 GHz: $\leq 1.05 + 0.01f$	

205	H+S type Item no.	33_PC7-BNC-50-1/1-UE 22543918
PC7 BNC	jack (f)	
Packaging	single	
Material: PC7 BNC	brass/gold stainless steel	
VSWR:	DC - 4 GHz: $\leq 1.02 + 0.006f$	

202	H+S type Item no.	33_BNC-N-50-51/-UE 22544052
BNC N	plug (m) jack (f)	
Packaging	single	
Material: BNC N	stainless steel stainless steel	
VSWR:	DC - 4 GHz: $\leq 1.05 + 0.01f$	

206	H+S type Item no.	31_MCX-PC35-50-1/111_NE 22651593
MCX PC35	jack (f) jack (f)	
Packaging	single	
Material: MCX PC35	CuBe/SUPR** CuBe/SUPR**	
VSWR:	DC - 3 GHz: ≤ 1.065 ; 3 - 6 GHz: ≤ 1.09	

203	H+S type Item no.	33_N-BNC-50-51/1-UE 22544050
N BNC	plug (m) jack (f)	
Packaging	single	
Material: N BNC	stainless steel stainless steel	
VSWR:	DC - 4 GHz: $\leq 1.05 + 0.01f$	

207	H+S type Item no.	32_MCX-PC35-50-1/111_NE 22651600
MCX PC35	plug (m) plug (m)	
Packaging	single	
Material: MCX PC35	CuBe/SUPR** CuBe/SUPR**	
VSWR:	DC - 3.5 GHz: ≤ 1.07 ; 3.5 - 6 GHz: ≤ 1.09	

208 H+S type 33_MCX-PC35-50-1/111_NE
Item no. 22651594

MCX
PC35


plug (m)
jack (f)

Packaging

single

Material:
MCX
PC35

CuBe/SUPR**
CuBe/SUPR**



VSWR: DC - 3.5 GHz: ≤ 1.065
3.5 - 6 GHz: ≤ 1.094

212 H+S type 33_MMCX-SMA-50-2/111_NE
Item no. 22658203

MMCX
SMA


plug (m)
jack (f)

Packaging

single

Material:
MMCX
SMA

CuBe/SUPR**
CuBe



VSWR: DC - 3.5 GHz: ≤ 1.065;
3.5 - 6 GHz: ≤ 1.094

209 H+S type 33_PC35-MCX-50-1/111_NE
Item no. 22651599

PC35
MCX


plug (m)
jack (f)

Packaging

single

Material:
PC35
MCX

CuBe/SUPR**
CuBe/SUPR**



VSWR: DC - 3.5 GHz: ≤ 1.065
3.5 - 6 GHz: ≤ 1.094

213 H+S type 33_SMA-MMCX-50-2/111_NE
Item no. 22658204

SMA
MMCX


plug (m)
jack (f)

Packaging

single

Material:
SMA
MMCX

CuBe/SUPR**
CuBe/SUPR**



VSWR: DC - 3.5 GHz: ≤ 1.065
3.5 - 6 GHz: ≤ 1.094

210 H+S type 31_MMCX-SMA-50-2/111_NE
Item no. 22658201

MMCX
SMA


jack (f)
jack (f)

Packaging

single

Material:
MMCX
SMA

CuBe/SUPR**
CuBe/SUPR**



VSWR: DC - 3.5 GHz: ≤ 1.07
3.5 - 6 GHz: ≤ 1.09

214 H+S type 31_N-4195-50-12/139_UE
Item no. 22646160

N
41/95


jack (f)
jack (f)

Packaging

single

Material:
N
41/95

stainless steel
brass/SUCO*



VSWR: DC - 6 GHz: ≤ 1.05; 6 - 14 GHz: ≤ 1.12

211 H+S type 32_MMCX-SMA-50-2/111_NE
Item no. 22658202

MMCX
SMA


plug (m)
plug (m)

Packaging

single

Material:
MMCX
SMA

CuBe/SUPR**
CuBe/SUPR**



VSWR: DC - 3.5 GHz: ≤ 1.07; 3.5 - 6 GHz: ≤ 1.09

215 H+S type 32_4195-N-50-1/1-UE
Item no. 22650781

41/95
N


plug (m)
plug (m)

Packaging


single


Material:
41/95
N


brass/SUCO*
stainless steel





VSWR: DC - 14 GHz: ≤ 1.06


216	H+S type Item no.	33_4195-N-50-1/_UE 22646154
41/95 N	plug (m) jack (f)	
Packaging	single	
Material: 41/95 N	brass/SUCO* stainless steel	
VSWR:	DC - 6 GHz: ≤ 1.05; 6 - 14 GHz: ≤ 1.12	


220	H+S type Item no.	32_N-716-50-51/-33_NE 22544127
N 7/16	plug (m) plug (m)	
Packaging	single	
Material: N 7/16	brass/silver brass/silver	
VSWR:	DC - 7.5 GHz: ≤ 1.03 + 0.004f	


217	H+S type Item no.	33_N-4195-50-51/1-3_UE 22648618
N 41/95	plug (m) jack (f)	
Packaging	single	
Material: N 41/95	stainless steel brass/SUCO*	
VSWR:	DC - 6 GHz: ≤ 1.05; 6 - 14 GHz: ≤ 1.12	


221	H+S type Item no.	33_N-716-50-51/-33_NE 22544123
N 7/16	plug (m) jack (f)	
Packaging	single	
Material: N 7/16	brass/SUCO* brass/SUCO*	
VSWR:	DC - 7.5 GHz: ≤ 1.03 + 0.004f	


218	H+S type Item no.	33_4195-716-50-1/-33_NE 22650069
41/95 7/16	plug (m) jack (f)	
Packaging	single	
Material: 41/95 7/16	brass/SUCO* brass/SUCO*	
VSWR:	DC - 7.5 GHz: ≤ 1.06	


222	H+S type Item no.	33_716-N-50-51/-33_NE 22544125
7/16 N	plug (m) jack (f)	
Packaging	single	
Material: 7/16 N	brass/SUCO* brass/SUCO*	
VSWR:	DC - 7.5 GHz: ≤ 1.03 + 0.004f	


219	H+S type Item no.	31_N-716-50-51/-33_NE 22544129
N 7/16	jack (f) jack (f)	
Packaging	single	
Material: N 7/16	brass/SUCO* brass/SUCO*	
VSWR:	DC - 7.5 GHz: ≤ 1.03 + 0.004f	


223	H+S type Item no.	31_N-PC35-50-1/1_UE 22643960
N PC35	jack (f) jack (f)	
Packaging	single	
Material: N PC35	stainless steel stainless steel	
VSWR:	DC - 12.4 GHz: ≤ 1.10 12.4 - 18 GHz: ≤ 1.15	


224	H+S type Item no.	32_N-PC35-50-1/1-UE 22643957
N PC35	plug (m) plug (m)	
Packaging	single	
Material: N PC35	stainless steel stainless steel	
VSWR:	DC - 12.4 GHz: ≤ 1.10 12.4 - 18 GHz: ≤ 1.15	


228	H+S type Item no.	32_N-PC7-50-1/1-UE 22543571
N PC7	plug (m)	
Packaging	single	
Material: N PC7	stainless steel brass/gold	
VSWR:	DC - 18 GHz: ≤ 1.02 + 0.002f	


225	H+S type Item no.	33_N-PC35-50-1/1-UE 22643959
N PC35	plug (m) jack (f)	
Packaging	single	
Material: N PC35	stainless steel stainless steel	
VSWR:	DC - 12.4 GHz: ≤ 1.10 12.4 - 18 GHz: ≤ 1.15	

229	H+S type Item no.	32_N-PC7-50-6/1-NE 23032917
N PC7	plug (m)	
Packaging	single	
Material: N PC7 El. length:	stainless steel brass/gold typ. 41.85mm	
VSWR:	DC - 3 GHz: ≤ 1.03; 3 - 6 GHz: ≤ 1.05 6 - 11 GHz: ≤ typ. 1.12	

226	H+S type Item no.	33_PC35-N-50-1/1-UE 22643958
PC35 N	plug (m) jack (f)	
Packaging	single	
Material: PC35 N	stainless steel stainless steel	
VSWR:	DC - 12.4 GHz: ≤ 1.10 12.4 - 18 GHz: ≤ 1.15	

230	H+S type Item no.	33_PC7-N-50-1/1-UE 22543547
PC7 N	jack (f)	
Packaging	single	
Material: PC7 N	brass/gold stainless steel	
VSWR:	DC - 18 GHz: ≤ 1.02 + 0.002f	


227	H+S type Item no.	39_PC35-N-50-1/1-UE 22660363
PC35 N	plug (m) jack (f)	
Packaging	single	
Material: PC35 N	stainless steel stainless steel	
VSWR:	DC - 12.4 GHz: ≤ 1.10 12.4 - 18 GHz: ≤ 1.15	

231	H+S type Item no.	33_PC7-N-50-5/33_NE 23004036
PC7 N	jack (f)	
Packaging	single	
Material: PC7 N	brass/gold stainless steel	
VSWR:	DC - 18 GHz: ≤ 1.03 + 0.002f	


235	H+S type Item no.	33_N-QMA-50-1/133_NE 23024265
N QMA	plug (m) jack (f)	
Packaging	single	
Material:		
N	brass/SUCO *	
QMA	brass/SUCO *	
VSWR:	DC - 6 GHz: ≤ 1.04	

239	H+S type Item no.	33_N-SMA-50-51/1_-UE 22543925
N SMA	plug (m) jack (f)	
Packaging	single	
Material:		
N	stainless steel	
SMA	CuBe/gold	
VSWR:	DC - 18 GHz: $\leq 1.025 + 0.007f$	


240	H+S type Item no.	33_N-SMA-50-51/1- _{UE} 22660180
N SMA	plug (m) jack (f)	
Packaging	single	
Material: N SMA	stainless steel CuBe/gold	
VSUR:	DC - 18 GHz: $\leq 1.025 + 0.007f$	




244	H+S type Item no.	31_N-TNC-50-51/1- _{UE} 22543954
N TNC	jack (f) jack (f)	
Packaging	single	
Material: N TNC	stainless steel stainless steel	
VSUR:	DC - 12.4 GHz: $\leq 1.05 + 0.01f$	




241	H+S type Item no.	33_SMA-N-50-51/1- _{UE} 22543926
SMA N	plug (m) jack (f)	
Packaging	single	
Material: SMA N	CuBe/gold stainless steel	
VSUR:	DC - 18 GHz: $\leq 1.025 + 0.007f$	




245	H+S type Item no.	32_N-TNC-50-51/1- _{UE} 22543953
N TNC	plug (m) plug (m)	
Packaging	single	
Material: N TNC	stainless steel stainless steel	
VSUR:	DC - 12.4 GHz: $\leq 1.05 + 0.01f$	




242	H+S type Item no.	33_SMA-N-50-51/1- _{UE} 22660181
SMA N	plug (m) jack (f)	
Packaging	single	
Material: SMA N	CuBe/gold stainless steel	
VSUR:	DC - 18 GHz: $\leq 1.025 + 0.007f$	




246	H+S type Item no.	33_N-TNC-50-51/1- _{UE} 22543955
N TNC	plug (m) jack (f)	
Packaging	single	
Material: N TNC	stainless steel stainless steel	
VSUR:	DC - 12.4 GHz: $\leq 1.05 + 0.01f$	



243	H+S type Item no.	37_N-SMA-50-51/1- _{UE} 22645162
N SMA	jack (f) jack (f)	
Packaging	single	
Material: N SMA	stainless steel CuBe/gold	
VSUR:	DC - 18 GHz: $\leq 1.025 + 0.007f$	



247	H+S type Item no.	33_TNC-N-50-51/- _{UE} 22544046
TNC N	plug (m) jack (f)	
Packaging	single	
Material: TNC N	stainless steel stainless steel	
VSUR:	DC - 12.4 GHz: $\leq 1.05 + 0.01f$	



248	H+S type Item no.	32_PC35-PC7-50-3/-33_NE 23003902
PC35 PC7	plug (m)	
Packaging	single	
Material: PC35 PC7	brass/SUCO* brass/gold	
VSWR:	DC - 18 GHz: ≤ 1.06	
249	H+S type Item no.	31_PC35-QMA-50-1/199_NE 23017468
PC35 QMA	jack (f) jack (f)	
Packaging	single	
Material: PC35 QMA El. length:	stainless steel stainless steel 25.4 ± 2.6 mm	
VSWR:	DC - 1.5 GHz: ≤ 1.036; 1.5 - 6 GHz: ≤ 1.065 6 - 18 GHz: ≤ 1.22	
250	H+S type Item no.	32_PC35-QMA-50-1/1-NE 23017489
PC35 QMA	plug (m) plug (m)	
Packaging	single	
Material: PC35 QMA El. length:	stainless steel st. steel/brass 25.4 ± 2.6 mm	
VSWR:	DC - 1.5 GHz: ≤ 1.036; 1.5 - 6 GHz: ≤ 1.065 6 - 18 GHz: ≤ 1.22	
251	H+S type Item no.	33_PC35-QMA-50-1/199_NE 23017467
PC35 QMA	plug (m) jack (f)	
Packaging	single	
Material: PC35 QMA El. length:	stainless steel stainless steel 25.4 ± 2.6 mm	
VSWR:	DC - 1.5 GHz: ≤ 1.036; 1.5 - 6 GHz: ≤ 1.065 6 - 18 GHz: ≤ 1.22	
252	H+S type Item no.	33_QMA-PC35-50-1/1-NE 23017488
QMA PC35	plug (m) jack (f)	
Packaging	single	
Material: QMA PC35 El. length:	stainless steel stainless steel 25.4 ± 2.6 mm	
VSWR:	DC - 1.5 GHz: ≤ 1.036; 1.5 - 6 GHz: ≤ 1.065 6 - 18 GHz: ≤ 1.22	
253	H+S type Item no.	32_PC7-716-50-1/-3_NE 22544128
PC7 7/16	plug (m)	
Packaging	single	
Material: PC7 7/16	brass/SUPR** brass/SUCO*	
VSWR:	DC - 7.5 GHz: ≤ 1.03 + 0.004f	
254	H+S type Item no.	33_PC7-716-50-1/-3_NE 22544126
PC7 7/16	jack (f)	
Packaging	single	
Material: PC7 7/16	brass/SUPR** brass/SUCO*	
VSWR:	DC - 7.5 GHz: ≤ 1.03 + 0.004f	
255	H+S type Item no.	32_PC7-PC35-50-1/1-UE 22644230
PC7 PC35	plug (m)	
Packaging	single	
Material: PC7 PC35	brass/gold stainless steel	
VSWR:	DC - 15 GHz: ≤ 1.05; 15 - 18 GHz: ≤ 1.09	

256 H+S type 33_PC7-PC35-50-1/1-UE
Item no. 22644231

PC7
PC35


jack (f)

Packaging

single

Material:
PC7
PC35

brass/gold
stainless steel



VSWR: DC - 15 GHz: ≤ 1.05 ; 15 - 18 GHz: ≤ 1.09

260 H+S type 33_PC7-SMA-50-1/1-UE
Item no. 22543548

PC7
SMA


jack (f)

Packaging

single

Material:
PC7
SMA

brass/gold
CuBe/gold



VSWR: DC - 18 GHz: $\leq 1.025 + 0.002f$

257 H+S type 32_PC7-QN-50-1/1-NE
Item no. 23032720

PC7
QN


plug (m)

Packaging

single

Material:
PC7
QN
El. length:

brass/gold
stainless steel
typ. 41.85mm



VSWR: DC - 3 GHz: ≤ 1.03 ; 3 - 6 GHz: ≤ 1.05
6 - 11 GHz: $\leq$ typ. 1.12

261 H+S type 32_PC7-TNC-50-1/1-UE
Item no. 22544048

PC7
TNC


plug (m)

Packaging

single

Material:
PC7
TNC

brass/gold
stainless steel



VSWR: DC - 12.4 GHz: $\leq 1.02 + 0.009f$

258 H+S type 33_PC7-QN-50-1/1-NE
Item no. 23032722

PC7
QN


jack (f)

Packaging

single

Material:
PC7
QN
El. length:

brass/gold
stainless steel
typ. 41.85mm



VSWR: DC - 3 GHz: ≤ 1.03 ; 3 - 6 GHz: ≤ 1.05
6 - 11 GHz: $\leq$ typ. 1.12

262 H+S type 32_PC7-TNC-50-52/-33_NE
Item no. 23003983

PC7
TNC


plug (m)

Packaging

single

Material:
PC7
TNC

brass/gold
stainless steel



VSWR: DC - 18 GHz: $\leq 1.03 + 0.009f$

259 H+S type 32_PC7-SMA-50-1/-UE
Item no. 22543546

PC7
SMA


plug (m)

Packaging

single

Material:
PC7
SMA

brass/gold
CuBe/gold



VSWR: DC - 18 GHz: $\leq 1.025 + 0.002f$

263 H+S type 33_PC7-TNC-50-51/11-UE
Item no. 22643455

PC7
TNC


jack (f)

Packaging

single

Material:
PC7
TNC

brass/SUCO*
stainless steel



VSWR: DC - 18 GHz: $\leq 1.05 + 0.005f$

264	H+S type Item no.	33_PC7-TNC-50-52/-33_NE 23003920
PC7 TNC	jack (f)	
Packaging	single	
Material: PC7 TNC	brass/gold stainless steel	
VSWR:	DC - 18 GHz: $\leq 1.03 + 0.009f$	

268	H+S type Item no.	32_PC24-SK-50-1/199_NE 23004729
PC24 SK	plug (m) plug (m)	
Packaging	single	
Material: PC24 SK	stainless steel stainless steel	
El. length:	16.1 ± 0.1 mm	
VSWR:	DC - 40 GHz: ≤ 1.12	

265	H+S type Item no.	33_PC24-N-50-1/199_NE 22650021
PC24 N	plug (m) jack (f)	
Packaging	single	
Material: PC24 N	stainless steel stainless steel	
VSWR:	DC - 10 GHz: ≤ 1.05 ; 10 - 18 GHz: ≤ 1.08	

269	H+S type Item no.	33_PC24-SK-50-2/199_NE 23004730
PC24 SK	plug (m) jack (f)	
Packaging	single	
Material: PC24 SK	stainless steel stainless steel	
El. length:	16.1 ± 0.1 mm	
VSWR:	DC - 40 GHz: ≤ 1.12	

266	H+S type Item no.	33_N-PC24-50-1/199_UE 22649932
N PC24	plug (m) jack (f)	
Packaging	single	
Material: N PC24	stainless steel stainless steel	
VSWR:	DC - 10 GHz: ≤ 1.05 ; 10 - 18 GHz: ≤ 1.08	

270	H+S type Item no.	33_SK-PC24-50-1/199_NE 23004731
SK PC24	plug (m) jack (f)	
Packaging	single	
Material: PC24 SK	stainless steel stainless steel	
El. length:	16.1 ± 0.1 mm	
VSWR:	DC - 40 GHz: ≤ 1.12	

267	H+S type Item no.	31_PC24-SK-50-1/199_NE 84008075
PC24 SK	jack (f) jack (f)	
Packaging	single	
Material: PC24 SK	stainless steel stainless steel	
VSWR:	DC - 40 GHz: ≤ 1.12	

271	H+S type Item no.	31_SK-SMPX-50-1/199_NE 23021816
SK SMPX	jack (f) jack (f)	
Packaging	single	
Material: SK SMPX	stainless steel stainless steel	
Note:	full detent	
VSWR:	DC - 15 GHz: ≤ 1.105 ; 15 - 30 GHz: ≤ 1.152 30 - 40 GHz: ≤ 1.222	

272 H+S type 31_SK-SMPX-50-2/199_NE
Item no. 23021817


SK
SMPX jack (f)
jack (f)

Packaging single

Material:
SK stainless steel
SMPX stainless steel

Note: limited detent

VSWR: DC - 15 GHz: ≤ 1.105 ; 15 - 30 GHz: ≤ 1.152
30 - 40 GHz: ≤ 1.222



276 H+S type 33_SK-SMPX-50-3/199_NE
Item no. 23021793


SK
SMPX plug (m)
jack (f)

Packaging single

Material:
SK stainless steel
SMPX stainless steel

Note: smooth bore

VSWR: DC - 15 GHz: ≤ 1.105 ; 15 - 30 GHz: ≤ 1.152
30 - 40 GHz: ≤ 1.222



273 H+S type 31_SK-SMPX-50-3/199_NE
Item no. 23021818


SK
SMPX jack (f)
jack (f)

Packaging single

Material:
SK stainless steel
SMPX stainless steel

Note: smooth bore

VSWR: DC - 15 GHz: ≤ 1.105 ; 15 - 30 GHz: ≤ 1.152
30 - 40 GHz: ≤ 1.222




277 H+S type 33_SMPX-SK-50-1/199_NE
Item no. 23032847

SMPX
SK plug (m)
jack (f)

Packaging single

Material:
SMPX stainless steel
SK stainless steel

VSWR: DC - 12 GHz: ≤ 1.05 ; 12 - 40 GHz: ≤ 1.2



274 H+S type 33_SK-SMPX-50-1/199_NE
Item no. 23021753


SK
SMPX plug (m)
jack (f)

Packaging single

Material:
SK stainless steel
SMPX stainless steel

Note: smooth bore full detent

VSWR: DC - 15 GHz: ≤ 1.105 ; 15 - 30 GHz: ≤ 1.152
30 - 40 GHz: ≤ 1.222



275 H+S type 33_SK-SMPX-50-2/199_NE
Item no. 23021792


SK
SMPX plug (m)
jack (f)

Packaging single

Material:
SK stainless steel
SMPX stainless steel







Note: limited detent

VSWR: DC - 15 GHz: ≤ 1.105 ; 15 - 30 GHz: ≤ 1.152
30 - 40 GHz: ≤ 1.222






QUICK-MATE ADAPTORS

300	H+S type Item no.	33_N-Q50-0-14/13_NE 23003160
N	plug (m) jack (f)	
Packaging	single	
Material:	brass/SUCO*	
VSWR:	DC - 4 GHz: ≤ 1.12; 4 - 8 GHz: ≤ 1.22	
303	H+S type Item no.	33_716-N-Q50-4/133_UE 23000487
7/16 N	plug (m) jack (f)	
Packaging	single	
Material:	brass/SUCO* brass/SUCO*	
VSWR:	DC - 4 GHz: ≤ 1.05; 4 - 7.5 GHz: ≤ 1.15	
301	H+S type Item no.	33_N-Q50-0-4/133_NE 22660297
N	plug (m) jack (f)	
Packaging	single	
Material:	brass/SUCO*	
VSWR:	DC - 5 GHz: ≤ 1.07; 5 - 8 GHz: ≤ 1.22 8 - 11 GHz: ≤ 1.28	
304	H+S type Item no.	33_SMA-Q50-0-4/1-9_NE 22660213
SMA	plug (m) jack (f)	
Packaging	single	
Material:	CuBe/SUPR**	
VSWR:	DC - 5 GHz: ≤ 1.07; 5 - 16 GHz: ≤ 1.22 16 - 18 GHz: ≤ 1.28	
302	H+S type Item no.	31_716-N-Q50-1/1-3_NE 23008294
7/16 N	jack (f) jack (f)	
Packaging	single	
Material:	brass/SUCO* brass/SUCO*	
VSWR:	DC - 4 GHz: ≤ 1.05 4 - 7.5 GHz: ≤ 1.17	
305	H+S type Item no.	33_BNC-N-Q50-4/133_NE 23003163
BNC N	plug (m) jack (f)	
Packaging	single	
Material:	BNC N	brass/SUCO* brass/SUCO*
VSWR:	DC - 4 GHz: ≤ 1.07	


Material and plating descriptions may refer to the connector housing or outer contact.

SUCO* = SUCOPLATE®
SUPR** = SUCOPRO


306	H+S type Item no.	32_N-PC7-Q50-4/1_NE 23003162
N PC7	plug (m)	
Packaging	single	
Material: N PC7	brass/SUPR** brass/SUPR**	
VSWR:	DC - 4 GHz: ≤ 1.07 ; 4 - 8 GHz: ≤ 1.18 8 - 11 GHz: ≤ 1.22	




309	H+S type Item no.	33_TNC-N-Q50-4/133_NE 22660360
TNC N	plug (m) jack (f)	
Packaging	single	
Material: TNC N	brass/SUCO* brass/SUCO*	
VSWR:	DC - 4 GHz: ≤ 1.065 ; 4 - 8 GHz: ≤ 1.12 8 - 11 GHz: ≤ 1.28	



307	H+S type Item no.	33_PC7-N-Q50-4/1_NE 23003161
PC7 N	jack (f)	
Packaging	single	
Material: PC7 N	brass/SUPR** brass/SUPR**	
VSWR:	DC - 4 GHz: ≤ 1.07 ; 4 - 18 GHz: ≤ 1.22	



308	H+S type Item no.	33_SMA-N-Q50-4/1-3_NE 22660211
SMA N	plug (m) jack (f)	
Packaging	single	
Material: SMA N	CuBe/SUPR** brass/SUCO*	
VSWR:	DC - 6 GHz: ≤ 1.07 ; 6 - 12.4 GHz: ≤ 1.18	





PIM ADAPTORS

400	H+S type Item no.	31_4195-716-50-1/133_WE 22658138
41/95 7/16	jack (f) jack (f)	
Packaging	single	
Material: 41/95 7/16	brass/SUCO* brass/SUCO*	
Intermodulation:	≥ -165 dBc	

401	H+S type Item no.	32_4195-716-50-1/133_WE 22658131
41/95 7/16	plug (m) plug (m)	
Packaging	single	
Material: 41/95 7/16	brass/SUCO* brass/SUCO*	
Intermodulation:	≥ -165 dBc	

402	H+S type Item no.	31_716-50-0-2/133_WE 22658136
7/16 7/16	jack (f) jack (f)	
Packaging	single	
Material:	brass/SUCO*	
Intermodulation:	≥ -165 dBc	

403	H+S type Item no.	31_N-716-50-2/133_WE 22658137
N 7/16	jack (f) jack (f)	
Packaging	single	
Material: N 7/16	brass/SUCO* brass/SUCO*	
Intermodulation:	≥ -165 dBc	

404	H+S type Item no.	32_716-50-0-2/133_WE 22658141
7/16 7/16	plug (m) plug (m)	
Packaging	single	
Material:	brass/SUCO*	
Intermodulation:	≥ -165 dBc	

405	H+S type Item no.	32_N-716-50-2/133_WE 22658140
N 7/16	plug (m) plug (m)	
Packaging	single	
Material: N 7/16	brass/SUCO* brass/SUCO*	
Intermodulation:	≥ -165 dBc	

406	H+S type Item no.	33_716-50-0-2/133_WE 22658193
7/16 7/16	plug (m) jack (f)	
Packaging	single	
Material:	brass/SUCO*	
Intermodulation:	≥ -165 dBc	


407	H+S type Item no.	33_716-N-50-3/133_WE 22658823
7/16 N	plug (m) jack (f)	
Packaging	single	
Material: 7/16 N	brass/SUCO* brass/SUCO*	
Intermodulation:	≥ -165 dBc	

408 H+S type
Item no. 33_N-716-50-3/133_WE
22658217

N
7/16 plug (m)
jack (f)

Packaging single

Material:
N brass/SUCO*
7/16 brass/SUCO*




Intermodulation: ≥ -165 dBc

409 H+S type
Item no. 31_PC35-716-50-1/133_WE
22658135

PC3.5
7/16 jack (f)
jack (f)

Packaging single

Material:
PC3.5 brass/SUCO*
7/16 brass/SUCO*




Intermodulation: ≥ -160 dBc

410 H+S type
Item no. 32_PC35-716-50-1/133_WE
22658143

PC3.5
7/16 plug (m)
plug (m)

Packaging single

Material:
PC3.5 brass/SUCO*
7/16 brass/SUCO*




Intermodulation: ≥ -160 dBc

411 H+S type
Item no. 33_716-PC35-50-1/133_WE
22658821

7/16
PC3.5 plug (m)
jack (f)

Packaging single

Material:
7/16 brass/SUCO*
PC3.5 brass/SUCO*




Intermodulation: ≥ -165 dBc

412 H+S type
Item no. 31_QN-716-50-1/113_WE
23033269

QN
7/16 jack (f)
jack (f)

Packaging single

Material:
QN brass/SUCO*
7/16 brass/SUCO*




Intermodulation: ≥ -165 dBc

413 H+S type
Item no. 32_QN-716-50-1/113_WE
23033643

QN
7/16 plug (m)
plug (m)

Packaging single

Material:
QN brass/SUCO*
7/16 brass/SUCO*




Intermodulation: ≥ -165 dBc

414 H+S type
Item no. 33_QN-716-50-1/113_WE
23033550

QN
7/16 plug (m)
jack (f)

Packaging single

Material:
QN brass/SUCO*
7/16 brass/SUCO*




Intermodulation: ≥ -165 dBc

415 H+S type
Item no. 33_716-QN-50-1/113_WE
23033644

7/16
QN plug (m)
jack (f)

Packaging single

Material:
716 brass/SUCO*
QN brass/SUCO*



Intermodulation: ≥ -165 dBc


416	H+S type	31_TNC-716-50-1/133_WE
	Item no.	22658134

TNC
7/16

jack (f)
jack (f)

Packaging: single

Material:
TNC: brass/SUCO*
7/16: brass/SUCO*



Intermodulation: ≥ -165 dBc


417	H+S type	32_TNC-716-50-1/133_WE
	Item no.	22658142

TNC
7/16

plug (m)
plug (m)

Packaging: single

Material:
TNC: brass/SUCO*
7/16: brass/SUCO*



Intermodulation: ≥ -165 dBc


418	H+S type	33_716-TNC-50-1/133_WE
	Item no.	22658824

7/16
TNC

plug (m)
jack (f)

Packaging: single

Material:
7/16: brass/SUCO*
TNC: brass/SUCO*



Intermodulation: ≥ -165 dBc

ASSEMBLY TOOLS

CONTENTS	PAGE
Crimping tools and inserts for flexible cables	385
Tool boxes	387
Tool sets for semi-rigid cable assembling (solder type)	389
Selection of common and helpful assembly tools	389
Assembly tools for BMA connectors with hermetic seal	394
Assembly tools for SK connectors	394
Spanners	395
Torque wrenches	395
Combination tool for MMBX/MMCX/MCX-right angle connectors	396
Special tools for QMA connectors	396
Special tools for QN connectors	397
Decoupling tool for MMPX	397
Tap drill	398
Various tools	398
Tools for HUBER+SUHNER QUICK-FIT connectors	399

CRIMPING TOOLS AND INSERTS FOR FLEXIBLE CABLES

small crimp tool with fixed inserts



H+S type	Item no.	Size	Colour code	Square-section (centre contact)	Hexagonal section (outer contact)
75_Z-0-3-4	22544613	2B	orange	1.6 mm / .063 in.	5.5 mm / .217 in.
75_Z-0-4-4	22544612	2C	yellow	1.6 mm / .063 in.	6.5 mm / .256 in.

small crimp tool with interchangeable inserts 1/2A, 2B, 2C




Fig. 1



Fig. 2

H+S type	Item no.	Description	Fig.
75_Z-0-0-50	22544754	tool without inserts	1
75_Z-0-0-51	22544755	tool with various inserts in wooden box (1/2A, 2B, 2C)	2

interchangeable inserts for small crimp tool



H+S type	Item no.	Size	Square-section (centre contact)	Hexagonal section (outer contact)
76_Z-0-1-1	23000884	0.54/A	0.54 mm / .021 in.	3.3 mm / .130 in.
76_Z-0-2-20	22645153	1/4.95	0.7 mm / .028 in.	4.95 mm / .195 in.
76_Z-0-2-51	22544756	1/2A	0.7/1.6 mm / .028/.063 in.	3.3 mm / .130 in.
76_Z-0-2-53	22645337	1/2.67	0.7 mm / .028 in.	2.7 mm / .106 in.
76_Z-0-3-51	22544757	2B	1.6 mm / .063 in.	5.5 mm / .217 in.
76_Z-0-4-51	22544758	2C	1.6 mm / .063 in.	6.5 mm / .256 in.

large crimp tool with interchangeable inserts 1/2A, 2B, 2C, 3D



Fig. 1



Fig. 2

H+S type	Item no.	Description	Fig.
75_Z-0-0-1	22543157	tool without inserts	1
76_Z-0-0-15	22543177	tool with various inserts in wooden box (1/2A, 2B, 2C, 3D)	2

TOOL BOXES



H+S type	Item no.	Description
76_Z-0-0-9	22644671	large tool box (empty)
76_Z-0-0-11	22543175	large tool box without tooling but including foam insert for tools and allen key

table press with interchangeable inserts



H+S type	Item no.	Description
75_Z-0-0-2	22543158	press without inserts (for inserts see next page)

**interchangeable inserts fitting large crimp tool
and table press**



H+S type	Item no.	Size	Colour code	Square-section (centre contact)	Hexagonal section (outer contact)
76_Z-0-1-2	23000885	0.54/A		0.54 mm / .021 in.	3.30 mm / .130 in.
76_Z-0-2-1	22543181	1/2 A	red	0.7/1.6 mm / .028/.063 in.	3.30 mm / .130 in.
76_Z-0-2-8	22544191	1/4.95		0.7 mm / .028 in.	4.95 mm / .195 in.
76_Z-0-3-1	22543185	2 B	orange	1.6 mm / .063 in.	5.50 mm / .217 in.
76_Z-0-3-9	22641133	B 1.22/1.22		1.2 mm / .047 in.	5.50 mm / .217 in.
76_Z-0-4-1	22543189	2 C	yellow	1.6 mm / .063 in.	6.50 mm / .256 in.
76_Z-0-4-8	22543190	C 1.22/1.22		1.2 mm / .047 in.	6.50 mm / .256 in.
76_Z-0-5-8	22543192	8/1.22/1.22		1.2 mm / .047 in.	8.00 mm / .315 in.
76_Z-0-5-21	22543193	2/8.0		1.6 mm / .063 in.	8.00 mm / .315 in.
76_Z-0-6-1	22649051	3/8.65		2.4 mm / .094 in.	8.65 mm / .341 in.
76_Z-0-6-21	22543194	2/9.75		1.6 mm / .063 in.	9.80 mm / .386 in.
76_Z-0-7-1	22543195	3 D	violet	2.4 mm / .094 in.	10.70 mm / .421 in.
76_Z-0-7-7	22543196	2 D		1.6 mm / .063 in.	10.70 mm / .421 in.
76_Z-0-7-8	22660322	2.5/D		2.5 mm / .098 in.	10.70 mm / .421 in.
76_Z-0-7-14	22544524	4 D		3.3 mm / .130 in.	10.70 mm / .421 in.
76_Z-0-10-14	23002630	12.4		—	12.40 mm / .488 in.
76_Z-0-0-26	22645880	1/2.67		0.7 mm / .028 in.	2.70 mm / .106 in.

**special inserts and tools for large crimp
tool and table press**



H+S type	Item no.	Description
76_Z-0-0-1	22543170	cutting insert for cables up to 12 mm/4.72 in. outer diameter
76_Z-0-0-2	22543172	spare blades for cutting insert (10 pieces per package)
76_Z-0-0-3	22543173	support plate for bench mounting of large crimp tool

TOOL SETS FOR SEMI-RIGID CABLE ASSEMBLING (SOLDER TYPE)

The tool sets include a solid wooden storage case. The composition of these sets is as indicated in the list of tools.



H+S type	Item no.	Series	Description
74_Z-0-0-70	22544725	SMA	includes all tools required for economic and reliable assembling of SMA connectors
74_Z-0-0-71	22641350	N	includes all tools required for assembling of N connectors to semi-rigid cables
74_Z-0-0-72	22544747	SMA	includes only the minimum of tools required for assembling of SMA connectors

SELECTION OF COMMON AND HELPFUL ASSEMBLY TOOLS

H+S type	Item no.	W-no.	for series	Description	Tool set 74 Z-0-0-			
					70	71	72	
74_Z-0-0-10	22543120	W10		"Soldomat" soldering device for center contacts				
74_Z-0-0-14	22543124	W14	SMA	locator tools for contact and insulators	●		●	
74_Z-0-0-21	22543130	W21	SMA	torque wrench 1 Nm	●			
74_Z-0-0-24	22543133		SMA	tap drill for SMA (1/4-36 UNS-2B thread)				
74_Z-0-0-29	22543138	W29	N	dielectric insertion tool for insulators series N		●		

H+S type	Item no.	W-no.	for series	Description	Tool set 74 Z-0-0-			
					70	71	72	
74_Z-0-0-35	22544282	W35	N	soldering gauge 0.45 mm / .018 in.		●		
74_Z-0-0-52	22544553	W52	SMA	dielectric insertion tool for SMA-plugs	●		●	
74_Z-0-0-53	22544554	W53	SMA	dielectric insertion tool for SMA-jacks	●		●	
74_Z-0-0-54	22544555	W54	SMA	contact holder for pins and sockets	●		●	
74_Z-0-0-55	22544516	W55	SMA	soldering gauge 0.25 mm / .010 in.	●		●	
74_Z-0-0-56	22544517	W56	SMA	soldering gauge 0.4 mm / .016 in.	●		●	
74_Z-0-0-58	22544557	W58	BMA, SK, N SMA	soldering fixture (works with W374)	●	●	●	
74_Z-0-0-59	22544558	W59	BMA N SMA	inserts for EZ 141 (works with W58 and W442)	●	●	●	
74_Z-0-0-60	22544559	W60	BMA N SMA	inserts for EZ 86 (works with W58 and W442)	●	●	●	
74_Z-0-0-61	22544560	W61	SMA	locator tool (works with W58 and W442)				
74_Z-0-0-62	22544561	W62	SMA	locator tool for SMA-plugs without pin (works with W58 and W442)				
74_Z-0-0-63	22544562	W63	SMA	trim tool for SMA-plugs without pin	●			
74_Z-0-0-66	22544616	W66	N	locator tool (works with W58 and W442)		●		
74_Z-0-0-67	22544640	W67	N	contact holder for pins and sockets series N		●		

H+S type	Item no.	W-no.	for series	Description	Tool set 74 Z-0-0-			
					70	71	72	
74_Z-0-0-68	22544715	W68	BMA SK, N SMA	1 set of blades with protector	●	●	●	
74_Z-0-0-73	22544688	W73		adaptor				
74_Z-0-0-75	22544807	W75	SK SMA	assembly tool for hermetic jacks				
74_Z-0-0-81	22641423		SK SMA	positioner for assembly of coupling nuts	●	●		
74_Z-0-0-142	22643462	W142	SMA	rebore tool	●		●	
74_Z-0-0-157	22643029	W157	BMA SK, N SMA	cable stripping jig for EZ 47, EZ 86, EZ 141, SUCOFORM 86 and 141	●	●	●	
74_Z-0-0-160	22643514			replacement cutting wheels; set for EZ 47, EZ 86, EZ 141 (works with W157)	●	●	●	
74_Z-0-0-164	22643028	W164	BMA N SMA	trim tool for centre contacts	●	●		
74_Z-0-0-196 74_Z-0-0-197 74_Z-0-0-198	22645359 22645360 22645361			replacement support cover for EZ 47 EZ 86 EZ 141 (works with W 157)				
74_Z-0-0-207 74_Z-0-0-208	22645363 22645362			replacement cutting wheels for EZ 47 EZ 86 EZ 141 (works with W157)				
74_Z-0-0-209	22645585	W209	BMA	locator tool used with W58 and W442 (for BMA plug)				
74_Z-0-0-210	22645586	W210	BMA	locator tool used with W58 and W442 (for BMA jack)				
74_Z-0-0-213	22645593	W213	BMA	removal tool for receptacles with snap-in mechanism				
74_Z-0-0-231	22646131	W231	SK	locator tool for SK-plugs (works with W58 and W442)				

H+S type	Item no.	W-no.	for series	Description	Tool set 74 Z-0-0-			
					70	71	72	
74_Z-0-0-232	22646132	W232	SK	locator tool for SK-jacks (works with W58 and W442)				
74_Z-0-0-233	22646133	W233	SK	inserts for semi-rigid cable EZ 118 (works with W58 and W442)				
74_Z-0-0-234	22646134	W234	SK	replacement cutting wheels for EZ 118 (works with W157)				
74_Z-0-0-246	22646873	W246	SMA	jacket remover for semi-rigid and Suco-form cables. After cutting and breaking of jacket with tool W-157, remove separated piece with tool W-246.				
74_Z-0-0-264	22646290	W264	SK	trim tool for centre conductor of semi-rigid cable EZ 118				
74_Z-0-0-265	22646291	W265	SK	spare blade for W264				
74_Z-0-0-270	22648901	W270	1.0/ 2.3	removal tool for 1.0/2.3 inserts				
74_Z-0-0-368	23021264	W368	SMA	locator tool for SMA female (works with W58 and W442)	●		●	
74_Z-0-0-369	23021266	W369	SMA	locator tool for SMA male (works with W58 and W442)	●		●	
74_Z-0-0-374	23022146	W374	BMA SK SMA N	support for soldering fixture (works with W58 and W442)				

H+S type	Item no.	W-no.	for series	Description	Tool set 74 Z-0-0-			
					70	71	72	
74_Z-0-0-375	23022145	W375	BMA SK SMA N	soldering fixture for centre contacts (works with W374)				
74_Z-0-0-441	23024586	W441	BMA SK SMA N	collecting tank for coolant or flux (works with W374)				
74_Z-0-0-442	23024588	W442	BMA SK SMA N	soldering fixture (works with W374)				
74_Z-0-0-443	23024584	W443	BMA SK SMA N	for positioning locator tools (works with W442)				
74_Z-0-3-2	22543148	W3-2	SMA N	stripping gauge for in- sulation EZ 141	●	●		
74_Z-0-3-4	22543150	W3-4	N	trim tool for EZ 141		●		

ASSEMBLY TOOLS FOR BMA CONNECTORS WITH HERMETIC SEAL

H+S type	Item no.	W-no.	Description	
74_Z-0-0-211	22645591		soldering fixture for hermetic seal (12_BMA-50-0-3 and 22_BMA-50-0-3)	
74_Z-0-0-214	22645579		torque wrench (box spanner) torque 2.00 Nm, 8 mm hex.	
74_Z-0-0-215	22645580		screw driver for 12_BMA-50-0-3 to use with 74_Z-0-0-214	

ASSEMBLY TOOLS FOR SK CONNECTORS


H+S type	Item no.	W-no.	Description	
74_Z-0-0-226	22646136	W226	soldering fixture for glass bead	
74_Z-0-0-227	22646137	W227	soldering fixture for glass bead	
74_Z-0-0-228	22646138	W228	assembling tool for dielectric bead	
74_Z-0-0-230	22646130	W230	step drill (only if sliding contacts are not used)	
74_Z-0-0-235	22646135	W235	step drill (only if sliding contacts are used)	

SPANNERS



H+S type	Item no.	Opening
74_Z-0-0-1	22543111	3/8"
74_Z-0-0-2	22543112	11.0 mm / .433 in.
74_Z-0-0-3	22543113	16.0 mm / .630 in.
74_Z-0-0-16	22543126	8.0 mm / .315 in.
74_Z-0-0-17	22644234	1/4" (6.35 mm / .250 in.)
74_Z-0-0-18	22543127	9.0 mm / .354 in.
74_Z-0-0-19	22543128	5.5 mm / .217 in.
74_Z-0-0-37	22543732	13.0 mm / .512 in.
74_Z-0-0-38	22543733	7.0 mm / .276 in.

TORQUE WRENCHES



H+S type	Item no.	for series	Torque	Opening	Notes
74_Z-0-0-21	22543130	SMA / PC 3.5	1.00 Nm	8.0 mm/.315 in.	standard style
74_Z-0-0-45	22544232	SMC	0.35 Nm	6.0 mm/.236 in.	standard style
74_Z-0-0-77	22544820	SMA	1.00 Nm	8.0 mm/.315 in.	box-spanner
74_Z-0-0-78	22641379	SMA economic	0.45 Nm	8.0 mm/.315 in.	box-spanner
74_Z-0-0-79	22642374	SMA economic	0.45 Nm	8.0 mm/.315 in.	standard style
74_Z-0-0-80	22544821	SMA hermetic	1.95 Nm	7.0 mm/.276 in.	standard style
74_Z-0-0-147	22644235	SMC	0.35 Nm	6.0 mm/.236 in.	box-spanner
74_Z-0-0-174	22643898	SK	1.30 Nm	8.0 mm/.315 in.	standard style
74_Z-0-0-189	22644368	SK hermetic	2.00 Nm	8.0 mm/.315 in.	standard style
74_Z-0-0-192	22645084	TNC	1.00 Nm	15.0 mm/.591 in.	standard style
74_Z-0-0-193	22645085	N	1.00 Nm	20.0 mm/.787 in.	standard style
74_Z-0-0-321	22651994	N	1.00 Nm	19.0 mm/.748 in.	standard style
74_Z-0-0-373	23021864	TNC	1.00 Nm	14.0 mm/.551 in.	standard style

COMBINATION TOOL FOR MMBX/MMCX/MCX-RIGHT ANGLE CONNECTORS

for protective cap mounting and decoupling



H+S type	Item no.	Description
74_Z-0-0-30	22543139	assembly tool for 16_MCX and MMBX right angle connectors (decoupling and cap mounting)
74_Z-0-0-225	22645861	16_MMCX-50-1-1, 16_MMCX-50-1-2, 16_MMCX-50-2-1 (decoupling and cap mounting)
74_Z-0-0-272	22648614	all 11_MMCX- and 16_MMCX-connectors (decoupling and cap mounting)
74_Z-0-0-276	22648710	decoupling tool for bulkhead jacks (MCX 75 Ω)
74_Z-0-0-350	23004135	removal tool (16_MMCX)

SPECIAL TOOLS FOR QMA CONNECTORS

decoupling tool for high density applications



H+S type	Item no.	W-no.	Description
74_Z-0-0-459	84032400	W459	decoupling tool for high density application (for QMA and QN)

assembly tool



H+S type	Item no.	W-no.	for series	Description
74_Z-0-0-360	23023444	W360	QMA	locator tools for QMA connectors (suitable for semi-rigid cables)

SPECIAL TOOLS FOR QN CONNECTORS

decoupling tool



H+S type	Item no.	W-no.	for series	Description
74_Z-0-0-459	84032400	W459	QN / QMA	decoupling tool for high density application

locator tool



H+S type	Item no.	W-no.	for series	Description
74_Z-0-0-390	23035218	W390	QN	locator tool for 11 QN and 16 QN connectors (works with W58 and W442)

locator tool



H+S type	Item no.	W-no.	for series	Description
74_Z-0-0-391	23035220	W391	QN	locator tool for 24 QN connectors (works with W58 and W442)

decoupling tool for MMPX



H+S type	Item no.	W-no.	for series	Description
74_Z-0-0-555_—_E	84020011	W555	MMPX	decoupling tool (distance washers included)
74_Z-0-0-556_—_E	84031617	W556	MMPX	distance washers (for replacement)

TAP DRILL



H+S type	Item no.	Thread
74_Z-0-0-24	22543133	1/4-36 UNS-2B
74_Z-0-0-82	22643835	3/8-32 UNEF-2B
74_Z-0-0-229	22646139	1/4-36 UNS (for blind hole threads)
74_Z-0-0-236	22646069	2-56 UNC
74_Z-0-0-237	22646070	10-56 UNS
74_Z-0-0-238	22646071	5/8-24 UNEF

VARIOUS TOOLS



H+S type	Item no.	Description
74_Z-0-0-12	22642718	small saw
74_Z-0-0-13	22644241	replacement saw blade for 74 Z-0-0-12
74_Z-0-0-25	22543134	face spanner for fastening nut (22 + 24 QLA)
74_Z-0-0-89	22644721	screw driver for female centre contacts (Series 7/16)
74_Z-0-0-115	22642492	syringe for casting compound
74_Z-0-0-116	22642493	casting compound (resin 6.75 cm ³ and accelerator 3.0 cm ³), 2 containers
74_Z-0-0-177	22644541	cover insertion tool for 16 SMB/C/S connectors

TOOLS FOR HUBER+SUHNER QUICK-FIT® CONNECTORS

cable stripping tools for easy cable preparation
in one single operation
(can be used manually or with electrical power tool)



H+S type	Item no.	Cable type	Assembly instructions
74_Z-0-8-15	23000296	3/8": Andrew LDF 2-50	0000180713
74_Z-0-9-15	23001006	1/2" Highflex: SUCOFEED®, Andrew, NK cables, RFS (Kabelmetal)	0000179418/ 0000201603
74_Z-0-12-15	23000319	1/2": SUCOFEED®, Andrew, NK cables, RFS (Kabelmetal)	0000179113
74_Z-0-23-16	23007928	7/8": SUCOFEED®, Andrew, NK cables, RFS (Kabelmetal) 7/8" Highflex: SUCOFEED®, Andrew	0000180164/ 0000201645 0000233737
74_Z-0-23-17	84017918	7/8" Low attenuation: SUCOFEED®, Andrew	0000243692/0000236366
74_Z-0-32-14	23010533	1 1/4": SUCOFEED®, Andrew, NK cables, RFS (Kabelmetal)	0000179128
74_Z-0-42-14	23010534	1 5/8": SUCOFEED®, Andrew, NK cables, RFS (Kabelmetal)	0000179128

HUBER+SUHNER® QUICK-FIT installation kit

Tool kit for all QUICK-FIT Connectors
(with additional space for other auxiliary tools and spare parts)

Stripping tools can be accomodated but are not included



H+S type	Item no.	Description	Content	Size
74_Z-0-0-600	23002174	tool box	all tools of the following table marked with *	620×430×140 mm/ 24.4×17×1.5 in.

Overview necessary tools for the assembly of QUICK-FIT connectors

H+S type	Item no.	Part description	Corrugated copper tube cables							
			$\frac{3}{8}$ " LFD 2-50	$\frac{1}{2}$ " HF	$\frac{1}{2}$ "	$\frac{7}{8}$ "	$\frac{7}{8}$ " HF	$\frac{7}{8}$ " LA	$1 \frac{1}{4}$ "	$1 \frac{5}{8}$ "
74_Z-0-8-15	23000296	stripping tool ($\frac{3}{8}$ " LFD 2-50)	X							
74_Z-0-9-15	23001006	stripping tool ($\frac{1}{2}$ " HF)		X						
74_Z-0-12-15	23000319	stripping tool ($\frac{1}{2}$ "			X					
74_Z-0-23-16	23007928	stripping tool ($\frac{7}{8}$ " + $\frac{7}{8}$ " HF)				optional	optional			
74_Z-0-23-17	84017918	stripping tool ($\frac{7}{8}$ " LA)						optional		
74_Z-0-32-14	23010533	stripping tool ($1 \frac{1}{4}$ "							optional	
74_Z-0-42-14	23010534	stripping tool ($1 \frac{5}{8}$ "								optional
74_Z-0-0-359	23014976	handle (for stripping tools)	X ⁴⁾	X ⁴⁾	X ⁴⁾	optional	optional	optional	optional	optional
74_Z-0-0-402	22652193	* abrasive paper 320	X	X	X					
74_Z-0-0-424	23001952	* spanner AF 17 mm	X							
74_Z-0-0-425	23001953	* spanner AF 18 mm	X							
74_Z-0-0-426	23001954	* spanner AF 19 mm	X							
74_Z-0-0-427	23001955	* spanner AF 21 mm	X	X						
74_Z-0-0-428	23001956	* spanner AF 22 mm		X	X					
74_Z-0-0-429	23001957	* spanner AF 24 mm			X					
74_Z-0-0-430	23001958	* spanner AF 30 mm				X	X	X		
74_Z-0-0-431	23001959	* spanner AF 36 mm				X	X	X		
74_Z-0-0-415	22652206	* counter sink				X ¹⁾	X ¹⁾	X ¹⁾	X ¹⁾	X ¹⁾
74_Z-0-0-418	22652209	* Stanley knife	X	X	X	X	X	X	X	X
74_Z-0-0-420	22652211	* steel brush			X	X	X	X	X	X
74_Z-0-0-422	22652213	* steel measure 200 mm	X ²⁾	X ²⁾	X ²⁾	X ²⁾	X ²⁾	X ²⁾	X ²⁾	X ²⁾
74_Z-0-0-432	23002005	* screw driver (2)	X		X					
74_Z-0-0-433	23002007	* screw driver (4)				X	X	X	X	X
74_Z-0-0-12	22642718	small metal saw	X	X	X	X	X	X	X	X
74_Z-0-0-434	23002166	monkey wrench ³⁾ (min. 65mm)							X	X
		small file	X ²⁾	X ²⁾	X ²⁾					

* = tools included in the HUBER+SUHNER QUICK-FIT installation kit 74_Z-0-0-600, (can be ordered with item no. 23002174)

1) for assembly use either the Stanley knife or the counter sink

2) only necessary without HUBER+SUHNER stripping tool

3) 2 wrenches are needed for assembling

4) handle included in QUICK-FIT stripping tool delivery

Spare parts for QUICK-FIT cable stripping tools



H+S type	Item no.	Description	Application	Function
74_Z-0-0-346	23000936	blade	74_Z-0-8-15 74_Z-0-8-16 74_Z-0-9-15 74_Z-0-12-15	stripping jacket
74_Z-0-0-347	23000937	blade	74_Z-0-8-15 74_Z-0-8-16 74_Z-0-12-15	cutting corrugated copper tube
74_Z-0-0-348	23000938	triangle knife	74_Z-0-8-15 74_Z-0-8-16 74_Z-0-9-15 74_Z-0-12-15	deburring inner conductor
74_Z-0-0-349	23001008	blade	74_Z-0-9-15	cutting corrugated copper tube
74_Z-0-0-297	22650531	blade	74_Z-0-23-16 74_Z-0-23-17	cutting corrugated copper, foam and inner conductor
74_Z-0-0-355	23008264	blade	74_Z-0-23-16 74_Z-0-32-14 74_Z-0-32-17	stripping jacket
74_Z-0-0-356	23010537	blade	74_Z-0-42-14	stripping jacket

Additional tools for HUBER+SUHNER® QUICK-FIT cable stripping tools

H+S type	Item no.	Tool description	Function
74_Z-0-0-416	22652207	* allen wrench AF 2.5 mm/.098 in.	spare blades for the stripping tools 74_Z-0-8-15, 74_Z-0-8-16, 74_Z-0-9-15, 74_Z-0-12-15, 74_Z-0-23-16, 74_Z-0-23-17, 74_Z-0-32-14 and 74_Z-0-42-14
74_Z-0-0-423	23000311	* allen wrench AF 4 mm/.157 in.	for removing the BIT adaptor
74_Z-0-0-421	22652212	* screwdriver, Torx 1 (Torx T7)	for changing the triangle knife 74_Z-0-0-348


* = not included in the HUBER+SUHNER QUICK-FIT installation kit 74_Z-0-0-600

A FURTHER HUBER+SUHNER PRODUCT!

RFID (Radio Frequency IDentification) antennas



Details on this product are to be found in the catalogue,
Item no. 84035963. Get your copy free of charge at
www.hubersuhner.com.




ACCESSORIES

CONTENTS	PAGE
Cable Terminators	403
Taper Sleeves	406
Coloured Plastic Caps	407
Fastening Screws	407
Insulating Washers	408
Solder Tags	409
Component Container "SUCOBOX"	410
Accessories for SK Connectors	411
Accessories for BMA Connectors	411
HUBER+SUHNER QUICK-FIT® Accessories	411

CABLE TERMINATORS


Straight PCB cable terminators

- > for flexible cables
- > cable entry crimp
- > 5.08 mm / .200 in. grid




H+S type	Item no.	Cable group (example)	Packaging	Plating body	Assembly Instruction/ Mounting Hole	Crimp insert
83_CT-0-3-1/-23_E	23013153	U7 (RG 58 C/U)	single	nickel	27407 / ML 49	B
83_CT-0-3-2/-23_E	23013154	U9 (RG 223/U)	single	nickel	27407 / ML 49	B

- > for flexible cables
- > cable entry crimp
- > 2.54 mm / .100 in. grid




H+S type	Item no.	Cable group (example)	Packaging	Plating body	Assembly Instruction/ Mounting Hole	Crimp insert
83_CT-0-1-1/-11_NE	23013158	U1 (RG 178 B/U)	single	gold	27408 / ML 45	A
83_CT-0-2-1/-11_NE	23013159	U2 (RG 316/U)	single	gold	27408 / ML 45	A
83_CT-0-2-1/-11_NH	23013160	U2 (RG 316/U)	bulk 100 pcs.	gold	27408 / ML 45	A
83_CT-0-2-2/-11_NE	23013161	U4 (K 02252 D)	single	gold	27408 / ML 45	A

- > for semi-rigid cables
- > cable entry soldered
- > 2.54 mm / .100 in. grid



H+S type	Item no.	Cable group (example)	Packaging	Plating body	Assembly instruction/ Mounting hole
83_CT-0-2-4/-11_NE	23013176	Y3, Y11 (EZ 86)	single	gold	27410 / ML 45
83_CT-0-2-4/-11_NH	23013177	Y3, Y11 (EZ 86)	bulk 100 pcs.	gold	27410 / ML 45

- > for flexible cables
- > cable entry crimp
- > 2.54 mm / .100 in. grid



H+S type	Item no.	Cable group (example)	Packaging	Plating body	Assembly Instruction/ Mounting Hole	Crimp insert
83_CT-0-2-3/-11_NE	23013192	U2 (RG 316/U)	single	gold	27409 / ML 15	A

- > for flexible cables
- > cable entry soldered




Fig. 1




Fig. 2





Fig. 3

H+S type	Item no.	Cable group (example)	Packaging	Plating body	Assembly Instruction/ Mounting Hole	Fig.
86_CT-0-1-1/111_NE	23013202	U1 (RG 178 B/U)	single	gold	27411 / ML 100	1
86_CT-0-1-1/111_NH	23013203	U1 (RG 178 B/U)	bulk 100 pcs.	gold	27411 / ML 100	1
86_CT-0-2-1/111_NH	23013216	U2 (RG 316/U)	bulk 100 pcs.	gold	27411 / ML 100	2
86_CT-0-2-5/111_NH	23016926	U2 (RG 316/U)	bulk 100 pcs.	gold	27432 / ML 164	3

- > for flexible cables
- > cable entry crimp



H+S type	Item no.	Cable group (example)	Packaging	Plating body	Assembly Instruction/ Mounting Hole	Crimp insert
86_CT-0-2-2/111_NE	23013227	U2 (RG 316/U)	single	gold	27412 / ML 15	A
86_CT-0-2-3/111_NE	23013228	U4 (K 02252 D)	single	gold	27412 / ML 15	A

TAPER SLEEVES AND SUITABLE ASSEMBLY TOOLS

Release spray is recommended for mounting (Acmos 70 - 2404, oil-less)

- > for connectors with cable entry crimp
- > made of EVA (ethylenevinylacetat)
- > temperature resistant - 40°C – + 70°C / - 40 °F + 158 °F
- > halogen free
- > can be recycled



Cable group	U1	U2, U5, S5	U4, R8	U7, U8, U11, U12, U13 + RG142 B/U, EF 142		U16*, U17	
example	RG 196 A/U	RG 188 A/U RG 179 B/U	G 02232 D K 02252 D	RG 58 C/U	RG 223/U G 03233 D	RG 59 B/U	G 04233 D
colour black	78_Z-0-1-1	78_Z-0-2-1	78_Z-0-2-3	78_Z-0-3-4	78_Z-0-3-5	78_Z-0-4-4	78_Z-0-4-5
Item no.	22544447	22544467	22544457	22544408	22641890	22544427	22641673
brown	78_Z-1-1-1	78_Z-1-2-1	78_Z-1-2-3	78_Z-1-3-4	78_Z-1-3-5	78_Z-1-4-4	78_Z-1-4-5
Item no.	22544448	22544468	22544458	22544416	22641664	22544436	22641674
red	78_Z-2-1-1	78_Z-2-2-1	78_Z-2-2-3	78_Z-2-3-4	78_Z-2-3-5	78_Z-2-4-4	78_Z-2-4-5
Item no.	22544449	22544469	22544459	22544415	22641665	22544435	22641675
orange	78_Z-3-1-1	78_Z-3-2-1	78_Z-3-2-3	78_Z-3-3-4	78_Z-3-3-5	78_Z-3-4-4	78_Z-3-4-5
Item no.	22544450	22544470	22544460	22544414	22641666	22544434	22641676
yellow	78_Z-4-1-1	78_Z-4-2-1	78_Z-4-2-3	78_Z-4-3-4	78_Z-4-3-5	78_Z-4-4-4	78_Z-4-4-5
Item no.	22544451	22544471	22544461	22544413	22641667	22544433	22641677
green	78_Z-5-1-1	78_Z-5-2-1	78_Z-5-2-3	78_Z-5-3-4	78_Z-5-3-5	78_Z-5-4-4	78_Z-5-4-5
Item no.	22544452	22544472	22544462	22544412	22641668	22544432	22641678
blue	78_Z-6-1-1	78_Z-6-2-1	78_Z-6-2-3	78_Z-6-3-4	78_Z-6-3-5	78_Z-6-4-4	78_Z-6-4-5
Item no.	22544453	22544473	22544463	22544411	22641669	22544431	22641679
violet	78_Z-7-1-1	78_Z-7-2-1	78_Z-7-2-3	78_Z-7-3-4	78_Z-7-3-5	78_Z-7-4-4	78_Z-7-4-5
Item no.	22544454	22544474	22544464	22544410	22641670	22544430	22641680
grey	78_Z-8-1-1	78_Z-8-2-1	78_Z-8-2-3	78_Z-8-3-4	78_Z-8-3-5	78_Z-8-4-4	78_Z-8-4-5
Item no.	22544455	22544475	22544465	22544409	22641671	22544429	22641681
white	78_Z-9-1-1	78_Z-9-2-1	78_Z-9-2-3	78_Z-9-3-4	78_Z-9-3-5	78_Z-9-4-4	78_Z-9-4-5
Item no.	22544456	22544476	22544466	22544508	22641672	22544428	22641682
length	20 mm/.79 in.	20 mm/.79 in.	20 mm/.79 in.	38 mm/1.5 in.	38 mm/1.5 in.	38 mm/1.5 in.	38 mm/1.5 in.
Assembly Tool	74_Z-0-2-1	74_Z-0-2-1	74_Z-0-2-1	74_Z-0-3-6	74_Z-0-3-6	74_Z-0-4-6	74_Z-0-4-6
Item no.	22543144	22543144	22543144	22544544	22544544	22544543	22544543

* without RG 302

The two types below are available in black only

Cable group	U29, U30, U34	U32, U36
example	RG 213/U	RG 214/U
colour black	78_Z-0-7-1	78_Z-0-7-2
Item no.	22641162	22641163
length	48 mm / 1.89 in.	48 mm / 1.89 in.
Assembly tool	74_Z-0-7-2	74_Z-0-7-3
Item no.	22641165	22641164



COLOURED PLASTIC CAPS

H+S type	Item no.	Packaging	Colour
61_BNC-0-0-7 /—_H	22543863	bulk 100 pcs.	black
61_BNC-1-0-7/—_H	22543864	bulk 100 pcs.	brown
61_BNC-2-0-7/—_H	22543865	bulk 100 pcs.	red
61_BNC-3-0-7/—_H	22543866	bulk 100 pcs.	orange
61_BNC-4-0-7/—_H	22543867	bulk 100 pcs.	yellow
61_BNC-5-0-7/—_H	22543868	bulk 100 pcs.	green
61_BNC-6-0-7/—_H	22543869	bulk 100 pcs.	blue
61_BNC-7-0-7/—_H	22543870	bulk 100 pcs.	violet
61_BNC-8-0-7/—_H	22543871	bulk 100 pcs.	grey
61_BNC-9-0-7/—_H	22543872	bulk 100 pcs.	white



Suitable for all HUBER+SUHNER® BNC plugs (can be pressed on to collar in front of coupling nut)

FASTENING SCREWS

for panel receptacles (pattern 13, 15, 23, 25)




Fig. 1




Fig. 2





Fig. 3

H+S type	Item no.	Packaging	Thread	Fig.
73_Z-0-0-2/—_3H	22543044	bulk 100 pcs.	3-56 UNF	1
73_Z-0-0-6/—_0H	22543050	bulk 100 pcs.	6-32 UNC	2
73_Z-0-0-7/—_3H	22543052	bulk 100 pcs.	6-32 UNC	3



INSULATING WASHERS




Fig. 1




Fig. 2




Fig. 3




Fig. 4




Fig. 5




Fig. 6




Fig. 7




Fig. 8




Fig. 9




Fig. 10

H+S type	Item no.	Suitable for:		Mounting hole	Material	Fig.	Notes
		Connector pattern *	Connector series				
77_Z-0-0-1/-_H	22543199	23, 25	N	ML 14	polyamide	1	10 pcs each
77_Z-0-0-2/-_H	22543200	12, 22	BNC, TNC	ML 102	polyamide	2	**/10 pairs
77_Z-0-0-4/-_Z	22543202	12,22,24,34	N	ML 113	polyamide	3	10 pairs
77_Z-0-0-8/-_H	22543204	82, 85	SMB/C/S, MCX, QLA 00, SMA	ML 41	PTFE	4	100 pcs
77_Z-0-0-9/-_Z	22543205	12, 22	BNC, TNC	ML 4	polycarbonate	5	**/10 pairs
77_Z-0-0-12/-_H	22543209	24, 34	BNC, TNC	ML 22	polycarbonate	6	10 pairs
77_Z-0-0-14/-_Z	22543211	22, 24, 34	QLA 00	ML 114	polyamide	7	**/10 pairs
77_Z-0-0-15/-_H	22641429	23, 25	BNC, TNC	ML 8	polyethylene	8	10 pcs each
77_Z-0-0-21/-_Z	22645782	22, 24, 34	SMB/C/S	ML 35	polycarbonate	9	10 pairs
77_Z-0-0-23/-_Z	22652083	22, 34***	SMA	ML 2	polycarbonate	10	for connectors with ML 35 only / 10 pairs

* see connector pattern on page 5

** without rotation protection

*** not all types of pattern 34 are suitable for insulated mounting

SOLDER TAGS




Fig. 1




Fig. 2




Fig. 3




Fig. 4




Fig. 5




Fig. 6




Fig. 7

H+S type	Item no.	Suitable for:		Packaging	Fig.	Notes
		Connector pattern*	Connector series			
72_Z-0-0-1/-_5H	22543029	12, 22	BNC, BNO, BNT, SHV, MHV, TNC	bulk 100 pcs.	1	single ended
72_Z-0-0-2/-_H	22543033	12, 22	BNC, BNO, BNT, SHV, MHV, TNC	bulk 100 pcs.	2	double ended
72_Z-0-0-6/-_0H	22543036	22, 24, 34	SMA	bulk 100 pcs.	3	single ended
72_Z-0-0-8/-_5H	22543038	22, 24	QLA 00	bulk 100 pcs.	4	single ended
72_Z-0-0-9/-_5H	22543039	12, 22, 24, 34	SMB/SMC/SMS, MCX	bulk 100 pcs.	5	single ended
72_Z-0-0-11/-_5H	22641496	24, 34	BNC, BNO, BNT, SHV, MHV, TNC	bulk 100 pcs.	6	single ended
72_Z-0-0-13/-_5H	22642507	22, 24, 34	N	bulk 100 pcs.	7	single ended


* see connector pattern on page 5

COMPONENT CONTAINER "SUCOBOX"


The HUBER+SUHNER "SUCOBOX" is a versatile component container with coaxial input and output connectors or cable entries.

SUCOBOX I

The basic element consists of two similar container parts, two soldering plates for easy soldering of the earthing and 8 tightening screws.



B = distance between pin end and soldering plate




H+S type	Item no.	Description	Length L	Material	Packaging
66_CB-35-0-1/-_E	22541510	basic element	35.0 mm / 1.38 in.	aluminium, anodized, blue	single
66_CB-50-0-1/-_E	22541514	basic element	50.0 mm / 1.97 in.	aluminium, anodized, blue	single
72_Z-0-0-5/-_OH	22543035	soldering plate, separate	—	brass, silver plated	bulk 100 pcs.
73_Z-0-0-9/-_H	22543056	shielding plate, separate	—	brass, silver plated	bulk 100 pcs.

Suitable connectors

H+S type	Item no.	Connector	Dimension B (see drawing top left)	Packaging
13_BNC-50-0-2/133_NE	22540160	plug	1.5 mm / 0.06 in.	single
23_BNC-50-0-2/133_NE	22540333	jack	8.0 mm / 0.31 in.	single
13_N-50-0-1/133_NE	22542173	plug	9.0 mm / 0.35 in.	single
23_N-50-0-1/133_NE	22542272	jack	9.0 mm / 0.35 in.	single


ACCESSORIES FOR SK CONNECTORS

Glass bead for 12 SK, 13 SK, 22 SK, 23 SK
connectors (package with 1 piece)



HUBER+SUHNER® TYPE
73_Z-0-0-203
Item no. 22645983


Microstrip stress relief contacts
(package with 100 pieces)



HUBER+SUHNER® TYPE
73_Z-0-0-204
Item no. 22645980
Mounting instruction 9183

ACCESSORIES FOR BMA CONNECTORS

Glass bead for 12_BMA-50-0-3
and 22_BMA-50-0-3



H+S type	Item no.	Ø A	Ø B	C	D	E
73_Z-0-0-198	22645655	0.5 mm / .020 in.	4.0 mm / .157 in.	1.75 mm / .069 in.	1.8 mm / .071 in.	5.6 mm / .220 in.

ACCESSORIES FOR HUBER+SUHNER QUICK-FIT®

Cold shrink tubes for additional protection




H+S type	Item no.	Packaging	Application of connector pair		
73_Z-0-0-337/—-Z	22658883	bulk 10 pcs.	3/8" - 1/2" 1/2" HF - 1/2" HF	3/8" EFX - 1/2" 1/2" HF - 1/2"	1/2" - 1/2"
73_Z-0-0-338/—-Z	22658884	bulk 10 pcs.	1/2" HF - 7/8" 7/8" - 7/8"	1/2" - 7/8"	
73_Z-0-0-339/—-Y	22658885	bulk (variable)	1/2" HF - 1 1/4" 1/2" HF - 1 5/8" 1/2" - 1 1/4" 1/2" - 1 5/8" 7/8" - 1 1/4" 7/8" - 1 5/8"		
73_Z-0-0-340/—-Y	22658886	bulk (variable)	1 1/4" - 1 1/4" 1 1/4" - 1 5/8" 1 5/8" - 1 5/8"		


MOUNTING HOLES, PCB LAYOUTS

DIMENSIONS OF MOUNTING HOLES (ML)


ML 1




ML 2




ML 3




ML 4



ML 5




rear panel mounting




front panel mounting

ML 6




rear panel mounting




front panel mounting

ML 7




rear panel mounting




front panel mounting

ML 8




rear panel mounting




front panel mounting

ML 9




rear panel mounting




front panel mounting


ML 10




ML 11




ML 12




ML 13




ML 14




ML 15



ML 16




rear panel mounting




front panel mounting

ML 17




rear panel mounting




front panel mounting

ML 18




rear panel mounting




front panel mounting


ML 19




ML 20




ML 21




ML 22




ML 23




ML 24




ML 25




ML 26




ML 27




ML 28




ML 29




ML 30




ML 31




ML 32




ML 33




ML 34



ML 35




ML 36



rear panel mounting

front panel mounting


ML 37




rear panel mounting

front panel mounting


ML 38




ML 39




ML 40




ML 41




ML 42




ML 43




ML 44





ML 45




ML 46




ML 47




ML 48




ML 49




ML 50




ML 51




ML 52




ML 53




ML 54




ML 55




ML 56




ML 57




ML 58




ML 59




ML 60




ML 61




ML 62




ML 63




ML 64




ML 65




ML 66




ML 67




ML 68




ML 69




ML 70




ML 71




ML 81




ML 82




ML 83




ML 84




ML 85




ML 86




ML 87




ML 88




ML 89




ML 90




ML 91




ML 92




ML 93




ML 94




ML 95




ML 96




ML 97




ML 98




ML 99




ML 100




ML 101




ML 102




ML 103





ML 104




ML 105




ML 106




ML 107




ML 108




ML 109




ML 110




ML 111




ML 112




ML 113




ML 114




ML 115




ML 118




ML 119




ML 128




ML 143



ML 146




ML 164




DIMENSIONS OF PCB LAYOUTS (ML)


ML 120




ML 121




ML 122



ML 123




ML 126




= Leiterzugmuster
 pattern
 = Lötfläche (frei von Lötstopplack)
 lands (free of solder mask)


ML 130



ML 131



ML 132



ML 134




Figure 10 shows a 4x4 grid of holes. The grid is 5.08 inches (200 mils) wide and 5.08 inches (200 mils) high. The holes are spaced 2.54 inches (100 mils) apart. The center hole is shaded. Dimensions are given in inches and mils.

[illegible]

Technical drawing of a mechanical part with dimensions in inches and millimeters. The drawing shows a cross-section of a part with a central rectangular hole and a smaller rectangular feature on the right side. The dimensions are as follows:

- Overall width: 5.1 (127)
- Overall height: 6 (152.4)
- Top left corner radius: R 1.1 (28)
- Top right corner radius: R 0.4 (10.16)
- Distance from top edge to center of hole: 2.7 (68.6)
- Distance from center of hole to right edge: 1.5 (38.1)
- Distance from right edge to center of smaller feature: 0.8 (20.3)
- Distance from center of hole to center of smaller feature: 2.3 (58.4)
- Distance from bottom edge to center of hole: 1.9 (48.3)
- Distance from bottom edge to center of smaller feature: 0.9 (22.9)
- Distance from center of hole to bottom edge of smaller feature: 1.6 (40.6)
- Bottom left corner radius: R 0.3 (7.62)
- Bottom right corner radius: R 0.7 (17.8)
- Bottom edge dimension: 5.1 (127)
- Bottom left corner radius: R 0.3 (7.62)
- Bottom right corner radius: R 0.7 (17.8)
- Bottom edge dimension: 5.1 (127)
- Bottom left corner radius: R 0.3 (7.62)
- Bottom right corner radius: R 0.7 (17.8)
- Bottom edge dimension: 5.1 (127)


[illegible]

A FURTHER HUBER+SUHNER PRODUCT GROUP!

WiMAX and WIFI antennas for broadband wireless



Details on this product are to be found in the brochure,
Item no. 84006561. Get your copy
free of charge at **www.hubersuhner.com**.





TYPE INDEX

Type	Page	Type	Page	Type	Page
7/16-Connectors		61_BNC-8-0-7/-_H	407	78_Z-0-7-1	407
11_716-50-0-2/003_E	317	61_BNC-9-0-7/-_H	407	78_Z-0-7-2	407
11_716-50-5-4/003_Z	309	66_CB-35-0-1/-_E	410	78_Z-1-1-1	406
11_716-50-5-6/003_Y	309	66_CB-50-0-1/-_E	410	78_Z-1-2-1	406
11_716-50-6-3/003_E	309	71_Z-0-3-21/-33_E	319	78_Z-1-2-3	406
11_716-50-7-1/003_E	310	71_Z-0-3-22/-33_E	319	78_Z-1-3-4	406
11_716-50-7-14/003_E	311	71_Z-0-7-21/-33_E	319	78_Z-1-3-5	406
11_716-50-7-2/003_E	310	71_Z-0-7-22/-33_E	319	78_Z-1-4-4	406
11_716-50-7-20/003_Z	310	71_Z-0-3-24/-33_E	320	78_Z-1-4-5	406
11_716-50-7-3/003_E	310	71_Z-0-7-23/-33_E	320	78_Z-2-1-1	406
11_716-50-7-4/003_E	310	71_Z-0-7-24/-33_E	320	78_Z-2-2-1	406
11_716-50-10-3/003_Z	311	72_Z-0-0-1/-_5H	409	78_Z-2-2-3	406
13_716-50-0-4/003_V	320	72_Z-0-0-11/-_5H	409	78_Z-2-3-4	406
16_716-50-5-2/003_Z	311	72_Z-0-0-13/-_5H	409	78_Z-2-3-5	406
16_716-50-7-10/003_E	312	72_Z-0-0-2/-_H	409	78_Z-2-4-4	406
16_716-50-7-11/003_E	312	72_Z-0-0-5/-_OH	410	78_Z-2-4-5	406
16_716-50-7-20/003_Z	312	72_Z-0-0-6/-_OH	409	78_Z-3-1-1	406
21_716-50-0-2/003_E	318	72_Z-0-0-8/-_5H	409	78_Z-3-2-1	406
21_716-50-5-400/003_Z	313	72_Z-0-0-9/-_5H	409	78_Z-3-2-3	406
21_716-50-7-1/003_E	313	73_Z-0-0-136/1-_UZ	138	78_Z-3-3-4	406
21_716-50-7-11/003_E	313	73_Z-0-0-138/1-_UZ	138	78_Z-3-3-5	406
21_716-50-7-2/003_E	313	73_Z-0-0-141/1-_UZ	138	78_Z-3-4-4	406
21_716-50-10-1/003_Z	314	73_Z-0-0-142/1-_UZ	139	78_Z-3-4-5	406
23_716-50-0-1/003_E	321	73_Z-0-0-151/1-_UZ	139	78_Z-4-1-1	406
23_716-50-0-57/003_V	321	73_Z-0-0-168	146	78_Z-4-2-1	406
24_716-50-0-1/003_E	318	73_Z-0-0-169	146	78_Z-4-2-3	406
24_716-50-5-400/003_Z	314	73_Z-0-0-170	146	78_Z-4-3-4	406
25_716-50-0-2/003_E	319	73_Z-0-0-198	411	78_Z-4-3-5	406
25_716-50-5-7/00_E	315	73_Z-0-0-2/-_3H	407	78_Z-4-4-4	406
25_716-50-6-2/003_V	315	73_Z-0-0-337/-_Z	411	78_Z-4-4-5	406
25_716-50-7-11/003_E	316	73_Z-0-0-338/-_Z	411	78_Z-5-1-1	406
25_716-50-7-21/003_Z	316	73_Z-0-0-339/-_Y	411	78_Z-5-2-1	406
29_716-50-5-400/003_Z	317	73_Z-0-0-340/-_Y	411	78_Z-5-2-3	406
61_716-0-0-3/-_H	321	73_Z-0-0-6/-_OH	407	78_Z-5-3-4	406
62_716-0-0-4/-_H	321	73_Z-0-0-7/-_3H	407	78_Z-5-3-5	406
		73_Z-0-0-9/-_H	410	78_Z-5-4-4	406
1.0/2.3-Connectors		77_Z-0-0-1/-_H	408	78_Z-5-4-5	406
11_1023-C50-2-2/111_NE	156	77_Z-0-0-12/-_H	408	78_Z-6-1-1	406
11_1023-C50-2-2/111_NH	156	77_Z-0-0-14/-_Z	408	78_Z-6-2-1	406
11_1023-C50-2-3/111_NE	156	77_Z-0-0-15/-_H	408	78_Z-6-2-3	406
11_1023-C50-2-3/111_NH	156	77_Z-0-0-2/-_H	408	78_Z-6-3-4	406
21_1023-C50-2-2/111_NE	156	77_Z-0-0-21/-_Z	408	78_Z-6-3-5	406
21_1023-C50-2-3/111_NE	156	77_Z-0-0-23/-_Z	408	78_Z-6-4-4	406
85_1023-C50-0-1/111_NE	156	77_Z-0-0-4/-_Z	408	78_Z-6-4-5	406
		77_Z-0-0-8/-_H	408	78_Z-7-1-1	406
		77_Z-0-0-9/-_Z	408	78_Z-7-2-1	406
Accessories		78_Z-0-1-1	406	78_Z-7-2-3	406
61_BNC-0-0-7 /-_H	407	78_Z-0-2-1	406	78_Z-7-3-4	406
61_BNC-1-0-7/-_H	407	78_Z-0-2-3	406	78_Z-7-3-5	406
61_BNC-2-0-7/-_H	407	78_Z-0-3-4	406	78_Z-7-4-4	406
61_BNC-3-0-7/-_H	407	78_Z-0-3-5	406	78_Z-7-4-5	406
61_BNC-4-0-7/-_H	407	78_Z-0-4-4	406	78_Z-8-1-1	406
61_BNC-5-0-7/-_H	407	78_Z-0-4-5	406	78_Z-8-2-1	406
61_BNC-6-0-7/-_H	407			78_Z-8-2-3	406
61_BNC-7-0-7/-_H	407			78_Z-8-3-4	406

Type	Page	Type	Page	Type	Page
78_Z-9-1-1	406	33_716-50-0-1/003_E	347	46_N-50-0-1/133_NE	345
78_Z-9-2-1	406	33_N-50-0-51/193_NE	344	46_N-50-0-1/133_UE	346
78_Z-9-2-3	406	33_N-50-0-52/199_UE	345	46_SMA-50-0-1/111_NE	337
78_Z-9-3-4	406	33_N-50-0-7/133_NE	344	46_SMB-50-0-2/111_NE	335
78_Z-9-3-5	406	33_PC35-50-0-1/199_UE	338	46_SMC-50-0-2/111_NE	336
78_Z-9-4-4	406	33_PC35-50-0-2/199_NE	338	46_TNC-50-0-1/133_NE	343
78_Z-9-4-5	406	33_QMA-50-0-1/1-_NE	340		
		33_SK-50-0-1/199_NE	338	53_716-50-0-1/003_NE	348
83_CT-0-1-1/-11_NE	404	33_SMA-50-0-1/111_NE	336	53_BNC-50-0-1/133_NE	341
83_CT-0-2-1/-11_NE	404	33_SMA-50-0-51/199_NE	336	53_BNC-75-0-1/133_NE	342
83_CT-0-2-1/-11_NH	404	33_TNC-50-0-1/133_NE	343	53_N-50-0-4/133_NE	346
83_CT-0-2-2/-11_NE	404			53_N-50-0-4/133_UE	346
83_CT-0-2-3/-11_NE	404	34_716-50-0-1/003_E	347	53_N-75-0-4/133_NE	346
83_CT-0-2-4/-11_NE	404	34_716-50-0-2/003_E	347	53_QLA-01-0-1/112_NE	339
83_CT-0-2-4/-11_NH	404	34_BNC-50-0-1/133_NE	340	53_SMA-50-0-51/199_NE	337
83_CT-0-3-1/-23_E	403	34_BNC-50-0-1/133_UE	340	53_TNC-50-0-1/133_NE	344
83_CT-0-3-2/-23_E	403	34_BNC-50-0-2/133_NE	340	53_TNC-50-0-1/133_UH	344
86_CT-0-1-1/111_NE	405	34_BNC-50-0-6/100_NE	340		
86_CT-0-1-1/111_NH	405	34_BNC-75-0-1/133_NE	341	Adaptors Between Series	
86_CT-0-2-1/111_NH	405	34_BNC-75-0-2/133_NE	342	31_BMA-SMA-50-1/1-9_UE	352
86_CT-0-2-2/111_NE	405	34_MCX-50-0-2/111_NE	334	31_BNC-MCX-50-1/1-_UE	353
86_CT-0-2-3/111_NE	405	34_MCX-75-0-1/111_NE	334	31_BNC-MMCX-50-1/1-_UE	353
86_CT-0-2-5/111_NH	405	34_MMCX-50-0-1/111_OE	334	31_BNC-N-50-1/133_UE	354
		34_N-50-0-1/133_NE	345	31_BNC-N-75-1/133_UE	354
		34_N-50-0-1/133_UE	345	31_BNC-SMA-50-1/1-_UE	356
		34_N-50-0-3/133_NE	345	31_BNC-SMB-50-2/1-_UE	356
		34_N-50-0-51/193_NE	345	31_BNC-SMC-50-2/1-_NE	357
		34_N-75-0-1/133_NE	346	31_BNC-TNC-50-1/133_NE	357
		34_QLA-01-0-2/112_NE	339	31_MCX-N-50-1/1-_UE	359
		34_SK-50-0-51/199_NE	339	31_MCX-N-75-10/133_NE	359
		34_SMA-50-0-1/111_NH	337	31_MCX-SMA-50-1/111_NE	360
		34_SMA-50-0-3/111_NE	337	31_MMBX-SMA-50-1/111_NE	358
		34_SMA-50-0-51/199_NE	337	31_MMCX-SMA-50-1/111_OE	359
		34_SMB-50-0-2/111_NE	335	31_N-716-50-1/-_UE	364
		34_SMC-50-0-2/111_NE	335	31_N-SMA-50-1/1-_UE	361
		34_TNC-50-0-1/133_NE	343	31_N-SMB-50-1/1-_UE	362
		34_TNC-50-0-4/133_NE	343	31_N-SMC-50-1/1-_NE	363
				31_N-TNC-50-1/133_UE	363
		37_716-50-0-1/003_E	347	31_SMA-SMB-50-1/111_UE	365
		37_BNC-50-0-1/133_NE	340	31_SMA-TNC-50-1/1-_UE	366
		37_BNC-50-0-2/133_NE	341		
		37_BNC-75-0-1/133_NE	342	32_BMA-SMA-50-1/199_UE	352
		37_BNC-75-0-2/133_NE	342	32_BNC-MCX-50-1/1-_UE	353
		37_N-50-0-1/133_NE	345	32_BNC-MMCX-50-1/1-_UE	353
		37_N-75-0-1/133_NE	346	32_BNC-N-50-1/133_UE	354
		37_TNC-50-0-1/133_NE	343	32_BNC-N-75-1/133_UE	355
		37_TNC-50-0-2/133_NE	343	32_BNC-SMA-50-1/1-_UE	356
		39_PC35-50-0-1/199_UE	338	32_BNC-SMB-50-2/1-_UE	356
				32_BNC-SMC-50-2/1-_NE	357
		43_716-50-0-1/003_NE	347	32_BNC-TNC-50-1/133_NE	358
		43_BNC-50-0-1/133_NE	341	32_MCX-N-50-1/1-_UE	360
		43_BNC-75-0-1/133_NE	342	32_MCX-SMA-50-1/111_NE	360
		43_N-50-0-1/133_NE	345	32_MMBX-SMA-50-1/119_NE	358
		43_QLA-01-0-1/112_NE	339	32_MMCX-SMA-50-1/111_OE	359
		43_SMA-50-0-1/111_NE	337	32_N-716-50-1/-_NE	364
		43_SMB-50-0-2/111_NE	335	32_N-SMA-50-1/11-_NE	361
		43_SMC-50-0-2/111_NE	336	32_N-SMB-50-1/1-_UE	362
		43_TNC-50-0-1/133_NE	343	32_N-SMC-50-1/1-_NE	363
		45_BNC-50-0-2/133_NE	341	32_N-TNC-50-1/-_UE	364
		45_BNC-75-0-1/133_NE	342	32_SMA-TNC-50-1/1-_UE	366
		45_QLA-01-0-1/112_NE	339		
		46_716-50-0-1/003_NE	347	33_716-N-50-1/-_UE	364
		46_BNC-50-0-1/133_NE	341	33_BMA-SMA-50-1/199_UE	352
		46_BNC-75-0-1/133_NE	342	33_BNC-MCX-50-1/1-_UE	354

Adaptors

Adaptors Within Series

Type	Page
33_BNC-MCX-75-1/1-NE	354
33_BNC-MMCX-50-1/1-NE	353
33_BNC-N-50-1/133_NE	355
33_BNC-N-75-1/133_NE	355
33_BNC-QLA-01-1/1-NE	355
33_BNC-SMA-50-1/1-UE	356
33_BNC-SMB-50-2/1-UE	357
33_BNC-SMC-50-2/1-NE	357
33_BNC-TNC-50-1/133_NE	358
33_MCX-BNC-50-1/1-UE	354
33_MCX-BNC-75-1/1-NE	354
33_MCX-N-50-1/1-UE	360
33_MCX-SMA-50-1/111_UE	360
33_MMBX-SMA-50-1/111_NE	358
33_MMCX-BNC-50-1/111_UE	353
33_MMCX-SMA-50-1/111_UE	359
33_N-716-50-1/-UE	364
33_N-BNC-50-1/133_UE	355
33_N-BNC-75-1/133_UE	355
33_N-MCX-50-1/1-UE	360
33_N-MCX-75-1/1-NE	360
33_N-QLA-01-1/1-NE	361
33_N-SMA-50-1/113_UE	361
33_N-SMB-50-1/1-UE	362
33_N-SMC-50-1/1-NE	363
33_N-TNC-50-1/133_NE	364
33_QLA-BNC-01-1/1-NE	355
33_SMA-BMA-50-1/1-9_UE	352
33_SMA-BNC-50-1/1-NE	356
33_SMA-MCX-50-1/111_NE	361
33_SMA-MMBX-50-1/119_NE	359
33_SMA-MMCX-50-1/111_NE	359
33_SMA-N-50-1/1-UE	362
33_SMA-TNC-50-1/1-NE	366
33_SMB-BNC-50-2/1-UE	357
33_SMB-N-50-1/1-UE	362
33_SMB-SMA-50-1/111_UE	366
33_SMB-TNC-50-2/1-UE	366
33_SMC-BNC-50-2/1-NE	357
33_SMC-N-50-1/1-NE	363
33_TNC-BNC-50-1/133_NE	358
33_TNC-BNC-75-1/133_UE	358
33_TNC-N-50-1/133_UE	364
33_TNC-N-75-1/133_UE	364
33_TNC-SMA-50-1/1-UE	366
34_BMA-SMA-50-2/1-UE	352
34_BNC-MCX-50-2/133_UE	354
34_BNC-N-50-1/133_UE	355
34_BNC-QLA-01-1/1-UE	356
34_BNC-SMA-50-2/1-UE	356
34_BNC-SMB-50-1/133_NH	357
34_MCX-N-50-1/133_UE	360
34_MCX-TNC-50-1/133_UE	361
34_N-SMA-50-1/193_UE	362
34_N-SMB-50-1/1-UE	363
35_BMA-SMA-50-1/193_UE	352
36_BMA-SMA-50-1/199_UE	352
37_BMA-SMA-50-1/1-UE	352
37_BNC-TNC-50-1/133_UE	358
37_N-716-50-1/003_E	365
37_N-SMA-50-1/1-UE	362
37_N-SMB-50-1/1-UE	363
37_N-SMC-50-1/1-UE	363
39_SMA-N-50-1/1-NE	362

Type	Page
Precision Adaptors	
31_BNC-N-50-51/1-UE	370
31_N-4195-50-12/139_UE	371
31_N-716-50-51/33_NE	372
31_N-PC35-50-1/1-UE	372
31_N-SMA-50-51/1-NE	374
31_N-SMA-50-51/1-UE	374
31_N-TNC-50-51/1-UE	375
31_PC24-SK-50-1/199_NE	378
31_SK-SMPX-50-1/199_NE	378
31_SK-SMPX-50-2/199_NE	379
31_SK-SMPX-50-3/199_NE	379
32_4195-N-50-1/1-UE	371
32_BNC-N-50-51/1-UE	370
32_BNC-PC7-50-1/1-UE	370
32_N-716-50-51/33_NE	372
32_N-PC35-50-1/1-UE	373
32_N-PC7-50-1/1-UE	373
32_N-SMA-50-51/1-UE	374
32_N-TNC-50-51/1-UE	375
32_PC24-SK-50-1/199_NE	378
32_PC7-716-50-1/-3_NE	376
32_PC7-PC35-50-1/1-UE	376
32_PC7-SMA-50-1/-UE	377
32_PC7-TNC-50-1/1-UE	377
33_4195-716-50-1/-33_NE	372
33_4195-N-50-1/-UE	372
33_716-N-50-51/33_NE	372
33_BNC-N-50-51/-UE	370
33_MCX-PC35-50-1/111_NE	371
33_N-4195-50-51/1-3_UE	372
33_N-716-50-51/33_NE	372
33_N-BNC-50-51/1-UE	370
33_N-PC24-50-1/199_UE	378
33_N-PC35-50-1/1-UE	373
33_N-QMA-50-1/133_NE	374
33_N-SMA-50-51/1-NE	375
33_N-SMA-50-51/1-UE	374
33_N-TNC-50-51/1-UE	375
33_PC24-N-50-1/199_NE	378
33_PC24-SK-50-2/199_NE	378
33_PC35-MCX-50-1/111_NE	371
33_PC35-N-50-1/1-UE	373
33_PC7-716-50-1/-3_NE	376
33_PC7-BNC-50-1/1-UE	370
33_PC7-N-50-1/1-UE	373
33_PC7-PC35-50-1/1-UE	377
33_PC7-SMA-50-1/1-UE	377
33_QMA-N-50-1/133_NE	374
33_SK-PC24-50-1/199_NE	378
33_SK-SMPX-50-1/199_NE	379
33_SK-SMPX-50-2/199_NE	379
33_SK-SMPX-50-3/199_NE	379
33_SMA-MMCX-50-2/111_NE	371
33_SMA-N-50-51/1-NE	375
33_SMA-N-50-51/1-UE	375
33_SMPX-SK-50-1/199_NE	379
33_TNC-N-50-51/-UE	375
37_N-SMA-50-51/1-NE	375
39_PC35-N-50-1/1-UE	373

Type	Page
Quick-Mate Adaptors	
31_716-N-Q50-1/1-3_NE	380
32_N-PC7-Q50-4/1-NE	381
33_716-N-Q50-4/133_UE	380
33_BNC-N-Q50-4/133_NE	380
33_N-Q50-0-14/13-NE	380
33_N-Q50-0-4/133_NE	380
33_PC7-N-Q50-4/1-NE	381
33_SMA-N-Q50-4/1-3_NE	381
33_SMA-Q50-0-4/1-9_NE	380
33_TNC-N-Q50-4/133_NE	381
PIM Adaptors	
31_4195-716-50-1/133_WE	382
31_716-50-0-2/133_WE	382
31_N-716-50-2/133_WE	382
31_PC35-716-50-1/133_WE	383
31_TNC-716-50-1/133_WE	384
32_4195-716-50-1/133_WE	382
32_716-50-0-2/133_WE	382
32_N-716-50-2/133_WE	382
32_PC35-716-50-1/133_WE	383
32_TNC-716-50-1/133_WE	384
33_716-50-0-2/133_WE	382
33_716-N-50-3/133_WE	382
33_716-PC35-50-1/133_WE	383
33_716-TNC-50-1/133_WE	384
33_N-716-50-3/133_WE	383
Assembly Tools	
74_Z00-1	395
74_Z00-10	389
74_Z00-115	398
74_Z00-116	398
74_Z00-12	398
74_Z00-12	400
74_Z00-13	398
74_Z00-14	389
74_Z00-142	391
74_Z00-147	395
74_Z00-157	391
74_Z00-16	395
74_Z00-160	391
74_Z00-164	391
74_Z00-17	395
74_Z00-174	395
74_Z00-177	398
74_Z00-18	395
74_Z00-189	395
74_Z00-19	395
74_Z00-192	395
74_Z00-193	395
74_Z00-196	391
74_Z00-197	391
74_Z00-198	391
74_Z00-199	391
74_Z00-2	395
74_Z00-207	391
74_Z00-208	391
74_Z00-209	391

Typ	Seite	Typ	Seite	Typ	Seite
74_Z-0-21	389	74_Z-0-426	400	75_Z-0-1	386
74_Z-0-21	395	74_Z-0-427	400	75_Z-0-2	387
74_Z-0-210	391	74_Z-0-428	400	75_Z-0-50	386
74_Z-0-211	394	74_Z-0-429	400	75_Z-0-51	386
74_Z-0-213	391	74_Z-0-430	400	75_Z-0-3-4	385
74_Z-0-214	394	74_Z-0-431	400	75_Z-0-4-4	385
74_Z-0-215	394	74_Z-0-432	400		
74_Z-0-225	396	74_Z-0-433	400	76_Z-0-1	388
74_Z-0-226	394	74_Z-0-434	400	76_Z-0-11	387
74_Z-0-227	394	74_Z-0-437	50	76_Z-0-15	386
74_Z-0-228	394	74_Z-0-441	393	76_Z-0-2	388
74_Z-0-229	398	74_Z-0-442	393	76_Z-0-26	388
74_Z-0-230	394	74_Z-0-443	393	76_Z-0-3	388
74_Z-0-231	391	74_Z-0-45	395	76_Z-0-9	387
74_Z-0-232	392	74_Z-0-459	396	76_Z-0-10-14	388
74_Z-0-233	392	74_Z-0-459	397	76_Z-0-1-1	386
74_Z-0-234	392	74_Z-0-52	390	76_Z-0-1-2	388
74_Z-0-235	394	74_Z-0-53	390	76_Z-0-2-1	388
74_Z-0-236	398	74_Z-0-54	390	76_Z-0-2-20	386
74_Z-0-237	398	74_Z-0-55	390	76_Z-0-2-51	386
74_Z-0-238	398	74_Z-0-555_--_E	397	76_Z-0-2-53	386
74_Z-0-24	389	74_Z-0-556_--_E	397	76_Z-0-2-8	388
74_Z-0-24	398	74_Z-0-557	50	76_Z-0-3-1	388
74_Z-0-246	392	74_Z-0-56	390	76_Z-0-3-51	386
74_Z-0-25	398	74_Z-0-58	390	76_Z-0-3-9	388
74_Z-0-264	392	74_Z-0-59	390	76_Z-0-4-1	388
74_Z-0-265	392	74_Z-0-60	390	76_Z-0-4-51	386
74_Z-0-270	392	74_Z-0-600	399	76_Z-0-4-8	388
74_Z-0-272	396	74_Z-0-61	390	76_Z-0-5-21	388
74_Z-0-276	396	74_Z-0-62	390	76_Z-0-5-8	388
74_Z-0-29	389	74_Z-0-63	390	76_Z-0-6-1	388
74_Z-0-297	401	74_Z-0-66	390	76_Z-0-6-21	388
74_Z-0-3	395	74_Z-0-67	390	76_Z-0-7-1	388
74_Z-0-30	396	74_Z-0-68	391	76_Z-0-7-14	388
74_Z-0-321	395	74_Z-0-70	389	76_Z-0-7-7	388
74_Z-0-346	401	74_Z-0-71	389	76_Z-0-7-8	388
74_Z-0-347	401	74_Z-0-72	389		
74_Z-0-348	401	74_Z-0-73	391	BMA-Verbinder	
74_Z-0-349	401	74_Z-0-75	391	12_BMA-50-0-3/199_NE	174
74_Z-0-35	390	74_Z-0-77	395	13_BMA-50-0-1/199_NE	175
74_Z-0-350	396	74_Z-0-78	395	13_BMA-50-0-13/199_NE	175
74_Z-0-355	401	74_Z-0-79	395	13_BMA-50-0-2/199_NE	176
74_Z-0-356	401	74_Z-0-80	395	14_BMA-50-1-15/111_NE	171
74_Z-0-359	400	74_Z-0-81	391	14_BMA-50-2-2/111_NE	171
74_Z-0-360	396	74_Z-0-82	398	14_BMA-50-2-3/199_NE	171
74_Z-0-368	392	74_Z-0-89	398	14_BMA-50-3-2/111_NE	171
74_Z-0-369	392	74_Z-0-12-15	399	14_BMA-50-3-3/199_NE	171
74_Z-0-37	395	74_Z-0-12-15	400	15_BMA-50-1-15/111_NE	172
74_Z-0-373	395	74_Z-0-23-16	399		
74_Z-0-374	392	74_Z-0-23-16	400	22_BMA-50-0-3/199_NE	175
74_Z-0-375	393	74_Z-0-23-17	399	23_BMA-50-0-1/199_NE	176
74_Z-0-38	395	74_Z-0-23-17	400	24_BMA-50-2-4/111_NE	172
74_Z-0-390	397	74_Z-0-3-2	393	24_BMA-50-2-5/119_NE	173
74_Z-0-391	397	74_Z-0-32-14	399	24_BMA-50-3-4/111_NE	172
74_Z-0-402	400	74_Z-0-32-14	400	24_BMA-50-3-5/119_NE	173
74_Z-0-415	400	74_Z-0-3-4	393	25_BMA-50-2-2/119_NE	173
74_Z-0-416	401	74_Z-0-42-14	399	25_BMA-50-2-3/119_NE	174
74_Z-0-418	400	74_Z-0-42-14	400	25_BMA-50-3-2/119_NE	173
74_Z-0-420	400	74_Z-0-8-15	399	25_BMA-50-3-3/119_NE	174
74_Z-0-421	401	74_Z-0-8-15	400		
74_Z-0-422	400	74_Z-0-9-15	399	81_BMA-50-0-1/111_NE	176
74_Z-0-423	401	74_Z-0-9-15	400	82_BMA-50-0-1/111_NE	177
74_Z-0-424	400				
74_Z-0-425	400				

Type	Page	Type	Page	Type	Page
BNC 50Ω-Connectors		23_BNC-50-0-16/133_NE	214	16_BNC-75-2-5/133_NE	222
11_BNC-50-1-1/133_NE	202	23_BNC-50-0-2/133_NE	213	16_BNC-75-3-4/133_NE	222
11_BNC-50-1-5/133_NE	203	24_BNC-50-1-1/133_NE	208	16_BNC-75-4-4/133_NE	222
11_BNC-50-2-1/133_NE	202	24_BNC-50-1-6/133_NE	208	16_BNC-75-4-5/133_NE	222
11_BNC-50-2-13/133_NE	203	24_BNC-50-1-6/133_NH	208	21_BNC-75-2-5/133_NE	223
11_BNC-50-2-13/133_NH	203	24_BNC-50-2-1/133_NE	208	21_BNC-75-2-5/133_NH	223
11_BNC-50-2-14/133_NE	203	24_BNC-50-2-13/133_NE	208	21_BNC-75-2-7/133_NE	223
11_BNC-50-2-14/133_NH	203	24_BNC-50-2-13/133_NH	208	21_BNC-75-4-4/133_NE	223
11_BNC-50-2-16/133_NE	203	24_BNC-50-2-14/133_NE	208	21_BNC-75-4-5/133_NE	223
11_BNC-50-2-16/133_NH	203	24_BNC-50-2-14/133_NH	208	22_BNC-75-0-1/133_NE	225
11_BNC-50-2-20/103_NE	202	24_BNC-50-2-20/133_NE	207	22_BNC-75-0-4/133NE	225
11_BNC-50-3-1/133_NE	202	24_BNC-50-2-29/133_NE	209	23_BNC-75-0-10/133_NE	225
11_BNC-50-3-16/133_NE	203	24_BNC-50-3-1/133_NE	208	24_BNC-75-2-12/133_NE	223
11_BNC-50-3-16/133_NH	203	24_BNC-50-3-25/133_NE	208	24_BNC-75-2-15/133_NE	224
11_BNC-50-3-36/133_NE	203	24_BNC-50-3-25/133_NH	208	24_BNC-75-2-15/133_NH	224
11_BNC-50-3-4/133_NE	203	24_BNC-50-3-33/133_NE	207	24_BNC-75-2-6/133_NE	223
11_BNC-50-3-4/133_NH	203	24_BNC-50-3-5/133_NE	208	24_BNC-75-2-6/133_NH	223
11_BNC-50-3-5/133_NE	202	24_BNC-50-3-8/133_NE	208	24_BNC-75-3-4/133_NE	224
11_BNC-50-3-52/133_NE	203	24_BNC-50-7-3/133_NE	209	24_BNC-75-3-5/133_NE	224
11_BNC-50-3-52/133_NH	203	25_BNC-50-2-13/133_NE	210	24_BNC-75-4-15/133_NE	224
11_BNC-50-3-54/103_NE	202	25_BNC-50-2-14/133_NE	210	24_BNC-75-4-3/133_NE	224
11_BNC-50-3-58/133_NE	203	25_BNC-50-2-16/133_NE	210	24_BNC-75-4-4/133_NE	224
11_BNC-50-3-58/133_NH	203	25_BNC-50-3-13/133_NE	210	25_BNC-75-2-7/133_NE	224
11_BNC-50-4-23/133_NE	203	27_BNC-50-0-1/133_NE	214	25_BNC-75-2-8/133_NE	224
11_BNC-50-4-4/133_NE	203	28_BNC-50-0-2/133_NE	215	61_BNC-0-0-1/-33_E	227
11_BNC-50-4-4/133_NH	203	61_BNC-0-0-1/-33_E	216	62_BNC-0-0-1/-33_E	227
11_BNC-50-7-1/133_NE	203	62_BNC-0-0-1/-33_E	216	62_BNC-0-0-2/-_H	227
11_BNC-50-7-2/133_NE	203	62_BNC-0-0-2/-_H	216	62_BNC-0-0-3/-33_E	227
11_BNC-50-7-6/133_NE	204	62_BNC-0-0-3/-33_E	216	82_BNC-75-0-2/122_NE	226
11_BNC-50-7-7/133_NE	204	64_BNC-50-0-1/133_NE	216	82_BNC-75-0-2/122_NH	226
12_BNC-50-0-1/133_NE	211	82_BNC-50-0-1/111_NH	215	85_BNC-75-0-1/133_NE	226
13_BNC-50-0-1/133_NE	213	82_BNC-50-0-1/133_NE	215	85_BNC-75-0-1/133_NH	226
13_BNC-50-0-2/133_NE	213	82_BNC-50-0-1/133_NH	215		
16_BNC-50-2-3/133_NE	205	85_BNC-50-0-1/111_NE	215		
16_BNC-50-2-3/133_NH	205	85_BNC-50-0-1/133_NE	215		
16_BNC-50-2-5/133_NE	205			BNO-Connectors	
16_BNC-50-2-5/133_NH	205			11_BNO-0-4-1/133_NE	252
16_BNC-50-2-9/133_NE	204			11_BNO-0-4-1/133_NH	252
16_BNC-50-3-13/133_NE	206			16_BNO-0-4-1/133_NE	252
16_BNC-50-3-25/133_NE	204	BNC 75Ω-Connectors		21_BNO-0-4-1/133_NE	252
16_BNC-50-3-5/133_NE	205	11_BNC-75-2-1/133_NE	220	22_BNO-0-0-1/133_NE	253
16_BNC-50-3-7/133_NE	205	11_BNC-75-2-12/133_NE	220	22_BNO-0-0-2/133_NE	253
16_BNC-50-3-7/133_NH	205	11_BNC-75-2-15/133_NE	221	23_BNO-0-0-1/133_NE	254
16_BNC-50-7-6/133_NE	205	11_BNC-75-2-15/133_NH	221	23_BNO-0-0-2/133_NE	254
		11_BNC-75-2-18/133_NH	221	24_BNO-0-4-1/133_NE	253
21_BNC-50-1-4/133_NE	207	11_BNC-75-2-21/133_NE	221		
21_BNC-50-2-1/133_NE	206	11_BNC-75-2-21/133_NH	221		
21_BNC-50-2-10/133_NE	207	11_BNC-75-3-11/133_NE	220	BNT-Connectors	
21_BNC-50-2-9/133_NE	207	11_BNC-75-3-8/133_NE	221	11_BNT-50-2-1/103_NE	258
21_BNC-50-3-12/133_NE	206	11_BNC-75-3-9/133_NE	221	11_BNT-50-3-1/103_NE	258
21_BNC-50-3-2/133_NE	207	11_BNC-75-4-3/133_NE	220	11_BNT-50-4-1/103_NE	258
21_BNC-50-3-9/133_NE	207	11_BNC-75-4-30/133_NE	221	22_BNT-50-0-1/103_NE	259
		11_BNC-75-4-4/133_NE	221	22_BNT-50-0-2/103_NE	259
22_BNC-50-0-16/133_NE	212	11_BNC-75-4-4/133_NH	221	23_BNT-50-0-1/103_NE	259
22_BNC-50-0-2/133_NE	211	11_BNC-75-4-6/133_NE	221	23_BNT-50-0-2/103_NE	259
22_BNC-50-0-24/100_NE	212	11_BNC-75-4-6/133_NH	221	24_BNT-50-2-1/103_NE	258
22_BNC-50-0-3/133_NE	211	11_BNC-75-5-6/133_NE	221	24_BNT-50-3-1/103_NE	258
22_BNC-50-0-3/133_NH	211	11_BNC-75-7-5/133_NE	221		
22_BNC-50-0-4/133_NE	212	11_BNC-75-7-6/133_NE	221		
22_BNC-50-0-5/133_NE	212				
22_BNC-50-0-5/133_NH	212	16_BNC-75-2-3/133_NE	222		
23_BNC-50-0-12/133_NE	214	16_BNC-75-2-3/133_NH	222		

Type Page

MCX 50Ω-Connectors

11_MCX-50-1-13/111_NH	78
11_MCX-50-1-13/133_NH	78
11_MCX-50-1-14/111_NE	78
11_MCX-50-2-15/111_NE	78
11_MCX-50-2-15/111_NH	78
11_MCX-50-2-15/133_NH	78
11_MCX-50-2-16/111_NE	78
11_MCX-50-2-16/111_NH	78
11_MCX-50-2-16/133_NH	78
11_MCX-50-2-19/111_NH	78
11_MCX-50-3-1/111_NE	78
11_MCX-50-3-1/111_NH	78
16_MCX-50-1-11/111_NE	79
16_MCX-50-1-11/111_NH	79
16_MCX-50-1-7/111_NH	79
16_MCX-50-1-7/133_NH	79
16_MCX-50-2-102/111_NH	80
16_MCX-50-2-104/111_NH	79
16_MCX-50-2-11/111_NH	79
16_MCX-50-2-11/133_NE	79
16_MCX-50-2-11/133_NH	79
16_MCX-50-2-14/111_NH	79
16_MCX-50-2-14/133_NE	79
16_MCX-50-2-14/133_NH	79
16_MCX-50-3-8/111_NH	79
21_MCX-50-1-11/111_NE	80
21_MCX-50-1-11/111_NH	80
21_MCX-50-2-12/111_NE	80
21_MCX-50-2-12/133_NH	80
21_MCX-50-2-13/111_NH	80
21_MCX-50-2-13/133_NH	80
22_MCX-50-0-19/111_NH	82
22_MCX-50-0-19/133_NH	82
22_MCX-50-0-2/111_NE	82
22_MCX-50-0-2/111_NH	82
22_MCX-50-0-2/133_NE	82
22_MCX-50-0-2/133_NH	82
24_MCX-50-1-13/111_NH	81
24_MCX-50-1-13/133_NH	81
24_MCX-50-1-3/111_NE	81
24_MCX-50-2-3/111_NE	81
24_MCX-50-2-6/111_NH	81
24_MCX-50-2-7/111_NH	81
81_MCX-50-0-6/111_NE	82
81_MCX-50-0-6/111_NH	82
81_MCX-50-0-9/111_NH	82
82_MCX-50-0-10/111_NE	83
82_MCX-50-0-10/111_NH	83
82_MCX-50-0-17/111_NH	83
82_MCX-50-0-19/111_NE	83
82_MCX-50-0-19/111_NH	83
82_MCX-50-0-19/111_NM	83
82_MCX-50-0-29/111_NE	83
82_MCX-50-0-29/111_NH	83
82_MCX-50-0-29/111_NM	83
82_MCX-S50-0-22/111_NE	84
82_MCX-S50-0-22/111_NM	84
85_MCX-50-0-16/111_NE	84
85_MCX-50-0-16/111_NH	84

Type Page

85_MCX-50-0-16/111_NM	84
85_MCX-S50-0-25/111_NH	84
85_MCX-S50-0-25/111_NM	84

MCX 75Ω-Connectors

11_MCX-75-2-1/113_NE	88
11_MCX-75-2-6/113_NE	88
16_MCX-75-2-5/133_NH	88
24_MCX-75-2-1/113_NE	88
82_MCX-75-0-4/111_NE	89
82_MCX-75-0-4/111_NH	89
82_MCX-75-0-5/111_NH	89
82_MCX-S75-0-2/111_NE	89
82_MCX-S75-0-2/111_NH	89
82_MCX-S75-0-2/111_NM	89
85_MCX-75-0-1/111_NE	89
85_MCX-75-0-1/111_NH	89

MHV-Connectors

11_H4-50-3-1/133_NE	270
11_H4-50-3-3/133_NE	270
11_H4-50-4-1/133_NE	270
11_H4-50-4-4/133_NE	270
12_H4-50-0-1/133_NE	272
21_H4-50-3-1/133_NE	270
22_H4-50-0-1/133_NE	271
22_H4-50-0-6/100_NE	271
23_H4-50-0-7/133_NE	272
23_H4-50-0-8/133_NE	272
24_H4-50-3-1/133_NE	271

MMBX-Connectors

11_MMBX-50-1-1/111_NE	43
11_MMBX-50-2-1/111_NE	43
11_MMBX-50-2-2/111_NE	43
11_MMBX-50-2-4/111_NE	43
11_MMBX-50-2-4/111_NH	43
16_MMBX-50-1-1/111_NE	44
16_MMBX-50-1-2/111_NH	43
16_MMBX-50-2-1/111_NE	44
16_MMBX-50-2-1/111_NH	44
16_MMBX-50-2-2/111_NE	44
16_MMBX-50-2-2/111_NH	44
16_MMBX-50-2-4/111_NE	43
16_MMBX-50-2-4/111_NH	43
22_MMBX-50-0-1/111_NE	44
22_MMBX-50-0-2/111_NY	44
32_MMBX-50-0-1/111_NE	48
32_MMBX-50-0-1/111_NY	48
32_MMBX-50-0-10/111_NY	48
32_MMBX-50-0-11/111_NE	48
32_MMBX-50-0-12/111_NH	48
32_MMBX-50-0-13/111_NE	48
32_MMBX-50-0-14/111_NY	48
32_MMBX-50-0-15/111_NY	48
32_MMBX-50-0-3/111_NE	48
32_MMBX-50-0-4/111_NE	48
32_MMBX-50-0-4/111_NY	48
32_MMBX-50-0-5/111_NE	48
32_MMBX-50-0-5/111_NY	48

Type Page

32_MMBX-50-0-6/111_NE	48
32_MMBX-50-0-6/111_NH	48
32_MMBX-50-0-8/111_NE	48
32_MMBX-50-0-9/111_NH	48
35_MMBX-50-0-1/111_NE	49
35_MMBX-50-0-1/111_NH	49
35_MMBX-50-0-5/111_NY	49
35_MMBX-U50-0-9/113_NY	49

81_MMBX-50-0-11/111_NM	45
81_MMBX-50-0-2/111_NE	45
81_MMBX-50-0-2/111_NH	45
81_MMBX-50-0-2/111_NM	45
81_MMBX-S50-0-1/111_NE	45
81_MMBX-S50-0-1/111_NH	45
81_MMBX-S50-0-1/111_NM	45
82_MMBX-50-0-14/111_NE	47
82_MMBX-50-0-14/111_NH	47
82_MMBX-50-0-2/111_NE	47
82_MMBX-50-0-2/111_NH	47
82_MMBX-50-0-2/111_NM	47
82_MMBX-50-0-4/111_NH	47
82_MMBX-S50-0-1/111_NE	46
82_MMBX-S50-0-1/111_NH	46
82_MMBX-S50-0-1/111_NM	46
82_MMBX-S50-0-13/111_NE	46
82_MMBX-S50-0-13/111_NH	46
82_MMBX-S50-0-13/111_NM	46
82_MMBX-S50-0-3/111_NE	46
82_MMBX-S50-0-3/111_NH	46
82_MMBX-S50-0-3/111_NM	46
92_MMBX-S50-0-12/111_NE	47
92_MMBX-S50-0-12/111_NM	47

MMCX-Connectors

11_MMCX-50-1-1/111_OE	54
11_MMCX-50-1-1/111_OH	54
11_MMCX-50-1-2/111_OE	54
11_MMCX-50-1-2/111_OH	54
11_MMCX-50-1-3/111_OE	54
11_MMCX-50-2-1/111_OE	54
11_MMCX-50-2-1/111_OH	54
11_MMCX-50-2-3/111_OE	54
11_MMCX-50-2-3/111_OH	54
11_MMCX-50-2-4/111_OE	54
16_MMCX-50-1-1/111_OE	55
16_MMCX-50-1-1/111_OH	55
16_MMCX-50-1-12/111_OE	55
16_MMCX-50-1-12/111_OH	55
16_MMCX-50-1-2/111_OE	56
16_MMCX-50-1-2/111_OH	56
16_MMCX-50-1-7/111_OE	56
16_MMCX-50-1-7/111_OH	56
16_MMCX-50-2-13/111_OE	55
16_MMCX-50-2-13/111_OH	55
16_MMCX-50-2-2/111_OE	56
16_MMCX-50-2-2/111_OH	56
16_MMCX-50-2-4/111_OE	56
16_MMCX-50-2-4/111_OH	56
21_MMCX-50-1-1/111_OE	57
21_MMCX-50-1-2/111_OE	57

Type	Page	Type	Page	Type	Page
21_MMCX-50-2-1/111_OE	56	16_N-50-4-14/133_NE	283	N 75Ω-Connectors	
22_MMCX-50-0-1/111_OE	58	16_N-50-6-8/133_NE	284	11_N-75-4-3/133_NE	302
22_MMCX-50-0-1/111_OH	58	16_N-50-7-22/133_NE	283	11_N-75-4-6/133_NE	302
22_MMCX-50-0-4/111_OH	58	16_N-50-7-26/133_NE	282	11_N-75-5-2/133_NE	302
24_MMCX-50-1-1/111_OE	57	16_N-50-7-28/133_NE	284	11_N-75-7-4/133_NE	302
24_MMCX-50-1-1/111_OH	57	16_N-50-7-29/133_NE	284	11_N-75-4-8/133_NE	302
24_MMCX-50-2-1/111_OE	57	16_N-50-7-30/133_NE	282	11_N-75-4-9/133_NE	302
		16_N-50-7-31/133_NE	282	11_N-75-7-16/133_NE	302
81_MMCX-50-0-1/111_OE	58	16_N-50-7-36/133_NE	284	11_N-75-7-18/133_NE	302
82_MMCX-50-0-1/111_NE	59	16_N-50-10-1/103_UV	283	21_N-75-4-8/133_NE	303
82_MMCX-50-0-1/111_NH	59			24_N-75-4-2/133_NE	303
82_MMCX-50-0-18/111_OM	59	21_N-50-2-14/133_NE	284	13_N-75-0-1/133_NE	304
82_MMCX-50-0-8/111_OE	59	21_N-50-3-11/133_NE	284	23_N-75-0-1/133_NE	304
82_MMCX-50-0-8/111_OM	59	21_N-50-3-12/133_NE	285		
82_MMCX-S50-0-2/111_KE	59	21_N-50-3-5/133_NE	285	PC 3.5-Connectors	
82_MMCX-S50-0-2/111_KG	59	21_N-50-3-7/133_NE	285	11_PC35-50-2-4/199_UE	144
82_MMCX-S50-0-2/111_KH	59	21_N-50-3-8/133_NE	285	11_PC35-50-3-4/199_UE	144
82_MMCX-S50-0-2/111_KL-1	59	21_N-50-7-13/133_NE	285	21_PC35-50-2-4/199_UE	144
82_MMCX-S50-0-55/119_OM	61	21_N-50-7-14/133_NE	285	21_PC35-50-3-3/199_UE	144
84_MMCX-50-0-1/111_OH	60	21_N-50-7-20/133_NE	286	23_PC35-50-0-51/199_UE	145
85_MMCX-50-0-1/111_OE	60	21_N-50-7-8/133_NE	285	23_PC35-50-0-53/199_UE	145
85_MMCX-50-0-1/111_OH	60	21_N-50-10-1/133_UF	286	23_PC35-50-0-54/199_UE	146
85_MMCX-S50-0-55/119_OM	61			24_PC35-50-2-2/199_UE	145
90_MMCX-S50-0-55/119_OE	61	22_N-50-0-2/133_NE	294	24_PC35-50-3-2/199_UE	145
90_MMCX-S50-0-55/119_OH	61	22_N-50-0-23/133_NF	294		
		22_N-50-0-3/133_NE	294		
N 50Ω-Connectors		23_N-50-0-1/133_NE	293		
11_N-50-2-1/133_NE	278	23_N-50-0-16/133_NE	297	QLA-Connectors	
11_N-50-2-11/133_NH	279	23_N-50-0-23/133_NE	295	11_QLA-01-1-8/122_NE	160
11_N-50-2-15/113_UE	277	23_N-50-0-30/133_NE	295	11_QLA-01-2-11/122_NE	160
11_N-50-2-16/133_NE	279	23_N-50-0-31/133_NE	296	11_QLA-01-2-13/122_NH	160
11_N-50-2-2/133_NE	278	23_N-50-0-33/133_NE	297	11_QLA-01-2-8/122_NE	160
11_N-50-3-13/113_NE	277	23_N-50-0-69/133_NX	296	11_QLA-01-2-8/122_NH	160
11_N-50-3-28/133_NE	279			11_QLA-01-2-9/122_NH	160
11_N-50-3-29/133_NE	279	24_N-50-2-1/133_NE	287	11_QLA-01-3-1/122_NE	160
11_N-50-3-31/133_NE	279	24_N-50-2-117/133_NE	288	11_QLA-01-3-2/122_NE	160
11_N-50-3-31/133_NH	279	24_N-50-2-14/133_NE	286		
11_N-50-3-5/133_NE	278	24_N-50-2-4/133_NE	288	16_QLA-01-1-1/122_NE	161
11_N-50-3-51/133_NE	278	24_N-50-3-10/133_NE	287	16_QLA-01-2-1/122_NE	161
11_N-50-3-54/133_NE	278	24_N-50-3-11/133_NE	288	16_QLA-01-2-13/122_NE	161
11_N-50-4-63/133_NE	279	24_N-50-3-12/133_NE	288	16_QLA-01-2-4/122_NE	161
11_N-50-5-18/103_NH	277	24_N-50-3-14/133_NE	286	16_QLA-01-2-4/122_NH	161
11_N-50-5-39/133_NE	278	24_N-50-3-51/19_NE	287		
11_N-50-6-1/133_NE	279	24_N-50-4-17/133_UE	288	21_QLA-01-2-1/112_NE	161
11_N-50-6-10/133_NH	280	24_N-50-7-14/133_NE	289	21_QLA-01-2-1/112_NH	161
11_N-50-6-5/133_NE	280	24_N-50-7-15/133_NE	289	21_QLA-01-2-5/112_NH	161
11_N-50-7-33/133_NE	280	24_N-50-7-24/133_NE	289	22_QLA-01-0-1/112_NE	163
11_N-50-7-43/133_NE	280	24_N-50-7-8/133_NE	287	22_QLA-01-0-1/112_NH	163
11_N-50-7-44/133_NE	280			22_QLA-01-0-2/112_NE	163
11_N-50-7-49/133_NE	280	25_N-50-2-10/133_NE	291		
11_N-50-7-5/133_NE	279	25_N-50-2-14/133_NE	290	24_QLA-01-1-11/112_NE	162
11_N-50-7-6/133_NE	279	25_N-50-2-2/133_NE	290	24_QLA-01-1-12/112_NH	162
11_N-50-7-61/133_NE	280	25_N-50-2-9/133_NE	291	24_QLA-01-2-1/112_NE	163
11_N-50-10-5/103_UV	281	25_N-50-3-20/133_NE	292	24_QLA-01-2-11/112_NE	162
13_N-50-0-1/133_NE	293	25_N-50-3-4/133_NE	290	24_QLA-01-2-5/112_NH	162
13_N-50-0-30/133_NE	295	25_N-50-3-6/133_NE	292		
13_N-50-0-33/133_NE	296	25_N-50-3-7/133_NE	292	64_QLA-01-0-1/122_NE	164
		25_N-50-3-9/133_NE	290	82_QLA-01-0-2/112_NE	164
16_N-50-3-103/133_NE	282	25_N-50-7-13/133_NE	292	85_QLA-01-0-2/110_NH	164
16_N-50-3-15/133_NE	281	25_N-50-7-14/133_NE	292	85_QLA-01-0-2/112_NE	164
16_N-50-3-26/133_NE	282	25_N-50-7-8/133_NE	291	85_QLA-01-0-2/122_NE	164
16_N-50-3-27/133_NE	282				
16_N-50-3-27/133_NH	282	61_N-0-0-1/-3_E	297		
		62_N-0-0-1/-3_E	297		

Type	Page	Type	Page	Type	Page
QMA-Connectors		16_QN-50-3-1/133_NE	195	22_SHV-50-0-3/100_NE	266
11_QMA-50-2-1/133_NE	181	16_QN-50-3-2/133_NE	195	22_SHV-50-0-6/133_NE	265
11_QMA-50-2-1/133_NH	181	16_QN-50-3-3/133_NE	195	23_SHV-50-0-1/133_NE	266
11_QMA-50-2-2/133_NE	181	16_QN-50-4-1/133_NE	195	23_SHV-50-0-2/133_NE	266
11_QMA-50-2-2/133_NH	181	16_QN-50-7-1/133_NE	195	24_SHV-50-3-1/133_NE	265
11_QMA-50-2-3/133_NE	181	16_QN-50-7-2/133_NE	195	24_SHV-50-4-1/133_NE	265
11_QMA-50-2-3/133_NH	181				
11_QMA-50-3-1/133_NE	182	22_QN-50-0-1/133_NE	197	SK-Connectors	
11_QMA-50-3-1/133_NH	182	22_QN-50-0-1/133_NY	197	11_SK-50-2-56/119_NE	149
11_QMA-50-3-2/133_NE	182	23_QN-50-0-1/133_NE	197	12_SK-50-0-51/199_NE	150
11_QMA-50-3-2/133_NH	182	23_QN-50-0-1/133_NY	197	13_SK-50-0-51/199_NE	150
11_QMA-50-3-3/133_NE	181	24_QN-50-3-1/133_NE	196	13_SK-50-0-52/199_NE	150
11_QMA-50-3-3/133_NH	181	24_QN-50-3-2/133_NE	196		
		24_QN-50-3-3/133_NE	196	21_SK-50-2-58/199_NE	149
16_QMA-50-2-1/133_NE	183	24_QN-50-7-1/133_NE	196	22_SK-50-0-51/199_NE	150
16_QMA-50-2-1/133_NH	183	24_QN-50-7-2/133_NE	196	23_SK-50-0-51/199_NE	150
16_QMA-50-2-2/133_NE	183	24_QN-50-7-3/133_NE	196	23_SK-50-0-52/199_NE	150
16_QMA-50-2-2/133_NH	183			24_SK-50-2-55/1-NE	149
16_QMA-50-2-3/133_NE	182	QUICK-FIT Connectors			
16_QMA-50-2-3/133_NH	182	11_716-50-9-9/003_E	325	SMA-Connectors	
16_QMA-50-3-1/133_NE	183	11_716-50-12-10/003_E	325	11_SMA-50-1-1/111_NE	118
16_QMA-50-3-1/133_NH	183	11_716-50-23-10/003_E	325	11_SMA-50-1-2/111_NE	118
16_QMA-50-3-2/133_NE	183	11_716-50-23-13/003_E	325	11_SMA-50-1-4/111_NE	120
16_QMA-50-3-2/133_NH	183	11_716-50-23-14/003_E	325	11_SMA-50-2-15/111_NH	118
16_QMA-50-3-3/133_NE	182	11_716-50-32-2/003_Y	326	11_SMA-50-2-27/111_NH	120
16_QMA-50-3-3/133_NH	182	11_716-50-42-2/003_Y	326	11_SMA-50-2-29/119_NH	118
16_QMA-50-4-1/133_NH	183	16_716-50-9-5/003_E	326	11_SMA-50-2-41/133_NH	120
		16_716-50-12-11/003_E	326	11_SMA-50-2-42/133_NH	120
22_QMA-50-0-3/133_NH	185	21_716-50-9-9/003_E	327	11_SMA-50-2-5/111_NH	120
22_QMA-50-0-4/133_NH	186	21_716-50-12-10/003_E	327	11_SMA-50-2-55/199_NE	120
22_QMA-50-0-7/111_NH	185	21_716-50-23-10/003_E	327	11_SMA-50-2-56/199_NH	120
22_QMA-50-0-7/133_NF	185	21_716-50-23-12/003_E	327	11_SMA-50-2-6/111_NH	120
23_QMA-50-0-2/111_NH	186	21_716-50-23-13/003_E	327	11_SMA-50-2-65/119_NH	118
23_QMA-50-0-3/111_NH	186	21_716-50-32-2/003_Y	328	11_SMA-50-3-10/111_NE	119
		21_716-50-42-2/003_Y	328	11_SMA-50-3-14/-11_NH	118
24_QMA-50-2-1/111_NE	184	11_N-50-9-9/003_E	328	11_SMA-50-3-15/111_NH	119
24_QMA-50-2-1/111_NH	184	11_N-50-12-10/003_E	329	11_SMA-50-3-16/-11_NH	119
24_QMA-50-2-2/133_NE	184	11_N-50-23-10/003_E	329	11_SMA-50-3-39/111_YH	119
24_QMA-50-2-2/133_NH	184	11_N-50-23-11/003_E	329	11_SMA-50-3-42/-33_NH	119
24_QMA-50-2-3/133_NE	184	11_N-50-23-11/003_E	329	11_SMA-50-3-45/133_NH	120
24_QMA-50-2-3/133_NH	184	11_N-50-32-2/003_Y	329	11_SMA-50-3-46/133_NH	120
24_QMA-50-3-1/133_NE	185	11_N-50-42-2/003_Y	329	11_SMA-50-3-5/111_NE	120
24_QMA-50-3-1/133_NH	185	16_N-50-9-6/003_E	330	11_SMA-50-3-55/199_NE	120
24_QMA-50-3-2/133_NE	185	16_N-50-12-9/003_E	330	11_SMA-50-3-56/199_NH	120
24_QMA-50-3-2/133_NH	185			11_SMA-50-3-6/111_NH	120
24_QMA-50-3-3/111_NE	184	21_N-50-9-9/003_E	330	11_SMA-50-3-64/-19_NH	118
24_QMA-50-3-3/111_NH	184	21_N-50-12-10/003_E	331	11_SMA-50-3-65/119_NH	119
		21_N-50-23-10/003_E	331	11_SMA-50-3-66/-19_NH	119
82_QMA-50-0-3/111_NH	187	21_N-50-23-11/003_E	331	11_SMA-50-3-7/111_NE	119
82_QMA-S50-0-2/111_NH	187	21_N-50-32-2/003_Y	331	11_SMA-50-3-8/111_NH	119
85_QMA-50-0-3/111_NH	188	21_N-50-42-2/003_Y	331		
85_QMA-S50-0-2/111_NM	187			12_SMA-50-0-110/111_NE	133
85_QMA-S50-0-5/111_NM	188			13_SMA-50-0-141/133_NH	132
				13_SMA-50-0-2/111_NE	131
QN-Connectors		SHV-Connectors			
11_QN-50-3-1/133_NE	194	11_SHV-50-3-1/133_NE	264	16_SMA-50-3-106/111_NH	122
11_QN-50-3-2/133_NE	194	11_SHV-50-3-10/133_NE	264	16_SMA-50-1-1/111_NH	122
11_QN-50-3-3/133_NE	194	11_SHV-50-4-1/133_NE	264	16_SMA-50-2-103/111_NH	121
11_QN-50-7-1/133_NE	194	11_SHV-50-4-10/133_NE	264	16_SMA-50-2-105/111_NH	122
11_QN-50-7-2/133_NE	194			16_SMA-50-2-106/111_NH	122
11_QN-50-7-3/133_NE	194	21_SHV-50-3-1/133_NE	264	16_SMA-50-2-141/133_NH	122
		21_SHV-50-4-1/133_NE	264	16_SMA-50-2-145/133_NH	122
		22_SHV-50-0-2/133_NE	265		

Type	Page	Type	Page	Type	Page
16_SMA-50-2-43/133_NE	121	25_SMA-50-3-15/111_NH	127	16_SMC-50-2-20/111_NE	106
16_SMA-50-2-53/119_NH	121	25_SMA-50-3-25/111_NH	127	16_SMC-50-2-25/111_NE	105
16_SMA-50-3-105/111_NH	122	27_SMA-50-0-11/111_NE	130	16_SMC-50-2-25/111_NH	105
16_SMA-50-3-145/133_NE	122	28_SMA-50-0-1/111_NH	130	16_SMC-50-2-5/111_NE	105
16_SMA-50-3-146/133_NE	122	28_SMA-50-0-41/133_NH	130		
16_SMA-50-3-3/111_NH	121			21_SMC-50-2-10/111_NE	106
16_SMA-50-3-43/133_NE	121	62_SMA-0-0-1/-11_NE	136	21_SMC-50-2-11/111_NE	106
		62_SMA-0-0-51/-99_NE	136	22_SMC-50-0-2/111_NE	107
21_SMA-50-1-1/111_NE	123	64_SMA-0-0-1/111_NE	136	22_SMC-50-0-3/111_NE	107
21_SMA-50-1-2/111_NE	123	82_SMA-50-0-1/111_NH	135	22_SMC-50-0-3/133_NE	107
21_SMA-50-2-15/111_NH	123	82_SMA-50-0-45/111_NE	135	24_SMC-50-1-10/111_NH	107
21_SMA-50-2-5/111_NE	124	85_SMA-50-0-101/111_NH	135	24_SMC-50-2-110/111_NH	107
21_SMA-50-2-6/111_NH	124	85_SMA-50-0-144/111_YH	136	24_SMC-50-2-13/111_NH	106
21_SMA-50-3-47/111_YE	123				
21_SMA-50-3-5/111_NE	124	SMB-Connectors		81_SMC-50-0-1/111_NE	108
21_SMA-50-3-6/111_NE	124			82_SMC-50-0-1/111_NH	108
		11_SMB-50-1-40/111_NH	94	85_SMC-50-0-1/111_NE	108
22_SMA-50-0-1/111_NE	128	11_SMB-50-2-13/111_NH	94	85_SMC-50-0-1/111_NH	108
22_SMA-50-0-10/111_NE	134	11_SMB-50-2-40/111_NH	94	85_SMC-50-0-1/133_NE	108
22_SMA-50-0-12/111_NY	134	11_SMB-50-2-41/111_NH	94		
22_SMA-50-0-15/111_NE	134			SMS-Connectors	
		16_SMB-50-1-40/111_NE	95		
22_SMA-50-0-203/111_NH	129	16_SMB-50-1-50/111_NE	95	11_SMS-50-1-10/111_NE	112
22_SMA-50-0-3/111_NE	130	16_SMB-50-2-23/111_NE	94	11_SMS-50-2-110/111_NH	112
22_SMA-50-0-4/111_NH	129	16_SMB-50-2-40/111_NH	95	12_SMS-50-0-3/133_NH	113
22_SMA-50-0-44/133_NE	129	16_SMB-50-2-41/111_NH	95	16_SMS-50-1-10/111_NH	112
22_SMA-50-0-53/199_NE	130	16_SMB-50-2-50/111_NH	95	16_SMS-50-2-10/111_NE	112
		16_SMB-50-2-51/111_NH	95	81_SMS-50-0-1/111_NH	113
23_SMA-0-165/199_NE	137			84_SMS-50-0-1/111_NE	114
23_SMA-0-166/199_NE	137	21_SMB-50-1-10/111_NE	96		
23_SMA-0-167/199_NE	137	21_SMB-50-2-10/111_NH	96	TNC 50Ω-Connectors	
23_SMA-0-168/199_NE	137	21_SMB-50-2-11/111_NE	96		
23_SMA-50-0-1/111_NH	129	21_SMB-50-2-13/111_NE	96	11_TNC-50-2-1/133_NE	232
23_SMA-50-0-11/111_NE	129	22_SMB-50-0-11/111_NE	98	11_TNC-50-2-112/133_NE	233
23_SMA-50-0-12/111_NE	132	22_SMB-50-0-2/133_NH	98	11_TNC-50-2-113/133_NE	233
23_SMA-50-0-13/111_NH	131	22_SMB-50-0-3/111_NE	97	11_TNC-50-2-20/103_NE	232
23_SMA-50-0-2/111_NE	132	22_SMB-50-0-5/111_NE	98	11_TNC-50-3-115/133_NE	233
23_SMA-50-0-21/111_NE	131	24_SMB-50-1-10/111_NE	97	11_TNC-50-3-115/133_NH	233
23_SMA-50-0-3/111_NE	131	24_SMB-50-2-110/111_NH	97	11_TNC-50-3-116/133_NE	233
23_SMA-50-0-4/111_NE	133	24_SMB-50-2-111/111_NH	97	11_TNC-50-3-117/133_NE	233
23_SMA-50-0-41/133_NH	129	24_SMB-50-2-111/111_NH	97	11_TNC-50-3-117/133_NE	233
23_SMA-50-0-44/133_NH	129	24_SMB-50-2-13/111_NE	96	11_TNC-50-3-29/103_NE	232
23_SMA-50-0-51/199_NE	129			11_TNC-50-3-29/113_NE	232
23_SMA-50-0-52/199_NE	132	81_SMB-S50-0-4/111_NM	99	11_TNC-50-3-5/133_NE	232
23_SMA-50-0-53/199_NE	131	82_SMB-50-0-1/111_NH	99	11_TNC-50-3-6/133_NE	232
23_SMA-50-0-53/199_NE	129	82_SMB-50-0-17/111_NH	99	11_TNC-50-7-2/133_NE	233
23_SMA-50-0-61/199_NE	129	82_SMB-50-0-17/111_NM	99	12_TNC-50-0-1/133_NE	239
23_SMA-50-0-62/199_NE	132	82_SMB-50-0-19/111_NH	99		
		82_SMB-S50-0-18/111_NH	100	16_TNC-50-2-10/133_NE	234
24_SMA-50-2-13/111_NH	125	85_SMB-Z50-0-19/111_NH	100	16_TNC-50-2-119/133_NE	234
24_SMA-50-2-14/111_NH	125			16_TNC-50-2-7/133_NE	234
24_SMA-50-2-15/111_NH	124	SMC-Connectors		16_TNC-50-3-111/133_NE	235
24_SMA-50-2-45/133_NH	125			16_TNC-50-3-112/133_NE	235
24_SMA-50-2-45/133_UH	125	11_SMC-50-1-10/111_NH	104	16_TNC-50-3-13/133_NE	235
24_SMA-50-2-46/133_NH	125	11_SMC-50-1-6/111_NE	104	16_TNC-50-3-18/133_NE	235
24_SMA-50-3-15/111_NH	125	11_SMC-50-2-10/111_NH	104	16_TNC-50-3-28/133_NE	234
24_SMA-50-3-42/133_NE	126	11_SMC-50-2-10/133_NE	104	16_TNC-50-4-115/133_NE	235
		11_SMC-50-2-11/111_NE	104	16_TNC-50-4-115/133_NH	235
25_SMA-50-1-2/111_NE	126	11_SMC-50-2-13/111_NH	104	16_TNC-50-7-4/133_NE	234
25_SMA-50-1-4/111_NE	126	11_SMC-50-2-5/111_NE	104		
25_SMA-50-2-15/111_NE	127			21_TNC-50-2-2/133_NE	236
25_SMA-50-2-25/111_NE	127	16_SMC-50-1-10/111_NH	105	21_TNC-50-3-31/133_NE	236
25_SMA-50-2-46/133_NE	128	16_SMC-50-1-20/111_NE	106	21_TNC-50-3-32/133_NE	236
25_SMA-50-2-5/111_NH	128	16_SMC-50-2-10/111_NH	105	21_TNC-50-3-4/133_NE	236
25_SMA-50-2-6/111_NE	128	16_SMC-50-2-11/111_NE	105	22_TNC-50-0-1/133_NE	240

Type Page

22_TNC-50-0-2/133_NE	240
23_TNC-50-0-2/133_NE	240
23_TNC-50-0-2/133_NH	240
23_TNC-50-0-6/133_NE	240

24_TNC-50-2-1/133_NE	237
24_TNC-50-2-27/133_NE	238
24_TNC-50-2-29/133_NH	238
24_TNC-50-2-31/133_NE	237
24_TNC-50-3-21/133_NE	238
24_TNC-50-3-23/133_NE	238
24_TNC-50-3-30/133_NH	237
25_TNC-50-2-1/133_NE	238
25_TNC-50-2-19/133_NE	239
25_TNC-50-3-19/133_NE	239
25_TNC-50-3-9/133_NE	238
27_TNC-50-0-1/133_NE	241

61_TNC-0-0-1/-33_E	241
62_TNC-0-0-1/-33_E	241

TNC 75Ω-Connectors

11_TNC-75-4-2/133_NE	246
11_TNC-75-4-30/133_NE	246
11_TNC-75-4-4/133_NE	246
11_TNC-75-4-9/133_NE	246
16_TNC-75-4-2/133_NE	246
24_TNC-75-4-8/133_NE	247
61_TNC-0-0-1/-33_E	247
62_TNC-0-0-1/-33_E	247

HUBER+SUHNER – Excellence in Connectivity Solutions

HUBER+SUHNER is a leading global supplier of components and systems for electrical and optical connectivity in communications, industrial and transportation markets. HUBER+SUHNER can draw on core competences in the

areas of high and low frequency technology, fibre optics and polymers. Working in close collaboration with our customers around the globe, we strive for excellence in the development and manufacturing of high quality products.



HUBER+SUHNER is certified according to ISO 9001 and ISO 14001.

WAIVER

It is exclusively in written agreements that we provide our customers with warrants and representations as to the technical specifications and/or the fitness for any particular purpose. The facts and figures contained herein are carefully compiled to the best of our knowledge, but they are intended for general informational purposes only.



HUBER+SUHNER AG

RF Technology

CH-9100 Herisau

Phone +41 (0)71 353 41 11

Fax +41 (0)71 353 45 90

www.hubersuhner.com